
python_ics Documentation

Release 913.16

David Rebbe

Aug 17, 2023

Contents

1	Whats New?	3
1.1	ISO 15765-2	3
1.2	Settings	4
1.3	PyInstaller	4
2	Versioning Information	7
2.1	v903	7
2.2	Older Versions:	7
3	Installation on Windows	9
3.1	Building from source	9
3.2	Intrepid icsneo40 Library	9
4	Installation on Linux	11
4.1	Fedora Dependencies (FC28)	11
4.2	Debian/Ubuntu Dependencies	11
4.3	libicsneo library	11
4.4	Others (Required dependencies)	11
4.5	Installation	12
5	Getting Started	13
6	Examples	15
6.1	Opening a device	15
6.2	Transmitting and Receiving a CAN message	15
6.3	ISO 15765-2 Example	15
6.4	Missing an example?	16
7	Module Documentation	17
8	Module Functions	63
9	Module Structures	89
10	Module Variables	205
	Python Module Index	227

Intrepid Control Systems, Inc. open source Python module for interfacing to Intrepid hardware. Basic knowledge of using and installing Python modules is assumed. Please see <https://docs.python.org/3/installing/index.html> for documentation on how to install Python modules.

This module is essentially just a wrapper around icsneo40.dll. For more documentation please visit neoVI DLL Documentation under <https://intrepides.com/support/support-resources/>

CHAPTER 1

Whats New?

v903+ is a new release that implements features that break existing API in some areas.

1.1 ISO 15765-2

old naming conventions have been updated to reflect closer to the actual codebase.

```
# Old:  
tx_msg = ics.CmISO157652TxMessage()  
rx_msg = ics.CmISO157652RxMessage()  
  
# New:  
tx_msg = ics.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message()  
rx_msg = ics.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message()
```

ics.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message() data structure is now a ctypes.c_ubyte array instead of a python list.

```
# Old:  
msg.data = [x for x in range(number_of_bytes)]  
  
# New:  
my_data = [x for x in range(number_of_bytes)]  
msg.data = (ctypes.c_ubyte*len(msg.data))(*my_data)  
  
>>> msg.data  
<ics.structures.st_cm_iso157652_tx_message.c_ubyte_Array_4096 object at  
0x0000023E534BE940>
```

1.2 Settings

v903 and up have converted over to a new auto generation of `icsnVC40.h`. This enables faster support for newer Intrepid devices and less error prone. With this switch we have moved to using `ics.s_device_settings`.

```
# Old behavior:
device = ics.open_device()
settings = ics.get_device_settings(device)
# settings is a Vcan3Settings type
settings.can1.Baudrate = 1
ics.set_device_settings(device, settings)

# New behavior
device = ics.open_device()
settings = ics.get_device_settings(device)
# settings is a s_device_settings type
settings.vcan3.can1.Baudrate = 1
ics.set_device_settings(device, settings)
```

1.3 PyInstaller

Due to the added complexity underneath when building PyInstaller `hidden_imports.py` should be used now in your spec script:

```
# -*- mode: python ; coding: utf-8 -*-

import ics

block_cipher = None

a = Analysis(['test.py'],
            pathex=['.'],
            binaries=[],
            datas=[],
            hiddenimports=ics.hiddenimports.hidden_imports,
            hookspath=[],
            runtime_hooks=[],
            excludes=[],
            win_no_prefer_redirects=False,
            win_private_assemblies=False,
            cipher=block_cipher,
            noarchive=False)
pyz = PYZ(a.pure, a.zipped_data,
          cipher=block_cipher)
exe = EXE(pyz,
          a.scripts,
          [],
          exclude_binaries=True,
          name='test',
          debug=False,
          bootloader_ignore_signals=False,
          strip=False,
          upx=True,
```

(continues on next page)

(continued from previous page)

```
        console=True )
coll = COLLECT(exe,
               a.binaries,
               a.zipfiles,
               a.datas,
               strip=False,
               upx=True,
               upx_exclude=[],
               name='test')
```


CHAPTER 2

Versioning Information

Minor differences can occur between different icsnVC40.h versions. These differences are usually just structures and constant differences. Below is a list of how the python_ics version correlates to the icsnVC40.h version:

2.1 v903

Starting with 903, python_ics module will now match official upstream version releases.

```
pip install 'python_ics>=5.0,<904.0' --force-reinstall
```

Note: Refer to platform specific installation if not on Windows

2.2 Older Versions:

- **v802** pip install 'python_ics>=2.0,<3.0' --force-reinstall

Note: Refer to platform specific installation if not on Windows

- **v803** pip install 'python_ics>=3.0,<4.0' --force-reinstall

Note: Refer to platform specific installation if not on Windows

- **v900** pip install 'python_ics>=4.0,<5.0' --force-reinstall

Note: Refer to platform specific installation if not on Windows

CHAPTER 3

Installation on Windows

PyPi provides binary packages for Windows. You can simply install the `python_ics` module by running the following command:

```
pip install python_ics
```

Note: `pip.exe` is usually located under the `Scripts` directory under the Python installation directory.

3.1 Building from source

Building from source on windows is not usually need so it won't really be covered here in detail. As a starting point you'll need to match the compiler version used to build the official Python binaries (MSVC). If the build environment is setup correctly, you should be able to run `python setup.py build` like usual.

3.2 Intrepid icsneo40 Library

`python_ics` module looks for `icsneo40.dll` in the normal windows DLL search paths. The module will throw an exception if its not found.

CHAPTER 4

Installation on Linux

python_ics does not provide binaries for linux distributions so we will have to compile from source. This can be easily achieved by utilizing Python's PIP. First we need to make sure we have some base packages installed.

4.1 Fedora Dependencies (FC28)

```
sudo dnf install redhat-rpm-config gcc g++ python3-devel clang  
clang-tools-extra
```

4.2 Debian/Ubuntu Dependencies

```
sudo apt install build-essential python-dev clang-format
```

4.3 libicsneo library

The legacy version of libicsneo library (`libicsneolegacy.so`) is required, see the specific repo for details: <https://github.com/intrepides/libicsneo>

4.4 Others (Required dependencies)

- GCC
- G++
- Python Development packages (We Need to link to Python.h)
- Clang (llvm)
- clang-format

4.5 Installation

After dependencies are installed we can run the following pip command:

```
pip install python_ics
```

Note: A lot of distributions have Python 2 and 3 installed side by side. As of this writing without a version suffix the commands still default to version 2 of the Python binaries. In order to utilize the Python 3 binaries you must append a 3 after the binary names (python3 and pip3 instead of just python and pip).

CHAPTER 5

Getting Started

Please see https://github.com/intrepidcs/python_ics/tree/master/examples for simple examples on how to use this module. Most function documentation has a simple example on how its intended to be used. Every function was designed to be as close as possible to it's C counterpart unless it was deemed to make the function more pythonic in nature.

For those experienced with the C API `ics.open_device (icsneoOpenNeoDevice())` behavior has been changed the most (no parameters makes it auto utilize `ics.find_devices (icsneoFindNeoDevices())` and open the first device). Also since python is a object oriented language the module utilizes this and auto cleans up device handles when going out of scope so there is usually no need to call `ics.close_device()`.

CHAPTER 6

Examples

Examples can be found at https://github.com/intrepidcs/python_ics/tree/master/examples

For extra information on data structures and underlying functionality, please visit neoVI DLL Documentation under <https://intrepidcs.com/support/support-resources/>

6.1 Opening a device

The `open_device_example.py` example shows how to successfully open and close an Intrepid device.

6.2 Transmitting and Receiving a CAN message

The following examples show how to interact with CAN messages on an Intrepid device.

- `transmit_can_example.py`: Basic example showing how to transmit and receive standard CAN frame
- `transmit_can_xtd_example.py`: Builds off of the CAN example and adds extended Arbitration ID attributes
- `canfd_transmit_example.py`: Bare minimum example on how to transmit over CANFD.

6.3 ISO 15765-2 Example

The `iso15765_example.py` example shows how to setup basic ISO 15765-2 receive filters and transmitting an ISO 15765-2 message.

After opening an Intrepid device `ics.iso15765_enable_networks` should be called to enable ISO 15765-2.

Receive filtering can be established by passing a custom `ics.CmISO157652RxMessage()` to `ics.iso15765_receive_message()`.

Similarly transmitting an ISO 15765-2 frame can be accomplished by passing a custom `ics.CmISO157652TxMessage()` to `ics.iso15765_transmit_message()`.

6.4 Missing an example?

Need an example on something that isn't covered here? Please submit an issue on [github](#) or feel free to send over a Pull Request of your own.

CHAPTER 7

Module Documentation

Python C Code module for interfacing to the icsneo40 dynamic library. Code tries to respect PEP 8 (<http://python.org/dev/peps/pep-0008>). Function naming convention does not follow the tradition c style icsneo40 naming convention as pyics module name acts as the namespace (icsneo portion of the function) and function names are suppose to be lowercase with underscores instead of mixedCase like icsneo API.

C API can be mimiced almost identically by doing the following:

```
>>> import ics as icsneo
>>> devices = icsneo.FindNeoDevices()
>>> for device in devices:
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

Recommended Python way by doing the following:

```
>>> import ics
>>> devices = ics.find_devices()
>>> for device in devices:
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

It should be noted that `ics.ics.NeoDevice` is used a little bit differently than the C API. `ics.ics.NeoDevice` contains two extra members: `ics.ics.NeoDevice.AutoHandleClose` and `ics.ics.NeoDevice._Handle`

The handle normally returned from `icsneoOpenNeoDevice()` is stored inside `_Handle` and setting `AutoHandleClose` to True (Default) will automatically close the handle when the `ics.ics.NeoDevice` goes out of scope.

Installation:

```
pip install python_ics
```

```
https://pypi.python.org/pypi/python-ics
```

```
exception ics.ics.ArgumentError
    Bases: Exception

exception ics.ics.RuntimeError
    Bases: Exception

class ics.ics.NeoDevice
    Bases: object

    NeoDevice object

    AutoHandleClose
        When NeoDevice is freed the handle will automatically be closed, if true.

    DeviceType

    Handle

    IsOpen
        This contains the handle returned from icsneoOpenDevice() API. If uncertain, don't use this.

    MaxAllowedClients

    Name
        String describing DeviceType, extension to Python api only.

    NumberOfClients

    SerialNumber

class ics.ics.SpyMessage
    Bases: object

    SpyMessage object

    AckBytes

    ArbIDOrHeader

    Data

    DescriptionID
        Not Used

    ExtraDataPtr

    ExtraDataPtrEnabled

    MessagePieceID
        Not Used

    MiscData

    NetworkID
        This value is used to identify which network this message was received on.

    NetworkID2
        This value is used to identify which network this message was received on.

    NodeID
        Not Used

    NumberBytesData
        Holds the number of bytes in the Data(1 to 8) array or the number of bytes in a CAN remote frame (The DLC).
```

NumberBytesHeader

Used for J1850/ISO messages. It indicates how many bytes are stored in the Header(1 to 4) array.

Protocol

Valid values are SPY_PROTOCOL_CAN, SPY_PROTOCOL_J1850VPW, and SPY_PROTOCOL_ISO9141.

StatusBitField

StatusBitField2

StatusBitField3

StatusBitField4

TimeHardware

Hardware time stamp. The TimeStamp is reset on device open

TimeHardware2

Hardware time stamp. The TimeStamp is reset on device open

TimeStampHardwareID

This is an identifier of what type of hardware timestamp is used. Since neoVI's timestamp is always the same, this doesn't change.

TimeStampSystemID

This is an identifier of what type of system timestamp is used. Since WIN32 neoVI's timestamp is always the same, from the timeGetTime API, this doesn't change.

TimeSystem

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

TimeSystem2

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

noExtraDataPtrCleanup

Tells Python to not clean up ExtraDataPtrMemory, If this is enabled. Ignore, if unsure.

class ics.ics.SpyMessageJ1850

Bases: object

SpyMessageJ1850 object

AckBytes

Data

DescriptionID

Not Used

ExtraDataPtr

ExtraDataPtrEnabled

Header

MessagePieceID

Not Used

MiscData

NetworkID

This value is used to identify which network this message was received on.

NetworkID2

This value is used to identify which network this message was received on.

NodeID

Not Used

NumberBytesData

Holds the number of bytes in the Data(1 to 8) array or the number of bytes in a CAN remote frame (The DLC).

NumberBytesHeader

Used for J1850/ISO messages. It indicates how many bytes are stored in the Header(1 to 4) array.

Protocol

Valid values are SPY_PROTOCOL_CAN, SPY_PROTOCOL_J1850VPW, and SPY_PROTOCOL_ISO9141.

StatusBitField

StatusBitField2

StatusBitField3

StatusBitField4

TimeHardware

Hardware time stamp. The TimeStamp is reset on device open

TimeHardware2

Hardware time stamp. The TimeStamp is reset on device open

TimeStampHardwareID

This is an identifier of what type of hardware timestamp is used. Since neoVI's timestamp is always the same, this doesn't change.

TimeStampSystemID

This is an identifier of what type of system timestamp is used. Since WIN32 neoVI's timestamp is always the same, from the timeGetTime API, this doesn't change.

TimeSystem

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

TimeSystem2

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

noExtraDataPtrCleanup

Tells Python to not clean up ExtraDataPtrMemory, If this is enabled. Ignore, if unsure.

`ics.ics.ClosePort()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.close_device()` method.

`ics.ics.EnableBusVoltageMonitor()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_bus_voltage_monitor()` method.

`ics.ics.EnableDOIPLine()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_doipline()` method.

`ics.ics.EnableNetworkCom()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_network_com()` method.

`ics.ics.FindNeoDevices()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.find_devices()` method.

`ics.ics.FirmwareUpdateRequired()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.firmware_update_required()` method.

`ics.ics.FlashPhyFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.flash_phy_firmware()` method.

`ics.ics.ForceFirmwareUpdate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.force_firmware_update()` method.

`ics.ics.GenericAPIGetStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.generic_api_get_status()` method.

`ics.ics.GenericAPIReadData()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.generic_api_read_data()` method.

`ics.ics.GenericAPISendCommand()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.generic_api_send_command()` method.

`ics.ics.GetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_active_vnet_channel()` method.

`ics.ics.GetAllChipVersions()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_all_chip_versions()` method.

`ics.ics.GetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_enabled()` method.

`ics.ics.GetBackupPowerReady()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_ready()` method.

`ics.ics.GetBusVoltage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_bus_voltage()` method.

`ics.ics.GetDLLFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_firmware_info()` method.

`ics.ics.GetDLLVersion()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_version()` method.

`ics.ics.GetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_settings()` method.

`ics.ics.GetDeviceStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_status()` method.

`ics.ics.GetErrorMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_error_messages()` method.

`ics.ics.GetGPTPStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_gptp_status()` method.

`ics.ics.GetHWFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_hw_firmware_info()` method.

`ics.ics.GetLastAPIError()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_last_api_error()` method.

`ics.ics.GetMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_messages()` method.

`ics.ics.GetPCBSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_pcb_serial_number()` method.

`ics.ics.GetPerformanceParameters()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_performance_parameters()` method.

`ics.ics.GetPhyFwVersion()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_phy_firmware_version()` method.

`ics.ics.GetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_rtc()` method.

`ics.ics.GetSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_serial_number()` method.

`ics.ics.GetTimeStampForMsg()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_timestamp_for_msg()` method.

`ics.ics.ISO15765_DisableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_disable_networks()` method.

`ics.ics.ISO15765_EnableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_enable_networks()` method.

`ics.ics.ISO15765_ReceiveMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.ics.ISO15765_TransmitMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.ics.IsDeviceFeatureSupported()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.is_device_feature_supported()` method.

`ics.ics.LoadDefaultSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.load_default_settings()` method.

`ics.ics.OpenNeoDevice()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.open_device()` method.

`ics.ics.ReadJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_jupiter_firmware()` method.

`ics.ics.ReadSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_sdcard()` method.

`ics.ics.RequestDiskDetails()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_details()` method.

`ics.ics.RequestDiskFormat()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format()` method.

`ics.ics.RequestDiskFormatCancel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format_cancel()` method.

`ics.ics.RequestDiskFormatProgress()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_format_progress()` method.

`ics.ics.RequestEnterSleepMode()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.request_enter_sleep_mode()` method.

`ics.ics.ScriptClear()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_clear()` method.

`ics.ics.ScriptGetFBlockStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_fblock_status()` method.

`ics.ics.ScriptGetScriptStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_status()` method.

`ics.ics.ScriptGetScriptStatusEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_script_status()` method.

`ics.ics.ScriptLoad()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_load()` method.

`ics.ics.ScriptReadAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_app_signal()` method.

`ics.ics.ScriptReadRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_rx_message()` method.

`ics.ics.ScriptReadTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_tx_message()` method.

`ics.ics.ScriptStart()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start()` method.

`ics.ics.ScriptStartFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start_fblock()` method.

`ics.ics.ScriptStop()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop()` method.

`ics.ics.ScriptStopFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop_fblock()` method.

`ics.ics.ScriptWriteAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_app_signal()` method.

`ics.ics.ScriptWriteRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_rx_message()` method.

`ics.ics.ScriptWriteTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_tx_message()` method.

`ics.ics.SetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_active_vnet_channel()` method.

`ics.ics.SetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_backup_power_enabled()` method.

`ics.ics.SetBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate()` method.

`ics.ics.SetBitRateEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate_ex()` method.

`ics.ics.SetContext()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_context()` method.

`ics.ics.SetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_device_settings()` method.

`ics.ics.SetFDBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_fd_bit_rate()` method.

`ics.ics.SetLedProperty()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_led_property()` method.

`ics.ics.SetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_rtc()` method.

`ics.ics.SetReflashDisplayCallback()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_reflash_callback()` method.

`ics.ics.StartDHCPServer()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.start_dhcp_server()` method.

`ics.ics.StopDHCPServer()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.stop_dhcp_server()` method.

`ics.ics.TxMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.transmit_messages()` method.

`ics.ics.UartGetBaudrate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_get_baudrate()` method.

`ics.ics.UartRead()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_read()` method.

`ics.ics.UartSetBaudrate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_set_baudrate()` method.

`ics.ics.UartWrite()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_write()` method.

`ics.ics.ValidateHObject()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.validate_hobject()` method.

`ics.ics.WriteJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_jupiter_firmware()` method.

`ics.ics.WriteSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_sdcard()` method.

`ics.ics.base36enc(serial)`

Converts a decimal serial number to base36.

Args: serial (int): serial number.

Raises: `ics.ics.RuntimeError`

Returns: Str: Serial Number

```
>>> ics.base36enc(device.SerialNumber)
CY0024
```

`ics.ics.close_device(device)`

Closes the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Error Count (int)

```
>>> for device in ics.find_devices():
...     ics.open_device(device)
...     # Do something with the device...
...     ics.close_device(device)
... 
```

Note: `ics.ics.NeoDevice` will automatically close the device when it goes out of scope.

ics.ics.coremini_clear(device, location)

Clears the CoreMini into the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`location (int): Accepts ics.ics.SCRIPT_LOCATION_FLASH_MEM, ics.ics.SCRIPT_LOCATION_SDCARD, or ics.ics.SCRIPT_LOCATION_VCAN3_MEM`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_clear(device, ics.SCRIPT_LOCATION_SDCARD)
```

ics.ics.coremini_get_fblock_status(device, index)

Gets the status of a Coremini Function Block at `index` on `device`.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`index (int): Index of the function block.`

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_get_fblock_status(device, 1)
True
```

ics.ics.coremini_get_status(device)

Gets the status of the CoreMini in the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: True if running, otherwise False.

```
>>> device = ics.open_device()
>>> ics.coremini_get_status(device)
>>>
```

ics.ics.coremini_load(device, coremini, location)

Loads the CoreMini into the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`coremini (str/tuple): Use string to load from file, Use Tuple if file data.`

`location (int): Accepts ics.ics.SCRIPT_LOCATION_FLASH_MEM, ics.ics.SCRIPT_LOCATION_SDCARD, or ics.ics.SCRIPT_LOCATION_VCAN3_MEM`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_load(device, 'cmvspy.vs3cmb', ics.SCRIPT_LOCATION_SDCARD)
```

`ics.ics.coremini_read_app_signal(device, index)`

Gets the value of a Coremini application signal at *index* on *device*.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`index (int): Index of the application signal.`

Raises: `ics.ics.RuntimeError`

Returns: float on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_read_app_signal(device, 1)
52
```

`ics.ics.coremini_read_rx_message(device, index, j1850=False)`

Gets the value of a Coremini Message at *index* on *device*.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`index (int): Index of the application signal.`

`j1850 (bool): Use ics.ics.SpyMessageJ1850 instead.`

Raises: `ics.ics.RuntimeError`

Returns: `ics.ics.SpyMessage` Success.

```
>>> device = ics.open_device()
>>> msg = ics.coremini_read_tx_message(device, 0)
```

`ics.ics.coremini_read_tx_message(device, index, j1850=False)`

Gets the value of a Coremini Message at *index* on *device*.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`index (int): Index of the application signal.`

`j1850 (bool): Use ics.ics.SpyMessageJ1850 instead.`

Raises: `ics.ics.RuntimeError`

Returns: `ics.ics.SpyMessage` Success.

```
>>> device = ics.open_device()
>>> msg = ics.coremini_read_tx_message(device, 0)
```

`ics.ics.coremini_start(device, location)`

Starts the CoreMini into the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`location (int): Accepts ics.ics.SCRIPT_LOCATION_FLASH_MEM, ics.ics.SCRIPT_LOCATION_SDCARD, or ics.ics.SCRIPT_LOCATION_VCAN3_MEM`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_start(device, ics.SCRIPT_LOCATION_SDCARD)
```

`ics.ics.coremini_start_fblock(device, index)`

Starts a Coremini Function Block at *index* on *device*.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

index (int): Index of the function block.

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_start_fblock(device, 1)
```

`ics.ics.coremini_stop(device)`

Stops the CoreMini into the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_stop(device)
```

`ics.ics.coremini_stop_fblock(device, index)`

Stops a Coremini Function Block at `index` on `device`.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

index (int): Index of the function block.

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_stop_fblock(device, 1)
```

`ics.ics.coremini_write_app_signal(device, index, value)`

Sets the value of a Coremini application signal at `index` on `device`.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

index (int): Index of the application signal.

value (float): New value of the application signal.

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_write_app_signal(device, 1, 52)
>>>
```

`ics.ics.coremini_write_rx_message(device, index, TODO)`

TODO

`ics.ics.coremini_write_tx_message(device, index, msg)`

TODO

`ics.ics.create_neovi_radio_message(Relay1, Relay2, Relay3, Relay4, Relay5, LED6, LED5, MSB_report_rate, LSB_report_rate, analog_change_report_rate, relay_timeout)`

Python API only. Generates data bytes for use with neoVI RADI/O CAN Messages

Kwargs: Relay1 (boolean): Enable/Disable Relay1
Relay2 (boolean): Enable/Disable Relay2
Relay3 (boolean): Enable/Disable Relay3
Relay4 (boolean): Enable/Disable Relay4
Relay5 (boolean): Enable/Disable Relay5
LED5 (boolean): Enable/Disable LED5
LED6 (boolean): Enable/Disable LED6
MSB_report_rate (int): MSB Report Rate in ms (0-255)
LSB_report_rate (int): LSB Report Rate in ms (0-255)
analog_change_report_rate (int): Analog change report rate
relay_timeout (int): Relay Timeout (0-255)*255ms

Returns:

Tuple of data bytes for use with `ics.ics.SpyMessage`

Raises: `ics.ics.RuntimeError`

```
>>> msg = ics.SpyMessage()  
>>> msg.Data = ics.create_neovi_radio_message(Relay1=True, Relay4=False, _  
    ↪LED6=True, MSB_report_rate=10)  
>>> msg.Data  
(65, 10, 0, 0, 0)
```

`ics.ics.disk_format(device)`

Starts disk formatting on the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics  
>>> d = ics.open_device()  
>>> details = ics.get_disk_details(d)  
>>> details. = ics.get_disk_details(d)  
>>> ics.disk_format(d, details)  
>>>
```

`ics.ics.disk_format_cancel(device)`

Cancel in progress disk formatting on the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics  
>>> d = ics.open_device()  
>>> ics.disk_format(d, details)  
>>> ics.disk_format_cancel(d)  
>>>
```

`ics.ics.enable_bus_voltage_monitor(device, enable, reserved)`

Enable or disable bus voltage monitoring.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`enable (bool): int`

`reserved (int): int: Optional. Should be set to zero. Don't set, if unsure.`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_bus_voltage_monitor(d, 1)
>>>
```

`ics.ics.enable_doip_line(device, enable)`

Activate or De-activate DOIP Line.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`enable (bool): bool`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_doip_line(d, True)
>>>
```

`ics.ics.enable_network_com(device, enable, net_id)`

Enable or disable network communication.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`enable (bool): bool`

`net_id (int): int: Optional. If left blank, disables/enables all networks.`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_network_com(d, True)
>>>
```

`ics.ics.find_devices(device_type=ics.ics.NEODEVICE_ALL)`

Finds all connected devices and returns a tuple of `ics.ics.NeoDevice` for use in `ics.ics.open_device()`

Args: `device_type (int): Accepts ics.ics.NEODEVICE_*` Macros

New in 3.0 (803):

`device_types (List/Tuple): Accepts a Container of ics.ics.NEODEVICE_*` Macros

`network_id (int): OptionsFindNeoEx.CANOptions.iNetworkID. Usually ics.NETID_CAN, if needed`

Raises: `ics.ics.RuntimeError`

Returns: Tuple of `ics.ics.NeoDevice` for use in `ics.ics.open_device()`

```
>>> for device in ics.find_devices():
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

New in 3.0 (803):

```
>>> for device in ics.find_devices([ics.NEODEVICE_FIRE, ics.NEODEVICE_VCAN3]):
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

`ics.ics.firmware_update_required(device)`

Determines if the device firmware needs flashing.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

```
>>> ics.force_firmware_update(device)
True
```

`ics.ics.flash_phy_firmware(device, data, phy_index[, check_success])`

Flashes PHY Firmware. If not sure, don't use this method

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`data (bytes): bytes: data of the firmware binary.`

`phy_index (int): int: phy Index enum.`

`check_success (bool): bool: Optional, raises an exception if not successful`

Raises: `ics.ics.RuntimeError`

Returns: None

`ics.ics.force_firmware_update(device)`

Forces the device to flash firmware.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

```
>>> ics.force_firmware_update(device)
True
```

`ics.ics.generic_api_get_status(device, api_index, instance_index)`

Reads data in a generic way.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`api_index (int): api_index.`

`instance_index (int): instance_index.`

Raises: `ics.ics.RuntimeError`

Returns: tuple of (int): (functionIndex, callbackError, finishedProcessing)

`ics.ics.generic_api_read_data(device, api_index, instance_index[, length])`
Reads data in a generic way.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
api_index (int): api_index.
instance_index (int): instance_index.
function_index (int): function_index.
length (int): (optional) Length of the data to read. defaults to `GENERIC_API_DATA_BUFFER_SIZE`

Raises: `ics.ics.RuntimeError`

Returns: tuple of (functionIndex, data)

`ics.ics.generic_api_send_command(device, api_index, instance_index, function_index, data)`
Sends a command in a generic way.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
api_index (int): api_index.
instance_index (int): instance_index.
function_index (int): function_index.
data (bytes): Data to be passed in.

Raises: `ics.ics.RuntimeError`

Returns: functionError (int): functionError.

`ics.ics.get_active_vnet_channel(device)`
Gets active vnet channel for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Int: Returns active vnet channel.

`ics.ics.get_all_chip_versions(device, api_index, instance_index)`
Get all the chip (firmware) versions of the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: `ics.structures.st_chip_versions.st_chip_versions` (`ics.structures.st_chip_versions.st_chip_versions`)

`ics.ics.get_backup_power_enabled(device)`
Returns the device backup power enabled for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.get_backup_power_ready(device)`
Returns the device backup power is ready for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.get_bus_voltage(device, reserved)`

Reads bus voltage. (`ics.ics.enable_bus_voltage_monitor`) needs to be called first.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

reserved (int): int: Optional. Should be set to zero. Don't set, if unsure.

Raises: `ics.ics.RuntimeError`

Returns: Int: value returned is in mV.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_bus_voltage_monitor(d, 1)
>>> ics.get_bus_voltage(d)
12000
>>>
```

`ics.ics.get_device_settings(device, device_type, vnet_slot)`

Gets the settings in the device. vnet_slot defaults to `ics.ics.PlasmaIonVnetChannelMain`

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

device_type (EDeviceSettingsType): Optional: Overrides default device settings type. Defaults to '-1'

vnet_slot (PlasmaIonVnetChannelMain): Optional: Defaults to `PlasmaIonVnetChannelMain`, Used only for PLASMA/ION Devices.

Raises: `ics.ics.RuntimeError`

Returns: `ics.ics.device_settings`

```
>>> d = ics.open_device()
>>> d.Name
'neoVI ION'
>>> d.SerialNumber
404444
>>> s = ics.get_device_settings(d)
>>> s.DeviceSettingType
2
>>> s.cyan
<ics.CyanSettings object at 0x01E61B40>
>>> s.cyan.canfd1.FDMode
4
>>> s2.cyan
<ics.CyanSettings object at 0x02B113C8>
>>> s2 = ics.get_device_settings(d, -1, ics.PlasmaIonVnetChannelA)
>>> s2.DeviceSettingType
2
>>> s2.cyan.canfd1.FDMode
4
```

`ics.ics.get_device_status(device)`

Returns the device status.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: (`ics.ics.ics_device_status`).

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.get_device_status(d)
>>> status.fire2Status.ethernetActivationLineEnabled
0
```

`ics.ics.get_disk_details(device)`

Returns the device disk details.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: (`ics.ics.srad_gigalog_disk_details`).

```
>>> import ics
>>> d = ics.open_device()
>>> details = ics.get_disk_details(d)
>>> details.structure.options
>>>
```

`ics.ics.get_disk_format_progress(device)`

Returns the device disk formatting progress.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: (`ics.ics.srad_gigalog_disk_format_progress`).

```
>>> import ics
>>> d = ics.open_device()
>>> d = ics.disk_format(d, details)
>>> progress = ics.get_disk_format_progress(d)
>>> progress.sectorsRemaining
>>>
```

`ics.ics.get_dll_firmware_info(device)`

Returns the DLL firmware info for the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: (`ics.ics.st_api_firmware_info`)

```
>>> device = ics.open_device()
>>> info = ics.get_dll_firmware_info(device)
>>> info.iAppMajor
7
>>> info.iAppMinor
55
>>>
```

`ics.ics.get_dll_version(device)`

Gets the DLL version.

Args: None

Raises: `ics.ics.RuntimeError`

Returns: Int: DLL Version

```
>>> ics.get_dll_version()
700
```

ics.ics.get_error_messages (device[,j1850,timeout])
Gets the error message(s) on the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: list of tuple's. :class:`tuple` contents: (error_number, description_short, description_long, severity, restart_needed)

```
>>> device = ics.open_device()
>>> errors = ics.get_error_messages(device)
```

ics.ics.get_gptp_status (device)
Gets the gPTP Status from the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: *ics.structures.gptp_status.gptp_status* (*ics.structures.gptp_status.gptp_status*)

ics.ics.get_hw_firmware_info (device)
Returns the device firmware info for the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: (*ics.ics.st_api_firmware_info*)

```
>>> device = ics.open_device()
>>> info = ics.get_hw_firmware_info(device)
>>> info.iAppMajor
7
>>> info.iAppMinor
55
>>>
```

ics.ics.get_last_api_error (device)
Gets the error message from the last API call.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Tuple: (error, description short, description long, severity, restart needed)

```
>>> device = ics.open_device()
>>> try:
...     msg = ics.coremini_read_tx_message(device, 0)
... except ics.RuntimeError as ex:
...     print(ex)
...     print(ics.get_last_api_error(device))
...
Error: coremini_read_tx_message(): icsneoScriptReadTxMessage() Failed
(224, 'Invalid Message Index for script.', 'Invalid Message Index for script.
˓→', 16, 0)
```

```
ics.ics.get_library_path()
ics.ics.get_messages(device[, j1850, timeout])
```

Gets the message(s) on the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

j1850 (bool): Return *ics.ics.SpyMessageJ1850* instead.

timeout (float): Optional timeout to wait for messages in seconds (0.1 = 100ms).

Raises: *ics.ics.RuntimeError*

Returns: tuple of two items. First item is a tuple of *ics.ics.SpyMessage* and second is the error count.

```
>>> device = ics.open_device()
>>> messages, errors = ics.get_messages(device)
>>> len(messages)
14
>>> hex(messages[0].ArbIDOrHeader)
'0x160'
>>> messages[0].Data
(36, 11, 11, 177, 37, 3, 11, 199)
>>> errors
0
```

```
ics.ics.get_pcb_serial_number(device)
```

Gets the unique PCB serial number of the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: (str): PCB Serial Number

```
>>> import ics
>>> d = ics.open_device()
>>> pcb_sn = ics.get_pcb_serial_number(d)
>>>
```

```
ics.ics.get_performance_parameters(device)
```

Gets the Performance Parameters on *device*.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Tuple on Success: (buffer count, buffer max, overflow count, reserved, reserved, reserved, reserved, reserved)

```
>>> device = ics.open_device()
>>> ics.get_performance_parameters(device)
(0, 24576, 0, 0, 0, 0, 0, 0)
```

```
ics.ics.get_phy_firmware_version(device, phy_index[, check_success])
```

Gets PHY Firmware version. If not sure, don't use this method

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

phy_index (int): int: phy Index enum.

check_success (bool): bool: Optional, raises an exception if not successful

Raises: `ics.ics.RuntimeError`

Returns: None

`ics.ics.get_rtc(device)`

Gets the Real-Time Clock of the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Tuple: (datetime.datetime object, offset in seconds)

```
>>> device = ics.open_device()
>>> ics.get_rtc(device)
(datetime.datetime(2014, 9, 10, 17, 45, 45), 3)
```

`ics.ics.get_script_status()`

Accepts a `ics.ics.NeoDevice`, exception on error. Returns a list of values of what ulParameters would hold

`ics.ics.get_serial_number(device)`

Gets the serial number out of the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Int: Serial Number Version

```
>>> ics.get_serial_number(device)
53123
```

`ics.ics.get_timestamp_for_msg(device, msg)`

Calculates the timestamp for a message.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`msg (ics.ics.SpyMessage): ics.ics.SpyMessage`

Raises: `ics.ics.RuntimeError`

Returns: Float: Timestamp for the message.

```
>>> import ics
>>> d = ics.open_device()
>>> msgs, error_count = ics.get_messages(d)
>>> ics.get_timestamp_for_msg(d, msgs[0])
354577568.9145524
```

`ics.ics.icsneoClosePort()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.close_device()` method.

`ics.ics.icsneoEnableBusVoltageMonitor()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_bus_voltage_monitor()` method.

`ics.ics.icsneoEnableDOIPLine()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_doip_line()` method.

`ics.ics.icsneoEnableNetworkCom()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_network_com()` method.

`ics.ics.icsneoFindNeoDevices()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.find_devices()` method.

`ics.ics.icsneoFirmwareUpdateRequired()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.firmware_update_required()` method.

`ics.ics.icsneoFlashPhyFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.flash_phy_firmware()` method.

`ics.ics.icsneoForceFirmwareUpdate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.force_firmware_update()` method.

`ics.ics.icsneoGenericAPIGetStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.generic_api_get_status()` method.

`ics.ics.icsneoGenericAPIReadData()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.generic_api_read_data()` method.

`ics.ics.icsneoGenericAPISendCommand()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.generic_api_send_command()` method.

`ics.ics.icsneoGetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_active_vnet_channel()` method.

`ics.ics.icsneoGetAllChipVersions()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_all_chip_versions()` method.

`ics.ics.icsneoGetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_enabled()` method.

`ics.ics.icsneoGetBackupPowerReady()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_ready()` method.

`ics.ics.icsneoGetBusVoltage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_bus_voltage()` method.

`ics.ics.icsneoGetDLLFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_firmware_info()` method.

`ics.ics.icsneoGetDLLVersion()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_version()` method.

`ics.ics.icsneoGetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_settings()` method.

`ics.ics.icsneoGetDeviceStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_status()` method.

`ics.ics.icsneoGetErrorMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_error_messages()` method.

`ics.ics.icsneoGetGPTPStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_gptp_status()` method.

`ics.ics.icsneoGetHWFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_hw_firmware_info()` method.

`ics.ics.icsneoGetLastAPIError()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_last_api_error()` method.

`ics.ics.icsneoGetMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_messages()` method.

`ics.ics.icsneoGetPCBSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_pcb_serial_number()` method.

`ics.ics.icsneoGetPerformanceParameters()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_performance_parameters()` method.

`ics.ics.icsneoGetPhyFwVersion()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_phy_firmware_version()` method.

`ics.ics.icsneoGetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_rtc()` method.

`ics.ics.icsneoGetSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_serial_number()` method.

`ics.ics.icsneoGetTimeStampForMsg()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_timestamp_for_msg()` method.

`ics.ics.icsneoISO15765_DisableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_disable_networks()` method.

`ics.ics.icsneoISO15765_EnableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_enable_networks()` method.

`ics.ics.icsneoISO15765_ReceiveMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.ics.icsneoISO15765_TransmitMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.ics.icsneoIsDeviceFeatureSupported()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.is_device_feature_supported()` method.

`ics.ics.icsneoLoadDefaultSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.load_default_settings()` method.

`ics.ics.icsneoOpenNeoDevice()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.open_device()` method.

`ics.ics.icsneoReadJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_jupiter_firmware()` method.

`ics.ics.icsneoReadSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_sdcard()` method.

`ics.ics.icsneoRequestDiskDetails()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_details()` method.

`ics.ics.icsneoRequestDiskFormat()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format()` method.

`ics.ics.icsneoRequestDiskFormatCancel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format_cancel()` method.

`ics.ics.icsneoRequestDiskFormatProgress()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_format_progress()` method.

`ics.ics.icsneoRequestEnterSleepMode()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.request_enter_sleep_mode()` method.

`ics.ics.icsneoScriptClear()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_clear()` method.

`ics.ics.icsneoScriptGetFBlockStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_fblock_status()` method.

`ics.ics.icsneoScriptGetScriptStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_status()` method.

`ics.ics.icsneoScriptGetScriptStatusEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_script_status()` method.

`ics.ics.icsneoScriptLoad()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_load()` method.

`ics.ics.icsneoScriptReadAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_app_signal()` method.

`ics.ics.icsneoScriptReadRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_rx_message()` method.

`ics.ics.icsneoScriptReadTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_tx_message()` method.

`ics.ics.icsneoScriptStart()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start()` method.

`ics.ics.icsneoScriptStartFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start_fblock()` method.

`ics.ics.icsneoScriptStop()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop()` method.

`ics.ics.icsneoScriptStopFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop_fblock()` method.

`ics.ics.icsneoScriptWriteAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_app_signal()` method.

`ics.ics.icsneoScriptWriteRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_rx_message()` method.

`ics.ics.icsneoScriptWriteTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_tx_message()` method.

`ics.ics.icsneoSetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_active_vnet_channel()` method.

`ics.ics.icsneoSetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_backup_power_enabled()` method.

`ics.ics.icsneoSetBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate()` method.

`ics.ics.icsneoSetBitRateEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate_ex()` method.

`ics.ics.icsneoSetContext()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_context()` method.

`ics.ics.icsneoSetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_device_settings()` method.

`ics.ics.icsneoSetFDBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_fd_bit_rate()` method.

`ics.ics.icsneoSetLedProperty()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_led_property()` method.

`ics.ics.icsneoSetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_rtc()` method.

`ics.ics.icsneoSetReflashDisplayCallbacks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_reflash_callback()` method.

`ics.ics.icsneoStartDHCPServer()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.start_dhcp_server()` method.

`ics.ics.icsneoStopDHCPServer()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.stop_dhcp_server()` method.

`ics.ics.icsneoTxMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.transmit_messages()` method.

`ics.ics.icsneoUartGetBaudrate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_get_baudrate()` method.

`ics.ics.icsneoUartRead()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_read()` method.

`ics.ics.icsneoUartSetBaudrate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_set_baudrate()` method.

`ics.ics.icsneoUartWrite()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_write()` method.

`ics.ics.icsneoValidateHObject()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.validate_hobject()` method.

`ics.ics.icsneoWriteJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_jupiter_firmware()` method.

`ics.ics.icsneoWriteSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_sdcard()` method.

`ics.ics.icsneowBMSManagerReset()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.wbms_manager_reset()` method.

`ics.ics.icsneowBMSManagerWriteLock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.wbms_manager_write_lock()` method.

`ics.ics.is_device_feature_supported(device, feature)`

Polls firmware in device to see if the feature is supported. As of 908 only ValueCAN4-2EL, ValueCAN4-4 and ValueCAN4-Industrial are supported.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`enable (DeviceFeature): DeviceFeature`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> from ics.structures.device_feature import DeviceFeature
>>> d = ics.open_device()
>>> supported = ics.is_device_feature_supported(d, DeviceFeature.
...networkTerminationDWCAN01)
>>>
```

ics.ics.iso15765_disable_networks (device)

Disables ISO15765 networks.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: None

ics.ics.iso15765_enable_networks (device, networks)

Enables ISO15765 networks.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: None

ics.ics.iso15765_receive_message (device, netid, rx_msg)

Setup rx ISO15765 Message.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

prx_msg	(<i>ics.ics.st_cm_iso157652_rx_message</i>):	<i>ics.ics.</i>
	<i>st_cm_iso157652_rx_message</i>	

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

ics.ics.iso15765_transmit_message (device, ulNetworkID, pMsg, ulBlockingTimeout)

Transmits an ISO15765 Message.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

pMsg	(<i>ics.ics.st_cm_iso157652_tx_message</i>):	<i>ics.ics.</i>
	<i>st_cm_iso157652_tx_message</i>	

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

ics.ics.load_default_settings (device)

Load the default settings in the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> device = ics.open_device()
>>> ics.load_default_settings(device)
>>>
```

ics.ics.open_device (device)

Opens the device. *device* can be omitted to return a *ics.ics.NeoDevice* of the first free available device, a *ics.ics.NeoDevice*, or a serial number of the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

device (int): Serial Number of the device

network_ids (List/Tuple): This is an array of number IDs which specify the NetworkID parameter of each network. This allows you to assign a custom network ID to each network. Normally, you will assign consecutive IDs to each of the networks. See NetworkIDList for a list of current network ID's. You may also set this parameter to NULL (zero) and the default network ID's will be used.

config_read (int): Specifies whether the DLL should read the neoVI's device configuration before enabling the device. It is recommended that this value be set to 1.

options (int): DEVICE_OPTION_* defines

network_id (int): OptionsFindNeoEx.CANOptions.iNetworkID. Usually ics.NETID_CAN, if needed

use_server (int): Defaults to False, Setting to True allows opening the same device more than once.

Raises: `ics.ics.RuntimeError`

Returns: If `ics.ics.NeoDevice` is passed as a parameter, None. If serial number is passed as a parameter, a `ics.ics.NeoDevice` will be returned. If `device` parameter is omitted, a `ics.ics.NeoDevice` will be returned with the first available free device.

```
>>> for device in ics.find_devices():
...     ics.open_device(device)
...
```

Note: `ics.ics.NeoDevice` will automatically close the device when it goes out of scope.

`ics.ics.override_library_name(new_name)`

Overrides the default search for loading the icsneo40 library

Args: name: Absolute path or relative path including filename.

Raises: `ics.ics.RuntimeError`

Returns: None

```
>>> import ics
>>> ics.find_devices()
Traceback (most recent call last):
  File "<stdin>", line 1, in <module>
ics.RuntimeError: Error: find_devices(): Failed to open library: 'icsneo40.dll'
-> with error code: #126
>>> ics.override_library_name(r"C:\Windows\SysWOW64\icsneo40-different.dll")
>>> ics.find_devices()
(<ics.NeoDevice object at 0x00284C50>, <ics.NeoDevice object at 0x007C9A10>)
```

`ics.ics.read_jupiter_firmware(device, size[, vnetChannel])`

Reads firmware binary from a RAD-Jupiter. If not sure, don't use this method

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

size (int): int: size of the bytes to read of the firmware binary.

vnetChannel (int): int: Optional. Don't set, if unsure.

Raises: `ics.ics.RuntimeError`

Returns: None

ics.ics.read_sdcard()

icsneoReadSDCard(), Accepts a ics.ics.NeoDevice and sector index. Returns a bytearray of 512 bytes max. Exception on error.

ics.ics.request_enter_sleep_mode (device, timeout_ms, mode, reserved_zero)

Signal neoVI to immediate go to sleep. Currently only supported by FIREVNET/PLASMA. If using over USB this will likely return true but never cause PLASMA to sleep since USB insertion keeps it alive. This API allows Android/Linux applications to invoke power management.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

timeout_ms (int): 16bit word for how long to wait on idle bus before going to sleep. If caller does not want to change it pass in 65535 (0xFFFF) and it will stay whatever it was set to in explorer/coremini.

mode (int): 16bit word for power mode to enter. If caller does not want to change it pass in 65535 (0xFFFF) and it will stay whatever it was set to in explorer/coremini. If it is zero then neoVI will do ‘normal sleep’. 0 - power mode off but calling this function will do ‘normal sleep’. 1 - normal sleep. 2 - instant sleep. 3 - comatose sleep.

reserved_zero (int): Reserved, Keep as zero.

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

```
>>> ics.request_enter_sleep_mode(device, 1, 0)
True
```

ics.ics.set_active_vnet_channel (device, channel)

Sets active vnet channel for the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

ics.ics.set_backup_power_enabled (device, enable)

Sets the device backup power enabled for the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

ics.ics.set_bit_rate (device, BitRate, NetworkID)

Specifies bit rate setting. Valid values depend on the network specified.

For the networks NETID_HSCAN, NETID_MSCAN, NETID_SWCAN, NETID_FIRE_HSCAN2, NETID_HSCAN3, NETID_LSFTCAN, valid bit rates are 2000, 33333, 50000, 62500, 83333, 100000, 125000, 250000, 500000, 800000, 1000000

For the networks NETID_LIN, NETID_ISO2, NETID_FIRE_LIN2, NETID_FIRE_LIN3, NETID_FIRE_LIN4, valid bit rates are

For the network NETID_FIRE_CGI valid bit rates are 625000 and 115200

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Int: None.

`ics.ics.set_bit_rate_ex(device, BitRate, NetworkID, iOptions)`
Sets the bitrate for a given Network ID on the device with extended options.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Int: None.

`ics.ics.set_context(device)`

Sets the “context” of how icsneoFindNeoDevices(Ex) and icsneoOpenNeoDevice(Ex) function. If the context is 0 (null) than icsneoFindNeoDevices(Ex) will be system wide, searching USB and other supported computer interfaces. icsneoFindNeoDevices can then be used to connect to devices found in this manner. If the context is a handle to connected CAN tool than icsneoFindNeoDevices(Ex) will search a specific CAN bus for supported IntrepidCS CAN Nodes. Again icsneoOpenNeoDevice(Ex) would be used create logical connections to found CAN Nodes.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

```
>>> ics.set_context(device)
True
```

`ics.ics.set_device_settings(device, settings, save_to_eeprom, vnet_slot)`

Sets the settings in the device. vnet_slot defaults to ics.ics.PlasmaIonVnetChannelMain

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`settings (ics.ics.device_settings): ics.ics.device_settings`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> d = ics.open_device()
>>> d.Name
'neoVI ION'
>>> d.SerialNumber
404444
>>> s = ics.get_device_settings(d, ics.PlasmaIonVnetChannelA) # Get Slave_
˓→settings, channel selection not needed if not a Plasma/Ion
>>> s.DeviceSettingType
2
>>> s.cyan.can_switch_mode
1
>>> s.cyan.can_switch_mode = 2
>>> ics.set_device_settings(d, s, True, ics.PlasmaIonVnetChannelA)
>>>
```

`ics.ics.set_fd_bit_rate(device, BitRate, NetworkID)`

Sets the FD bitrate for a given Network ID on the device..

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Int: None.

`ics.ics.set_led_property(device, led, prop, value)`

Sets the LED property on the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

led (int): Index or position of the LED

prop (int): Property of the LED

value (int): Value of the LED Property

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> ics.set_led_property(d, TODO, TODO, TODO)
>>>
```

`ics.ics.set_reflash_callback(callback)`

Sets the reflash display callback.

Args: callback (function): Must be a callable Python function (`def callback(msg, progress)`)

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> def callback(msg, progress):
...     print(msg, progress)
...
>>> ics.set_reflash_callback(callback)
>>>
```

`ics.ics.set_rtc(device[, time])`

Sets the Real-Time Clock of the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

time (`datetime.datetime`): Optional. Sets to current time, if omitted.

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.set_rtc(device)
```

`ics.ics.start_dhcp_server(device, network_id, device_ip_address, subnet_mask, gateway, start_address, end_address, overwrite_dhcp_settings, lease_time, reserved)`

Starts a DHCP Server.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

network_id (int): NetworkID

device_ip_address (str): Device IP Address

subnet_mask (str): Subnet Mask

gateway (str): Gateway

start_address (str): Start Address

end_address (str): End Address

overwrite_dhcp_settings (bool): Overwrite DHCP Settings

lease_time (int): Lease time
reserved (int): (Optional) Reserved, set to 0

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> ics.start_dhcp_server(d, TODO)
>>>
```

`ics.ics.stop_dhcp_server(device, network_id)`

Stops the DHCP Server

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

network_id (int): NetworkID

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> ics.stop_dhcp_server(d, TODO)
>>>
```

`ics.ics.transmit_messages(device, messages)`

Transmits message(s) on the device. `messages` can be a tuple of `ics.ics.SpyMessage`

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

messages (`ics.ics.SpyMessage`): `ics.ics.SpyMessage`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> msg = ics.SpyMessage()
>>> msg.ArbitIDOrHeader = 0xFF
>>> msg.NetworkID = ics.NETID_HSCAN
>>> msg.Data = (0,1,2,3,4,5,6,7)
>>> ics.transmit_messages(device, msg)
>>>
```

`ics.ics.uart_get_baudrate(device, port)`

Gets the UART baudrate on the given port.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

port (`ics.ics.structures.e_uart_port_t.e_uart_port_t`): `ics.ics.structures.e_uart_port_t.e_uart_port_t`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> from ics.structures.e_uart_port_t import e_uart_port_t
>>> d = ics.open_device()
```

(continues on next page)

(continued from previous page)

```
>>> baudrate = ics.uart_set_baudrate(d, e_uart_port_t.eUART0)
>>>
```

ics.ics.uart_read(device, port, bytes_to_read, flags)

Reads UART on the given port.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*port (*ics.ics.structures.e_uart_port_t.e_uart_port_t*): *ics.ics.structures.e_uart_port_t.e_uart_port_t*

bytes_to_read (int): Optional. How many bytes to read from the UART, 256 if omitted.

flags (int): Optional. Flags to be used. Don't use if unsure.

Raises: *ics.ics.RuntimeError***Returns:** None.

```
>>> import ics
>>> from ics.structures.e_uart_port_t import e_uart_port_t
>>> d = ics.open_device()
>>> data = ics.uart_read(d, e_uart_port_t.eUART0)
>>> print(f"Read {len(data)} bytes: {data}")
>>>
```

ics.ics.uart_set_baudrate(device, port, baudrate)

Sets the UART baudrate on the given port.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*port (*ics.ics.structures.e_uart_port_t.e_uart_port_t*): *ics.ics.structures.e_uart_port_t.e_uart_port_t*

baudrate (int): Baudrate of the UART to set.

Raises: *ics.ics.RuntimeError***Returns:** None.

```
>>> import ics
>>> from ics.structures.e_uart_port_t import e_uart_port_t
>>> d = ics.open_device()
>>> ics.uart_set_baudrate(d, e_uart_port_t.eUART0, 115200)
>>> print(f"Read {len(data)} bytes: {data}")
>>>
```

ics.ics.uart_write(device, port, data, flags)

Writes UART on the given port

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*port (*ics.ics.structures.e_uart_port_t.e_uart_port_t*): *ics.ics.structures.e_uart_port_t.e_uart_port_t*

data (bytes): bytes

Raises: *ics.ics.RuntimeError***Returns:** None.

```
>>> import ics
>>> from ics.structures.e_uart_port_t import e_uart_port_t
>>> d = ics.open_device()
>>> ics uart_write(d, e_uart_port_t.eUART0, b'my uart data goes here')
>>>
```

ics.ics.validate_hobject (device)

Validates the handle is valid for a *device*. Handles are only valid when the device is open.

Args: *device* (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

or:

device (int): c style integer handle to the device.

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True if valid, false otherwise.

```
>>> device = ics.open_device()
>>> ics.validate_hobject(device)
1
>>> ics.validate_hobject(device._Handle)
1
```

ics.ics.wBMSManagerReset ()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.wbms_manager_reset ()* method.

ics.ics.wBMSManagerWriteLock ()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.wbms_manager_write_lock ()* method.

ics.ics.wbms_manager_reset (*device, manager*)

Resets the manager

Args: *device* (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

manager (*ics.ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t*):
ics.ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> from ics.structures.ew_bms_manager_port_t import ew_bms_manager_port_t
>>> d = ics.open_device()
>>> ics.wbms_manager_reset(d, ew_bms_manager_port_t.eManagerPortA.value)
>>>
```

ics.ics.wbms_manager_write_lock (*device, manager, lock_state*)

Sets the lock state on the manager

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
manager (`ics.ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t`):
`ics.ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t`
lock_state (`ics.ics.structures.ew_bms_manager_lock_state_t.ew_bms_manager_lock_state_t`):
`ics.ics.structures.ew_bms_manager_lock_state_t.ew_bms_manager_lock_state_t`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> from ics.structures.ew_bms_manager_port_t import ew_bms_manager_port_t
>>> from ics.structures.ew_bms_manager_lock_state_t import ew_bms_manager_
    lock_state_t
>>> d = ics.open_device()
>>> ics.wbms_manager_write_lock(d, ew_bms_manager_port_t.eManagerPortA.value,_
    ew_bms_manager_lock_state_t.eLockManager.value)
>>>
```

`ics.ics.write_jupiter_firmware(device, bytes[, vnetChannel])`
 Writes firmware binary to a RAD-Jupiter. If not sure, don't use this method

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
bytes (bytes): bytes: bytes of the firmware binary.
vnetChannel (int): int: Optional. Don't set, if unsure.

Raises: `ics.ics.RuntimeError`
Returns: None

`ics.ics.write_sdcard()`
 icsneoReadSDCard(), Accepts a ics.ics.NeoDevice, sector index, and a bytearray of 512 bytes. Exception on error.

CHAPTER 8

Module Functions

`ics.ISO15765_DisableNetworks`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_disable_networks()` method.

`ics.ISO15765_EnableNetworks`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_enable_networks()` method.

`ics.ISO15765_ReceiveMessage`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.ISO15765_TransmitMessage`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.close_device(device)`

Closes the device.

`ics.coremini_clear(device, location)`

Clears the CoreMini into the device.

Continued on next page

Table 1 – continued from previous page

<code>ics.coremini_get_fblock_status(device, index)</code>	Gets the status of a Coremini Function Block at <i>index</i> on <i>device</i> .
<code>ics.coremini_get_status(device)</code>	Gets the status of the CoreMini in the device.
<code>ics.coremini_load(device, coremini, location)</code>	Loads the CoreMini into the device.
<code>ics.coremini_read_app_signal(device, index)</code>	Gets the value of a Coremini application signal at <i>index</i> on <i>device</i> .
<code>ics.coremini_read_rx_message(device, index)</code>	Gets the value of a Coremini Message at <i>index</i> on <i>device</i> .
<code>ics.coremini_read_tx_message(device, index)</code>	Gets the value of a Coremini Message at <i>index</i> on <i>device</i> .
<code>ics.coremini_start(device, location)</code>	Starts the CoreMini into the device.
<code>ics.coremini_start_fblock(device, index)</code>	Starts a Coremini Function Block at <i>index</i> on <i>device</i> .
<code>ics.coremini_stop(device)</code>	Stops the CoreMini into the device.
<code>ics.coremini_stop_fblock(device, index)</code>	Stops a Coremini Function Block at <i>index</i> on <i>device</i> .
<code>ics.coremini_write_app_signal(device, index, ...)</code>	Sets the value of a Coremini application signal at <i>index</i> on <i>device</i> .
<code>ics.coremini_write_rx_message(device, index, ...)</code>	TODO
<code>ics.coremini_write_tx_message(device, index, msg)</code>	TODO
<code>ics.create_neovi_radio_message(Relay1, ...)</code>	Python API only.
<code>ics.disk_format(device)</code>	Starts disk formatting on the device.
<code>ics.disk_format_cancel(device)</code>	Cancel in progress disk formatting on the device.
<code>ics.enable_bus_voltage_monitor(device, ...)</code>	Enable or disable bus voltage monitoring.
<code>ics.enable_doipl_line(device, enable)</code>	Activate or De-activate DOIP Line.
<code>ics.enable_network_com(device, net_id)</code>	enable, Enable or disable network communication.
<code>ics.find_devices([device_type])</code>	Finds all connected devices and returns a tuple of <code>ics.ics.NeoDevice</code> for use in <code>ics.ics.open_device()</code>
<code>ics.firmware_update_required(device)</code>	Determines if the device firmware needs flashing.
<code>ics.flash_phy_firmware(device, data, ...)</code>	Flashes PHY Firmware.
<code>ics.force_firmware_update(device)</code>	Forces the device to flash firmware.
<code>ics.generic_api_get_status(device, ...)</code>	Reads data in a generic way.
<code>ics.generic_api_read_data(device, api_index, ...)</code>	Reads data in a generic way.
<code>ics.generic_api_send_command(device, ...)</code>	Sends a command in a generic way.
<code>ics.get_active_vnet_channel(device)</code>	Gets active vnet channel for the device.
<code>ics.get_all_chip_versions(device, api_index, ...)</code>	Get all the chip (firmware) versions of the device.
<code>ics.get_backup_power_enabled(device)</code>	Returns the device backup power enabled for the device.
<code>ics.get_backup_power_ready(device)</code>	Returns the device backup power is ready for the device.
<code>ics.get_bus_voltage(device, reserved)</code>	Reads bus voltage.
<code>ics.get_device_settings(device, device_type, ...)</code>	Gets the settings in the device.
<code>ics.get_device_status(device)</code>	Returns the device status.
<code>ics.get_disk_details(device)</code>	Returns the device disk details.
<code>ics.get_disk_format_progress(device)</code>	Returns the device disk formatting progress.
<code>ics.get_dll_firmware_info(device)</code>	Returns the DLL firmware info for the device.

Continued on next page

Table 1 – continued from previous page

<code>ics.get_dll_version(device)</code>	Gets the DLL version.
<code>ics.get_error_messages(device[, j1850, timeout])</code>	Gets the error message(s) on the device.
<code>ics.get_gptp_status(device)</code>	Gets the gPTP Status from the device.
<code>ics.get_hw_firmware_info(device)</code>	Returns the device firmware info for the device.
<code>ics.get_last_api_error(device)</code>	Gets the error message from the last API call.
<code>ics.get_library_path</code>	
<code>ics.get_messages(device[, j1850, timeout])</code>	Gets the message(s) on the device.
<code>ics.get_pcb_serial_number(device)</code>	Gets the unique PCB serial number of the device.
<code>ics.get_performance_parameters(device)</code>	Gets the Performance Parameters on <i>device</i> .
<code>ics.get_phy_firmware_version(device, ...)</code>	Gets PHY Firmware version.
<code>ics.get_rtc(device)</code>	Gets the Real-Time Clock of the device.
<code>ics.get_script_status</code>	Accepts a <code>ics.ics.NeoDevice</code> , exception on error.
<code>ics.get_serial_number(device)</code>	Gets the serial number out of the device.
<code>ics.get_timestamp_for_msg(device, msg)</code>	Calculates the timestamp for a message.
<code>ics.is_device_feature_supported(device, feature)</code>	Polls firmware in device to see if the feature is supported.
<code>ics.iso15765_disable_networks(device)</code>	Disables ISO15765 networks.
<code>ics.iso15765_enable_networks(device, networks)</code>	Enables ISO15765 networks.
<code>ics.iso15765_receive_message(device, netid, ...)</code>	Setup rx ISO15765 Message.
<code>ics.iso15765_transmit_message(device, ...)</code>	Transmits an ISO15765 Message.
<code>ics.load_default_settings(device)</code>	Load the default settings in the device.
<code>ics.open_device(device)</code>	Opens the device.
<code>ics.override_library_name(new_name)</code>	Overrides the default search for loading the <code>icsneo40</code> library
<code>ics.read_jupiter_firmware(device, size, ...)</code>	Reads firmware binary from a RAD-Jupiter.
<code>ics.read_sdcard</code>	<code>icsneoReadSDCard()</code> , Accepts a <code>ics.ics.NeoDevice</code> and sector index.
<code>ics.request_enter_sleep_mode(device, ...)</code>	Signal neoVI to immediate go to sleep.
<code>ics.set_active_vnet_channel(device, channel)</code>	Sets active vnet channel for the device.
<code>ics.set_backup_power_enabled(device, enable)</code>	Sets the device backup power enabled for the device.
<code>ics.set_bit_rate(device, BitRate, NetworkID)</code>	Specifies bit rate setting.
<code>ics.set_bit_rate_ex(device, BitRate, ...)</code>	Sets the bitrate for a given Network ID on the device with extended options.
<code>ics.set_context(device)</code>	Sets the “context” of how <code>icsneoFindNeoDevices(Ex)</code> and <code>icsneoOpenNeoDevice(Ex)</code> function.
<code>ics.set_device_settings(device, settings, ...)</code>	Sets the settings in the device.
<code>ics.set_fd_bit_rate(device, BitRate, NetworkID)</code>	Sets the FD bitrate for a given Network ID on the device..
<code>ics.set_led_property(device, led, prop, value)</code>	Sets the LED property on the device.
<code>ics.set_reflash_callback(callback)</code>	Sets the reflash display callback.
<code>ics.set_rtc(device[, time])</code>	Sets the Real-Time Clock of the device.
<code>ics.start_dhcp_server(device, network_id, ...)</code>	Starts a DHCP Server.
<code>ics.stop_dhcp_server(device, network_id)</code>	Stops the DHCP Server
<code>ics.transmit_messages(device, messages)</code>	Transmits message(s) on the device.

Continued on next page

Table 1 – continued from previous page

<code>ics.uart_get_baudrate(device, port)</code>	Gets the UART baudrate on the given port.
<code>ics.uart_read(device, port, bytes_to_read, flags)</code>	Reads UART on the given port.
<code>ics.uart_set_baudrate(device, port, baudrate)</code>	Sets the UART baudrate on the given port.
<code>ics.uart_write(device, port, data, flags)</code>	Writes UART on the given port
<code>ics.validate_hobject(device)</code>	Validates the handle is valid for a <i>device</i> .
<code>ics.wbms_manager_reset(device, manager)</code>	Resets the manager
<code>ics.wbms_manager_write_lock(device, manager, ...)</code>	Sets the lock state on the manager
<code>ics.write_jupiter_firmware(device, bytes, ...)</code>	Writes firmware binary to a RAD-Jupiter.
<code>ics.write_sdcard</code>	<code>icsneoReadSDCard()</code> , Accepts a <code>ics.ics.NeoDevice</code> , sector index, and a bytarray of 512 bytes.
<code>ics.ClosePort</code>	
	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.close_device()</code> method.
<code>ics.EnableBusVoltageMonitor</code>	
	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_bus_voltage_monitor()</code> method.
<code>ics.EnableDOIPLine</code>	
	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_doip_line()</code> method.
<code>ics.EnableNetworkCom</code>	
	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_network_com()</code> method.
<code>ics.FindNeoDevices</code>	
	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.find_devices()</code> method.
<code>ics.FirmwareUpdateRequired</code>	
	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.firmware_update_required()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.FlashPhyFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.flash_phy_firmware()</code> method.
<code>ics.ForceFirmwareUpdate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.force_firmware_update()</code> method.
<code>ics.GenericAPIGetStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_get_status()</code> method.
<code>ics.GenericAPIReadData</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_read_data()</code> method.
<code>ics.GenericAPISendCommand</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_send_command()</code> method.
<code>ics.GetActiveVNETChannel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_active_vnet_channel()</code> method.
<code>ics.GetAllChipVersions</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_all_chip_versions()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.GetBackupPowerEnabled</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_enabled()</code> method.
<code>ics.GetBackupPowerReady</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_ready()</code> method.
<code>ics.GetBusVoltage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_bus_voltage()</code> method.
<code>ics.GetDLLFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_firmware_info()</code> method.
<code>ics.GetDLLVersion</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_version()</code> method.
<code>ics.GetDeviceSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_settings()</code> method.
<code>ics.GetDeviceStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_status()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.GetErrorMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_error_messages()</code> method.
<code>ics.GetGPTPStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_gptp_status()</code> method.
<code>ics.GetHWFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_hw_firmware_info()</code> method.
<code>ics.GetLastError</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_last_api_error()</code> method.
<code>ics.GetMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_messages()</code> method.
<code>ics.GetPCBSerialNumber</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_pcb_serial_number()</code> method.
<code>ics.GetPerformanceParameters</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_performance_parameters()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.GetPhyFwVersion</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_phy_firmware_version()</code> method.
<code>ics.GetRTC</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_RTC()</code> method.
<code>ics.GetSerialNumber</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_serial_number()</code> method.
<code>ics.GetTimeStampForMsg</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_timestamp_for_msg()</code> method.
<code>ics.IsDeviceFeatureSupported</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.is_device_feature_supported()</code> method.
<code>ics.LoadDefaultSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.load_default_settings()</code> method.
<code>ics.OpenNeoDevice</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.open_device()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.ReadJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_jupiter_firmware()</code> method.
<code>ics.ReadSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_sdcard()</code> method.
<code>ics.RequestDiskDetails</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_details()</code> method.
<code>ics.RequestDiskFormat</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format()</code> method.
<code>ics.RequestDiskFormatCancel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format_cancel()</code> method.
<code>ics.RequestDiskFormatProgress</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_format_progress()</code> method.
<code>ics.RequestEnterSleepMode</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.request_enter_sleep_mode()</code> method.
<code>ics.ScriptClear</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_clear()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.ScriptGetFBlockStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_fblock_status()</code> method.
<code>ics.ScriptGetScriptStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_status()</code> method.
<code>ics.ScriptGetScriptStatusEx</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_script_status()</code> method.
<code>ics.ScriptLoad</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_load()</code> method.
<code>ics.ScriptReadAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_app_signal()</code> method.
<code>ics.ScriptReadRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_rx_message()</code> method.
<code>ics.ScriptReadTxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_tx_message()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.ScriptStart</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start()</code> method.
<code>ics.ScriptStartFBBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start_fblock()</code> method.
<code>ics.ScriptStop</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop()</code> method.
<code>ics.ScriptStopFBBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop_fblock()</code> method.
<code>ics.ScriptWriteAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_app_signal()</code> method.
<code>ics.ScriptWriteRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_rx_message()</code> method.
<code>ics.ScriptWriteTxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_tx_message()</code> method.

Continued on next page

Table 1 – continued from previous page

ics.SetActiveVNETChannel	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_active_vnet_channel()</i> method.
ics.SetBackupPowerEnabled	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_backup_power_enabled()</i> method.
ics.SetBitRate	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_bit_rate()</i> method.
ics.SetBitRateEx	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_bit_rate_ex()</i> method.
ics.SetContext	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_context()</i> method.
ics.SetDeviceSettings	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_device_settings()</i> method.
ics.SetFDBitRate	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_fd_bit_rate()</i> method.
ics.SetLedProperty	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_led_property()</i> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.SetRTC</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_rtc()</code> method.
<code>ics.SetReflashDisplayCallback</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_reflash_callback()</code> method.
<code>ics.StartDHCPServer</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.start_dhcp_server()</code> method.
<code>ics.StopDHCPServer</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.stop_dhcp_server()</code> method.
<code>ics.TxMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.transmit_messages()</code> method.
<code>ics.UartGetBaudrate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_get_baudrate()</code> method.
<code>ics.UartRead</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_read()</code> method.
<code>ics.UartSetBaudrate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_set_baudrate()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.UartWrite</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_write()</code> method.
<code>ics.ValidateHObject</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.validate_hobject()</code> method.
<code>ics.WriteJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.write_jupiter_firmware()</code> method.
<code>ics.WriteSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.write_sdcard()</code> method.
<code>ics.base36enc(serial)</code>	Converts a decimal serial number to base36.
<code>ics.wBMSManagerReset</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.wbms_manager_reset()</code> method.
<code>ics.wBMSManagerWriteLock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.wbms_manager_write_lock()</code> method.
<code>ics.icsneoClosePort</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.close_device()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoEnableBusVoltageMonitor</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_bus_voltage_monitor()</code> method.
<code>ics.icsneoEnableDOIPLine</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_doip_line()</code> method.
<code>ics.icsneoEnableNetworkCom</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_network_com()</code> method.
<code>ics.icsneoFindNeoDevices</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.find_devices()</code> method.
<code>ics.icsneoFirmwareUpdateRequired</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.firmware_update_required()</code> method.
<code>ics.icsneoFlashPhyFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.flash_phy_firmware()</code> method.
<code>ics.icsneoForceFirmwareUpdate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.force_firmware_update()</code> method.

Continued on next page

Table 1 – continued from previous page

ics.icsneoGenericAPIGetStatus	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_get_status()</code> method.</p>
ics.icsneoGenericAPIReadData	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_read_data()</code> method.</p>
ics.icsneoGenericAPISendCommand	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_send_command()</code> method.</p>
ics.icsneoGetActiveVNETChannel	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_active_vnet_channel()</code> method.</p>
ics.icsneoGetAllChipVersions	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_all_chip_versions()</code> method.</p>
ics.icsneoGetBackupPowerEnabled	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_enabled()</code> method.</p>
ics.icsneoGetBackupPowerReady	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_ready()</code> method.</p>

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoGetBusVoltage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_bus_voltage()</code> method.
<code>ics.icsneoGetDLLFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_firmware_info()</code> method.
<code>ics.icsneoGetDLLVersion</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_version()</code> method.
<code>ics.icsneoGetDeviceSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_settings()</code> method.
<code>ics.icsneoGetDeviceStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_status()</code> method.
<code>ics.icsneoGetErrorMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_error_messages()</code> method.
<code>ics.icsneoGetGPTPStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_gptp_status()</code> method.
<code>ics.icsneoGetHWFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_hw_firmware_info()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoGetLastError</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_last_api_error()</code> method.
<code>ics.icsneoGetMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_messages()</code> method.
<code>ics.icsneoGetPCBSerialNumber</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_pcb_serial_number()</code> method.
<code>ics.icsneoGetPerformanceParameters</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_performance_parameters()</code> method.
<code>ics.icsneoGetPhyFwVersion</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_phy_firmware_version()</code> method.
<code>ics.icsneoGetRTC</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_rtc()</code> method.
<code>ics.icsneoGetSerialNumber</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_serial_number()</code> method.

Continued on next page

Table 1 – continued from previous page

`ics.icsneoGetTimeStampForMsg`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_timestamp_for_msg()` method.

`ics.icsneoISO15765_DisableNetworks`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_disable_networks()` method.

`ics.icsneoISO15765_EnableNetworks`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_enable_networks()` method.

`ics.icsneoISO15765_ReceiveMessage`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.icsneoISO15765_TransmitMessage`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.icsneoIsDeviceFeatureSupported`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.is_device_feature_supported()` method.

`ics.icsneoLoadDefaultSettings`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.load_default_settings()` method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoOpenNeoDevice</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.open_device()</code> method.
<code>ics.icsneoReadJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_jupiter_firmware()</code> method.
<code>ics.icsneoReadSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_sdcard()</code> method.
<code>ics.icsneoRequestDiskDetails</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_details()</code> method.
<code>ics.icsneoRequestDiskFormat</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format()</code> method.
<code>ics.icsneoRequestDiskFormatCancel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format_cancel()</code> method.
<code>ics.icsneoRequestDiskFormatProgress</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_format_progress()</code> method.
<code>ics.icsneoRequestEnterSleepMode</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.request_enter_sleep_mode()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoScriptClear</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_clear()</code> method.
<code>ics.icsneoScriptGetFBlockStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_fblock_status()</code> method.
<code>ics.icsneoScriptGetScriptStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_status()</code> method.
<code>ics.icsneoScriptGetScriptStatusEx</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_script_status()</code> method.
<code>ics.icsneoScriptLoad</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_load()</code> method.
<code>ics.icsneoScriptReadAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_app_signal()</code> method.
<code>ics.icsneoScriptReadRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_rx_message()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoScriptReadTxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_tx_message()</code> method.
<code>ics.icsneoScriptStart</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start()</code> method.
<code>ics.icsneoScriptStartFBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start_fblock()</code> method.
<code>ics.icsneoScriptStop</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop()</code> method.
<code>ics.icsneoScriptStopFBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop_fblock()</code> method.
<code>ics.icsneoScriptWriteAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_app_signal()</code> method.
<code>ics.icsneoScriptWriteRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_rx_message()</code> method.

Continued on next page

Table 1 – continued from previous page

`ics.icsneoScriptWriteTxMessage`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_tx_message()` method.

`ics.icsneoSetActiveVNETChannel`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_active_vnet_channel()` method.

`ics.icsneoSetBackupPowerEnabled`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_backup_power_enabled()` method.

`ics.icsneoSetBitRate`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate()` method.

`ics.icsneoSetBitRateEx`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate_ex()` method.

`ics.icsneoSetContext`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_context()` method.

`ics.icsneoSetDeviceSettings`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_device_settings()` method.

`ics.icsneoSetFDBitRate`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_fd_bit_rate()` method.

Continued on next page

Table 1 – continued from previous page

ics.icsneoSetLedProperty	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_led_property()</code> method.
ics.icsneoSetRTC	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_RTC()</code> method.
ics.icsneoSetReflashDisplayCallbacks	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_reflash_callback()</code> method.
ics.icsneoStartDHCPServer	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.start_dhcp_server()</code> method.
ics.icsneoStopDHCPServer	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.stop_dhcp_server()</code> method.
ics.icsneoTxMessages	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.transmit_messages()</code> method.
ics.icsneoUartGetBaudrate	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_get_baudrate()</code> method.
ics.icsneoUartRead	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_read()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoUartSetBaudrate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_set_baudrate()</code> method.
<code>ics.icsneoUartWrite</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_write()</code> method.
<code>ics.icsneoValidateHObject</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.validate_hobject()</code> method.
<code>ics.icsneoWriteJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.write_jupiter_firmware()</code> method.
<code>ics.icsneoWriteSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.write_sdcard()</code> method.
<code>ics.icsneowBMSManagerReset</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.wbms_manager_reset()</code> method.
<code>ics.icsneowBMSManagerWriteLock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.wbms_manager_write_lock()</code> method.

CHAPTER 9

Module Structures

```
class ics.structures.a2_b_monitor_settings.a2_b_monitor_settings

    downstreamChannelOffset
        Structure/Union member

    flags
        Structure/Union member

    nodeType
        Structure/Union member

    reserved
        Structure/Union member

    tdmMode
        Structure/Union member

    upstreamChannelOffset
        Structure/Union member

class ics.structures.a2_b_node_type.a2_b_node_type(*args, **kwds)
    A ctypes-compatible IntEnum superclass.

    a2bNodeTypeMaster = 1
    a2bNodeTypeMonitor = 0
    a2bNodeTypeSlave = 2

    from_param = <bound method a2_b_node_type.from_param of <enum 'a2_b_node_type'>>

class ics.structures.a2_bt dm_mode.a2_bt dm_mode(*args, **kwds)
    A ctypes-compatible IntEnum superclass.

    from_param = <bound method a2_bt dm_mode.from_param of <enum 'a2_bt dm mode'>>
    tdmModeTDM12 = 3
    tdmModeTDM16 = 4
```

```
    tdmModeTDM2 = 0
    tdmModeTDM20 = 5
    tdmModeTDM24 = 6
    tdmModeTDM32 = 7
    tdmModeTDM4 = 1
    tdmModeTDM8 = 2

class ics.structures.can_settings.can_settings

    BRP
        Structure/Union member

    Baudrate
        Structure/Union member

    Mode
        Structure/Union member

    SetBaudrate
        Structure/Union member

    TqProp
        Structure/Union member

    TqSeg1
        Structure/Union member

    TqSeg2
        Structure/Union member

    TqSync
        Structure/Union member

    auto_baud
        Structure/Union member

    innerFrameDelay25us
        Structure/Union member

    transceiver_mode
        Structure/Union member

class ics.structures.canfd_settings.canfd_settings

    FDBRP
        Structure/Union member

    FDBaudrate
        Structure/Union member

    FDMode
        Structure/Union member

    FDTDC
        Structure/Union member

    FDTqProp
        Structure/Union member
```

```
FDTqSeg1
    Structure/Union member

FDTqSeg2
    Structure/Union member

FDTqSync
    Structure/Union member

reserved
    Structure/Union member

class ics.structures.canterm_settings.canterm_settings

reserved
    Structure/Union member

term_enabled
    Structure/Union member

term_network
    Structure/Union member

class ics.structures.clock_quality_.clock_quality_

clock_accuracy
    Structure/Union member

clock_class
    Structure/Union member

offset_scaled_log_variance
    Structure/Union member

class ics.structures.device_feature.device_feature(*args, **kwds)
A ctypes-compatible IntEnum superclass.

NUM_VALID_DEVICE_FEATURES = 17
enhancedFlashDriver = 16
from_param = <bound method device_feature.from_param of <enum 'device_feature'>>
networkDWCAN01 = 0
networkDWCAN02 = 1
networkDWCAN03 = 2
networkDWCAN04 = 3
networkDWCAN05 = 4
networkDWCAN06 = 5
networkDWCAN07 = 6
networkDWCAN08 = 7
networkTerminationDWCAN01 = 8
networkTerminationDWCAN02 = 9
networkTerminationDWCAN03 = 10
```

```
networkTerminationDWCAN04 = 11
networkTerminationDWCAN05 = 12
networkTerminationDWCAN06 = 13
networkTerminationDWCAN07 = 14
networkTerminationDWCAN08 = 15
supportedFeatureMax = 65535

class ics.structures.disk_settings.disk_settings

    disk_enables
        Structure/Union member

    disk_format
        Structure/Union member

    disk_layout
        Structure/Union member

    rsvd
        Structure/Union member

class ics.structures.e_device_settings_type.e_device_settings_type(*args,
                                                               **kwds)
    A ctypes-compatible IntEnum superclass.

    DeviceCANHUBSettingsType = 19
    DeviceCMProbeSettingsType = 22
    DeviceECU_AVBSettingsType = 9
    DeviceEEVBSettingsType = 15
    DeviceEtherBadgeSettingsType = 30
    DeviceFire2SettingsType = 2
    DeviceFire3FlexraySettingsType = 37
    DeviceFire3SettingsType = 36
    DeviceFireSettingsType = 0
    DeviceFireVnetSettingsType = 1
    DeviceFlexVnetzSettingsType = 18
    DeviceIEVBSettingsType = 20
    DeviceNeoECU12SettingsType = 17
    DeviceOBD2LCSettingsType = 33
    DeviceOBD2ProSettingsType = 23
    DeviceOBD2SimSettingsType = 21
    DeviceRADA2BSettingsType = 31
    DeviceRADBMSSettingsType = 34
    DeviceRADCometSettingsType = 38
    DeviceRADEpsilonSettingsType = 32
```

```

DeviceRADGalaxySettingsType = 4
DeviceRADGigalogSettingsType = 13
DeviceRADGigastarSettingsType = 26
DeviceRADJupiterSettingsType = 27
DeviceRADMoon2SettingsType = 11
DeviceRADMoon3SettingsType = 35
DeviceRADPlutoSettingsType = 12
DeviceRADPlutoSwitchSettingsType = 25
DeviceRADStar2SettingsType = 5
DeviceRADSuperMoonSettingsType = 10
DeviceRadMoonDuoSettingsType = 29
DeviceRed2OemSettingsType = 39
DeviceRed2SettingsType = 28
DeviceRedSettingsType = 24
DeviceSettingsNone = 4294967295
DeviceSettingsTypeMax = 40
DeviceVCAN3SettingsType = 3
DeviceVCAN412SettingsType = 7
DeviceVCAN4IndSettingsType = 16
DeviceVCAN4SettingsType = 6
DeviceVCANRFSettingsType = 14
DeviceVividCANSettingsType = 8
from_param = <bound method e_device_settings_type.from_param of <enum 'e_device_set

class ics.structures.e_disk_format.e_disk_format(*args, **kwds)
A ctypes-compatible IntEnum superclass.

DiskFormatFAT32 = 1
DiskFormatUnknown = 0
DiskFormatexFAT = 2
from_param = <bound method e_disk_format.from_param of <enum 'e_disk_format'>>
class ics.structures.e_disk_layout.e_disk_layout(*args, **kwds)
A ctypes-compatible IntEnum superclass.

DiskLayoutIndividual = 4
DiskLayoutRAID0 = 1
DiskLayoutRAID1 = 2
DiskLayoutRAID5 = 3
DiskLayoutSpanned = 0
from_param = <bound method e_disk_layout.from_param of <enum 'e_disk_layout'>>

```

```
class ics.structures.e_generic_api_options.e_generic_api_options(*args,
                                                               **kwds)
    A ctypes-compatible IntEnum superclass.

    eADI_WIL_API = 1
    eGENERIC_API = 0

    from_param = <bound method e_generic_api_options.from_param of <enum 'e_generic_api_options'>>

class ics.structures.e_gptp_port.e_gptp_port(*args, **kwds)
    A ctypes-compatible IntEnum superclass.

    ePortDisabled = 0
    ePortOpEth1 = 1
    ePortOpEth10 = 10
    ePortOpEth11 = 11
    ePortOpEth12 = 12
    ePortOpEth2 = 2
    ePortOpEth3 = 3
    ePortOpEth4 = 4
    ePortOpEth5 = 5
    ePortOpEth6 = 6
    ePortOpEth7 = 7
    ePortOpEth8 = 8
    ePortOpEth9 = 9
    ePortStdEth1 = 13
    ePortStdEth2 = 14

    from_param = <bound method e_gptp_port.from_param of <enum 'e_gptp_port'>>

class ics.structures.e_gptp_role.e_gptp_role(*args, **kwds)
    A ctypes-compatible IntEnum superclass.

    eRoleDisabled = 0
    eRoleMaster = 2
    eRolePassive = 1
    eRoleSlave = 3

    from_param = <bound method e_gptp_role.from_param of <enum 'e_gptp_role'>>

class ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet_channel_t(*args,
                                                                           **kwds)
    A ctypes-compatible IntEnum superclass.

    PlasmaIonVnetChannelA = 1
    PlasmaIonVnetChannelB = 2
    PlasmaIonVnetChannelMain = 0
    eFpgaStatusResp = 4
```

```

eSoftCore = 3

from_param = <bound method e_plasma_ion_vnet_channel_t.from_param of <enum 'e_plasma_ion_vnet_channel_t'>

class ics.structures.e_uart_port_t.e_uart_port_t(*args, **kwds)
    A ctypes-compatible IntEnum superclass.

    eUART0 = 0
    eUART1 = 1

    from_param = <bound method e_uart_port_t.from_param of <enum 'e_uart_port_t'>>
class ics.structures.ethernet10_g_settings.ethernet10_g_settings

    flags
        Structure/Union member

    gateway
        Structure/Union member

    ip_addr
        Structure/Union member

    link_speed
        Structure/Union member

    netmask
        Structure/Union member

    rsvd2
        Structure/Union member

class ics.structures.ethernet10_t1_s_settings.ethernet10_t1_s_settings

    burst_timer
        Structure/Union member

    flags
        Structure/Union member

    local_id
        Structure/Union member

    local_id_alternate
        Structure/Union member

    max_burst_count
        Structure/Union member

    max_num_nodes
        Structure/Union member

    rsvd
        Structure/Union member

    to_timer
        Structure/Union member

class ics.structures.ethernet_network_status_t.ethernet_network_status_t

```

```
linkFullDuplex
    Structure/Union member

linkMode
    Structure/Union member

linkSpeed
    Structure/Union member

linkStatus
    Structure/Union member

networkId
    Structure/Union member

class ics.structures.ethernet_settings.ethernet_settings

auto_neg
    Structure/Union member

duplex
    Structure/Union member

led_mode
    Structure/Union member

link_speed
    Structure/Union member

rsvd
    Structure/Union member

class ics.structures.ethernet_settings2.ethernet_settings2

flags
    Structure/Union member

flags2
    Structure/Union member

gateway
    Structure/Union member

ip_addr
    Structure/Union member

link_speed
    Structure/Union member

netmask
    Structure/Union member

rsvd
    Structure/Union member

class ics.structures.ew_bms_instance_t.ew_bms_instance_t(*args,
                                                       **kwds)
A ctypes-compatible IntEnum superclass.

ewBMSInstance0 = 0
ewBMSInstance1 = 1
```

```

from_param = <bound method ew_bms_instance_t.from_param of <enum 'ew_bms_instance_t'>
class ics.structures.ew_bms_manager_lock_state_t.ew_bms_manager_lock_state_t(*args,
**kwds)
    A ctypes-compatible IntEnum superclass.

eLockManager = 0
eUnlockManager = 1
from_param = <bound method ew_bms_manager_lock_state_t.from_param of <enum 'ew_bms_
manager_lock_state_t'>
class ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t(*args,
**kwds)
    A ctypes-compatible IntEnum superclass.

eManagerPortA = 0
eManagerPortB = 1
from_param = <bound method ew_bms_manager_port_t.from_param of <enum 'ew_bms_manager_
port_t'>
class ics.structures.extended_response_code.extended_response_code(*args,
**kwds)
    A ctypes-compatible IntEnum superclass.

EXTENDED_RESPONSE_INVALID_COMMAND = -1
EXTENDED_RESPONSE_INVALID_PARAMETER = -5
EXTENDED_RESPONSE_INVALID_STATE = -2
EXTENDED_RESPONSE_OK = 0
EXTENDED_RESPONSE_OPERATION_FAILED = -3
EXTENDED_RESPONSE_OPERATION_PENDING = -4
from_param = <bound method extended_response_code.from_param of <enum 'extended_respon
ce_code'>
class ics.structures.extended_response_generic.extended_response_generic

    commandType
        Structure/Union member

    returnCode
        Structure/Union member

class ics.structures.fire3_linux_settings.fire3_linux_settings

    allowBoot
        Structure/Union member

    ethConfigurationPort
        Structure/Union member

    reserved
        Structure/Union member

    useExternalWifiAntenna
        Structure/Union member

class ics.structures.flex_vnet_mode.flex_vnet_mode(*args, **kwds)
    A ctypes-compatible IntEnum superclass.

flexVnetModeColdStart = 4

```

```
flexVnetModeDisabled = 0
flexVnetModeOneDual = 2
flexVnetModeOneSingle = 1
flexVnetModeTwoSingle = 3
from_param = <bound method flex_vnet_mode.from_param of <enum 'flex_vnet_mode'>>
class ics.structures.generic_api_data.generic_api_data

api
    Structure/Union member
bData
    Structure/Union member
length
    Structure/Union member
class ics.structures.generic_api_data_old.generic_api_data_old

api
    Structure/Union member
bData
    Structure/Union member
length
    Structure/Union member
class ics.structures.generic_api_selector.generic_api_selector

apiIndex
    Structure/Union member
functionID
    Structure/Union member
instance
    Structure/Union member
class ics.structures.generic_api_status.generic_api_status

api
    Structure/Union member
callbackError
    Structure/Union member
finishedProcessing
    Structure/Union member
functionError
    Structure/Union member
class ics.structures.generic_binary_status.generic_binary_status
```

```
index
    Structure/Union member

reserved
    Structure/Union member

size
    Structure/Union member

status
    Structure/Union member

class ics.structures.get_component_versions.get_component_versions

reserved
    Structure/Union member

class ics.structures.get_component_versions_response.get_component_versions_response

numVersions
    Structure/Union member

versions
    Structure/Union member

class ics.structures.get_supported_features_response.get_supported_features_response

cmdVersion
    Structure/Union member

featureBitfields
    Structure/Union member

numValidBits
    Structure/Union member

class ics.structures.global_settings.global_settings

Nameless59426
    Structure/Union member

canhub
    Structure/Union member

chksum
    Structure/Union member

cmprobe
    Structure/Union member

cyan
    Structure/Union member

ecu
    Structure/Union member

eevb
    Structure/Union member
```

epsilon
Structure/Union member

etherBadge
Structure/Union member

fire
Structure/Union member

fire3
Structure/Union member

fire3fr
Structure/Union member

firevnet
Structure/Union member

flexvnetz
Structure/Union member

ievb
Structure/Union member

jupiter
Structure/Union member

len
Structure/Union member

neoecu12
Structure/Union member

neoecu_avb
Structure/Union member

neoobd2_sim
Structure/Union member

obd2lc
Structure/Union member

obd2pro
Structure/Union member

pendant
Structure/Union member

pluto
Structure/Union member

rad_a2b
Structure/Union member

rad_bms
Structure/Union member

radcomet
Structure/Union member

radgalaxy
Structure/Union member

```
radgigalog
    Structure/Union member

radgigastar
    Structure/Union member

radmoon2
    Structure/Union member

radmoon3
    Structure/Union member

radmoonduo
    Structure/Union member

radstar2
    Structure/Union member

radsupermoon
    Structure/Union member

red
    Structure/Union member

red2
    Structure/Union member

vcan3
    Structure/Union member

vcan4
    Structure/Union member

vcan412
    Structure/Union member

vcan4_12
    Structure/Union member

vcan4_ind
    Structure/Union member

vcanrf
    Structure/Union member

version
    Structure/Union member

vividcan
    Structure/Union member

class ics.structures.gptp_status.gptp_status

    as_capable
        Structure/Union member

    current_time
        Structure/Union member

    gm_priority
        Structure/Union member
```

```
    is_sync
        Structure/Union member

    is_syntonized
        Structure/Union member

    link_delay_ns
        Structure/Union member

    link_status
        Structure/Union member

    ms_offset_ns
        Structure/Union member

    reserved
        Structure/Union member

    selected_role
        Structure/Union member

class ics.structures.hw_eth_settings.hw_eth_settings

    General_Settings
        Structure/Union member

class ics.structures.ics_device_status.ics_device_status

    epsilonStatus
        Structure/Union member

    fire2Status
        Structure/Union member

    fire3Status
        Structure/Union member

    flexVnetzStatus
        Structure/Union member

    jupiterStatus
        Structure/Union member

    obd2proStatus
        Structure/Union member

    plutoStatus
        Structure/Union member

    radBMSStatus
        Structure/Union member

    radMoonDuoStatus
        Structure/Union member

    vcan4Status
        Structure/Union member

    vcan4indStatus
        Structure/Union member
```

```
class ics.structures.ics_fire2_device_status.ics_fire2_device_status

    backupPowerEnabled
        Structure/Union member

    backupPowerGood
        Structure/Union member

    ethernetActivationLineEnabled
        Structure/Union member

    ethernetStatus
        Structure/Union member

    usbHostPowerEnabled
        Structure/Union member

class ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device_status

    ethernetActivationLineEnabled
        Structure/Union member

    ethernetStatus
        Structure/Union member

    unused
        Structure/Union member

class ics.structures.ics_fire3_device_status.ics_fire3_device_status

    ethernetActivationLineEnabled
        Structure/Union member

    ethernetActivationLineEnabled_2
        Structure/Union member

    ethernetStatus
        Structure/Union member

class ics.structures.ics_flex_vnetz_device_status.ics_flex_vnetz_device_status

    ethernetActivationLineEnabled
        Structure/Union member

    ethernetStatus
        Structure/Union member

    unused
        Structure/Union member

class ics.structures.ics_obd2_pro_device_status.ics_obd2_pro_device_status

    ethernetStatus
        Structure/Union member

class ics.structures.ics_rad_bms_device_status.ics_rad_bms_device_status
```

```
    ethernetStatus
        Structure/Union member

class ics.structures.ics_rad_epsilon_device_status.ics_rad_epsilon_device_status

    ethernetStatus
        Structure/Union member

class ics.structures.ics_rad_jupiter_device_status.ics_rad_jupiter_device_status

    ethernetStatus
        Structure/Union member

class ics.structures.ics_rad_moon_duo_device_status.ics_rad_moon_duo_device_status

    ethernetStatus
        Structure/Union member

class ics.structures.ics_rad_pluto_device_status.ics_rad_pluto_device_status

    ethernetStatus
        Structure/Union member

class ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray

    AckBytes
        Structure/Union member

    ArbIDOrHeader
        Structure/Union member

    Data
        Structure/Union member

    DescriptionID
        Structure/Union member

    ExtraDataPtr
        Structure/Union member

    ExtraDataPtrEnabled
        Structure/Union member

    MessagePieceID
        Structure/Union member

    MiscData
        Structure/Union member

    Nameless9872
        Structure/Union member

    Nameless9992
        Structure/Union member

    NetworkID
        Structure/Union member
```

NetworkID2
Structure/Union member

NodeID
Structure/Union member

NumberBytesData
Structure/Union member

NumberBytesHeader
Structure/Union member

Protocol
Structure/Union member

Reserved
Structure/Union member

StatusBitField
Structure/Union member

StatusBitField2
Structure/Union member

StatusBitField3
Structure/Union member

StatusBitField4
Structure/Union member

TimeHardware
Structure/Union member

TimeHardware2
Structure/Union member

TimeStampHardwareID
Structure/Union member

TimeStampSystemID
Structure/Union member

TimeSystem
Structure/Union member

TimeSystem2
Structure/Union member

chA
Structure/Union member

chB
Structure/Union member

cycle
Structure/Union member

dynamic
Structure/Union member

fcrc0
Structure/Union member

```
fcrc1
    Structure/Union member

fcrc2
    Structure/Union member

frame_len_12_5ns
    Structure/Union member

frame_reserved
    Structure/Union member

hcrc_lsbs
    Structure/Union member

hcrc_msbs
    Structure/Union member

id
    Structure/Union member

null_frame
    Structure/Union member

payload_preamble
    Structure/Union member

res1
    Structure/Union member

res2
    Structure/Union member

startup
    Structure/Union member

sync
    Structure/Union member

tss_len_12_5ns
    Structure/Union member

class ics.structures.ics_spy_message_long.ics_spy_message_long

AckBytes
    Structure/Union member

ArbIDOrHeader
    Structure/Union member

DataLsb
    Structure/Union member

DataMsb
    Structure/Union member

DescriptionID
    Structure/Union member

ExtraDataPtr
    Structure/Union member
```

ExtraDataPtrEnabled
Structure/Union member

MessagePieceID
Structure/Union member

MiscData
Structure/Union member

Nameless18511
Structure/Union member

NetworkID
Structure/Union member

NetworkID2
Structure/Union member

NodeID
Structure/Union member

NumberBytesData
Structure/Union member

NumberBytesHeader
Structure/Union member

Protocol
Structure/Union member

Reserved
Structure/Union member

StatusBitField
Structure/Union member

StatusBitField2
Structure/Union member

StatusBitField3
Structure/Union member

StatusBitField4
Structure/Union member

TimeHardware
Structure/Union member

TimeHardware2
Structure/Union member

TimeStampHardwareID
Structure/Union member

TimeStampSystemID
Structure/Union member

TimeSystem
Structure/Union member

TimeSystem2
Structure/Union member

```
class ics.structures.ics_spy_message_mdio.ics_spy_message_mdio

    AckBytes
        Structure/Union member

    ArbIDOrHeader
        Structure/Union member

    Data
        Structure/Union member

    DescriptionID
        Structure/Union member

    DevType
        Structure/Union member

    ExtraDataPtr
        Structure/Union member

    ExtraDataPtrEnabled
        Structure/Union member

    MessagePieceID
        Structure/Union member

    MiscData
        Structure/Union member

    Nameless18906
        Structure/Union member

    Nameless45381
        Structure/Union member

    NetworkID
        Structure/Union member

    NetworkID2
        Structure/Union member

    NodeID
        Structure/Union member

    NumberBytesData
        Structure/Union member

    NumberBytesHeader
        Structure/Union member

    PhyAddr
        Structure/Union member

    Protocol
        Structure/Union member

    RegAddr
        Structure/Union member

    Reserved
        Structure/Union member
```

```
    StatusBitField
        Structure/Union member

    StatusBitField2
        Structure/Union member

    StatusBitField3
        Structure/Union member

    StatusBitField4
        Structure/Union member

    TimeHardware
        Structure/Union member

    TimeHardware2
        Structure/Union member

    TimeStampHardwareID
        Structure/Union member

    TimeStampSystemID
        Structure/Union member

    TimeSystem
        Structure/Union member

    TimeSystem2
        Structure/Union member

class ics.structures.ics_spy_message_vsb.ics_spy_message_vsb

    AckBytes
        Structure/Union member

    ArbIDOrHeader
        Structure/Union member

    Data
        Structure/Union member

    DescriptionID
        Structure/Union member

    ExtraDataPtr
        Structure/Union member

    ExtraDataPtrEnabled
        Structure/Union member

    MessagePieceID
        Structure/Union member

    MiscData
        Structure/Union member

    Nameless54558
        Structure/Union member

    NetworkID
        Structure/Union member
```

```
NetworkID2
    Structure/Union member

NodeID
    Structure/Union member

NumberBytesData
    Structure/Union member

NumberBytesHeader
    Structure/Union member

Protocol
    Structure/Union member

Reserved
    Structure/Union member

StatusBitField
    Structure/Union member

StatusBitField2
    Structure/Union member

StatusBitField3
    Structure/Union member

StatusBitField4
    Structure/Union member

TimeHardware
    Structure/Union member

TimeHardware2
    Structure/Union member

TimeStampHardwareID
    Structure/Union member

TimeStampSystemID
    Structure/Union member

TimeSystem
    Structure/Union member

TimeSystem2
    Structure/Union member

class ics.structures.ics_vcan4_device_status.ics_vcan4_device_status

    ethernetActivationLineEnabled
        Structure/Union member

    ethernetStatus
        Structure/Union member

    unused
        Structure/Union member

class ics.structures.ics_vcan4_industrial_device_status.ics_vcan4_industrial_device_st
```

```
    ethernetStatus
        Structure/Union member

class ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message

    Nameless43713
        Structure/Union member

    blockSize
        Structure/Union member

    data
        Structure/Union member

    ext_address_enable
        Structure/Union member

    extendedAddress
        Structure/Union member

    fc_ext_address_enable
        Structure/Union member

    fc_id
        Structure/Union member

    fc_id_29_bit_enable
        Structure/Union member

    fc_id_mask
        Structure/Union member

    flags
        Structure/Union member

    flowControlExtendedAddress
        Structure/Union member

    fs_timeout
        Structure/Union member

    fs_wait
        Structure/Union member

    id
        Structure/Union member

    id_29_bit_enable
        Structure/Union member

    isBRSEnabled
        Structure/Union member

    iscanFD
        Structure/Union member

    num_bytes
        Structure/Union member

    overrideBlockSize
        Structure/Union member
```

```
    overrideSTmin
        Structure/Union member

    padding
        Structure/Union member

    paddingEnable
        Structure/Union member

    stMin
        Structure/Union member

    tx_dl
        Structure/Union member

    tx_index
        Structure/Union member

    vs_netid
        Structure/Union member

class ics.structures.iso9141_keyword2000_init_step.iso9141_keyword2000_init_step

    k
        Structure/Union member

    l
        Structure/Union member

    time_500us
        Structure/Union member

class ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings

    Baudrate
        Structure/Union member

    brgh
        Structure/Union member

    chksum_enabled
        Structure/Union member

    init_step_count
        Structure/Union member

    init_steps
        Structure/Union member

    p2_500us
        Structure/Union member

    p3_500us
        Structure/Union member

    p4_500us
        Structure/Union member

    spbrg
        Structure/Union member
```

```
class ics.structures.j1708_settings.j1708_settings

    enable_convert_mode
        Structure/Union member

class ics.structures.lin_settings.lin_settings

    Baudrate
        Structure/Union member

    MasterResistor
        Structure/Union member

    Mode
        Structure/Union member

    brgh
        Structure/Union member

    numBitsDelay
        Structure/Union member

    spbrg
        Structure/Union member

class ics.structures.logger_settings.logger_settings

    extraction_timeout
        Structure/Union member

    rsvd
        Structure/Union member

class ics.structures.op_eth_general_settings.op_eth_general_settings

    Nameless19471
        Structure/Union member

    flags
        Structure/Union member

    reserved0
        Structure/Union member

    tapPair0
        Structure/Union member

    tapPair1
        Structure/Union member

    tapPair2
        Structure/Union member

    tapPair3
        Structure/Union member

    tapPair4
        Structure/Union member
```

```
tapPair5
    Structure/Union member

uFlags
    Structure/Union member

ucInterfaceType
    Structure/Union member

class ics.structures.op_eth_link_mode.op_eth_link_mode(*args, **kwds)
    A ctypes-compatible IntEnum superclass.

    OPETH_LINK_AUTO = 0
    OPETH_LINK_MASTER = 1
    OPETH_LINK_SLAVE = 2
    from_param = <bound method op_eth_link_mode.from_param of <enum 'op_eth_link_mode'>

class ics.structures.op_eth_settings.op_eth_settings

    Nameless14996
        Structure/Union member

    link_spd
        Structure/Union member

    mac_addr1
        Structure/Union member

    mac_addr2
        Structure/Union member

    mac_spoofing_en
        Structure/Union member

    mac_spoofing_isDstOrSrc
        Structure/Union member

    preemption_en
        Structure/Union member

    q2112_phy_mode
        Structure/Union member

    reserved
        Structure/Union member

    reserved0
        Structure/Union member

    ucConfigMode
        Structure/Union member

class ics.structures.phy_error_type.phy_error_type(*args, **kwds)
    A ctypes-compatible IntEnum superclass.

    PhyFlashingDeinitError = 7
    PhyFlashingEraseError = 3
    PhyFlashingInitError = 2
    PhyFlashingInvalidDataFile = 9
```

```
PhyFlashingInvalidHardware = 8
PhyFlashingReadError = 5
PhyFlashingVerifyError = 6
PhyFlashingWriteError = 4
PhyGetVersionError = 10
PhyIndexError = 11
PhyOperationError = 0
PhyOperationSuccess = 1
from_param = <bound method phy_error_type.from_param of <enum 'phy_error_type'>>
class ics.structures.port_identity.port_identity

    clock_identity
        Structure/Union member
    port_number
        Structure/Union member
class ics.structures.priority_vector.priority_vector

    port_number
        Structure/Union member
    portid
        Structure/Union member
    steps_removed
        Structure/Union member
    sysid
        Structure/Union member
class ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_converter_settings

    converter1Mode
        Structure/Union member
    ipAddress
        Structure/Union member
    ipGateway
        Structure/Union member
    ipMask
        Structure/Union member
    linkMode0
        Structure/Union member
    linkMode1
        Structure/Union member
class ics.structures.rad_reporting_settings.rad_reporting_settings
```

```
fan_speed_interval_ms
    Structure/Union member

flags
    Structure/Union member

gps_interval_ms
    Structure/Union member

io_interval_ms
    Structure/Union member

rsvd
    Structure/Union member

serdes_interval_ms
    Structure/Union member

temp_interval_ms
    Structure/Union member

class ics.structures.s_cm_probe_settings.s_cm_probe_settings

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

class ics.structures.s_cyan_settings.s_cyan_settings

ain_sample_period
    Structure/Union member

ain_threshold
    Structure/Union member

can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can5
    Structure/Union member

can6
    Structure/Union member

can7
    Structure/Union member

can8
    Structure/Union member
```

can_switch_mode
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

digitalIoThresholdEnable
Structure/Union member

digitalIoThresholdTicks
Structure/Union member

disk
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

idle_wakeup_network_enables_3
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

```
iso9141_kwp_settings_3
    Structure/Union member

iso9141_kwp_settings_4
    Structure/Union member

iso_9141_kwp_enable_reserved
    Structure/Union member

iso_msg_termination_1
    Structure/Union member

iso_msg_termination_2
    Structure/Union member

iso_msg_termination_3
    Structure/Union member

iso_msg_termination_4
    Structure/Union member

iso_parity_1
    Structure/Union member

iso_parity_2
    Structure/Union member

iso_parity_3
    Structure/Union member

iso_parity_4
    Structure/Union member

lin1
    Structure/Union member

lin2
    Structure/Union member

lin3
    Structure/Union member

lin4
    Structure/Union member

lin5
    Structure/Union member

lin6
    Structure/Union member

lsftcan1
    Structure/Union member

lsftcan2
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member
```

```
misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

slaveVnetA
    Structure/Union member

slaveVnetB
    Structure/Union member

swcan1
    Structure/Union member

swcan2
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

timeSync
    Structure/Union member

class ics.structures.s_device_settings.s_device_settings

DeviceSettingType
    Structure/Union member

Settings
    Structure/Union member

class ics.structures.s_disk_details.s_disk_details
```

```
    status
        Structure/Union member

    structure
        Structure/Union member

class ics.structures.s_disk_format_progress.s_disk_format_progress

    sectorsRemaining
        Structure/Union member

    state
        Structure/Union member

class ics.structures.s_disk_status.s_disk_status

    bytesPerSector
        Structure/Union member

    sectors
        Structure/Union member

    status
        Structure/Union member

class ics.structures.s_disk_structure.s_disk_structure

    options
        Structure/Union member

    settings
        Structure/Union member

class ics.structures.s_ether_badge_settings.s_ether_badge_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    ethernet
        Structure/Union member

    ethernet2
        Structure/Union member
```

```
flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_enable_reserved
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_parity
    Structure/Union member

iso_tester_pullup_enable
    Structure/Union member

lin1
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

termination_enables
    Structure/Union member
```

```
text_api
    Structure/Union member

class ics.structures.s_ext_sub_cmd_hdr.s_ext_sub_cmd_hdr

    command
        Structure/Union member

    length
        Structure/Union member

class ics.structures.s_extended_data_flash_header.s_extended_data_flash_header

    chksum
        Structure/Union member

    len
        Structure/Union member

    version
        Structure/Union member

class ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can10
        Structure/Union member

    can11
        Structure/Union member

    can12
        Structure/Union member

    can13
        Structure/Union member

    can14
        Structure/Union member

    can15
        Structure/Union member

    can2
        Structure/Union member

    can3
        Structure/Union member

    can4
        Structure/Union member

    can5
        Structure/Union member
```

can6
Structure/Union member

can7
Structure/Union member

can8
Structure/Union member

can9
Structure/Union member

canfd1
Structure/Union member

canfd10
Structure/Union member

canfd11
Structure/Union member

canfd12
Structure/Union member

canfd13
Structure/Union member

canfd14
Structure/Union member

canfd15
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

canfd9
Structure/Union member

digitalIoThresholdEnable
Structure/Union member

digitalIoThresholdTicks
Structure/Union member

```
disk
    Structure/Union member

ethernet2_1
    Structure/Union member

ethernet2_2
    Structure/Union member

ethernet2_3
    Structure/Union member

ethernet_1
    Structure/Union member

ethernet_2
    Structure/Union member

ethernet_3
    Structure/Union member

flags
    Structure/Union member

flex_mode
    Structure/Union member

flex_termination
    Structure/Union member

gPTP
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso9141_kwp_settings_2
    Structure/Union member

iso9141_kwp_settings_3
    Structure/Union member

iso9141_kwp_settings_4
    Structure/Union member

iso_msg_termination_1
    Structure/Union member

iso_msg_termination_2
    Structure/Union member

iso_msg_termination_3
    Structure/Union member

iso_msg_termination_4
    Structure/Union member

iso_parity_1
    Structure/Union member
```

iso_parity_2
Structure/Union member

iso_parity_3
Structure/Union member

iso_parity_4
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

lin3
Structure/Union member

lin4
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

os_settings
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reserved
Structure/Union member

```
slaveVnetA
    Structure/Union member

termination_enables_1
    Structure/Union member

termination_enables_2
    Structure/Union member

text_api
    Structure/Union member

timeSync
    Structure/Union member

class ics.structures.s_fire3_settings.s_fire3_settings

ain_threshold
    Structure/Union member

can1
    Structure/Union member

can10
    Structure/Union member

can11
    Structure/Union member

can12
    Structure/Union member

can13
    Structure/Union member

can14
    Structure/Union member

can15
    Structure/Union member

can16
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can5
    Structure/Union member

can6
    Structure/Union member

can7
    Structure/Union member
```

can8
Structure/Union member

can9
Structure/Union member

canfd1
Structure/Union member

canfd10
Structure/Union member

canfd11
Structure/Union member

canfd12
Structure/Union member

canfd13
Structure/Union member

canfd14
Structure/Union member

canfd15
Structure/Union member

canfd16
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

canfd9
Structure/Union member

digitalIoThresholdEnable
Structure/Union member

digitalIoThresholdTicks
Structure/Union member

disk
Structure/Union member

ethernet2_1
Structure/Union member

ethernet2_2
Structure/Union member

ethernet2_3
Structure/Union member

ethernet_1
Structure/Union member

ethernet_2
Structure/Union member

ethernet_3
Structure/Union member

flags
Structure/Union member

gPTP
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso9141_kwp_settings_3
Structure/Union member

iso9141_kwp_settings_4
Structure/Union member

iso9141_kwp_settings_5
Structure/Union member

iso9141_kwp_settings_6
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_msg_termination_3
Structure/Union member

iso_msg_termination_4
Structure/Union member

iso_msg_termination_5
Structure/Union member

iso_msg_termination_6
Structure/Union member

```
iso_parity_1
    Structure/Union member

iso_parity_2
    Structure/Union member

iso_parity_3
    Structure/Union member

iso_parity_4
    Structure/Union member

iso_parity_5
    Structure/Union member

iso_parity_6
    Structure/Union member

iso_tester_pullup_enable
    Structure/Union member

lin1
    Structure/Union member

lin2
    Structure/Union member

lin3
    Structure/Union member

lin4
    Structure/Union member

lin5
    Structure/Union member

lin6
    Structure/Union member

lin7
    Structure/Union member

lin8
    Structure/Union member

lsftcan1
    Structure/Union member

lsftcan2
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member
```

```
misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

os_settings
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

selectable_network_1
    Structure/Union member

selectable_network_2
    Structure/Union member

slaveVnetA
    Structure/Union member

swcan1
    Structure/Union member

swcan2
    Structure/Union member

termination_enables_1
    Structure/Union member

termination_enables_2
    Structure/Union member

text_api
    Structure/Union member

timeSync
    Structure/Union member

class ics.structures.s_fire_settings.s_fire_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member
```

```
can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

cgi_baud
    Structure/Union member

cgi_chksum_enable
    Structure/Union member

cgi_enable_reserved
    Structure/Union member

cgi_rx_ifs_bit_times
    Structure/Union member

cgi_tx_ifs_bit_times
    Structure/Union member

fast_init_network_enables_1
    Structure/Union member

fast_init_network_enables_2
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_enable_reserved
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso9141_kwp_settings_2
    Structure/Union member

iso9141_kwp_settings_3
    Structure/Union member

iso9141_kwp_settings_4
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_msg_termination_2
    Structure/Union member

iso_msg_termination_3
    Structure/Union member

iso_msg_termination_4
    Structure/Union member
```

iso_parity
Structure/Union member

iso_parity_2
Structure/Union member

iso_parity_3
Structure/Union member

iso_parity_4
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

lin3
Structure/Union member

lin4
Structure/Union member

lsftcan
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

neoMostGateway
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

perf_en
Structure/Union member

pwm_man_timeout
Structure/Union member

```
pwr_man_enable
    Structure/Union member

swcan
    Structure/Union member

text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

vnetBits
    Structure/Union member

class ics.structures.s_fire_vnet_settings.s_fire_vnet_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    can3
        Structure/Union member

    can4
        Structure/Union member

    can5
        Structure/Union member

    can6
        Structure/Union member

    cgi_baud
        Structure/Union member

    cgi_chksum_enable
        Structure/Union member

    cgi_enable_reserved
        Structure/Union member

    cgi_rx_ifs_bit_times
        Structure/Union member

    cgi_tx_ifs_bit_times
        Structure/Union member

    fast_init_network_enables_1
        Structure/Union member
```

```
fast_init_network_enables_2
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_enable_reserved
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso9141_kwp_settings_2
    Structure/Union member

iso9141_kwp_settings_3
    Structure/Union member

iso9141_kwp_settings_4
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_msg_termination_2
    Structure/Union member

iso_msg_termination_3
    Structure/Union member

iso_msg_termination_4
    Structure/Union member

iso_parity
    Structure/Union member

iso_parity_2
    Structure/Union member

iso_parity_3
    Structure/Union member

iso_parity_4
    Structure/Union member

iso_tester_pullup_enable
    Structure/Union member

lin1
    Structure/Union member

lin2
    Structure/Union member

lin3
    Structure/Union member

lin4
    Structure/Union member

lin5
    Structure/Union member
```

```
lsftcan
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

neoMostGateway
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

perf_en
    Structure/Union member

pwm_man_timeout
    Structure/Union member

pwr_man_enable
    Structure/Union member

swcan
    Structure/Union member

swcan2
    Structure/Union member

text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

vnetBits
    Structure/Union member

class ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings

can1
    Structure/Union member
```

```
can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can5
    Structure/Union member

can6
    Structure/Union member

can7
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

canfd3
    Structure/Union member

canfd4
    Structure/Union member

canfd5
    Structure/Union member

canfd6
    Structure/Union member

canfd7
    Structure/Union member

disk
    Structure/Union member

ethernet
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

flex_mode
    Structure/Union member

flex_termination
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

misc_io_on_report_events
    Structure/Union member
```

```
network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

slaveVnetA
    Structure/Union member

slaveVnetB
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

timeSync
    Structure/Union member

class ics.structures.s_jupiter_ptp_params_s.s_jupiter_ptp_params_s

gPTPportRole
    Structure/Union member

initLogPDelayReqInterval
    Structure/Union member

initLogSyncInterval
    Structure/Union member

neighborPropDelay
    Structure/Union member

operationLogPDelayReqInterval
    Structure/Union member

operationLogSyncInterval
    Structure/Union member

class ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings

ain_sample_period
    Structure/Union member

ain_threshold
    Structure/Union member

can1
    Structure/Union member
```

```
can2
    Structure/Union member

can_switch_mode
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

ecu_id
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso_9141_kwp_enable_reserved
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_parity
    Structure/Union member

lin1
    Structure/Union member

lsftcan1
    Structure/Union member

lsftcan2
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member
```

```
perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved_field
    Structure/Union member

swcan1
    Structure/Union member

swcan2
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway_settings

Config
    Structure/Union member

netId
    Structure/Union member

zero0
    Structure/Union member

class ics.structures.s_pendant_settings.s_pendant_settings

ain_sample_period
    Structure/Union member

ain_threshold
    Structure/Union member

can1
    Structure/Union member

can2
    Structure/Union member

ecu_id
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso9141_kwp_settings_2
    Structure/Union member
```

```
iso_msg_termination
    Structure/Union member

iso_msg_termination_2
    Structure/Union member

iso_parity
    Structure/Union member

iso_parity_2
    Structure/Union member

lin1
    Structure/Union member

lin2
    Structure/Union member

lsftcan
    Structure/Union member

lsftcan2
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

selected_network
    Structure/Union member

swcan
    Structure/Union member

swcan2
    Structure/Union member
```

```
text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

class ics.structures.s_phy_reg_pkt.s_phy_reg_pkt

    BusIndex
        Structure/Union member

    Clause45Enable
        Structure/Union member

    Enabled
        Structure/Union member

    Nameless23244
        Structure/Union member

    Nameless5269
        Structure/Union member

    WriteEnable
        Structure/Union member

    clause22
        Structure/Union member

    clause45
        Structure/Union member

    flags
        Structure/Union member

    reserved
        Structure/Union member

    status
        Structure/Union member

    version
        Structure/Union member

class ics.structures.s_phy_reg_pkt_clause22_mess.s_phy_reg_pkt_clause22_mess

    page
        Structure/Union member

    phyAddr
        Structure/Union member

    regAddr
        Structure/Union member

    regVal
        Structure/Union member
```

```
class ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt_clause45_mess

    device
        Structure/Union member

    port
        Structure/Union member

    regAddr
        Structure/Union member

    regVal
        Structure/Union member

class ics.structures.s_phy_reg_pkt_hdr.s_phy_reg_pkt_hdr

    entryBytes
        Structure/Union member

    numEntries
        Structure/Union member

    version
        Structure/Union member

class ics.structures.s_phy_reg_pkt_rw.s_phy_reg_pkt_rw(*args, **kwds)
    A ctypes-compatible IntEnum superclass.

    PHYREG_BOTH = 2
    PHYREG_READ = 0
    PHYREG_WRITE = 1
    from_param = <bound method s_phy_reg_pkt_rw.from_param of <enum 's_phy_reg_pkt_rw'>

class ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_status(*args,
                                                               **kwds)
    A ctypes-compatible IntEnum superclass.

    PHYREG_FAILURE = 1
    PHYREG_INVALID_MDIO_BUS_INDEX = 2
    PHYREG_INVALID_PHY_ADDR = 3
    PHYREG_RESERVED1 = 5
    PHYREG_RESERVED2 = 6
    PHYREG_RESERVED3 = 7
    PHYREG_SUCCESS = 0
    PHYREG_UNSUPPORTED_MDIO_CLAUSE = 4
    from_param = <bound method s_phy_reg_pkt_status.from_param of <enum 's_phy_reg_pkt_status'>

class ics.structures.s_pluto_avb_params_s.s_pluto_avb_params_s

    destmeta
        Structure/Union member
```

```
srcmeta
    Structure/Union member

class ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_sync_params_s

accdevwin
    Structure/Union member

asytensyen
    Structure/Union member

caentmout
    Structure/Union member

etssrcpcf
    Structure/Union member

fullcbg
    Structure/Union member

intcydur
    Structure/Union member

inttosyncth
    Structure/Union member

inttotentth
    Structure/Union member

ipcframesy
    Structure/Union member

listentmout
    Structure/Union member

maxintegcy
    Structure/Union member

maxtranspclk
    Structure/Union member

numstbcy
    Structure/Union member

numunstbcy
    Structure/Union member

obvwinsz
    Structure/Union member

pad1
    Structure/Union member

pad2
    Structure/Union member

pad3
    Structure/Union member

pcfpriority
    Structure/Union member
```

pcfsze
Structure/Union member

srcport
Structure/Union member

stabasyen
Structure/Union member

stth
Structure/Union member

sttointth
Structure/Union member

swmaster
Structure/Union member

syasyen
Structure/Union member

sydomain
Structure/Union member

sypriority
Structure/Union member

syrelen
Structure/Union member

sysyen
Structure/Union member

syth
Structure/Union member

sytostben
Structure/Union member

sytousyth
Structure/Union member

tentsyrelen
Structure/Union member

tsyth
Structure/Union member

tsytoсыth
Structure/Union member

tsytousyth
Structure/Union member

unsytoсыth
Structure/Union member

unsytotsyth
Structure/Union member

vlidimnmin
Structure/Union member

```
vlidinmax
    Structure/Union member

vlidout
    Structure/Union member

vlidselect
    Structure/Union member

waitthsync
    Structure/Union member

wfintmout
    Structure/Union member

class ics.structures.s_pluto_custom_params_s.s_pluto_custom_params_s

ae1Select
    Structure/Union member

enablePhy
    Structure/Union member

mode
    Structure/Union member

pad
    Structure/Union member

ptpParams
    Structure/Union member

speed
    Structure/Union member

usbSelect
    Structure/Union member

class ics.structures.s_pluto_general_params_s.s_pluto_general_params_s

casc_port
    Structure/Union member

host_port
    Structure/Union member

hostprio
    Structure/Union member

ignore2stf
    Structure/Union member

incl_srcpt0
    Structure/Union member

incl_srcpt1
    Structure/Union member

mac_flt0
    Structure/Union member
```

```
mac_flt1
    Structure/Union member

mac_fltres0
    Structure/Union member

mac_fltres1
    Structure/Union member

mirr_port
    Structure/Union member

mirr_ptacu
    Structure/Union member

send_meta0
    Structure/Union member

send_meta1
    Structure/Union member

switchid
    Structure/Union member

tpid
    Structure/Union member

tpid2
    Structure/Union member

vllupformat
    Structure/Union member

vlmarker
    Structure/Union member

vlmask
    Structure/Union member

class ics.structures.s_pluto_12_address_lookup_entry_s.s_pluto_12_address_lookup_entry:

    destports
        Structure/Union member

    enfport
        Structure/Union member

    index
        Structure/Union member

    learnedEntry
        Structure/Union member

    macaddr
        Structure/Union member

    pad1
        Structure/Union member

    pad2
        Structure/Union member
```

```
pad3
    Structure/Union member

vlanID
    Structure/Union member

class ics.structures.s_pluto_12_address_lookup_params_s.s_pluto_12_address_lookup_params_s

dyn_tbsz
    Structure/Union member

maxage
    Structure/Union member

no_enf_hostprt
    Structure/Union member

no_mgmt_learn
    Structure/Union member

pad
    Structure/Union member

poly
    Structure/Union member

shared_learn
    Structure/Union member

class ics.structures.s_pluto_12_forwarding_entry_s.s_pluto_12_forwarding_entry_s

bc_domain
    Structure/Union member

f1_domain
    Structure/Union member

pad
    Structure/Union member

reach_port
    Structure/Union member

vlan_pmap
    Structure/Union member

class ics.structures.s_pluto_12_forwarding_params_s.s_pluto_12_forwarding_params_s

max_dynp
    Structure/Union member

pad
    Structure/Union member

part_spc
    Structure/Union member

class ics.structures.s_pluto_12_policing_s.s_pluto_12_policing_s
```

```
 maxlen
    Structure/Union member

 partition
    Structure/Union member

 rate
    Structure/Union member

 sharindx
    Structure/Union member

 smax
    Structure/Union member

class ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s

 base
    Structure/Union member

 drpdtag
    Structure/Union member

 drpnona664
    Structure/Union member

 drpuntag
    Structure/Union member

 dyn_learn
    Structure/Union member

 egr_mirr
    Structure/Union member

 egress
    Structure/Union member

 enabled
    Structure/Union member

 ifg
    Structure/Union member

 ing_mirr
    Structure/Union member

 ingress
    Structure/Union member

 maxage
    Structure/Union member

 pad
    Structure/Union member

 retag
    Structure/Union member

 speed
    Structure/Union member
```

```
top
    Structure/Union member

tp_delin
    Structure/Union member

tp_delout
    Structure/Union member

vlanid
    Structure/Union member

vlan prio
    Structure/Union member

class ics.structures.s_pluto_ptp_params_s.s_pluto_ptp_params_s

clockaccuracy
    Structure/Union member

clockclass
    Structure/Union member

gPTPportRole
    Structure/Union member

logAnnounceInterval
    Structure/Union member

logPDelayReqInterval
    Structure/Union member

logSyncInterval
    Structure/Union member

neighborPropDelayThresh
    Structure/Union member

offset_scaled_log_variance
    Structure/Union member

portEnable
    Structure/Union member

priority1
    Structure/Union member

priority2
    Structure/Union member

profile
    Structure/Union member

sys_phc_sync_interval
    Structure/Union member

class ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s

destports
    Structure/Union member
```

```
do_not_learn
    Structure/Union member

egr_port
    Structure/Union member

ing_port
    Structure/Union member

pad
    Structure/Union member

use_dest_ports
    Structure/Union member

vlan_egress
    Structure/Union member

vlan_ingress
    Structure/Union member

class ics.structures.s_pluto_switch_settings_s.s_pluto_switch_settings_s

flashHeader
    Structure/Union member

generalParams
    Structure/Union member

l2_ForwardingEntries
    Structure/Union member

l2_addressLookupEntries
    Structure/Union member

l2_addressLookupParams
    Structure/Union member

l2_forwardingParams
    Structure/Union member

l2_policing
    Structure/Union member

macConfig
    Structure/Union member

retagging
    Structure/Union member

vlan_LookupEntries
    Structure/Union member

class ics.structures.s_pluto_vl_forwarding_entry_s.s_pluto_vl_forwarding_entry_s

destports
    Structure/Union member

partition
    Structure/Union member
```

```
priority
    Structure/Union member

type
    Structure/Union member

class ics.structures.s_pluto_vl_forwarding_params_s.s_pluto_vl_forwarding_params_s

debugen
    Structure/Union member

pad
    Structure/Union member

partspc
    Structure/Union member

class ics.structures.s_pluto_vl_lookup_entry_s.s_pluto_vl_lookup_entry_s

Nameless11656
    Structure/Union member

vllupformat0
    Structure/Union member

vllupformat1
    Structure/Union member

class ics.structures.s_pluto_vl_policing_entry_s.s_pluto_vl_policing_entry_s

bag
    Structure/Union member

jitter
    Structure/Union member

maxlen
    Structure/Union member

sharindx
    Structure/Union member

type
    Structure/Union member

class ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_s

pad
    Structure/Union member

tag_port
    Structure/Union member

vegr_mirr
    Structure/Union member

ving_mirr
    Structure/Union member
```

```
vlan_bc
    Structure/Union member

vlanid
    Structure/Union member

vmemb_port
    Structure/Union member

class ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings

converter
    Structure/Union member

flags
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

class ics.structures.s_red2_settings.s_red2_settings

ain_threshold
    Structure/Union member

can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can5
    Structure/Union member

can6
    Structure/Union member

can7
    Structure/Union member

can8
    Structure/Union member
```

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

digitalIoThresholdEnable
Structure/Union member

digitalIoThresholdTicks
Structure/Union member

disk
Structure/Union member

ethernet2_1
Structure/Union member

ethernet2_2
Structure/Union member

ethernet_1
Structure/Union member

ethernet_2
Structure/Union member

flags
Structure/Union member

gPTP
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso_msg_termination_1
Structure/Union member

```
iso_msg_termination_2
    Structure/Union member

iso_parity_1
    Structure/Union member

iso_parity_2
    Structure/Union member

iso_tester_pullup_enable
    Structure/Union member

lin1
    Structure/Union member

lin2
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

os_settings
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

slaveVnetA
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member
```

```
timeSync
Structure/Union member

class ics.structures.s_red_settings.s_red_settings

can1
Structure/Union member

can2
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

class ics.structures.s_spi_port_setting.s_spi_port_setting

byte
Structure/Union member

config
Structure/Union member

class ics.structures.s_spi_port_settings.s_spi_port_settings

port_a
Structure/Union member

port_b
Structure/Union member

class ics.structures.s_text_api_settings.s_text_api_settings

can1_options
Structure/Union member

can1_rx_id
Structure/Union member

can1_tx_id
Structure/Union member

can2_options
Structure/Union member

can2_rx_id
Structure/Union member

can2_tx_id
Structure/Union member

can3_options
Structure/Union member

can3_rx_id
Structure/Union member
```

```
can3_tx_id
Structure/Union member

can4_options
Structure/Union member

can4_rx_id
Structure/Union member

can4_tx_id
Structure/Union member

network_enables
Structure/Union member

reserved
Structure/Union member

class ics.structures.s_vivid_can_settings.s_vivid_can_settings

can1
Structure/Union member

can_switch_mode
Structure/Union member

ecu_id
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

lsftcan1
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

swcan1
Structure/Union member

termination_enables
Structure/Union member

class ics.structures.s_wil_bridge_config.s_wil_bridge_config
```

```
config
    Structure/Union member

dword
    Structure/Union member

class ics.structures.s_wil_connection_settings.s_wil_connection_settings

attemptConnect
    Structure/Union member

fault_servicing_config
    Structure/Union member

network_data_capture_config
    Structure/Union member

sensor_buffer_size
    Structure/Union member

using_port_a
    Structure/Union member

using_port_b
    Structure/Union member

class ics.structures.s_wil_fault_servicing_settings.s_wil_fault_servicing_settings

enabled
    Structure/Union member

wBMSDeviceID
    Structure/Union member

class ics.structures.s_wil_network_data_capture_settings.s_wil_network_data_capture_se

enabled
    Structure/Union member

class ics.structures.scan_hub_settings.scan_hub_settings

can1
    Structure/Union member

canfd1
    Structure/Union member

ecu_id
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member
```

```
pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

sleep_id
    Structure/Union member

termination_enables
    Structure/Union member

class ics.structures.scan_sleep_id.scan_sleep_id

    id
        Structure/Union member

    word
        Structure/Union member

class ics.structures.secu_avb_settings.secu_avb_settings

    can1
        Structure/Union member

    can2
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    flags
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    network_enabled_on_boot
        Structure/Union member

    network_enables
        Structure/Union member

    perf_en
        Structure/Union member

    pwr_man_enable
        Structure/Union member

    pwr_man_timeout
        Structure/Union member

    termination_enables
        Structure/Union member

    text_api
        Structure/Union member
```

```
class ics.structures.secu_settings.secu_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    ecu_id
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    iso9141_kwp_settings
        Structure/Union member

    iso9141_kwp_settings_2
        Structure/Union member

    iso_msg_termination
        Structure/Union member

    iso_msg_termination_2
        Structure/Union member

    iso_parity
        Structure/Union member

    iso_parity_2
        Structure/Union member

    lin1
        Structure/Union member

    lin2
        Structure/Union member

    lsftcan
        Structure/Union member

    lsftcan2
        Structure/Union member

    misc_io_analog_enable
        Structure/Union member

    misc_io_initial_ddr
        Structure/Union member

    misc_io_initial_latch
        Structure/Union member

    misc_io_on_report_events
        Structure/Union member
```

```
misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

selected_network
    Structure/Union member

swcan
    Structure/Union member

swcan2
    Structure/Union member

text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

class ics.structures.seevb_settings.seevb_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    ecu_id
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    network_enabled_on_boot
        Structure/Union member

    network_enables
        Structure/Union member

    perf_en
        Structure/Union member
```

```
rsvd
    Structure/Union member

class ics.structures.serdescam_settings.serdescam_settings

    bitPos
        Structure/Union member

    flags
        Structure/Union member

    frameSkip
        Structure/Union member

    mode
        Structure/Union member

    resHeight
        Structure/Union member

    resWidth
        Structure/Union member

    rsvd1
        Structure/Union member

    rsvd2
        Structure/Union member

    videoFormat
        Structure/Union member

class ics.structures.serdesgen_settings.serdesgen_settings

    flags
        Structure/Union member

    mod_id
        Structure/Union member

    rsvd1
        Structure/Union member

    rsvd2
        Structure/Union member

    rx_speed
        Structure/Union member

    tx_speed
        Structure/Union member

class ics.structures.serdespoc_settings.serdespoc_settings

    chksum
        Structure/Union member

    mode
        Structure/Union member
```

```
    rsvd
        Structure/Union member

    voltage
        Structure/Union member

class ics.structures.sievb_settings.sievb_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    ecu_id
        Structure/Union member

    idle_wakeup_network_enables_1
        Structure/Union member

    idle_wakeup_network_enables_2
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    iso9141_kwp_settings
        Structure/Union member

    iso9141_kwp_settings_2
        Structure/Union member

    iso_msg_termination
        Structure/Union member

    iso_msg_termination_2
        Structure/Union member

    iso_parity
        Structure/Union member

    iso_parity_2
        Structure/Union member

    iso_tester_pullup_enable
        Structure/Union member

    lin1
        Structure/Union member

    lin2
        Structure/Union member

    misc_io_analog_enable
        Structure/Union member
```

```
misc_io_analog_enable_2
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved_1
    Structure/Union member

reserved_2
    Structure/Union member

selected_network
    Structure/Union member

text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

class ics.structures.sobd2_lc_settings.sobd2_lc_settings

    can1
        Structure/Union member

    can2
        Structure/Union member

    can3
        Structure/Union member

    can4
        Structure/Union member
```

```
can_switch_mode
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

canfd3
    Structure/Union member

canfd4
    Structure/Union member

disk
    Structure/Union member

ethernet
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso_msg_termination_1
    Structure/Union member

iso_parity_1
    Structure/Union member

lin1
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

swcan1
    Structure/Union member
```

```
text_api
    Structure/Union member

class ics.structures.sobd2_pro_settings.sobd2_pro_settings

can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can_switch_mode
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

canfd3
    Structure/Union member

canfd4
    Structure/Union member

ethernet
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso9141_kwp_settings_2
    Structure/Union member

iso_msg_termination_1
    Structure/Union member

iso_msg_termination_2
    Structure/Union member

iso_parity_1
    Structure/Union member

iso_parity_2
    Structure/Union member
```

```
lin1
    Structure/Union member

lin2
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

swcan1
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.sobd2_sim_settings.sobd2_sim_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    flags
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    misc_io_analog_enable
        Structure/Union member

    misc_io_initial_ddr
        Structure/Union member
```

```
misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.software_update_command.software_update_command

    commandData
        Structure/Union member

    commandSizeOrProgress
        Structure/Union member

    commandType
        Structure/Union member

    componentIdentifier
        Structure/Union member

    offset
        Structure/Union member

class ics.structures.spy_filter_long.spy_filter_long

    ByteDataLSB
        Structure/Union member

    ByteDataLength
        Structure/Union member

    ByteDataMSB
        Structure/Union member

    ByteDataMaskLSB
        Structure/Union member

    ByteDataMaskMSB
        Structure/Union member

    ExpectedLength
        Structure/Union member

    FrameMaster
        Structure/Union member
```

```
    Header
        Structure/Union member

    HeaderLength
        Structure/Union member

    HeaderMask
        Structure/Union member

    MiscData
        Structure/Union member

    MiscDataMask
        Structure/Union member

    NetworkID
        Structure/Union member

    NodeID
        Structure/Union member

    Status2Mask
        Structure/Union member

    Status2Value
        Structure/Union member

    StatusMask
        Structure/Union member

    StatusValue
        Structure/Union member

    bStuff2
        Structure/Union member

    bUseArbIdRangeFilter
        Structure/Union member

class ics.structures.srad_comet_settings.srad_comet_settings

    can1
        Structure/Union member

    can2
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    ecu_id
        Structure/Union member

    ethT1
        Structure/Union member

    ethT1sl
        Structure/Union member
```

ethT1s2
Structure/Union member

ethernet
Structure/Union member

flags
Structure/Union member

gPTP
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_5
Structure/Union member

opEth1
Structure/Union member

opEthGen
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reporting
Structure/Union member

t1s1
Structure/Union member

t1s2
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

```
timeSyncSettings
    Structure/Union member

class ics.structures.srad_epsilon_settings.srad_epsilon_settings

can1
    Structure/Union member

can2
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

ethernet
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_enable_reserved
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_parity
    Structure/Union member

iso_tester_pullup_enable
    Structure/Union member

lin1
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member
```

```
network_enables_3
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

switchSettings
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings

enablePhy
    Structure/Union member

legacy
    Structure/Union member

pad
    Structure/Union member

phyMode
    Structure/Union member

speed
    Structure/Union member

spoofMacFlag
    Structure/Union member

spoofedMac
    Structure/Union member

class ics.structures.srad_galaxy_settings.srad_galaxy_settings

ain_sample_period
    Structure/Union member

ain_threshold
    Structure/Union member

can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member
```

can4
Structure/Union member

can5
Structure/Union member

can6
Structure/Union member

can7
Structure/Union member

can8
Structure/Union member

can_switch_mode
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

disk
Structure/Union member

ethernet1
Structure/Union member

ethernet2
Structure/Union member

gPTP
Structure/Union member

hwComLatencyTestEn
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

```
idle_wakeup_network_enables_3
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso_9141_kwp_enable_reserved
    Structure/Union member

iso_msg_termination_1
    Structure/Union member

iso_parity_1
    Structure/Union member

lin1
    Structure/Union member

logger
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

network_enables_4
    Structure/Union member

network_enables_5
    Structure/Union member

opEth1
    Structure/Union member

opEth10
    Structure/Union member
```

```
opEth11
    Structure/Union member

opEth12
    Structure/Union member

opEth2
    Structure/Union member

opEth3
    Structure/Union member

opEth4
    Structure/Union member

opEth5
    Structure/Union member

opEth6
    Structure/Union member

opEth7
    Structure/Union member

opEth8
    Structure/Union member

opEth9
    Structure/Union member

opEthGen
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reporting
    Structure/Union member

swcan1
    Structure/Union member

swcan2
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.srad_gigalog_settings.srad_gigalog_settings

can1
    Structure/Union member
```

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

can5
Structure/Union member

can6
Structure/Union member

can7
Structure/Union member

can8
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

disk
Structure/Union member

ecu_id
Structure/Union member

ethernet
Structure/Union member

ethernet10g
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

```
idle_wakeup_network_enables_1
    Structure/Union member

idle_wakeup_network_enables_2
    Structure/Union member

idle_wakeup_network_enables_3
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso_9141_kwp_enable_reserved
    Structure/Union member

iso_msg_termination_1
    Structure/Union member

iso_parity_1
    Structure/Union member

lin1
    Structure/Union member

logger
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

network_enables_4
    Structure/Union member

network_enables_5
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reporting
    Structure/Union member

rsvd1
    Structure/Union member
```

```
rsvd2
    Structure/Union member

serdescam1
    Structure/Union member

serdescam2
    Structure/Union member

serdescam3
    Structure/Union member

serdescam4
    Structure/Union member

serdesgen
    Structure/Union member

serdespoc
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.srad_gigastar_settings.srad_gigastar_settings

can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can5
    Structure/Union member

can6
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

canfd3
    Structure/Union member

canfd4
    Structure/Union member
```

canfd5
Structure/Union member

canfd6
Structure/Union member

disk
Structure/Union member

ecu_id
Structure/Union member

ethernet1
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

gPTP
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

idle_wakeup_network_enables_3
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

logger
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

```
network_enables_3
    Structure/Union member

network_enables_4
    Structure/Union member

network_enables_5
    Structure/Union member

opEth1
    Structure/Union member

opEth2
    Structure/Union member

opEthGen
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reporting
    Structure/Union member

serdescam1
    Structure/Union member

serdescam2
    Structure/Union member

serdescam3
    Structure/Union member

serdescam4
    Structure/Union member

serdesgen
    Structure/Union member

serdespoc
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.srad_gptp_and_tap_settings_s.srad_gptp_and_tap_settings_s

gPTP
    Structure/Union member
```

```
    tap
        Structure/Union member

class ics.structures.srad_gptp_settings_s.srad_gptp_settings_s

    clockaccuracy
        Structure/Union member

    clockclass
        Structure/Union member

    enableClockSyntonization
        Structure/Union member

    gPTPportRole
        Structure/Union member

    gptpEnabledPort
        Structure/Union member

    logAnnounceInterval
        Structure/Union member

    logPDelayReqInterval
        Structure/Union member

    logSyncInterval
        Structure/Union member

    neighborPropDelayThresh
        Structure/Union member

    offset_scaled_log_variance
        Structure/Union member

    priority1
        Structure/Union member

    priority2
        Structure/Union member

    profile
        Structure/Union member

    rsvd
        Structure/Union member

    sys_phc_sync_interval
        Structure/Union member

class ics.structures.srad_jupiter_settings.srad_jupiter_settings

    can1
        Structure/Union member

    can2
        Structure/Union member

    canfd1
        Structure/Union member
```

canfd2
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_enable_reserved
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso_msg_termination
Structure/Union member

iso_parity
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

misc_io_analog_enable
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

switchSettings
Structure/Union member

termination_enables
Structure/Union member

```
text_api
    Structure/Union member

class ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings

enablePhy
    Structure/Union member

pad
    Structure/Union member

phyMode
    Structure/Union member

port7Select
    Structure/Union member

port8Legacy
    Structure/Union member

port8Select
    Structure/Union member

port8Speed
    Structure/Union member

ptpParams_unused
    Structure/Union member

spoofMacFlag
    Structure/Union member

spoofedMac
    Structure/Union member

class ics.structures.srad_moon2_settings.srad_moon2_settings

gPTP
    Structure/Union member

hwComLatencyTestEn
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

network_enables_5
    Structure/Union member

opEth1
    Structure/Union member
```

```
opEthGen
    Structure/Union member

pc_com_mode
    Structure/Union member

perf_en
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.srad_moon3_settings.srad_moon3_settings

autoEth10g
    Structure/Union member

eth10g
    Structure/Union member

flags
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

network_enables_5
    Structure/Union member

perf_en
    Structure/Union member

class ics.structures.srad_pluto_settings.srad_pluto_settings

can1
    Structure/Union member

can2
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

custom
    Structure/Union member
```

```
    ethernet
        Structure/Union member

    ethernet2
        Structure/Union member

    flags
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    iso9141_kwp_enable_reserved
        Structure/Union member

    iso9141_kwp_settings
        Structure/Union member

    iso_msg_termination
        Structure/Union member

    iso_parity
        Structure/Union member

    iso_tester_pullup_enable
        Structure/Union member

    lin1
        Structure/Union member

    misc_io_analog_enable
        Structure/Union member

    network_enabled_on_boot
        Structure/Union member

    network_enables
        Structure/Union member

    network_enables_2
        Structure/Union member

    network_enables_3
        Structure/Union member

    perf_en
        Structure/Union member

    pwr_man_enable
        Structure/Union member

    pwr_man_timeout
        Structure/Union member

    termination_enables
        Structure/Union member

    text_api
        Structure/Union member

class ics.structures.srad_star2_settings.srad_star2_settings
```

ain_sample_period
Structure/Union member

ain_threshold
Structure/Union member

can1
Structure/Union member

can2
Structure/Union member

can_switch_mode
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

ethernet
Structure/Union member

gPTP
Structure/Union member

hwComLatencyTestEn
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

idle_wakeup_network_enables_3
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

```
misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

network_enables_5
    Structure/Union member

opEth1
    Structure/Union member

opEth2
    Structure/Union member

opEthGen
    Structure/Union member

pc_com_mode
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reporting
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.srad_super_moon_settings.srad_super_moon_settings

Eth2
    Structure/Union member

gPTP
    Structure/Union member
```

```
hwComLatencyTestEn
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

network_enables_5
    Structure/Union member

opEth1
    Structure/Union member

opEthGen
    Structure/Union member

pc_com_mode
    Structure/Union member

perf_en
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.srada2_b_settings.srada2_b_settings

a2b_monitor
    Structure/Union member

a2b_node
    Structure/Union member

can1
    Structure/Union member

can2
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

disk
    Structure/Union member

ethernet
    Structure/Union member
```

```
flags
    Structure/Union member

gPTP
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso_msg_termination_1
    Structure/Union member

iso_parity_1
    Structure/Union member

lin1
    Structure/Union member

logger
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_5
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reporting
    Structure/Union member

termination_enables
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.sradbms_settings.sradbms_settings

can1
    Structure/Union member

can2
    Structure/Union member

canfd1
    Structure/Union member
```

canfd2
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

gateway
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

network_enables_4
Structure/Union member

network_enables_5
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

spi_config
Structure/Union member

termination_enables
Structure/Union member

wbms_wil_1
Structure/Union member

wbms_wil_2
Structure/Union member

will_nwk_metadata_buff_count
Structure/Union member

wil2_nwk_metadata_buff_count
Structure/Union member

```
wil_config
    Structure/Union member

class ics.structures.st_api_firmware_info.st_api_firmware_info

    iAppMajor
        Structure/Union member

    iAppMinor
        Structure/Union member

    iBoardRevMajor
        Structure/Union member

    iBoardRevMinor
        Structure/Union member

    iBootLoaderVersionMajor
        Structure/Union member

    iBootLoaderVersionMinor
        Structure/Union member

    iMainFirmChkSum
        Structure/Union member

    iMainFirmDateDay
        Structure/Union member

    iMainFirmDateHour
        Structure/Union member

    iMainFirmDateMin
        Structure/Union member

    iMainFirmDateMonth
        Structure/Union member

    iMainFirmDateSecond
        Structure/Union member

    iMainFirmDateYear
        Structure/Union member

    iMainVnetHWrevMajor
        Structure/Union member

    iMainVnetHWrevMinor
        Structure/Union member

    iMainVnetSRAMSize
        Structure/Union member

    iManufactureDay
        Structure/Union member

    iManufactureMonth
        Structure/Union member

    iManufactureYear
        Structure/Union member
```

```
iPhySiliconRev
    Structure/Union member

iType
    Structure/Union member

class ics.structures.st_chip_versions.st_chip_versions

    cmprobe_versions
        Structure/Union member

    epsilon_versions
        Structure/Union member

    ether_badge_versions
        Structure/Union member

    fire3_flexray_versions
        Structure/Union member

    fire3_versions
        Structure/Union member

    fire_versions
        Structure/Union member

    jupiter_versions
        Structure/Union member

    neoecu_avb_versions
        Structure/Union member

    obd2dev_versions
        Structure/Union member

    obd2lc_versions
        Structure/Union member

    obd2pro_versions
        Structure/Union member

    plasma_fire_vnet
        Structure/Union member

    pluto_versions
        Structure/Union member

    rad_a2b_versions
        Structure/Union member

    rad_comet_versions
        Structure/Union member

    rad_moon_duo_versions
        Structure/Union member

    rad_wbms_versions
        Structure/Union member

    radgalaxy_versions
        Structure/Union member
```

```
radgigalog3_versions
    Structure/Union member

radgigalog_versions
    Structure/Union member

radgigastar_usbz_versions
    Structure/Union member

radgigastar_versions
    Structure/Union member

radmoon2_versions
    Structure/Union member

radmoon2_z7010_versions
    Structure/Union member

radmoon3_versions
    Structure/Union member

radstar2_versions
    Structure/Union member

radsupermoon_versions
    Structure/Union member

red2_versions
    Structure/Union member

vcan3_versions
    Structure/Union member

vcan41_versions
    Structure/Union member

vcan42_versions
    Structure/Union member

vcanrf_versions
    Structure/Union member

vividcan_versions
    Structure/Union member

class ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message

Nameless61974
    Structure/Union member

blockSize
    Structure/Union member

cf_timeout
    Structure/Union member

enableFlowControlTransmission
    Structure/Union member

ext_address_enable
    Structure/Union member
```

```
    extendedAddress
        Structure/Union member

    fc_ext_address_enable
        Structure/Union member

    fc_id
        Structure/Union member

    fc_id_29_bit_enable
        Structure/Union member

    flags
        Structure/Union member

    flowControlExtendedAddress
        Structure/Union member

    id
        Structure/Union member

    id_29_bit_enable
        Structure/Union member

    id_mask
        Structure/Union member

    isBRSEnabled
        Structure/Union member

    iscanFD
        Structure/Union member

    padding
        Structure/Union member

    paddingEnable
        Structure/Union member

    reserved
        Structure/Union member

    stMin
        Structure/Union member

    vs_netid
        Structure/Union member

class ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message

    Nameless9252
        Structure/Union member

    blockSize
        Structure/Union member

    data
        Structure/Union member

    ext_address_enable
        Structure/Union member
```

extendedAddress
Structure/Union member

fc_ext_address_enable
Structure/Union member

fc_id
Structure/Union member

fc_id_29_bit_enable
Structure/Union member

fc_id_mask
Structure/Union member

flags
Structure/Union member

flowControlExtendedAddress
Structure/Union member

fs_timeout
Structure/Union member

fs_wait
Structure/Union member

id
Structure/Union member

id_29_bit_enable
Structure/Union member

isBRSEnabled
Structure/Union member

iscanFD
Structure/Union member

num_bytes
Structure/Union member

overrideBlockSize
Structure/Union member

overrideSTmin
Structure/Union member

padding
Structure/Union member

paddingEnable
Structure/Union member

stMin
Structure/Union member

tx_dl
Structure/Union member

tx_index
Structure/Union member

```
vs_netid
Structure/Union member

class ics.structures.start_dhcp_server_command.start_dhcp_server_command

endAddress
Structure/Union member

gatewayAddress
Structure/Union member

leaseTime
Structure/Union member

networkId
Structure/Union member

overwrite
Structure/Union member

serverIpAddress
Structure/Union member

startAddress
Structure/Union member

subnetMask
Structure/Union member

class ics.structures.stop_dhcp_server_command.stop_dhcp_server_command

networkId
Structure/Union member

class ics.structures.svcanc3_settings.svcan3_settings

can1
Structure/Union member

can2
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member
```

```
network_enables
    Structure/Union member

perf_en
    Structure/Union member

class ics.structures.svcancan412_settings.svcancan412_settings

can1
    Structure/Union member

can2
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.svcancan4_ind_settings.svcancan4_ind_settings

can1
    Structure/Union member

can2
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member
```

```
    ethernet
        Structure/Union member

    ethernet2
        Structure/Union member

    flags
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    iso9141_kwp_settings
        Structure/Union member

    iso_msg_termination
        Structure/Union member

    iso_parity
        Structure/Union member

    lin1
        Structure/Union member

    network_enabled_on_boot
        Structure/Union member

    network_enables
        Structure/Union member

    perf_en
        Structure/Union member

    pwr_man_enable
        Structure/Union member

    pwr_man_timeout
        Structure/Union member

    termination_enables
        Structure/Union member

class ics.structures.svcanc4_settings.svcanc4_settings

    can1
        Structure/Union member

    can2
        Structure/Union member

    can3
        Structure/Union member

    can4
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member
```

```
canfd3
    Structure/Union member

canfd4
    Structure/Union member

ethernet
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso_9141_kwp_enable_reserved
    Structure/Union member

iso_msg_termination_1
    Structure/Union member

iso_parity_1
    Structure/Union member

lin1
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.svcancrf_settings.svcancrf_settings
```

can1
Structure/Union member

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

disableFwLEDs
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_enable_reserved
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso_msg_termination
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_parity
Structure/Union member

iso_parity_2
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

```
misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reservedZero
    Structure/Union member

class ics.structures.swcan_settings.swcan_settings

    BRP
        Structure/Union member

    Baudrate
        Structure/Union member

    Mode
        Structure/Union member

    RESERVED
        Structure/Union member

    SetBaudrate
        Structure/Union member

    TqProp
        Structure/Union member

    TqSeg1
        Structure/Union member

    TqSeg2
        Structure/Union member

    TqSync
        Structure/Union member

    auto_baud
        Structure/Union member

    high_speed_auto_switch
        Structure/Union member
```

```
transceiver_mode
    Structure/Union member

class ics.structures.system_identity.system_identity

    clock_identity
        Structure/Union member

    clock_quality
        Structure/Union member

    priority_1
        Structure/Union member

    priority_2
        Structure/Union member

class ics.structures.tag_options_find_neo_ex.tag_options_find_neo_ex

    CANOptions
        Structure/Union member

    Reserved
        Structure/Union member

class ics.structures.tag_options_open_neo_ex.tag_options_open_neo_ex

    CANOptions
        Structure/Union member

    Reserved
        Structure/Union member

class ics.structures.tagicsneo_vi_command.tagicsneo_vi_command

    CommandByteLength
        Structure/Union member

    CommandType
        Structure/Union member

    Data
        Structure/Union member

class ics.structures.timestamp_.timestamp_

    nanoseconds
        Structure/Union member

    seconds_lsb
        Structure/Union member

    seconds_msb
        Structure/Union member

class ics.structures.timesync_icshardware_settings.timesync_icshardware_settings
```

```
    MasterEnable
        Structure/Union member

    MasterNetwork
        Structure/Union member

    SlaveEnable
        Structure/Union member

    SlaveNetwork
        Structure/Union member

class ics.structures.uart_port_config.uart_port_config

    baudrate
        Structure/Union member

    port
        Structure/Union member

    reserve
        Structure/Union member

class ics.structures.uart_port_data.uart_port_data

    bData
        Structure/Union member

    len
        Structure/Union member

    port
        Structure/Union member

class ics.structures.uart_port_port_bytes.uart_port_port_bytes

    flag
        Structure/Union member

    len
        Structure/Union member

    port
        Structure/Union member

class ics.structures.uart_settings.uart_settings

    Baudrate
        Structure/Union member

    Nameless2284
        Structure/Union member

    bOptions
        Structure/Union member

    brgh
        Structure/Union member
```

```
flow_control
    Structure/Union member

half_duplex
    Structure/Union member

invert_rx
    Structure/Union member

invert_tx
    Structure/Union member

parity
    Structure/Union member

reserved_1
    Structure/Union member

reserved_bits
    Structure/Union member

reserved_bits2
    Structure/Union member

spbrg
    Structure/Union member

stop_bits
    Structure/Union member

class ics.structures.version_report.version_report

    commitHash
        Structure/Union member

    componentInfo
        Structure/Union member

    dotVersion
        Structure/Union member

    expansionSlot
        Structure/Union member

    identifier
        Structure/Union member

    reserved
        Structure/Union member

    valid
        Structure/Union member

class ics.structures.w_bms_manager_reset.w_bms_manager_reset

    managerIndex
        Structure/Union member

class ics.structures.w_bms_manager_set_lock.w_bms_manager_set_lock
```

```
managerIndex
Structure/Union member

setLock
Structure/Union member

class ics.structures.wbms_gateway_settings.wbms_gateway_settings

reserved
Structure/Union member

wbms1_canfd_enable
Structure/Union member

wbms1_network
Structure/Union member

wbms2_canfd_enable
Structure/Union member

wbms2_network
Structure/Union member
```

CHAPTER 10

Module Variables

```
ics.ics.A2B_SETTINGS_FLAG_16BIT = 1
ics.ics.AUTO = 0
ics.ics.BPS100 = 5
ics.ics.BPS1000 = 10
ics.ics.BPS100000 = 7
ics.ics.BPS10400 = 1
ics.ics.BPS117647 = 8
ics.ics.BPS125 = 6
ics.ics.BPS20 = 0
ics.ics.BPS2000 = 12
ics.ics.BPS250 = 7
ics.ics.BPS33 = 1
ics.ics.BPS3333 = 2
ics.ics.BPS4000 = 13
ics.ics.BPS50 = 2
ics.ics.BPS500 = 8
ics.ics.BPS5000 = 0
ics.ics.BPS50000 = 3
ics.ics.BPS62 = 3
ics.ics.BPS62500 = 4
ics.ics.BPS666 = 11
ics.ics.BPS71429 = 5
```

```
  ics.ics.BPS800 = 9
  ics.ics.BPS83 = 4
  ics.ics.BPS83333 = 6
  ics.ics.BUILD_DATETIME = Jun 28 2023 16:13:59
  ics.ics.CANFD_BRS_ENABLED = 2
  ics.ics.CANFD_BRS_ENABLED_ISO = 4
  ics.ics.CANFD_ENABLED = 1
  ics.ics.CANFD_ENABLED_ISO = 3
  ics.ics.CANFD_SETTINGS_SIZE = 10
  ics.ics.CANNODE_STATUS_COREMINI_IS_RUNNING = 1
  ics.ics.CANNODE_STATUS_IN_BOOTLOADER = 2
  ics.ics.CANTERM_SETTINGS_SIZE = 6
  ics.ics.CAN_BPS10000 = 17
  ics.ics.CAN_BPS5000 = 14
  ics.ics.CAN_BPS6667 = 15
  ics.ics.CAN_BPS8000 = 16
  ics.ics.CAN_SETTINGS_SIZE = 12
  ics.ics.DEVICECOUNT_FOR_EXPLORER = 46
  ics.ics.DISABLE = 1
  ics.ics.DISK_SETTINGS_SIZE = 14
  ics.ics.DISK_STATUS_FLAG_INITIALIZED = 2
  ics.ics.DISK_STATUS_FLAG_PRESENT = 1
  ics.ics.DISK_STRUCTURE_FLAG_FULL_FORMAT = 1
  ics.ics.DRIVER_MASK = 192
  ics.ics.DRIVER_USB1 = 64
  ics.ics.DRIVER_USB2 = 128
  ics.ics.DRIVER_USB3 = 192
  ics.ics.ETHERNET10G_SETTINGS_SIZE = 24
  ics.ics.ETHERNET10T1S_SETTINGS_FLAG_ENABLE_PLCA = 1
  ics.ics.ETHERNET10T1S_SETTINGS_FLAG_TERMINATION = 2
  ics.ics.ETHERNET10T1S_SETTINGS_SIZE = 12
  ics.ics.ETHERNET_SETTINGS10G_FLAG_AUTO_NEG = 2
  ics.ics.ETHERNET_SETTINGS10G_FLAG_COMM_IN_USE = -2147483648
  ics.ics.ETHERNET_SETTINGS10G_FLAG_CONFIG_NOT_ALLOWED = 32
  ics.ics.ETHERNET_SETTINGS10G_FLAG_DEVICE_HOSTING_ENABLE = 16
  ics.ics.ETHERNET_SETTINGS10G_FLAG_FULL_DUPLEX = 1
```

```
    ics.ics.ETHERNET_SETTINGS10G_FLAG_ICS_SFP = 64
    ics.ics.ETHERNET_SETTINGS10G_FLAG_LINK_MODE = 128
    ics.ics.ETHERNET_SETTINGS10G_FLAG_LINK_MODE_AUTO = 512
    ics.ics.ETHERNET_SETTINGS10G_FLAG_PHY_MODE = 256
    ics.ics.ETHERNET_SETTINGS10G_FLAG_RTSP_ENABLE = 8
    ics.ics.ETHERNET_SETTINGS10G_FLAG_TCPIP_ENABLE = 4
    ics.ics.ETHERNET_SETTINGS2_FLAG2_LINK_MODE = 1
    ics.ics.ETHERNET_SETTINGS2_FLAG2_LINK_MODE_AUTO = 4
    ics.ics.ETHERNET_SETTINGS2_FLAG2_PHY_MODE = 2
    ics.ics.ETHERNET_SETTINGS2_FLAG_AUTO_NEG = 2
    ics.ics.ETHERNET_SETTINGS2_FLAG_COMM_IN_USE = 128
    ics.ics.ETHERNET_SETTINGS2_FLAG_CONFIG_NOT_ALLOWED = 32
    ics.ics.ETHERNET_SETTINGS2_FLAG_DEVICE_HOSTING_ENABLE = 16
    ics.ics.ETHERNET_SETTINGS2_FLAG_FULL_DUPLEX = 1
    ics.ics.ETHERNET_SETTINGS2_FLAG_ICS_SFP = 64
    ics.ics.ETHERNET_SETTINGS2_FLAG_RTSP_ENABLE = 8
    ics.ics.ETHERNET_SETTINGS2_FLAG_TCPIP_ENABLE = 4
    ics.ics.ETHERNET_SETTINGS2_SIZE = 16
    ics.ics.ETHERNET_SETTINGS_SIZE = 8
    ics.ics.EXTENDED_RESPONSE_INVALID_COMMAND = -1
    ics.ics.EXTENDED_RESPONSE_INVALID_PARAMETER = -5
    ics.ics.EXTENDED_RESPONSE_INVALID_STATE = -2
    ics.ics.EXTENDED_RESPONSE_OK = 0
    ics.ics.EXTENDED_RESPONSE_OPERATION_FAILED = -3
    ics.ics.EXTENDED_RESPONSE_OPERATION_PENDING = -4
    ics.ics.FAST_MODE = 3
    ics.ics.FIRE2_REPORT_EMISC1_ANALOG = 32
    ics.ics.FIRE2_REPORT_EMISC1_DIGITAL = 2
    ics.ics.FIRE2_REPORT_EMISC2_ANALOG = 64
    ics.ics.FIRE2_REPORT_EMISC2_DIGITAL = 4
    ics.ics.FIRE2_REPORT_GPS = 1024
    ics.ics.FIRE2_REPORT_MISC5_DIGITAL = 8
    ics.ics.FIRE2_REPORT_MISC6_DIGITAL = 16
    ics.ics.FIRE2_REPORT_PERIODIC = 1
    ics.ics.FIRE2_REPORT_PWM_IN = 512
    ics.ics.FIRE2_REPORT_TEMP_ANALOG = 256
```

```
ics.ics.FIRE2_REPORT_VBATT_ANALOG = 128
ics.ics.FIRE3_REPORT_ORIENTATION = 2048
ics.ics.GENERIC_API_DATA_BUFFER_SIZE = 513
ics.ics.GENERIC_BINARY_STATUS_ERROR_ANY_MASK = 7
ics.ics.GENERIC_BINARY_STATUS_ERROR_BINARY_EMPTY = 4
ics.ics.GENERIC_BINARY_STATUS_ERROR_OVERSIZE = 2
ics.ics.GENERIC_BINARY_STATUS_ERROR_UNKNOWN_BINARY = 1
ics.ics.GET_SUPPORTED_FEATURES_COMMAND_VERSION = 1
ics.ics.GLOBAL_SETTINGS_SIZE = 1478
ics.ics.GS_VERSION = 5
ics.ics.HARDWARE_TIMESTAMP_ID_AVT_716 = 2
ics.ics.HARDWARE_TIMESTAMP_ID_AVT_717 = 5
ics.ics.HARDWARE_TIMESTAMP_ID_DOUBLE_SEC = 7
ics.ics.HARDWARE_TIMESTAMP_ID_NEORED_10NS = 10
ics.ics.HARDWARE_TIMESTAMP_ID_NEORED_10US = 8
ics.ics.HARDWARE_TIMESTAMP_ID_NEORED_25NS = 9
ics.ics.HARDWARE_TIMESTAMP_ID_NEOVI = 4
ics.ics.HARDWARE_TIMESTAMP_ID_NI_CAN = 3
ics.ics.HARDWARE_TIMESTAMP_ID_NONE = 0
ics.ics.HARDWARE_TIMESTAMP_ID_VSI = 1
ics.ics.HW_ETH_SETTINGS_SIZE = 20
ics.ics.ISO15765_2_NETWORK_HSCAN = 1
ics.ics.ISO15765_2_NETWORK_HSCAN2 = 4
ics.ics.ISO15765_2_NETWORK_HSCAN3 = 8
ics.ics.ISO15765_2_NETWORK_HSCAN4 = 20
ics.ics.ISO15765_2_NETWORK_HSCAN5 = 24
ics.ics.ISO15765_2_NETWORK_HSCAN6 = 28
ics.ics.ISO15765_2_NETWORK_HSCAN7 = 32
ics.ics.ISO15765_2_NETWORK_MSCAN = 2
ics.ics.ISO15765_2_NETWORK_SWCAN = 16
ics.ics.ISO15765_2_NETWORK_SWCAN2 = 36
ics.ics.ISO9141_KEYWORD2000_SETTINGS_SIZE = 114
ics.ics.ISO9141_KEYWORD2000_INIT_STEP_SIZE = 6
ics.ics.J1708_SETTINGS_SIZE = 2
ics.ics.JUPITER_PTP_ROLE_DISABLED = 0
ics.ics.JUPITER_PTP_ROLE_MASTER = 1
```

```
  ics.ics.JUPITER_PTP_ROLE_SLAVE = 2
  ics.ics.LINUX_BOOT_ALLOWED = 1
  ics.ics.LINUX_CONFIG_PORT_ETH_01 = 1
  ics.ics.LINUX_CONFIG_PORT_ETH_02 = 2
  ics.ics.LINUX_CONFIG_PORT_NONE = 0
  ics.ics.LIN_SETTINGS_SIZE = 10
  ics.ics.LISTEN_ALL = 7
  ics.ics.LISTEN_ONLY = 3
  ics.ics.LOGGER_SETTINGS_SIZE = 4
  ics.ics.LOOPBACK = 2
  ics.ics.MAIN_VNET = 1
  ics.ics.MAX_NUMBYTES_PHYSETTINGS = 512
  ics.ics.MAX_PHY_REG_PKT_ENTRIES = 128
  ics.ics.MAX_PHY_SETTINGS_STRUCT = 128
  ics.ics.MAX_REPORTED VERSIONS = 16
  ics.ics.MAX_VL_FORWARDING_ENTRIES = 1024
  ics.ics.MAX_VL_POLICING_ENTRIES = 1024
  ics.ics.NEODEVICE_ANY_ION = 262144
  ics.ics.NEODEVICE_ANY_PLASMA = 4096
  ics.ics.NEODEVICE_BLUE = 1
  ics.ics.NEODEVICE_CMPROBE = 8388608
  ics.ics.NEODEVICE_CT_OBD = 32768
  ics.ics.NEODEVICE_DONT_REUSE0 = 8192
  ics.ics.NEODEVICE_DONT_REUSE1 = 65536
  ics.ics.NEODEVICE_DONT_REUSE2 = 131072
  ics.ics.NEODEVICE_DONT_REUSE3 = 1048576
  ics.ics.NEODEVICE_DW_VCAN = 4
  ics.ics.NEODEVICE_ECU = 128
  ics.ics.NEODEVICE_ECU22 = 27
  ics.ics.NEODEVICE_ECUCHIP_UART = 2048
  ics.ics.NEODEVICE_ECU_AVB = 2
  ics.ics.NEODEVICE_EEVB = 16777216
  ics.ics.NEODEVICE_ETHER_BADGE = 22
  ics.ics.NEODEVICE_FIRE = 8
  ics.ics.NEODEVICE_FIRE2 = 67108864
  ics.ics.NEODEVICE_FIRE2_REDLINE = 21
```

```
    ics.ics.NEODEVICE_FIRE3 = 15
    ics.ics.NEODEVICE_FIRE3_FLEXRAY = 37
    ics.ics.NEODEVICE_FLEX = 134217728
    ics.ics.NEODEVICE_GIGASTAR = 19
    ics.ics.NEODEVICE_IIEVB = 256
    ics.ics.NEODEVICE_ION = 262144
    ics.ics.NEODEVICE_NEOANALOG = 16384
    ics.ics.NEODEVICE_NEOECU12 = 12
    ics.ics.NEODEVICE_NEOECUCHIP = 256
    ics.ics.NEODEVICE_NEW_DEVICE_58 = 31
    ics.ics.NEODEVICE_NEW_DEVICE_59 = 33
    ics.ics.NEODEVICE_OBD2_DEV = 26
    ics.ics.NEODEVICE_OBD2_LC = 13
    ics.ics.NEODEVICE_OBD2_PRO = 1024
    ics.ics.NEODEVICE_OBD2_SIM = -2147483648
    ics.ics.NEODEVICE_OBD2_SIM_DOIP = 25
    ics.ics.NEODEVICE_PENDANT = 512
    ics.ics.NEODEVICE_PLASMA = 4096
    ics.ics.NEODEVICE_RADCOMET = 36
    ics.ics.NEODEVICE_RADEPSILON = 24
    ics.ics.NEODEVICE_RADEPSILON_EXPRESS = 29
    ics.ics.NEODEVICE_RADEPSILON_T = 28
    ics.ics.NEODEVICE_RADGALAXY = 268435456
    ics.ics.NEODEVICE_RADGIGALOG = 6
    ics.ics.NEODEVICE_RADIO_CANHUB = 11
    ics.ics.NEODEVICE_RADJUPITER = 17
    ics.ics.NEODEVICE_RADMOON2 = 5
    ics.ics.NEODEVICE_RADMOON3 = 35
    ics.ics.NEODEVICE_RADPLUTO = 9
    ics.ics.NEODEVICE_RADPROXIMA = 30
    ics.ics.NEODEVICE_RADSTAR = 524288
    ics.ics.NEODEVICE_RADSTAR2 = 536870912
    ics.ics.NEODEVICE_RADSUPERMOON = 3
    ics.ics.NEODEVICE_RAD_A2B = 23
    ics.ics.NEODEVICE_RAD_BMS = 34
    ics.ics.NEODEVICE_RAD_MOON_DUO = 14
```

```
ics.ics.NEODEVICE_RED = 64
ics.ics.NEODEVICE_RED2 = 20
ics.ics.NEODEVICE_RED2_OEM = 38
ics.ics.NEODEVICE_UNKNOWN = 0
ics.ics.NEODEVICE_VCAN3 = 16
ics.ics.NEODEVICE_VCAN41 = 7
ics.ics.NEODEVICE_VCAN42 = 4194304
ics.ics.NEODEVICE_VCAN42_EL = 10
ics.ics.NEODEVICE_VCAN44 = 2097152
ics.ics.NEODEVICE_VCAN4_IND = 18
ics.ics.NEODEVICE_VCANRF = 33554432
ics.ics.NEODEVICE_VIVIDCAN = 1073741824
ics.ics.NEOVI6_VCAN_TIMESTAMP_1 = 1e-06
ics.ics.NEOVI6_VCAN_TIMESTAMP_2 = 0.065536
ics.ics.NEOVIPRO_VCAN_TIMESTAMP_1 = 1e-06
ics.ics.NEOVIPRO_VCAN_TIMESTAMP_2 = 0.065536
ics.ics.NEOVI_3G_MAX_SETTINGS_SIZE = 1478
ics.ics.NEOVI_COMMTYPE_FIRE_USB = 5
ics.ics.NEOVI_COMMTYPE_RS232 = 0
ics.ics.NEOVI_COMMTYPE_TCPIP = 3
ics.ics.NEOVI_COMMTYPE_USB_BULK = 1
ics.ics.NEOVI_RED_TIMESTAMP_1_10NS = 1e-08
ics.ics.NEOVI_RED_TIMESTAMP_1_25NS = 2.5e-08
ics.ics.NEOVI_RED_TIMESTAMP_2_10NS = 429.4967296
ics.ics.NEOVI_RED_TIMESTAMP_2_25NS = 107.3741824
ics.ics.NEOVI_TIMESTAMP_1 = 1.6e-06
ics.ics.NEOVI_TIMESTAMP_2 = 0.1048576
ics.ics.NEO_CFG_MPIC_HS_CAN_CNF1 = 522
ics.ics.NEO_CFG_MPIC_HS_CAN_CNF2 = 521
ics.ics.NEO_CFG_MPIC_HS_CAN_CNF3 = 520
ics.ics.NEO_CFG_MPIC_HS_CAN_MODE = 566
ics.ics.NEO_CFG_MPIC_LSFT_CAN_CNF1 = 558
ics.ics.NEO_CFG_MPIC_LSFT_CAN_CNF2 = 557
ics.ics.NEO_CFG_MPIC_LSFT_CAN_CNF3 = 556
ics.ics.NEO_CFG_MPIC_MS_CAN_CNF1 = 534
ics.ics.NEO_CFG_MPIC_MS_CAN_CNF2 = 533
```

```
    ics.ics.NEO_CFG_MPIC_MS_CAN_CNF3 = 532
    ics.ics.NEO_CFG_MPIC_SW_CAN_CNF1 = 546
    ics.ics.NEO_CFG_MPIC_SW_CAN_CNF2 = 545
    ics.ics.NEO_CFG_MPIC_SW_CAN_CNF3 = 544
    ics.ics.NETID_3G_APP_SIGNAL_STATUS = 56
    ics.ics.NETID_3G_FB_STATUS = 55
    ics.ics.NETID_3G_LOGGING_OVERFLOW = 59
    ics.ics.NETID_3G_READ_DATALINK_CM_RX_MSG = 58
    ics.ics.NETID_3G_READ_DATALINK_CM_TX_MSG = 57
    ics.ics.NETID_3G_READ_SETTINGS_EX = 60
    ics.ics.NETID_3G_RESET_STATUS = 54
    ics.ics.NETID_A2B_01 = 522
    ics.ics.NETID_A2B_02 = 523
    ics.ics.NETID_AUTOSAR = 515
    ics.ics.NETID_AUX = 7
    ics.ics.NETID_CAN_SWITCH = 526
    ics.ics.NETID_CGI = 53
    ics.ics.NETID_DATA_TO_HOST = 70
    ics.ics.NETID_DEVICE = 0
    ics.ics.NETID_DEVICE_STATUS = 513
    ics.ics.NETID_DWCAN_09 = 534
    ics.ics.NETID_DWCAN_10 = 535
    ics.ics.NETID_DWCAN_11 = 536
    ics.ics.NETID_DWCAN_12 = 537
    ics.ics.NETID_DWCAN_13 = 538
    ics.ics.NETID_DWCAN_14 = 539
    ics.ics.NETID_DWCAN_15 = 540
    ics.ics.NETID_DWCAN_16 = 541
    ics.ics.NETID_ETHERNET = 93
    ics.ics.NETID_ETHERNET2 = 520
    ics.ics.NETID_ETHERNET3 = 524
    ics.ics.NETID_ETHERNET_DAQ = 69
    ics.ics.NETID_ETHERNET_TX_WRAP = 521
    ics.ics.NETID_FLEXRAY = 85
    ics.ics.NETID_FLEXRAY1A = 80
    ics.ics.NETID_FLEXRAY1B = 81
```

```
  ics.ics.NETID_FLEXRAY2 = 86
  ics.ics.NETID_FLEXRAY2A = 82
  ics.ics.NETID_FLEXRAY2B = 83
  ics.ics.NETID_FORDSCP = 5
  ics.ics.NETID_FORWARDED_MESSAGE = 516
  ics.ics.NETID_GMFSA = 94
  ics.ics.NETID_HSCAN = 1
  ics.ics.NETID_HSCAN2 = 42
  ics.ics.NETID_HSCAN3 = 44
  ics.ics.NETID_HSCAN4 = 61
  ics.ics.NETID_HSCAN5 = 62
  ics.ics.NETID_HSCAN6 = 96
  ics.ics.NETID_HSCAN7 = 97
  ics.ics.NETID_HW_COM_LATENCY_TEST = 512
  ics.ics.NETID_I2C1 = 88
  ics.ics.NETID_I2C2 = 517
  ics.ics.NETID_I2C3 = 518
  ics.ics.NETID_I2C4 = 519
  ics.ics.NETID_INVALID = 65535
  ics.ics.NETID_ISM_LOGGER = 525
  ics.ics.NETID_ISO = 9
  ics.ics.NETID_ISO14230 = 15
  ics.ics.NETID_ISO2 = 14
  ics.ics.NETID_ISO3 = 41
  ics.ics.NETID_ISO4 = 47
  ics.ics.NETID_ISOPIC = 10
  ics.ics.NETID_J1708 = 6
  ics.ics.NETID_JVPW = 8
  ics.ics.NETID_LIN = 16
  ics.ics.NETID_LIN2 = 48
  ics.ics.NETID_LIN3 = 49
  ics.ics.NETID_LIN4 = 50
  ics.ics.NETID_LIN5 = 84
  ics.ics.NETID_LIN6 = 98
  ics.ics.NETID_LIN_07 = 542
  ics.ics.NETID_LIN_08 = 543
```

```
    ics.ics.NETID_LSFTCAN = 4
    ics.ics.NETID_LSFTCAN2 = 99
    ics.ics.NETID_MAIN51 = 11
    ics.ics.NETID_MAX = 100
    ics.ics.NETID_MDIO_01 = 545
    ics.ics.NETID_MDIO_02 = 546
    ics.ics.NETID_MDIO_03 = 547
    ics.ics.NETID_MDIO_04 = 548
    ics.ics.NETID_MDIO_05 = 549
    ics.ics.NETID_MDIO_06 = 550
    ics.ics.NETID_MDIO_07 = 551
    ics.ics.NETID_MDIO_08 = 552
    ics.ics.NETID_MOST = 51
    ics.ics.NETID_MOST150 = 92
    ics.ics.NETID_MOST25 = 90
    ics.ics.NETID_MOST50 = 91
    ics.ics.NETID_MSCAN = 2
    ics.ics.NETID_OP_ETHERNET1 = 17
    ics.ics.NETID_OP_ETHERNET10 = 78
    ics.ics.NETID_OP_ETHERNET11 = 79
    ics.ics.NETID_OP_ETHERNET12 = 87
    ics.ics.NETID_OP_ETHERNET2 = 18
    ics.ics.NETID_OP_ETHERNET3 = 19
    ics.ics.NETID_OP_ETHERNET4 = 45
    ics.ics.NETID_OP_ETHERNET5 = 46
    ics.ics.NETID_OP_ETHERNET6 = 73
    ics.ics.NETID_OP_ETHERNET7 = 75
    ics.ics.NETID_OP_ETHERNET8 = 76
    ics.ics.NETID_OP_ETHERNET9 = 77
    ics.ics.NETID_RED = 12
    ics.ics.NETID_RED_APP_ERROR = 52
    ics.ics.NETID_RED_VBAT = 74
    ics.ics.NETID_RS232 = 63
    ics.ics.NETID_SCI = 13
    ics.ics.NETID_SPI1 = 72
    ics.ics.NETID_SPI2 = 544
```

```
  ics.ics.NETID_SWCAN = 3
  ics.ics.NETID_SWCAN2 = 68
  ics.ics.NETID_TCP = 95
  ics.ics.NETID_TEXTAPI_TO_HOST = 71
  ics.ics.NETID_UART = 64
  ics.ics.NETID_UART2 = 65
  ics.ics.NETID_UART3 = 66
  ics.ics.NETID_UART4 = 67
  ics.ics.NETID_UDP = 514
  ics.ics.NETID_WBMS = 532
  ics.ics.NETID_WBMS2 = 533
  ics.ics.NORMAL = 0
  ics.ics.NORMAL_MODE = 2
  ics.ics.NO_CANFD = 0
  ics.ics.NUM_DEVICE_FEATURE_BITFIELDS = 1
  ics.ics.NUM_VALID_DEVICE_FEATURES = 17
  ics.ics.OPETH_FUNC_MEDIACONVERTER = 1
  ics.ics.OPETH_FUNC_RAW_MEDIA_CONVERTER = 3
  ics.ics.OPETH_FUNC_RAW_MEDIA_CONVERTER2 = 4
  ics.ics.OPETH_FUNC_RAW_MEDIA_CONVERTER2_LOW_LATENCY = 5
  ics.ics.OPETH_FUNC_TAP = 0
  ics.ics.OPETH_FUNC_TAP_LOW_LATENCY = 2
  ics.ics.OPETH_LINK_AUTO = 0
  ics.ics.OPETH_LINK_MASTER = 1
  ics.ics.OPETH_LINK_SLAVE = 2
  ics.ics.OPETH_MAC_SPOOF_DST_ADDR = 0
  ics.ics.OPETH_MAC_SPOOF_SRC_ADDR = 1
  ics.ics.OP_ETH_GENERAL_SETTINGS_SIZE = 20
  ics.ics.OP_ETH_SETTINGS_SIZE = 16
  ics.ics.PHYREG_BOTH = 2
  ics.ics.PHYREG_FAILURE = 1
  ics.ics.PHYREG_INVALID_MDIO_BUS_INDEX = 2
  ics.ics.PHYREG_INVALID_PHY_ADDR = 3
  ics.ics.PHYREG_READ = 0
  ics.ics.PHYREG_RESERVED1 = 5
  ics.ics.PHYREG_RESERVED2 = 6
```

```
    ics.ics.PHYREG_RESERVED3 = 7
    ics.ics.PHYREG_SUCCESS = 0
    ics.ics.PHYREG_UNSUPPORTED_MDIO_CLAUSE = 4
    ics.ics.PHYREG_WRITE = 1
    ics.ics.PHY_REG_PKT_VERSION = 1
    ics.ics.PLASMA_SLAVE1_OFFSET = 100
    ics.ics.PLASMA_SLAVE1_OFFSET_RANGE2 = 4608
    ics.ics.PLASMA_SLAVE2_OFFSET = 200
    ics.ics.PLASMA_SLAVE2_OFFSET_RANGE2 = 8704
    ics.ics.PLASMA_SLAVE3_OFFSET_RANGE2 = 12800
    ics.ics.PLASMA_SLAVE_NUM = 51
    ics.ics.PLUTO_MAX_FORWARDING_ENTRIES = 13
    ics.ics.PLUTO_MAX_L2_ADDRESS_LOOKUP = 1024
    ics.ics.PLUTO_MAX_L2_POLICING = 45
    ics.ics.PLUTO_MAX_MAC_CONFIG_ENTRIES = 5
    ics.ics.PLUTO_MAX RETAGGING_ENTRIES = 32
    ics.ics.PLUTO_MAX_VLAN_LOOKUP = 4096
    ics.ics.PLUTO_NUM_PORTS = 5
    ics.ics.PLUTO_NUM_PRIORITY = 8
    ics.ics.RADEPSILON_MAX_PHY = 18
    ics.ics.RADEPSILON_NUM_PORTS = 9
    ics.ics.RADJUPITER_NUM_PORTS = 8
    ics.ics.RADMOONDUO_CONVERTER_SETTINGS_SIZE = 16
    ics.ics.RAD_GPTP_AND_TAP_SETTINGS_SIZE = 40
    ics.ics.RAD_GPTP_SETTINGS_SIZE = 36
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_AIN1 = 256
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_FAN_SPEED_ENABLE = 1024
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_INT_GPS_ENABLE = 4
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE = 2
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE2 = 8
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC1_DIN = 16
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC1_PWMIN = 64
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC2_DIN = 32
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC2_PWMIN = 128
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_SERDES_ENABLE = 512
    ics.ics.RAD_REPORTING_SETTINGS_FLAG_TEMP_ENABLE = 1
```

```
  ics.ics.RAD_REPORTING_SETTINGS_SIZE = 16
  ics.ics.REGISTER_BY_SERIAL = 16
  ics.ics.REPORT_ON_GPS = 15
  ics.ics.REPORT_ON_KLINE = 9
  ics.ics.REPORT_ON_LED1 = 7
  ics.ics.REPORT_ON_LED2 = 8
  ics.ics.REPORT_ON_MISC1 = 1
  ics.ics.REPORT_ON_MISC2 = 2
  ics.ics.REPORT_ON_MISC3 = 3
  ics.ics.REPORT_ON_MISC3_AIN = 10
  ics.ics.REPORT_ON_MISC4 = 4
  ics.ics.REPORT_ON_MISC4_AIN = 11
  ics.ics.REPORT_ON_MISC5 = 5
  ics.ics.REPORT_ON_MISC5_AIN = 12
  ics.ics.REPORT_ON_MISC6 = 6
  ics.ics.REPORT_ON_MISC6_AIN = 13
  ics.ics.REPORT_ON_PERIODIC = 0
  ics.ics.RESISTOR_OFF = 1
  ics.ics.RESISTOR_ON = 0
  ics.ics.SCRIPT_LOCATION_EMMC = 6
  ics.ics.SCRIPT_LOCATION_FLASH_MEM = 0
  ics.ics.SCRIPT_LOCATION_INTERNAL_FLASH = 2
  ics.ics.SCRIPT_LOCATION_SDCARD = 1
  ics.ics.SCRIPT_LOCATION_VCAN3_MEM = 4
  ics.ics.SCRIPT_STATUS_RUNNING = 1
  ics.ics.SCRIPT_STATUS_STOPPED = 0
  ics.ics.SERDESCAM_MODE_COUNT = 4
  ics.ics.SERDESCAM_MODE_CUSTOM = 3
  ics.ics.SERDESCAM_MODE_LOG_ONLY = 2
  ics.ics.SERDESCAM_MODE_SPLITTER = 1
  ics.ics.SERDESCAM_MODE_TAP_REPEAT = 0
  ics.ics.SERDESCAM_PIXEL_BIT_POS_0 = 0
  ics.ics.SERDESCAM_PIXEL_BIT_POS_1 = 1
  ics.ics.SERDESCAM_PIXEL_BIT_POS_2 = 2
  ics.ics.SERDESCAM_PIXEL_BIT_POS_3 = 3
  ics.ics.SERDESCAM_SETTINGS_FLAG_AUTO_DET_RES_ENABLE = 4
```

```
    ics.ics.SERDESCAM_SETTINGS_FLAG_CONFIG_ENABLE = 8
    ics.ics.SERDESCAM_SETTINGS_FLAG_ENABLE = 1
    ics.ics.SERDESCAM_SETTINGS_FLAG_LOGGING_ENABLE = 16
    ics.ics.SERDESCAM_SETTINGS_FLAG_RTSP_ENABLE = 2
    ics.ics.SERDESCAM_SETTINGS_FLAG_TX0_ENABLE = 32
    ics.ics.SERDESCAM_SETTINGS_FLAG_TX1_ENABLE = 64
    ics.ics.SERDESCAM_SETTINGS_FLAG_TX2_ENABLE = 128
    ics.ics.SERDESCAM_SETTINGS_FLAG_TX3_ENABLE = 256
    ics.ics.SERDESCAM_SETTINGS_SIZE = 32
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_10LE_PACKED = 19
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_12LE_PACKED = 20
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16BE = 22
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16LE = 21
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_8 = 4
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_10LE_PACKED = 74
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_12LE_PACKED = 75
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_16BE = 77
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_16LE = 76
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_8 = 73
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_10LE_PACKED = 82
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_12LE_PACKED = 83
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_16BE = 85
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_16LE = 84
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_8 = 81
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_10LE_PACKED = 66
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_12LE_PACKED = 67
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_16BE = 69
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_16LE = 68
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_8 = 65
    ics.ics.SERDESCAM_VIDEO_FORMAT_COUNT = 89
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_10LE_PACKED = 51
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_12LE_PACKED = 52
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_8 = 50
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GBRG_10LE_PACKED = 79
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GBRG_12LE_PACKED = 80
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GBRG_8 = 78
```

```
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GRBG_10LE_PACKED = 87
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GRBG_12LE_PACKED = 88
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GRBG_8 = 86
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_RGGB_10LE_PACKED = 71
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_RGGB_12LE_PACKED = 72
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_RGGB_8 = 70
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_10 = 54
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_12 = 56
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_14 = 58
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_16 = 59
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_20 = 60
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_24 = 61
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_30 = 62
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_32 = 63
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_36 = 64
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_8 = 53
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RGB565 = 47
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RGB666 = 48
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RGB888 = 49
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_10LE_PACKED = 39
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_12LE_PACKED = 43
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_8 = 35
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_10LE_PACKED = 42
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_12LE_PACKED = 46
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_8 = 38
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_10LE_PACKED = 40
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_12LE_PACKED = 44
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_8 = 36
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_10LE_PACKED = 41
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_12LE_PACKED = 45
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_8 = 37
    ics.ics.SERDESCAM_VIDEO_FORMAT_JPEG = 23
    ics.ics.SERDESCAM_VIDEO_FORMAT_NONE = -1
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_10 = 6
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_12 = 7
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_14 = 34
```

```
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_16 = 8
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_20 = 9
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_24 = 10
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_30 = 11
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_32 = 12
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_36 = 13
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_8 = 5
    ics.ics.SERDESCAM_VIDEO_FORMAT_RGB565 = 30
    ics.ics.SERDESCAM_VIDEO_FORMAT_RGB666 = 31
    ics.ics.SERDESCAM_VIDEO_FORMAT_RGB888 = 14
    ics.ics.SERDESCAM_VIDEO_FORMAT_UYVY_422_10LE_PACKED = 15
    ics.ics.SERDESCAM_VIDEO_FORMAT_UYVY_422_12LE_PACKED = 24
    ics.ics.SERDESCAM_VIDEO_FORMAT_UYVY_422_8 = 0
    ics.ics.SERDESCAM_VIDEO_FORMAT_VYUY_422_10LE_PACKED = 18
    ics.ics.SERDESCAM_VIDEO_FORMAT_VYUY_422_12LE_PACKED = 27
    ics.ics.SERDESCAM_VIDEO_FORMAT_VYUY_422_8 = 3
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUV422_10LE_PLANAR = 28
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUV422_16LE_PLANAR = 29
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUYV_422_10LE_PACKED = 16
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUYV_422_12LE_PACKED = 25
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUYV_422_8 = 1
    ics.ics.SERDESCAM_VIDEO_FORMAT_YVYU_422_10LE_PACKED = 17
    ics.ics.SERDESCAM_VIDEO_FORMAT_YVYU_422_12LE_PACKED = 26
    ics.ics.SERDESCAM_VIDEO_FORMAT_YVYU_422_8 = 2
    ics.ics.SERDESGEN_MOD_ID_NONE = 0
    ics.ics.SERDESGEN_MOD_ID_UNKNOWN = -1
    ics.ics.SERDESGEN_SETTINGS_FLAG_TX_PATGEN_ENABLE = 1
    ics.ics.SERDESGEN_SETTINGS_SIZE = 32
    ics.ics.SERDESPOC_SETTINGS_MODE_DISABLED = 0
    ics.ics.SERDESPOC_SETTINGS_MODE_SERIALIZER = 2
    ics.ics.SERDESPOC_SETTINGS_MODE_SUPPLY = 1
    ics.ics.SERDESPOC_SETTINGS_SIZE = 10
    ics.ics.SLAVE_VNET_A = 2
    ics.ics.SLAVE_VNET_B = 4
    ics.ics.SLEEP_MODE = 0
    ics.ics.SLOW_MODE = 1
```

```
  ics.ics.SPI_MODE_MASTER = 0
  ics.ics.SPI_MODE_PMS_EMULATION = 2
  ics.ics.SPI_MODE_SLAVE = 1
  ics.ics.SPI_PORT_EXTERNAL = 1
  ics.ics.SPI_PORT_ONBOARD = 0
  ics.ics.SPI_TYPE_RAW = 1
  ics.ics.SPI_TYPE_WIL = 0
  ics.ics.SPY_PROTOCOL_A2B = 35
  ics.ics.SPY_PROTOCOL_AUTOSAR = 34
  ics.ics.SPY_PROTOCOL_BEAN = 11
  ics.ics.SPY_PROTOCOL_CAN = 1
  ics.ics.SPY_PROTOCOL_CANFD = 30
  ics.ics.SPY_PROTOCOL_CGI = 18
  ics.ics.SPY_PROTOCOL_CHRYSLER_CCD = 8
  ics.ics.SPY_PROTOCOL_CHRYSLER_JVPW = 14
  ics.ics.SPY_PROTOCOL_CHRYSLER_SCI = 9
  ics.ics.SPY_PROTOCOL_CUSTOM = 0
  ics.ics.SPY_PROTOCOL_DALLAS_1WIRE = 25
  ics.ics.SPY_PROTOCOL_ETHERNET = 29
  ics.ics.SPY_PROTOCOL_FLEXRAY = 16
  ics.ics.SPY_PROTOCOL_FORD_UBP = 10
  ics.ics.SPY_PROTOCOL_GENERIC_MANCHSESTER = 26
  ics.ics.SPY_PROTOCOL_GENERIC_UART = 22
  ics.ics.SPY_PROTOCOL_GME_CIM_SCL_KLINE = 19
  ics.ics.SPY_PROTOCOL_GMFSA = 31
  ics.ics.SPY_PROTOCOL_GMLAN = 2
  ics.ics.SPY_PROTOCOL_GM_ALDL_UART = 7
  ics.ics.SPY_PROTOCOL_I2C = 21
  ics.ics.SPY_PROTOCOL_ISO9141 = 5
  ics.ics.SPY_PROTOCOL_J1708 = 13
  ics.ics.SPY_PROTOCOL_J1850PWM = 4
  ics.ics.SPY_PROTOCOL_J1850VPW = 3
  ics.ics.SPY_PROTOCOL_J1939 = 15
  ics.ics.SPY_PROTOCOL_JTAG = 23
  ics.ics.SPY_PROTOCOL_LIN = 12
  ics.ics.SPY_PROTOCOL_MDIO = 37
```

```
    ics.ics.SPY_PROTOCOL_MOST = 17
    ics.ics.SPY_PROTOCOL_SENT_PROTOCOL = 27
    ics.ics.SPY_PROTOCOL_SPI = 20
    ics.ics.SPY_PROTOCOL_TCP = 32
    ics.ics.SPY_PROTOCOL_UART = 28
    ics.ics.SPY_PROTOCOL_UDP = 33
    ics.ics.SPY_PROTOCOL_UNIO = 24
    ics.ics.SPY_PROTOCOL_WBMS = 36
    ics.ics.SPY_STATUS2_CAN_HAVE_LINK_DATA = 4194304
    ics.ics.SPY_STATUS2_CAN_ISO15765_LOGICAL_FRAME = 2097152
    ics.ics.SPY_STATUS2_END_OF_LONG_MESSAGE = 1048576
    ics.ics.SPY_STATUS2_ERROR_FRAME = 131072
    ics.ics.SPY_STATUS2_ETHERNET_CRC_ERROR = 2097152
    ics.ics.SPY_STATUS2_ETHERNET_FCS_VERIFIED = 268435456
    ics.ics.SPY_STATUS2_ETHERNET_FRAME_TOO_SHORT = 4194304
    ics.ics.SPY_STATUS2_ETHERNET_MANUALFCS_ENABLED = 134217728
    ics.ics.SPY_STATUS2_ETHERNET_NO_PADDING = 16777216
    ics.ics.SPY_STATUS2_ETHERNET_PREEMPTION_ENABLED = 33554432
    ics.ics.SPY_STATUS2_ETHERNET_UPDATE_CHECKSUMS = 67108864
    ics.ics.SPY_STATUS2_FLEXRAY_NO_CRC = 33554432
    ics.ics.SPY_STATUS2_FLEXRAY_NO_HEADERCRC = 67108864
    ics.ics.SPY_STATUS2_FLEXRAY_TX_AB = 2097152
    ics.ics.SPY_STATUS2_FLEXRAY_TX_AB_NO_A = 4194304
    ics.ics.SPY_STATUS2_FLEXRAY_TX_AB_NO_B = 8388608
    ics.ics.SPY_STATUS2_FLEXRAY_TX_AB_NO_MATCH = 16777216
    ics.ics.SPY_STATUS2_GLOBAL_CHANGE = 65536
    ics.ics.SPY_STATUS2_HAS_VALUE = 1
    ics.ics.SPY_STATUS2_HIGH_VOLTAGE = 4
    ics.ics.SPY_STATUS2_I2C_DIR_READ = 8388608
    ics.ics.SPY_STATUS2_I2C_ERR_NACK = 4194304
    ics.ics.SPY_STATUS2_I2C_ERR_TIMEOUT = 2097152
    ics.ics.SPY_STATUS2_ISO_FRAME_ERROR = 134217728
    ics.ics.SPY_STATUS2_ISO_OVERFLOW_ERROR = 268435456
    ics.ics.SPY_STATUS2_ISO_PARITY_ERROR = 536870912
    ics.ics.SPY_STATUS2_LIN_ERR_MSG_ID_PARITY = 67108864
    ics.ics.SPY_STATUS2_LIN_ERR_RX_BREAK_NOT_0 = 2097152
```

```
    ics.ics.SPY_STATUS2_LIN_ERR_RX_BREAK_TOO_SHORT = 4194304
    ics.ics.SPY_STATUS2_LIN_ERR_RX_DATA_GREATER_8 = 16777216
    ics.ics.SPY_STATUS2_LIN_ERR_RX_SYNC_NOT_55 = 8388608
    ics.ics.SPY_STATUS2_LIN_ERR_TX_RX_MISMATCH = 33554432
    ics.ics.SPY_STATUS2_LIN_ID_FRAME_ERROR = 268435456
    ics.ics.SPY_STATUS2_LIN_NO_SLAVE_DATA = -2147483648
    ics.ics.SPY_STATUS2_LIN_SLAVE_BYTE_ERROR = 536870912
    ics.ics.SPY_STATUS2_LIN_SYNC_FRAME_ERROR = 134217728
    ics.ics.SPY_STATUS2_LONG_MESSAGE = 8
    ics.ics.SPY_STATUS2_MDIO_CLAUSE45 = 536870912
    ics.ics.SPY_STATUS2_MDIO_ERR_TIMEOUT = 2097152
    ics.ics.SPY_STATUS2_MDIO_INVALID_BUS = 8388608
    ics.ics.SPY_STATUS2_MDIO_INVALID_PHYADDR = 16777216
    ics.ics.SPY_STATUS2_MDIO_INVALID_REGADDR = 33554432
    ics.ics.SPY_STATUS2_MDIO_JOB_CANCELLED = 4194304
    ics.ics.SPY_STATUS2_MDIO_OVERFLOW = 268435456
    ics.ics.SPY_STATUS2_MDIO_READ = 1073741824
    ics.ics.SPY_STATUS2_MDIO_UNSUPPORTED_CLAUSE = 67108864
    ics.ics.SPY_STATUS2_MDIO_UNSUPPORTED_OPCODE = 134217728
    ics.ics.SPY_STATUS2_MOST_CHANGED_PAR = -2147483648
    ics.ics.SPY_STATUS2_MOST_CONTROL_DATA = 16777216
    ics.ics.SPY_STATUS2_MOST_I2S_DUMP = 134217728
    ics.ics.SPY_STATUS2_MOST_LOW_LEVEL = 8388608
    ics.ics.SPY_STATUS2_MOST_MHP_CONTROL_DATA = 67108864
    ics.ics.SPY_STATUS2_MOST_MHP_USER_DATA = 33554432
    ics.ics.SPY_STATUS2_MOST_MOST150 = 1073741824
    ics.ics.SPY_STATUS2_MOST_MOST50 = 536870912
    ics.ics.SPY_STATUS2_MOST_PACKET_DATA = 2097152
    ics.ics.SPY_STATUS2_MOST_TOO_SHORT = 268435456
    ics.ics.SPY_STATUS2_RX_TIMEOUT_ERROR = 1073741824
    ics.ics.SPY_STATUS2_VALUE_IS_BOOLEAN = 2
    ics.ics.SPY_STATUS2_WBMS_API_IS_CALLBACK = 2097152
    ics.ics.SPY_STATUS3_CANFD_BRS = 16
    ics.ics.SPY_STATUS3_CANFD_ESI = 1
    ics.ics.SPY_STATUS3_CANFD_FDF = 8
    ics.ics.SPY_STATUS3_CANFD_IDE = 2
```

```
ics.ics.SPY_STATUS3_CANFD_RTR = 4
ics.ics.SPY_STATUS3_LIN_JUST_BREAK_SYNC = 1
ics.ics.SPY_STATUS3_LIN_ONLY_UPDATE_SLAVE_TABLE_ONCE = 4
ics.ics.SPY_STATUS3_LIN_SLAVE_DATA_TOO_SHORT = 2
ics.ics.SPY_STATUS_A2B_CONTROL = 524288
ics.ics.SPY_STATUS_A2B_MONITOR = 536870912
ics.ics.SPY_STATUS_A2B_SCF_VALID_WAITING = 8
ics.ics.SPY_STATUS_A2B_UPSTREAM = 1073741824
ics.ics.SPY_STATUS_ANALOG_DIGITAL_INPUT = 16777216
ics.ics.SPY_STATUS_AUDIO_COMMENT = 4194304
ics.ics.SPY_STATUS_AVSI_REC_OVERFLOW = 1048576
ics.ics.SPY_STATUS_BAD_MESSAGE_BIT_TIME_ERROR = 16384
ics.ics.SPY_STATUS_BREAK = 524288
ics.ics.SPY_STATUS_BUS_RECOVERED = 1024
ics.ics.SPY_STATUS_BUS_SHORTED_GND = 4096
ics.ics.SPY_STATUS_BUS_SHORTED_PLUS = 2048
ics.ics.SPY_STATUS_CANFD = 536870912
ics.ics.SPY_STATUS_CAN_BUS_OFF = 512
ics.ics.SPY_STATUS_CAN_ERROR_PASSIVE = 32
ics.ics.SPY_STATUS_CHECKSUM_ERROR = 8192
ics.ics.SPY_STATUS_COMM_IN_OVERFLOW = 65536
ics.ics.SPY_STATUS_CRC_ERROR = 16
ics.ics.SPY_STATUS_EXPECTED_LEN_MISMATCH = 131072
ics.ics.SPY_STATUS_EXTENDED = -2147483648
ics.ics.SPY_STATUS_FLEXRAY_PDU = 268435456
ics.ics.SPY_STATUS_FLEXRAY_PDU_NO_UPDATE_BIT = 8
ics.ics.SPY_STATUS_FLEXRAY_PDU_UPDATE_BIT_SET = 1073741824
ics.ics.SPY_STATUS_GLOBAL_ERR = 1
ics.ics.SPY_STATUS_GPS_DATA = 8388608
ics.ics.SPY_STATUS_HEADERCRC_ERROR = 32
ics.ics.SPY_STATUS_HIGH_SPEED = 1073741824
ics.ics.SPY_STATUS_INCOMPLETE_FRAME = 64
ics.ics.SPY_STATUS_INIT_MESSAGE = 536870912
ics.ics.SPY_STATUS_LIN_MASTER = 536870912
ics.ics.SPY_STATUS_LOST_ARBITRATION = 128
ics.ics.SPY_STATUS_MSG_NO_MATCH = 262144
```

```
 ics.ics.SPY_STATUS_NETWORK_MESSAGE_TYPE = 67108864
 ics.ics.SPY_STATUS_PDU = 268435456
 ics.ics.SPY_STATUS_REMOTE_FRAME = 8
 ics.ics.SPY_STATUS_TEST_TRIGGER = 2097152
 ics.ics.SPY_STATUS_TEXT_COMMENT = 33554432
 ics.ics.SPY_STATUS_TX_MSG = 2
 ics.ics.SPY_STATUS_TX_NOMATCH = 32768
 ics.ics.SPY_STATUS_UNDEFINED_ERROR = 256
 ics.ics.SPY_STATUS_VSI_IFR_CRC_BIT = 268435456
 ics.ics.SPY_STATUS_VSI_TX_UNDERRUN = 134217728
 ics.ics.SPY_STATUS_XTD_FRAME = 4
 ics.ics.SWCAN_AUTOSWITCH_DISABLED = 0
 ics.ics.SWCAN_AUTOSWITCH_DISABLED_RESISTOR_ENABLED = 3
 ics.ics.SWCAN_AUTOSWITCH_NO_RESISTOR = 1
 ics.ics.SWCAN_AUTOSWITCH_WITH_RESISTOR = 2
 ics.ics.SWCAN_SETTINGS_SIZE = 14
 ics.ics.TCP_SUPPORTED = 32
 ics.ics.TIMESYNC_ICSHARDWARE_SETTINGS_SIZE = 4
 ics.ics.UART_SETTINGS_SIZE = 16
 ics.ics.USE_TQ = 1
 ics.ics.VNETBITS_FEATURE_ANDROID_MSGS = 1
 ics.ics.VNETBITS_FEATURE_DISABLE_USB_CHECK = 2
 ics.ics.WBMS_GATEWAY_NETWORK_DWCAN_01 = 1
 ics.ics.WBMS_GATEWAY_NETWORK_DWCAN_02 = 2
 ics.ics.WBMS_GATEWAY_NETWORK_NONE = 0
 ics.ics.WBMS_GATEWAY_NETWORK_UDP_MULTICAST = 3
 ics.ics.WIFI_ANTENNA_EXTERNAL = 1
 ics.ics.WIFI_ANTENNA_INTERNAL = 0
 ics.ics.WIFI_CONNECTION = 8
```

Python Module Index

i

ics.ics, [17](#)

Index

A

a2_b_monitor_settings (class *ics.structures.a2_b_monitor_settings*), 89
a2_b_node_type (class *ics.structures.a2_b_node_type*), 89
a2_btdm_mode (class *ics.structures.a2_btdm_mode*), 89
a2b_monitor (*ics.structures.srada2_b_settings.srada2_b_settings* attribute), 133
a2b_node (*ics.structures.srada2_b_settings.srada2_b_settings* attribute), 137
A2B_SETTINGS_FLAG_16BIT (in module *ics.ics*), 205
a2bNodeTypeMaster (*ics.structures.a2_b_node_type.a2_b_node_type* attribute), 89
a2bNodeTypeMonitor (*ics.structures.a2_b_node_type.a2_b_node_type* attribute), 89
a2bNodeTypeSlave (*ics.structures.a2_b_node_type.a2_b_node_type* attribute), 160
accdevwin (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params* attribute), 143
AckBytes (*ics.ics.SpyMessage* attribute), 18
AckBytes (*ics.ics.SpyMessageJ1850* attribute), 19
AckBytes (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray* attribute), 166
AckBytes (*ics.structures.ics_spy_message_long.ics_spy_message_long* attribute), 171
AckBytes (*ics.structures.ics_spy_message_mdio.ics_spy_message_mdio* attribute), 108
AckBytes (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb* attribute), 184
ae1Select (*ics.structures.s_pluto_custom_params.s.s_pluto_custom_params* attribute), 116
ain_sample_period (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 116
ain_sample_period

(*ics.structures.s_ether_badge_settings.s_ether_badge_settings* attribute), 120
ain_sample_period
(*ics.structures.s_fire_settings.s_fire_settings* attribute), 130
ain_sample_period
(*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 133
ain_sample_period
(*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings* attribute), 137
ain_sample_period
(*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 139
ain_sample_period
(*ics.structures.secvb_settings.secvb_settings* attribute), 159
ain_sample_period
(*ics.structures.sieveb_settings.sieveb_settings* attribute), 162
ain_sample_period
(*ics.structures.sobd2_sim_settings.sobd2_sim_settings* attribute), 166
ain_sample_period
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 171
ain_sample_period
(*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 104
ain_threshold (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 116
ain_threshold (*ics.structures.s_ether_badge_settings.s_ether_badge_settings* attribute), 120
ain_threshold (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings* attribute), 122
ain_threshold (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 126

```

ain_threshold(ics.structures.s_fire_settings.s_fire_settings      attribute), 96
    attribute), 130                                         autoEth10g(ics.structures.srad_moon3_settings.srad_moon3_settings
ain_threshold(ics.structures.s_fire_vnet_settings.s_fire_vnet_setting attribute), 183
    attribute), 133                                         AutoHandleClose (ics.ics.NeoDevice attribute), 18
ain_threshold(ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
    attribute), 137                                         B
ain_threshold(ics.structures.s_pendant_settings.s_pendant_settings
    attribute), 139                                         backupPowerEnabled
                                                (ics.structures.ics_fire2_device_status.ics_fire2_device_status
ain_threshold(ics.structures.s_red2_settings.s_red2_settings      attribute), 103
    attribute), 152                                         backupPowerGood (ics.structures.ics_fire2_device_status.ics_fire2_device
ain_threshold(ics.structures.secu_settings.secu_settings      attribute), 103
    attribute), 159                                         bag (ics.structures.s_pluto_vl_policing_entry.s.s_pluto_vl_policing_entry
ain_threshold(ics.structures.seevb_settings.seevb_settings      attribute), 151
    attribute), 160                                         base (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config_s
ain_threshold(ics.structures.sievb_settings.sievb_settings      attribute), 148
    attribute), 162                                         base36enc () (in module ics.ics), 30
ain_threshold(ics.structures.sobd2_sim_settings.sobd2_sim_settings      attribute), 166
    attribute), 166                                         Baudrate (ics.structures.can_settings.can_settings at-
                                                tribute), 90
ain_threshold(ics.structures.srad_galaxy_settings.srad_galaxy_settings      attribute), 171
    attribute), 171                                         Baudrate (ics.structures.iso9141_keyword2000_settings.iso9141_keyword
ain_threshold(ics.structures.srad_star2_settings.srad_star2_settings      attribute), 185
    attribute), 185                                         Baudrate (ics.structures.lin_settings.lin_settings at-
                                                tribute), 113
allowBoot (ics.structures.fire3_linux_settings.fire3_linux_settings      attribute), 97
    attribute), 97                                         Baudrate (ics.structures.swcan_settings.swcan_settings
api (ics.structures.generic_api_data.generic_api_data      attribute), 98
    attribute), 98                                         baudrate (ics.structures.uart_port_config.uart_port_config
api (ics.structures.generic_api_data_old.generic_api_data      attribute), 98
    attribute), 98                                         baudrate (ics.structures.uart_settings.uart_settings at-
                                                tribute), 202
api (ics.structures.generic_api_status.generic_api_status      attribute), 98
    attribute), 98                                         bc_domain (ics.structures.s_pluto_l2_forwarding_entry.s.s_pluto_l2_for-
                                                tribute), 147
apiIndex (ics.structures.generic_api_selector.generic_api_selector      attribute), 98
    attribute), 98                                         bData (ics.structures.generic_api_data.old.generic_api_data_old
ArbIDOrHeader (ics.ics.SpyMessage attribute), 18
ArbIDOrHeader (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray
    attribute), 104                                         bData (ics.structures.uart_port_data.uart_port_data at-
                                                tribute), 200
ArbIDOrHeader (ics.structures.ics_spy_message_long.ics_spy_message_long
    attribute), 106                                         bData (ics.structures.uart_port_data.uart_port_data at-
                                                tribute), 202
ArbIDOrHeader (ics.structures.ics_spy_message_mdio.ics_spy_message_mdio
    attribute), 108                                         bitPos (ics.structures.serdescam_settings.serdescam_settings
ArbIDOrHeader (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
    attribute), 109                                         bitPos (ics.structures.serdescam_settings.serdescam_settings
ArgumentError, 17                                         blockSize (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_
as_capable (ics.structures.gptp_status.gptp_status attribute), 101
    attribute), 101                                         blockSize (ics.structures.st_cm_iso157652_rx_message.st_cm_iso15765_
asytensyen (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params
    attribute), 143                                         blockSize (ics.structures.st_cm_iso157652_tx_message.st_cm_iso15765_
attemptConnect (ics.structures.s_wil_connection_settings.s_wil_connection_settings
    attribute), 157                                         blockSize (ics.structures.st_cm_iso157652_tx_message.st_cm_iso15765_
AUTO (in module ics.ics), 205                                         BPS1000 (in module ics.ics), 205
auto_baud (ics.structures.can_settings.can_settings
    attribute), 90                                         BPS100000 (in module ics.ics), 205
auto_baud (ics.structures.swcan_settings.swcan_settings
    attribute), 200                                         BPS10400 (in module ics.ics), 205
auto_neg (ics.structures.ethernet_settings.ethernet_settings
    attribute), 200                                         BPS117647 (in module ics.ics), 205
auto_neg (ics.structures.ethernet_settings.ethernet_settings
    attribute), 200                                         BPS125 (in module ics.ics), 205
auto_neg (ics.structures.ethernet_settings.ethernet_settings
    attribute), 200                                         BPS20 (in module ics.ics), 205
auto_neg (ics.structures.ethernet_settings.ethernet_settings
    attribute), 200                                         BPS2000 (in module ics.ics), 205

```

BPSS250 (*in module ics.ics*), 205
 BPSS33 (*in module ics.ics*), 205
 BPSS33333 (*in module ics.ics*), 205
 BPSS4000 (*in module ics.ics*), 205
 BPSS50 (*in module ics.ics*), 205
 BPSS500 (*in module ics.ics*), 205
 BPSS5000 (*in module ics.ics*), 205
 BPSS50000 (*in module ics.ics*), 205
 BPSS62 (*in module ics.ics*), 205
 BPSS62500 (*in module ics.ics*), 205
 BPSS666 (*in module ics.ics*), 205
 BPSS71429 (*in module ics.ics*), 205
 BPSS800 (*in module ics.ics*), 205
 BPSS83 (*in module ics.ics*), 206
 BPSS83333 (*in module ics.ics*), 206
 brgh (*ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings*.attribute), 112
 brgh (*ics.structures.lin_settings.lin_settings*.attribute), 113
 brgh (*ics.structures.uart_settings.uart_settings*.attribute), 202
 BRP (*ics.structures.can_settings.can_settings*.attribute), 90
 BRP (*ics.structures.swcan_settings.swcan_settings*.attribute), 200
 bStuff2 (*ics.structures.spy_filter_long.spy_filter_long*.attribute), 168
 BUILD_DATETIME (*in module ics.ics*), 206
 burst_timer (*ics.structures.ethernet10_t1_s_settings.ethernet10_t1_s_settings*.attribute), 95
 bUseArbIdRangeFilter
 (*ics.structures.spy_filter_long.spy_filter_long*.attribute), 168
 BusIndex (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt*.attribute), 141
 byte (*ics.structures.s_spi_port_setting.s_spi_port_setting*.attribute), 155
 ByteDataLength (*ics.structures.spy_filter_long.spy_filter_long*.attribute), 167
 ByteDataLSB (*ics.structures.spy_filter_long.spy_filter_long*.attribute), 167
 ByteDataMaskLSB (*ics.structures.spy_filter_long.spy_filter_long*.attribute), 167
 ByteDataMaskMSB (*ics.structures.spy_filter_long.spy_filter_long*.attribute), 167
 ByteDataMSB (*ics.structures.spy_filter_long.spy_filter_long*.attribute), 167
 bytesPerSector (*ics.structures.s_disk_status.s_disk_status*.attribute), 120

C
 caentmout (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s*.attribute), 143
 callbackError (*ics.structures.generic_api_status.generic_api_status*.attribute), 98
 can1 (*ics.structures.s_cyan_settings.s_cyan_settings*.attribute), 116
 can1 (*ics.structures.s_ether_badge_settings.s_ether_badge_settings*.attribute), 120
 can1 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*.attribute), 122
 can1 (*ics.structures.s_fire3_settings.s_fire3_settings*.attribute), 126
 can1 (*ics.structures.s_fire_settings.s_fire_settings*.attribute), 130
 can1 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*.attribute), 133
 can1 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*.attribute), 134
 can1 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*.attribute), 137
 can1 (*ics.structures.s_pendant_settings.s_pendant_settings*.attribute), 139
 can1 (*ics.structures.s_red2_settings.s_red2_settings*.attribute), 152
 can1 (*ics.structures.s_red_settings.s_red_settings*.attribute), 155
 can1 (*ics.structures.s_vivid_can_settings.s_vivid_can_settings*.attribute), 156
 can1 (*ics.structures.scan_hub_settings.scan_hub_settings*.attribute), 157
 can1 (*ics.structures.secu_settings.secu_settings*.attribute), 158
 can1 (*ics.structures.seevb_settings.seevb_settings*.attribute), 160
 can1 (*ics.structures.sievb_settings.sievb_settings*.attribute), 162
 can1 (*ics.structures.sobd2_lc_settings.sobd2_lc_settings*.attribute), 163
 can1 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings*.attribute), 165
 can1 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings*.attribute), 166
 can1 (*ics.structures.srad_comet_settings.srad_comet_settings*.attribute), 168
 can1 (*ics.structures.srad_epsilon_settings.srad_epsilon_settings*.attribute), 168
 can1 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*.attribute), 171
 can1 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*.attribute), 174
 can1 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*.attribute), 177
 can1 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings*.attribute), 180

can1 (*ics.structures.srad_pluto_settings.srad_pluto_settings*.
attribute), 183
can1 (*ics.structures.srad_star2_settings.srad_star2_settings*.
attribute), 185
can1 (*ics.structures.srada2_b_settings.srada2_b_settings*.
attribute), 187
can1 (*ics.structures.srdbms_settings.srdbms_settings*.
attribute), 188
can1 (*ics.structures.svcan3_settings.svcan3_settings*.
attribute), 195
can1 (*ics.structures.svcan412_settings.svcan412_settings*.
attribute), 196
can1 (*ics.structures.svcan4_ind_settings.svcan4_ind_settings*.
attribute), 196
can1 (*ics.structures.svcan4_settings.svcan4_settings*.
attribute), 197
can1 (*ics.structures.svcanrf_settings.svcanrf_settings*.
attribute), 198
can10 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*.
attribute), 122
can10 (*ics.structures.s_fire3_settings.s_fire3_settings*.
attribute), 126
can11 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*.
attribute), 122
can11 (*ics.structures.s_fire3_settings.s_fire3_settings*.
attribute), 126
can12 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*.
attribute), 122
can12 (*ics.structures.s_fire3_settings.s_fire3_settings*.
attribute), 126
can13 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*.
attribute), 122
can13 (*ics.structures.s_fire3_settings.s_fire3_settings*.
attribute), 126
can14 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*.
attribute), 122
can14 (*ics.structures.s_fire3_settings.s_fire3_settings*.
attribute), 126
can15 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*.
attribute), 122
can15 (*ics.structures.s_fire3_settings.s_fire3_settings*.
attribute), 126
can16 (*ics.structures.s_fire3_settings.s_fire3_settings*.
attribute), 126
can1_options (*ics.structures.s_text_api_settings.s_text_api_settings*.
attribute), 155
can1_rx_id (*ics.structures.s_text_api_settings.s_text_api_settings*.
attribute), 155
can1_tx_id (*ics.structures.s_text_api_settings.s_text_api_settings*.
attribute), 155
can2 (*ics.structures.s_cyan_settings.s_cyan_settings*.
attribute), 116
can2 (*ics.structures.s_ether_badge_settings.s_ether_badge_settings*.
attribute), 120
can2 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*.
attribute), 122
can2 (*ics.structures.s_fire3_settings.s_fire3_settings*.
attribute), 126
can2 (*ics.structures.s_fire_settings.s_fire_settings*.
attribute), 131
can2 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*.
attribute), 133
can2 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*.
attribute), 135
can2 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*.
attribute), 137
can2 (*ics.structures.s_pendant_settings.s_pendant_settings*.
attribute), 139
can2 (*ics.structures.s_red2_settings.s_red2_settings*.
attribute), 152
can2 (*ics.structures.s_red_settings.s_red_settings*.
attribute), 155
can2 (*ics.structures.secu_avb_settings.secu_avb_settings*.
attribute), 158
can2 (*ics.structures.secu_settings.secu_settings*.
attribute), 159
can2 (*ics.structures.sievb_settings.sievb_settings*.
attribute), 162
can2 (*ics.structures.sobd2_lc_settings.sobd2_lc_settings*.
attribute), 163
can2 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings*.
attribute), 165
can2 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings*.
attribute), 166
can2 (*ics.structures.srad_comet_settings.srad_comet_settings*.
attribute), 168
can2 (*ics.structures.srad_epsilon_settings.srad_epsilon_settings*.
attribute), 170
can2 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*.
attribute), 171
can2 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*.
attribute), 174
can2 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*.
attribute), 177
can2 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings*.
attribute), 180
can2 (*ics.structures.srad_pluto_settings.srad_pluto_settings*.
attribute), 183
can2 (*ics.structures.srad_star2_settings.srad_star2_settings*.
attribute), 185
can2 (*ics.structures.srada2_b_settings.srada2_b_settings*.
attribute), 187
can2 (*ics.structures.srdbms_settings.srdbms_settings*.
attribute), 188
can2 (*ics.structures.svcan3_settings.svcan3_settings*.
attribute), 195
can2 (*ics.structures.svcan412_settings.svcan412_settings*.
attribute), 196


```
can6 (ics.structures.s_red2_settings.s_red2_settings at-attribute), 152
can6 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 172
can6 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 175
can6 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 177
can7 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 116
can7 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute), 123
can7 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 126
can7 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 136
can7 (ics.structures.s_red2_settings.s_red2_settings attribute), 152
can7 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 172
can7 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 175
can8 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 116
can8 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute), 123
can8 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 126
can8 (ics.structures.s_red2_settings.s_red2_settings attribute), 152
can8 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 172
can8 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 175
can9 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute), 123
can9 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 127
CAN_BPS10000 (in module ics.ics), 206
CAN_BPS5000 (in module ics.ics), 206
CAN_BPS6667 (in module ics.ics), 206
CAN_BPS8000 (in module ics.ics), 206
can_settings (class in ics.structures.can_settings), 90
CAN_SETTINGS_SIZE (in module ics.ics), 206
can_switch_mode (ics.structures.s_cyan_settings.s_cyan_setting attribute), 116
can_switch_mode (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_setting attribute), 138
can_switch_mode (ics.structures.s_vivid_can_settings.s_vivid_can_setting attribute), 156
can_switch_mode (ics.structures.sobd2_lc_settings.sobd2_lc_setting attribute), 163
can_switch_mode (ics.structures.sobd2_pro_settings.sobd2_pro_setting attribute), 166
can_switch_mode (ics.structures.sobd2_sim_settings.sobd2_sim_setting attribute), 169
can_attribute), 165
canfd1 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 117
canfd1 (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 120
canfd1 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute), 123
canfd1 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 127
canfd1 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 136
canfd1 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 138
canfd1 (ics.structures.s_red2_settings.s_red2_settings attribute), 152
canfd1 (ics.structures.scan_hub_settings.scan_hub_settings attribute), 157
canfd1 (ics.structures.secu_avb_settings.secu_avb_settings attribute), 158
canfd1 (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 164
canfd1 (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 165
canfd1 (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 166
canfd1 (ics.structures.srad_comet_settings.srad_comet_settings attribute), 168
canfd1 (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 170
canfd1 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 172
canfd1 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 175
canfd1 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 177
canfd1 (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 180
canfd1 (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 183
canfd1 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 185
canfd1 (ics.structures.srada2_b_settings.srada2_b_settings attribute), 187
canfd1 (ics.structures.srdbms_settings.srdbms_settings attribute), 188
canfd1 (ics.structures.svcn412_settings.svcn412_settings attribute), 196
canfd1 (ics.structures.svcn4_ind_settings.svcn4_ind_settings attribute), 196
canfd1 (ics.structures.svcn4_settings.svcn4_settings attribute), 198
```

attribute), 197
 canfd10 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.srad_gigalog_settings.srad_gigalog_settings
 attribute), 123
 canfd10 (ics.structures.s_fire3_settings.s_fire3_settings canfd2 (ics.structures.srad_gigastar_settings.srad_gigastar_settings
 attribute), 127
 canfd11 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.srad_jupiter_settings.srad_jupiter_settings
 attribute), 123
 canfd11 (ics.structures.s_fire3_settings.s_fire3_settings canfd2 (ics.structures.srad_pluto_settings.srad_pluto_settings
 attribute), 127
 canfd12 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.srad_star2_settings.srad_star2_settings
 attribute), 123
 canfd12 (ics.structures.s_fire3_settings.s_fire3_settings canfd2 (ics.structures.srada2_b_settings.srada2_b_settings
 attribute), 127
 canfd13 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.sradbms_settings.sradbms_settings
 attribute), 123
 canfd13 (ics.structures.s_fire3_settings.s_fire3_settings canfd2 (ics.structures.svcan412_settings.svcan412_settings
 attribute), 127
 canfd14 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.svcan4_ind_settings.svcan4_ind_settings
 attribute), 123
 canfd14 (ics.structures.s_fire3_settings.s_fire3_settings canfd2 (ics.structures.svcan4_settings.svcan4_settings
 attribute), 127
 canfd15 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.s_s_cyan_settings.s_cyan_settings
 attribute), 123
 canfd15 (ics.structures.s_fire3_settings.s_fire3_settings canfd3 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings
 attribute), 127
 canfd16 (ics.structures.s_fire3_settings.s_fire3_settings canfd3 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 127
 canfd2 (ics.structures.s_cyan_settings.s_cyan_settings canfd3 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings
 attribute), 117
 canfd2 (ics.structures.s_ether_badge_settings.s_ether_badge_settings.s_red2_settings.s_red2_settings
 attribute), 120
 canfd2 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 123
 canfd2 (ics.structures.s_fire3_settings.s_fire3_settings canfd3 (ics.structures.sobd2_pro_settings.sobd2_pro_settings
 attribute), 127
 canfd2 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 136
 canfd2 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 138
 canfd2 (ics.structures.s_red2_settings.s_red2_settings canfd3 (ics.structures.srad_galaxy_settings.srad_galaxy_settings
 attribute), 153
 canfd2 (ics.structures.secu_avb_settings.secu_avb_settings canfd3 (ics.structures.svcan4_settings.svcan4_settings
 attribute), 158
 canfd2 (ics.structures.sobd2_lc_settings.sobd2_lc_setting canfd4 (ics.structures.s_cyan_settings.s_cyan_settings
 attribute), 164
 canfd2 (ics.structures.sobd2_pro_settings.sobd2_pro_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 165
 canfd2 (ics.structures.sobd2_sim_settings.sobd2_sim_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 166
 canfd2 (ics.structures.srad_comet_settings.srad_comet_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 168
 canfd2 (ics.structures.srad_epsilon_settings.srad_epsilon_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 170
 canfd2 (ics.structures.srad_galaxy_settings.srad_galaxy_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 172
 canfd2 (ics.structures.srad_gigalog_settings.srad_gigalog_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 175
 canfd2 (ics.structures.srad_gigastar_settings.srad_gigastar_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 177
 canfd2 (ics.structures.srad_jupiter_settings.srad_jupiter_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 180
 canfd2 (ics.structures.srad_pluto_settings.srad_pluto_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 183
 canfd2 (ics.structures.srad_star2_settings.srad_star2_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 185
 canfd2 (ics.structures.srada2_b_settings.srada2_b_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 187
 canfd2 (ics.structures.svcan412_settings.svcan412_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 196
 canfd2 (ics.structures.svcan4_ind_settings.svcan4_ind_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 196
 canfd2 (ics.structures.svcan4_settings.svcan4_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 197
 canfd2 (ics.structures.svcan412_settings.svcan412_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 198
 canfd2 (ics.structures.svcan4_settings.svcan4_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 199
 canfd2 (ics.structures.svcan412_settings.svcan412_settings.sobd2_lc_settings.sobd2_lc_settings
 attribute), 200

attribute), 164
canfd4 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings*) attribute), 165
canfd4 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*) attribute), 172
canfd4 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*) attribute), 175
canfd4 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*) attribute), 175
canfd4 (*ics.structures.svcn4_settings.svcn4_settings*) attribute), 198
canfd5 (*ics.structures.s_cyan_settings.s_cyan_settings*) attribute), 117
canfd5 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*) attribute), 123
canfd5 (*ics.structures.s_red2_settings.s_red2_settings*) attribute), 153
canfd5 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*) attribute), 136
canfd5 (*ics.structures.s_red2_settings.s_red2_settings*) attribute), 153
canfd5 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*) attribute), 172
canfd5 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*) attribute), 175
canfd5 (*ics.structures.s_fire3_settings.s_fire3_settings*) attribute), 127
canfd5 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*) attribute), 123
canfd6 (*ics.structures.s_cyan_settings.s_cyan_settings*) attribute), 117
canfd6 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*) attribute), 123
canfd6 (*ics.structures.s_fire3_settings.s_fire3_settings*) attribute), 127
canfd6 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*) attribute), 136
canfd6 (*ics.structures.s_red2_settings.s_red2_settings*) attribute), 153
canfd6 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*) attribute), 172
canfd6 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*) attribute), 175
canfd6 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*) attribute), 177
canfd6 (*ics.structures.s_cyan_settings.s_cyan_settings*) attribute), 117
canfd6 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*) attribute), 123
canfd6 (*ics.structures.s_fire3_settings.s_fire3_settings*) attribute), 127
canfd6 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*) attribute), 136
canfd6 (*ics.structures.s_red2_settings.s_red2_settings*) attribute), 153
canfd6 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*) attribute), 172
canfd6 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*) attribute), 175
canfd6 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*) attribute), 178
canfd7 (*ics.structures.s_cyan_settings.s_cyan_settings*) attribute), 117
canfd7 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*) attribute), 123
canfd7 (*ics.structures.s_fire3_settings.s_fire3_settings*) attribute), 127
canfd7 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*) attribute), 136
canfd7 (*ics.structures.s_red2_settings.s_red2_settings*) attribute), 153
canfd7 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*) attribute), 172
canfd7 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*) attribute), 175
canfd7 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*) attribute), 178
canfd8 (*ics.structures.s_cyan_settings.s_cyan_settings*) attribute), 117
canfd8 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*) attribute), 123
canfd8 (*ics.structures.s_red2_settings.s_red2_settings*) attribute), 153
canfd8 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*) attribute), 172
canfd8 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*) attribute), 175
canfd9 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*) attribute), 123
canfd9 (*ics.structures.s_fire3_settings.s_fire3_settings*) attribute), 127
CANFD_BRS_ENABLED (in module *ics.ics*), 206
CANFD_BRS_ENABLED_ISO (in module *ics.ics*), 206
CANFD_ENABLED (in module *ics.ics*), 206
CANFD_ENABLED_ISO (in module *ics.ics*), 206
canfd_settings (class in *ics.structures.canfd_settings*), 90
CANFD_SETTINGS_SIZE (in module *ics.ics*), 206
canhub (in *ics.structures.global_settings.global_settings*) attribute), 99
CANNODE_STATUS_COREMINI_IS_RUNNING (in module *ics.ics*), 206
CANNODE_STATUS_IN_BOOTLOADER (in module *ics.ics*), 206
CANOptions (in *ics.structures.tag_options_find_neo_ex.tag_options_find_neo_ex*), 201
CANOptions (in *ics.structures.tag_options_open_neo_ex.tag_options_open_neo_ex*), 201
canterm_settings (class in *ics.structures.canterm_settings*), 91
CANTERM_SETTINGS_SIZE (in module *ics.ics*), 206
canfd_port (in *ics.structures.s_pluto_general_params.s.s_pluto_general_params*) attribute), 145
canfd_port (in *ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message*) attribute), 192
cgi_baud (in *ics.structures.s_fire_settings.s_fire_settings*) attribute), 131
cgi_isettings (in *ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*) attribute), 133
cgi_chksum_enable (in *ics.structures.s_fire_settings.s_fire_settings*) attribute), 131
cgi_chksum_enable (in *ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*) attribute), 133
enable_reserved

(*ics.structures.s_fire_settings.s_fire_settings*
attribute), 131

cgi_enable_reserved (*ics.structures.s_fire_vnet_settings.s_fire_vnet_setting*
attribute), 133

cgi_rx_ifs_bit_times (*ics.structures.s_fire_settings.s_fire_settings*
attribute), 131

cgi_rx_ifs_bit_times (*ics.structures.s_fire_vnet_settings.s_fire_vnet_setting*
attribute), 133

cgi_tx_ifs_bit_times (*ics.structures.s_fire_settings.s_fire_settings*
attribute), 131

cgi_tx_ifs_bit_times (*ics.structures.s_fire_vnet_settings.s_fire_vnet_setting*
attribute), 133

chA (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray*
attribute), 105

chB (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray*
attribute), 105

chksum (*ics.structures.global_settings.global_settings*
attribute), 99

chksum (*ics.structures.s_extended_data_flash_header.s_extended_data_flash_header*
attribute), 122

chksum (*ics.structures.serdespoc_settings.serdespoc_settings*
attribute), 161

chksum_enabled (*ics.structures.iso9141_keyword2000_setting*
attribute), 112

clause22 (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt*
attribute), 141

clause45 (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt*
attribute), 141

Clause45Enable (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt*
attribute), 141

clock_accuracy (*ics.structures.clock_quality.clock_quality*
attribute), 91

clock_class (*ics.structures.clock_quality.clock_quality*
attribute), 91

clock_identity (*ics.structures.port_identity.port_identity*
attribute), 115

clock_identity (*ics.structures.system_identity.system_identity*
attribute), 201

clock_quality (*ics.structures.system_identity.system_identity*
attribute), 201

clock_quality_ (*class*
ics.structures.clock_quality_), 91

clockaccuracy (*ics.structures.s_pluto_ptp_params.s_pluto_ptp_params*
attribute), 149

clockaccuracy (*ics.structures.srad_gptp_settings.s.srad_gptp_settings*
attribute), 180

clockclass (*ics.structures.s_pluto_ptp_params.s_pluto_ptp_params*
attribute), 149

clockclass (*ics.structures.srad_gptp_settings.s.srad_gptp_settings*
attribute), 180

close_device () (*in module ics.ics*), 30

ClosePort () (*in module ics.ics*), 20

Version (*ics.structures.get_supported_features_response.get_supported_features_response*
attribute), 99

cmpprobe (*ics.structures.global_settings.global_settings*
attribute), 99

cmpprobe_versions (*ics.structures.st_chip_versions.st_chip_versions*
attribute), 191

command (*ics.structures.s_ext_sub_cmd_hdr.s_ext_sub_cmd_hdr*
attribute), 122

CommandByteLength (*ics.structures.tagicsneo_vi_command.tagicsneo_vi_command*
attribute), 201

commandData (*ics.structures.software_update_command.software_update_com*
attribute), 167

commandSizeOrProgress

attribute), 167

attribute), 97

commandType (*ics.structures.software_update_command.software_update_com*
attribute), 167

attribute), 201

commitHash (*ics.structures.version_report.version_report*
attribute), 203

componentInfo (*ics.structures.version_report.version_report*
attribute), 203

Config (*ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway*
attribute), 139

config (*ics.structures.s_spi_port_setting.s_spi_port_setting*
attribute), 155

config (*ics.structures.s_wil_bridge_config.s_wil_bridge_config*
attribute), 156

converter (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_s*
attribute), 152

converter1Mode (*ics.structures.rad_moon_duo_converter_settings.rad*
attribute), 115

coremini_clear () (*in module ics.ics*), 31

coremini_get_fblock_status () (*in module ics.ics*), 31

coremini_load () (*in module ics.ics*), 31

ics.ics, 31

ics.ics, 31

ics.ics, 32

ics.ics, 32

ics.ics, 32

ics.ics, 32

coremini_start_fblock() (in module `ics.ics`), 32
coremini_stop() (in module `ics.ics`), 33
coremini_stop_fblock() (in module `ics.ics`), 33
coremini_write_app_signal() (in module `ics.ics`), 33
coremini_write_rx_message() (in module `ics.ics`), 33
coremini_write_tx_message() (in module `ics.ics`), 33
create_neovi_radio_message() (in module `ics.ics`), 33
current_time (`ics.structures.gptp_status.gptp_status` attribute), 101
custom(`ics.structures.srad_pluto_settings.srad_pluto_setting` attribute), 183
cyan (`ics.structures.global_settings.global_settings` attribute), 99
cycle (`ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex` attribute), 105

D

Data (`ics.ics.SpyMessage` attribute), 18
Data (`ics.ics.SpyMessageJ1850` attribute), 19
Data (`ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex` attribute), 92
Data (`ics.structures.ics_spy_message_mdio.ics_spy_message_mdio` attribute), 108
Data (`ics.structures.ics_spy_message_vsb.ics_spy_message_vsb` attribute), 109
data (`ics.structures.iso15765_2015_tx_message.iso15765_2015_tx` attribute), 111
data (`ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652` attribute), 193
Data (`ics.structures.tagicsneo_vi_command.tagicsneo_vi_demand` attribute), 201
DataLsb (`ics.structures.ics_spy_message_long.ics_spy_message_long` attribute), 106
DataMsb (`ics.structures.ics_spy_message_long.ics_spy_message_long` attribute), 106
debugen (`ics.structures.s_pluto_vl_forwarding_params.s_pluto_vl_forwarding_params` attribute), 151
DescriptionID (`ics.ics.SpyMessage` attribute), 18
DescriptionID (`ics.ics.SpyMessageJ1850` attribute), 19
DescriptionID (`ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex` attribute), 104
DescriptionID (`ics.structures.ics_spy_message_long.ics_spy_message_long` attribute), 106
DescriptionID (`ics.structures.ics_spy_message_mdio.ics_spy_message_mdio` attribute), 108
DescriptionID (`ics.structures.ics_spy_message_vsb.ics_spy_message_vsb` attribute), 109
destmeta (`ics.structures.s_pluto_avb_params.s_pluto_avb_params` attribute), 142
destports (`ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2` attribute), 146
destports (`ics.structures.s_pluto_retagging_entry.s.s_pluto_retagging` attribute), 149
destports (`ics.structures.s_pluto_vl_forwarding_entry.s.s_pluto_vl_for` attribute), 150
device (`ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt_clau` attribute), 142
device_feature (class in `ics.structures.device_feature`), 91
DeviceCANHUBSettingsType
DeviceCMPProbeSettingsType
DeviceCOUNT_FOR_EXPLORER (in module `ics.ics`), 206
DeviceECU_AVBSettingsType
DeviceEEVBSettingsType
DeviceEtherBadgeSettingsType
DeviceFire2SettingsType
DeviceFire3FlexraySettingsType
DeviceFire3SettingsType
DeviceFireSettingsType
DeviceFlexVnetzSettingsType
DeviceFlexVnetzSettingsType
DeviceIEVBSettingsType
DeviceOBD2LCSettingsType
DevicePCUAVBSettingsType
DeviceSpyMessageAVBSettingsType

DeviceOBD2ProSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 92	DeviceRed2SettingsType (<i>acs.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceOBD2SimSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 92	DeviceRedSettingsType (<i>acs.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceRADA2BSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 92	DeviceSettingsNone (<i>acs.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceRADBMSSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 92	DeviceSettingsTypeMax (<i>acs.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceRADCometSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 92	DeviceSettingType (<i>acs.structures.s_device_settings.s_device_settings.attribute</i>), 119
DeviceRADEpsilonSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 92	DeviceType (<i>ics.ics.NeoDevice</i> attribute), 18
DeviceRADGalaxySettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 92	DeviceTypePCAN3SettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceRADGigalogSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	DeviceTypePCAN412SettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceRADGigastarSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	DeviceTypePCAN4IndSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceRADJupiterSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	DeviceTypePCAN4SettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceRADMoon2SettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	DeviceTypePCANRESettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceRADMoon3SettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	DeviceTypePCANSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93
DeviceRadMoonDuoSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	digitalIoThresholdEnable (<i>acs.structures.s_cyan_settings.s_cyan_settings.attribute</i>), 117
DeviceRADPlutoSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	digitalIoThresholdEnable (<i>acs.structures.s_fire3 flexray_settings.s_fire3 flexray_settings.attribute</i>), 123
DeviceRADPlutoSwitchSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	digitalIoThresholdEnable (<i>acs.structures.s_fire3_SETTINGS.s_fire3_SETTINGS.attribute</i>), 127
DeviceRADStar2SettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	digitalIoThresholdEnable (<i>acs.structures.s_red2_SETTINGS.s_red2_SETTINGS.attribute</i>), 153
DeviceRADSuperMoonSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	digitalIoThresholdTicks (<i>acs.structures.s_cyan_SETTINGS.s_cyan_SETTINGS.attribute</i>), 117
DeviceRed20emSettingsType (<i>ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.attribute</i>), 93	digitalIoThresholdTicks (<i>acs.structures.s_fire3 flexray_settings.s_fire3 flexray_settings.attribute</i>), 123

```

digitalIoThresholdTicks
    (ics.structures.s_fire3_settings.s_fire3_settings
     attribute), 127
digitalIoThresholdTicks
    (ics.structures.s_red2_settings.s_red2_settings
     attribute), 153
DISABLE (in module ics.ics), 206
disableFwLEDs (ics.structures.svcanrf_settings.svcanrf_settings
   attribute), 199
disk (ics.structures.s_cyan_settings.s_cyan_settings
   attribute), 117
disk (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings
   attribute), 123
disk (ics.structures.s_fire3_settings.s_fire3_settings
   attribute), 127
disk (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings
   attribute), 136
disk (ics.structures.s_red2_settings.s_red2_settings
   attribute), 153
disk (ics.structures.sobd2_lc_settings.sobd2_lc_settings
   attribute), 164
disk (ics.structures.srad_galaxy_settings.srad_galaxy_settings
   attribute), 172
disk (ics.structures.srad_gigalog_settings.srad_gigalog_settings
   attribute), 175
disk (ics.structures.srad_gigastar_settings.srad_gigastar_settings
   attribute), 178
disk (ics.structures.srada2_b_settings.srada2_b_settings
   attribute), 187
disk_enables (ics.structures.disk_settings.disk_settings
   attribute), 92
disk_format (ics.structures.disk_settings.disk_settings
   attribute), 92
disk_format () (in module ics.ics), 34
disk_format_cancel () (in module ics.ics), 34
disk_layout (ics.structures.disk_settings.disk_settings
   attribute), 92
disk_settings (class in ics.structures.disk_settings),
   92
DISK_SETTINGS_SIZE (in module ics.ics), 206
DISK_STATUS_FLAG_INITIALIZED (in module
   ics.ics), 206
DISK_STATUS_FLAG_PRESENT (in module ics.ics),
   206
DISK_STRUCTURE_FLAG_FULL_FORMAT (in module
   ics.ics), 206
DiskFormatexFAT (ics.structures.e_disk_format.e_disk_format
   attribute), 93
DiskFormatFAT32 (ics.structures.e_disk_format.e_disk_format
   attribute), 93
DiskFormatUnknown
    (ics.structures.e_disk_format.e_disk_format
     attribute), 93
DiskLayoutIndividual
    (ics.structures.e_disk_layout.e_disk_layout
     attribute), 93
DiskLayoutRAID0 (ics.structures.e_disk_layout.e_disk_layout
   attribute), 93
DiskLayoutRAID1 (ics.structures.e_disk_layout.e_disk_layout
   attribute), 93
DiskLayoutRAID5 (ics.structures.e_disk_layout.e_disk_layout
   attribute), 93
DiskLayoutSpanned
    (ics.structures.e_disk_layout.e_disk_layout
     attribute), 93
dotVersion (ics.structures.version_report.version_report
   attribute), 203
dwstreamChannelOffset
    (ics.structures.a2_b_monitor_settings.a2_b_monitor_settings
     attribute), 89
DRIVER_MASK (in module ics.ics), 206
DRIVER_USB1 (in module ics.ics), 206
DRIVER_USB2 (in module ics.ics), 206
DRIVER_USB3 (in module ics.ics), 206
drpdtag (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config
   attribute), 148
drpnona664 (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config
   attribute), 148
drpuntag (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config
   attribute), 148
duplex (ics.structures.ethernet_settings.ethernet_settings
   attribute), 96
dword (ics.structures.s_wil_bridge_config.s_wil_bridge_config
   attribute), 157
dyn_learn (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config
   attribute), 148
dyn_tbsz (ics.structures.s_pluto_l2_address_lookup_params.s.s_pluto_l
   attribute), 147
dynamic (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex
   attribute), 105

```

E

<i>e_device_settings_type</i>	(class	<i>in</i>
<i>ics.structures.e_device_settings_type</i>),	92	
<i>e_disk_format</i>	(class	<i>in</i>
<i>ics.structures.e_disk_format</i>),	93	
<i>e_disk_layout</i>	(class	<i>in</i>
<i>ics.structures.e_disk_layout</i>),	93	
<i>e_generic_api_options</i>	(class	<i>in</i>
<i>ics.structures.e_generic_api_options</i>),	93	
<i>e_gptp_port</i>	(class in <i>ics.structures.e_gptp_port</i>),	94
<i>e_gptp_role</i>	(class in <i>ics.structures.e_gptp_role</i>),	94
<i>e_plasma_ion_vnet_channel_t</i>	(class	<i>in</i>
<i>ics.structures.e_plasma_ion_vnet_channel_t</i> ,		
	94	

e_uart_port_t	(class <i>ics.structures.e_uart_port_t</i>), 95	in	<i>(ics.structures.srad_gptp_settings_s.srad_gptp_settings_s attribute)</i> , 180
eADI_WIL_API	(<i>ics.structures.e_generic_api_options.e_generic_api_options</i>)	<i>(ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute)</i> , 141	<i>(ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute)</i> , 141
ecu	(<i>ics.structures.global_settings.global_settings</i> at- tribute), 99	enabled	(<i>ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute</i>), 148
ecu_id	(<i>ics.structures.s_neo_ecu12_settings.s_neo_ecu12</i> at- tribute), 138	enabled	(<i>ics.structures.s_wil_fault_servicing_settings.s_wil_fault_servic- ing</i> attribute), 157
ecu_id	(<i>ics.structures.s_pendant_settings.s_pendant_settings</i> at- tribute), 139	enabled	(<i>ics.structures.s_wil_network_data_capture_settings.s_wil_netw- ork_data_capture</i> attribute), 157
ecu_id	(<i>ics.structures.s_vivid_can_settings.s_vivid_can_settings</i> at- tribute), 156	enableDOIPLine()	(in module <i>ics.ics</i>), 20
ecu_id	(<i>ics.structures.scan_hub_settings.scan_hub_settings</i> at- tribute), 157	enableFlowControlTransmission	
ecu_id	(<i>ics.structures.secu_settings.secu_settings</i> at- tribute), 159	EnableNetworkCom()	(in module <i>ics.ics</i>), 21
ecu_id	(<i>ics.structures.seevb_settings.seevb_settings</i> at- tribute), 160	enablePhy	(<i>ics.structures.s_pluto_custom_params.s_pluto_custom_params</i> attribute), 145
ecu_id	(<i>ics.structures.sievb_settings.sievb_settings</i> at- tribute), 162	enablePhy	(<i>ics.structures.srad_epsilon_switch_settings.srad_epsilon_swit- ch</i> attribute), 171
ecu_id	(<i>ics.structures.srad_comet_settings.srad_comet_settings</i> at- tribute), 168	enablePhy	(<i>ics.structures.srad_jupiter_switch_settings.srad_jupiter_swit- ch</i> attribute), 182
ecu_id	(<i>ics.structures.srad_gigalog_settings.srad_gigalog_settings</i> attribute), 195	endAddress	(<i>ics.structures.start_dhcp_server_command.start_dhcp_serv- er</i> attribute), 195
ecu_id	(<i>ics.structures.srad_gigastar_settings.srad_gigastar_settings</i> attribute), 146	enfport	(<i>ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_a- ddress_lookup_entry</i> attribute), 146
eevb	(<i>ics.structures.global_settings.global_settings</i> at- tribute), 99	enhancedFlashDriver	
eFpgaStatusResp	(<i>ics.structures.e_plasma Ion_vnet_channel</i> at- tribute), 94	(<i>ics.structures.device_feature.device_feature</i> attribute), 91	
eGENERIC_API	(<i>ics.structures.e_generic_api_options.e_generic_api_options</i>)	<i>(ics.structures.e_gptp_port.e_gptp_port attribute)</i> , 94	<i>(ics.structures.e_gptp_port.e_gptp_port attribute)</i> , 94
egr_mirr	(<i>ics.structures.s_pluto_mac_config.s.s_pluto_mac_config</i> at- tribute), 148	ePortConfigEth1	(<i>ics.structures.e_gptp_port.e_gptp_port</i> attribute), 94
egr_port	(<i>ics.structures.s_pluto_retagging_entry.s.s_pluto_retagging_entry</i> at- tribute), 150	ePortConfigEth1	(<i>ics.structures.e_gptp_port.e_gptp_port</i> attribute), 94
egress	(<i>ics.structures.s_pluto_mac_config.s.s_pluto_mac_config</i> at- tribute), 148	ePortOpEth11	(<i>ics.structures.e_gptp_port.e_gptp_port</i> attribute), 94
eLockManager	(<i>ics.structures.ew_bms_manager_lock_state</i> at- tribute), 97	ePortOpEth11	(<i>ics.structures.e_gptp_port.e_gptp_port</i> attribute), 94
eManagerPortA	(<i>ics.structures.ew_bms_manager_port_teal_blinking_icpatt</i> at- tribute), 97	ePortOpEth4	(<i>ics.structures.e_gptp_port.e_gptp_port</i> attribute), 94
eManagerPortB	(<i>ics.structures.ew_bms_manager_port_teal_blinking_icpatt</i> at- tribute), 97	ePortOpEth5	(<i>ics.structures.e_gptp_port.e_gptp_port</i> attribute), 94
enable_bus_voltage_monitor()	(in module <i>ics.ics</i>), 34	ePortOpEth6	(<i>ics.structures.e_gptp_port.e_gptp_port</i> attribute), 94
enable_convert_mode	(<i>ics.structures.j1708_settings.j1708_settings</i> attribute), 113	ePortOpEth7	(<i>ics.structures.e_gptp_port.e_gptp_port</i> attribute), 94
enable_doip_line()	(in module <i>ics.ics</i>), 35	ePortOpEth8	(<i>ics.structures.e_gptp_port.e_gptp_port</i> attribute), 94
enable_network_com()	(in module <i>ics.ics</i>), 35		
EnableBusVoltageMonitor()	(in module <i>ics.ics</i>), 20		
enableClockSyncronization			

ePortOpEth9 (*ics.structures.e_gptp_port.e_gptp_port* attribute), 94 ethernet (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 185
ePortStdEth1 (*ics.structures.e_gptp_port.e_gptp_port* attribute), 94 ethernet (*ics.structures.srada2_b_settings.srada2_b_settings* attribute), 187
ePortStdEth2 (*ics.structures.e_gptp_port.e_gptp_port* attribute), 94 ethernet (*ics.structures.sradbms_settings.sradbms_settings* attribute), 189
epsilon (*ics.structures.global_settings.global_settings* attribute), 99 ethernet (*ics.structures.svcn4_ind_settings.svcn4_ind_settings* attribute), 196
epsilon_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 191 ethernet (*ics.structures.svcn4_settings.svcn4_settings* attribute), 198
epsilonStatus (*ics.structures.ics_device_status.ics_device_status* attribute), 102 ethernet1 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 172
eRoleDisabled (*ics.structures.e_gptp_role.e_gptp_role* attribute), 94 ethernet1 (class in *ics.structures.ethernet10_g_settings*), 95
eRoleMaster (*ics.structures.e_gptp_role.e_gptp_role* attribute), 94 ethernet10_g_settings (class in *ics.structures.ethernet10_g_settings*), 95
eRolePassive (*ics.structures.e_gptp_role.e_gptp_role* attribute), 94 ethernet10_t1_s_settings (class in *ics.structures.ethernet10_t1_s_settings*), 95
eRoleSlave (*ics.structures.e_gptp_role.e_gptp_role* attribute), 94 ethernet10g (*ics.structures.srad_gigalog_settings.srad_gigalog_setting* attribute), 183
eSoftCore (*ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet_channel_t* attribute), 94 ETHERNET10G_SETTINGS_SIZE (in module *ics.ics*), 206
eth10g (*ics.structures.srad_moon3_settings.srad_moon3_settings* attribute), 183 ETHERNET10T1S_SETTINGS_FLAG_ENABLE_PLCA
Eth2 (*ics.structures.srad_super_moon_settings.srad_super_moon_settings* attribute), 186 ETHERNET10T1S_SETTINGS_FLAG_TERMINATION
ethConfigurationPort (*ics.structures.fire3_linux_settings.fire3_linux_settings* attribute), 97 (in module *ics.ics*), 206
ether_badge_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 191 ETHERNET10T1S_SETTINGS_SIZE (in module *ics.ics*), 206
etherBadge (*ics.structures.global_settings.global_settings* attribute), 100 ethernet2 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 117
ethernet (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 117 ethernet2 (*ics.structures.s_ether_badge_settings.s_ether_badge_settings* attribute), 120
ethernet (*ics.structures.s_ether_badge_settings.s_ether_badge_settings* attribute), 120 ethernet2 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 136
ethernet (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 136 ethernet2 (*ics.structures.sobd2_lc_settings.sobd2_lc_settings* attribute), 164
ethernet (*ics.structures.sobd2_lc_settings.sobd2_lc_settings* attribute), 164 ethernet2 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 165
ethernet (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 165 ethernet2 (*ics.structures.srad_epsilon_settings.srad_epsilon_settings* attribute), 170
ethernet (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 165 ethernet2 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 172
ethernet (*ics.structures.srad_comet_settings.srad_comet_settings* attribute), 169 ethernet2 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings* attribute), 175
ethernet (*ics.structures.srad_epsilon_settings.srad_epsilon_settings* attribute), 170 ethernet2 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 184
ethernet (*ics.structures.srad_epsilon_settings.srad_epsilon_settings* attribute), 170 ethernet2 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings* attribute), 181
ethernet (*ics.structures.srad_gigalog_settings.srad_gigalog_settings* attribute), 175 ethernet2 (*ics.structures.srad_pluto_settings.srad_pluto_settings* attribute), 189
ethernet (*ics.structures.srad_jupiter_settings.srad_jupiter_settings* attribute), 181 ethernet2 (*ics.structures.sradbms_settings.sradbms_settings* attribute), 189
ethernet (*ics.structures.srad_pluto_settings.srad_pluto_settings* attribute), 183 ethernet2 (*ics.structures.svcn4_ind_settings.svcn4_ind_settings* attribute), 198

attribute), 197

`ethernet2 (ics.structures.svcn4_settings.svcn4_settings
 attribute), 198`

`ETHERNET_SETTINGS10G_FLAG_LINK_MODE_AUTO
 (in module ics.ics), 207`

`ethernet2_1 (ics.structures.s_fire3_flexray_settings.s_fire3_flexraynoetmiges.ics), 207
 attribute), 124`

`ETHERNET_SETTINGS10G_FLAG_PHY_MODE
 (in module ics.ics), 207`

`ethernet2_1 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 127`

`ETHERNET_SETTINGS10G_FLAG_RTSP_ENABLE
 (in module ics.ics), 207`

`ethernet2_1 (ics.structures.s_red2_settings.s_red2_settings
 attribute), 153`

`ETHERNET_SETTINGS10G_FLAG_TCP_IP_ENABLE
 (in module ics.ics), 207`

`ethernet2_2 (ics.structures.s_fire3_flexray_settings.s_fire3_flexraycsettingstures.ethernet_settings2), 96
 attribute), 124`

`ETHERNET_SETTINGS2_FLAG2_LINK_MODE
 (in module ics.ics), 207`

`ethernet2_2 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 128`

`ETHERNET_SETTINGS2_FLAG2_LINK_MODE_AUTO
 (in module ics.ics), 207`

`ethernet2_2 (ics.structures.s_red2_settings.s_red2_settings
 attribute), 153`

`ETHERNET_SETTINGS2_FLAG2_PHY_MODE
 (in module ics.ics), 207`

`ethernet2_3 (ics.structures.s_fire3_flexray_settings.s_fire3_flexraynoetmiges.ics), 207
 attribute), 124`

`ETHERNET_SETTINGS2_FLAG_AUTO_NEG
 (in module ics.ics), 207`

`ethernet2_3 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 128`

`ETHERNET_SETTINGS2_FLAG_COMM_IN_USE
 (in module ics.ics), 207`

`ethernet_1 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_mattmiges.ics), 207
 attribute), 124`

`ETHERNET_SETTINGS2_FLAG_CONFIG_NOT_ALLOWED
 (in module ics.ics), 207`

`ethernet_1 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 128`

`ETHERNET_SETTINGS2_FLAG_DEVICE_HOSTING_ENABLE
 (in module ics.ics), 207`

`ethernet_1 (ics.structures.s_red2_settings.s_red2_settings
 attribute), 153`

`ETHERNET_SETTINGS2_FLAG_FULL_DUPLEX
 (in module ics.ics), 207`

`ethernet_2 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_mattmiges.ics), 207
 attribute), 124`

`ETHERNET_SETTINGS2_FLAG_ICS_SFP
 (in module ics.ics), 207`

`ethernet_2 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 128`

`ETHERNET_SETTINGS2_FLAG_RTSP_ENABLE
 (in module ics.ics), 207`

`ethernet_2 (ics.structures.s_red2_settings.s_red2_settings
 attribute), 153`

`ETHERNET_SETTINGS2_FLAG_TCP_IP_ENABLE
 (in module ics.ics), 207`

`ethernet_3 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_mattmiges.ics), 207
 attribute), 124`

`ETHERNET_SETTINGS2_SIZE
 (in module ics.ics), 207`

`ethernet_3 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 128`

`ETHERNET_SETTINGS_SIZE
 (in module ics.ics), 207`

`ethernet_network_status_t
 (class
 in
 ics.structures.ethernet_network_status_t), 95`

`ethernet_settings
 (class
 in
 ics.structures.ethernet_settings), 96`

`ETHERNET_SETTINGS10G_FLAG_AUTO_NEG
 (in module ics.ics), 206`

`ETHERNET_SETTINGS10G_FLAG_COMM_IN_USE
 (in module ics.ics), 206`

`ETHERNET_SETTINGS10G_FLAG_CONFIG_NOT_ALLOWED
 (in module ics.ics), 206`

`ETHERNET_SETTINGS10G_FLAG_DEVICE_HOSTING_ENABLE
 (in module ics.ics), 206`

`ETHERNET_SETTINGS10G_FLAG_FULL_DUPLEX
 (in module ics.ics), 206`

`ETHERNET_SETTINGS10G_FLAG_ICS_SFP
 (in module ics.ics), 206`

`ETHERNET_SETTINGS10G_FLAG_LINK_MODE
 (in module ics.ics), 207`

`ethernetActivationLineEnabled
 (ics.structures.ics_fire2_device_status.ics_fire2_device_status
 attribute), 103`

`ethernetActivationLineEnabled
 (ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device
 attribute), 103`

`ethernetActivationLineEnabled
 (ics.structures.ics_fire3_device_status.ics_fire3_device_status
 attribute), 103`

`ethernetActivationLineEnabled
 (ics.structures.ics_fire3_vnetz_device_status.ics_fire3_vnetz_device
 attribute), 103`

`ethernetActivationLineEnabled
 (ics.structures.ics_vcan4_device_status.ics_vcan4_device_status
 attribute), 110`

`ethernetActivationLineEnabled_2
 (ics.structures.ics_fire3_device_status.ics_fire3_device_status
 attribute), 103`

`ethernetStatus
 (ics.structures.ics_fire2_device_status.ics_fire2_device`

attribute), 103
 ethernetStatus (*ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device_status*
 attribute), 103
 ethernetStatus (*ics.structures.ics_fire3_device_status.ics_fire3_device_status*
 attribute), 103
 ethernetStatus (*ics.structures.ics_flex_vnetz_device_status.ics_flex_vnetz_device_status*
 attribute), 103
 ethernetStatus (*ics.structures.ics_obd2_pro_device_status.ics_obd2_pro_device_status*
 attribute), 103
 ethernetStatus (*ics.structures.ics_rad_bms_device_status.ics_rad_bms_device_status*
 attribute), 103
 ethernetStatus (*ics.structures.ics_rad_epsilon_device_status.ics_rad_epsilon_device_status*
 attribute), 104
 ethernetStatus (*ics.structures.ics_rad_jupiter_device_status.ics_rad_jupiter_device_status*
 attribute), 104
 ethernetStatus (*ics.structures.ics_rad_moon_duo_device_status.ics_rad_moon_duo_device_status*
 attribute), 104
 ethernetStatus (*ics.structures.ics_rad_pluto_device_status.ics_rad_pluto_device_status*
 attribute), 104
 ethernetStatus (*ics.structures.ics_vcan4_device_status.ics_vcan4_device_status*
 attribute), 110
 ethernetStatus (*ics.structures.ics_vcan4_industrial_device_status.ics_vcan4_industrial_device_status*
 attribute), 110
 ethT1 (*ics.structures.srad_comet_settings.srad_comet_settings*
 attribute), 168
 ethT1s1 (*ics.structures.srad_comet_settings.srad_comet_settings*
 attribute), 168
 ethT1s2 (*ics.structures.srad_comet_settings.srad_comet_settings*
 attribute), 168
 etssrcpcf (*ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params*
 attribute), 143
 eUART0 (*ics.structures.e_uart_port_t.e_uart_port_t*
 attribute), 95
 eUART1 (*ics.structures.e_uart_port_t.e_uart_port_t*
 attribute), 95
 eUnlockManager (*ics.structures.ew_bms_manager_lock_state_t.ew_bms_manager_lock_state_t*
 attribute), 97
 ew_bms_instance_t (class
ics.structures.ew_bms_instance_t), 96
 ew_bms_manager_lock_state_t (class
ics.structures.ew_bms_manager_lock_state_t),
 97
 ew_bms_manager_port_t (class
ics.structures.ew_bms_manager_port_t),
 97
 ewBMSInstance0 (*ics.structures.ew_bms_instance_t.ew_bms_instance_t*
 attribute), 96
 ewBMSInstance1 (*ics.structures.ew_bms_instance_t.ew_bms_instance_t*
 attribute), 96
 expansionSlot (*ics.structures.version_report.version_report*
 attribute), 203
 ExpectedLength (*ics.structures.spy_filter_long.spy_filter_long*
 attribute), 167
 ext_address_enable

(ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message)
 ext_address_enable
(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message)
 attribute), 192
(ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message)
 attribute), 97
(ics.structures.extended_response_generic),
 EXTENDED_RESPONSE_INVALID_COMMAND
(ics.structures.extended_response_code.extended_response_code)
 attribute), 97
(module ics.ics), 207
(ics.structures.extended_response_code.extended_response_code)
 EXTENDED_RESPONSE_INVALID_PARAMETER
(module ics.ics), 207
 EXTENDED_RESPONSE_INVALID_STATE
(ics.structures.extended_response_code.extended_response_code)
 attribute), 97
 EXTENDED_RESPONSE_INVALID_STATE (in module ics.ics), 207
(ics.structures.extended_response_code.extended_response_code)
 attribute), 97
 EXTENDED_RESPONSE_OK (in module ics.ics), 207
 EXTENDED_RESPONSE_OPERATION_FAILED
(ics.structures.extended_response_code.extended_response_code)
 attribute), 97
 EXTENDED_RESPONSE_OPERATION_FAILED (in module ics.ics), 207
 EXTENDED_RESPONSE_OPERATION_PENDING
(ics.structures.extended_response_code.extended_response_code)
 attribute), 97
 EXTENDED_RESPONSE_OPERATION_PENDING (in module ics.ics), 207
 extendedAddress (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message*
 attribute), 111
(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message)
 attribute), 192
(ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message)
 attribute), 193
(ics.structures.logger_settings.logger_settings)
 attribute), 113
 ExtraDataPtr (*ics.ics.SpyMessage* attribute), 18
 ExtraDataPtr (*ics.ics.SpyMessageJ1850* attribute),

19
attribute), 194
ExtraDataPtr(ics.structures.ics_spy_message_flex_ray.ics_spy_message_attributes.iso15765_2015_tx_message.iso15765_2015_tx_message_attributes), 104 attribute), 111
ExtraDataPtr(ics.structures.ics_spy_message_long.ics_spy_message_attributes.iso157652_rx_message.st_cm_iso157652_rx_message_attributes), 106 attribute), 193
ExtraDataPtr(ics.structures.ics_spy_message_mdio.ics_spy_message_attributes.iso157652_tx_message.st_cm_iso157652_tx_message_attributes), 108 attribute), 194
ExtraDataPtr(ics.structures.ics_spy_message_vsb.ics_spy_message_attributes), 109 attribute), 109
ExtraDataPtrEnabled (ics.ics.SpyMessage attribute), 18 attribute), 111
fc_id_29_bit_enable (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message_attributes), 193
ExtraDataPtrEnabled (ics.ics.SpyMessageJ1850 attribute), 19 attribute), 194
fc_id_29_bit_enable (ics.structures.ics_spy_message_flex_ray.ics_spy_message_attributes.iso157652_tx_message.st_cm_iso157652_tx_message_attributes), 104 attribute), 194
ExtraDataPtrEnabled (ics.structures.ics_spy_message_long.ics_spy_message_attributes), 106 attribute), 111
fc_id_mask (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message_attributes), 106 attribute), 194
ExtraDataPtrEnabled (ics.structures.ics_spy_message_mdio.ics_spy_message_attributes), 108 attribute), 105
fcrc1 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray_attributes), 105
fcrc2 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray_attributes), 106
F
fan_speed_interval_ms (ics.structures.rad_reporting_settings.rad_reporting_attributes), 115 attribute), 115
fast_init_network_enables_1 (ics.structures.s_fire_settings.s_fire_settings_attributes), 131
fast_init_network_enables_1 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings_attributes), 133
fast_init_network_enables_2 (ics.structures.s_fire_settings.s_fire_settings_attributes), 131
fast_init_network_enables_2 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings_attributes), 133
FAST_MODE (in module ics.ics), 207
fault_servicing_config (ics.structures.s_wil_connection_settings.s_wil_connection_attributes), 157
fc_ext_address_enable (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message_attributes), 111
fc_ext_address_enable (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message_attributes), 193
fc_ext_address_enable (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message_attributes), 193
FD_Baudrate (ics.structures.canfd_settings.canfd_settings_attributes), 90
FD_Baudrate (ics.structures.canfd_settings.canfd_settings_attributes), 90
FDMode (ics.structures.canfd_settings.canfd_settings_attributes), 90
FDTDC (ics.structures.canfd_settings.canfd_settings_attributes), 90
FDTqProp (ics.structures.canfd_settings.canfd_settings_attributes), 90
FDTqSeg1 (ics.structures.canfd_settings.canfd_settings_attributes), 90
FDTqSeg2 (ics.structures.canfd_settings.canfd_settings_attributes), 91
FDTqSync (ics.structures.canfd_settings.canfd_settings_attributes), 91
featureBitfields (ics.structures.get_supported_features_response.get_attributes), 99
findDevices() (in module ics.ics), 35
FindNeoDevices() (in module ics.ics), 21
finishedProcessing
fire (ics.structures.global_settings.global_settings_attributes), 100
FIRE2_REPORT_EMISC1_ANALOG (in module ics.ics), 207
FIRE2_REPORT_EMISC1_DIGITAL (in module ics.ics), 207

```

    ics.ics), 207
FIRE2_REPORT_EMISC2_ANALOG (in module ics.ics), 207
FIRE2_REPORT_EMISC2_DIGITAL (in module ics.ics), 207
FIRE2_REPORT_GPS (in module ics.ics), 207
FIRE2_REPORT_MISC5_DIGITAL (in module ics.ics), 207
FIRE2_REPORT_MISC6_DIGITAL (in module ics.ics), 207
FIRE2_REPORT_PERIODIC (in module ics.ics), 207
FIRE2_REPORT_PWM_IN (in module ics.ics), 207
FIRE2_REPORT_TEMP_ANALOG (in module ics.ics), 207
FIRE2_REPORT_VBATT_ANALOG (in module ics.ics), 207
fire2Status (ics.structures.ics_device_status.ics_device_status attribute), 102
fire3 (ics.structures.global_settings.global_settings attribute), 100
fire3_flexray_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 191
fire3_linux_settings (class ics.structures.fire3_linux_settings), 97
FIRE3_REPORT_ORIENTATION (in module ics.ics), 208
fire3_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 191
fire3fr (ics.structures.global_settings.global_settings attribute), 100
fire3Status (ics.structures.ics_device_status.ics_device_status attribute), 102
fire_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 191
firevnet (ics.structures.global_settings.global_settings attribute), 100
firmware_update_required () (in module ics.ics), 36
FirmwareUpdateRequired () (in module ics.ics), 21
fl_domain (ics.structures.s_pluto_l2_forwarding_entry_sfl_pluto_l2_forwarding_entry attribute), 147
flag (ics.structures.uart_port_port_bytes.uart_port_port_bytes attribute), 202
flags (ics.structures.a2_b_monitor_settings.a2_b_monitor_settings attribute), 89
flags (ics.structures.ethernet10_g_settings.ethernet10_g_settings attribute), 95
flags (ics.structures.ethernet10_t1_s_settings.ethernet10_t1_s_settings attribute), 95
flags (ics.structures.ethernet_settings2.ethernet_settings2 attribute), 96
flags (ics.structures.iso15765_2015_tx_message.iso15765_tx_message attribute), 2045
attribute), 111
flags (ics.structures.op_eth_general_settings.op_eth_general_settings attribute), 113
flags (ics.structures.rad_reporting_settings.rad_reporting_settings attribute), 116
flags (ics.structures.s_cyan_settings.s_cyan_settings attribute), 117
flags (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 120
flags (ics.structures.s_fire3	flexray_settings.s_fire3	flexray_settings attribute), 124
flags (ics.structures.s_fire3_settings.s_fire3_settings attribute), 128
flags (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 136
flags (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 138
flags (ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute), 141
flags (ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings attribute), 152
flags (ics.structures.s_red2_settings.s_red2_settings attribute), 153
flags (ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute), 156
flags (ics.structures.secu_avb_settings.secu_avb_settings attribute), 158
flags (ics.structures.serdescam_settings.serdescam_settings attribute), 161
flags (ics.structures.serdesgen_settings.serdesgen_settings attribute), 161
flags (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 164
flags (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 165
flags (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 166
flags (ics.structures.srad_comet_settings.srad_comet_settings attribute), 169
flags (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 170
flags (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 175
flags (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 178
flags (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 181
flags (ics.structures.srad_moon3_settings.srad_moon3_settings attribute), 183
flags (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 184
flags (ics.structures.srada2_b_settings.srada2_b_settings attribute), 187
flags (ics.structures.srdbms_settings.srdbms_settings attribute), 187

```

```

attribute), 189
flowControlExtendedAddress
flags (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_tx_message.st_cm_iso157652_tx_
attribute), 193
attribute), 194
flags (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_messageupdate () (in module ics.ics), 36
attribute), 194
ForceFirmwareUpdate () (in module ics.ics), 21
flags (ics.structures.svcn412_settings.svcn412_settingsframe_len_12_5ns (ics.structures.ics_spy_message_flex_ray.ics_spy_m
attribute), 196
attribute), 106
flags (ics.structures.svcn4_ind_settings.svcn4_ind_settingssame_reserved (ics.structures.ics_spy_message_flex_ray.ics_spy_m
attribute), 197
attribute), 106
flags (ics.structures.svcn4_settings.svcn4_settingsFrameMaster (ics.structures.spy_filter_long.spy_filter_long
attribute), 198
attribute), 167
flags2 (ics.structures.ethernet_settings2.ethernet_settingsFrameSkip (ics.structures.serdescam_settings.serdescam_settings
attribute), 96
attribute), 161
flash_phy_firmware () (in module ics.ics), 36
from_param (ics.structures.a2_b_node_type.a2_b_node_type
flashHeader (ics.structures.s_pluto_switch_settings.s_s_pluto_switattribute), 89
attribute), 150
from_param (ics.structures.a2_bt dm_mode.a2_bt dm_mode
FlashPhyFirmware () (in module ics.ics), 21
attribute), 89
flex_mode (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_setting (ics.structures.device_feature.device_feature
attribute), 124
attribute), 91
flex_mode (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_setting (ics.structures.e_device_settings_type.e_device_settings_typ
attribute), 136
attribute), 93
flex_termination (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_setting (ics.structures.e_disk_format.e_disk_format
attribute), 124
attribute), 93
flex_termination (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_setting (ics.structures.e_disk_layout.e_disk_layout
attribute), 136
attribute), 93
flex_vnet_mode (class
in from_param (ics.structures.e_generic_api_options.e_generic_api_option
ics.structures.flex_vnet_mode), 97
attribute), 94
flexVnetModeColdStart
from_param (ics.structures.e_gptp_port.e_gptp_port
attribute), 94
flexVnetModeDisabled
from_param (ics.structures.e_gptp_role.e_gptp_role
attribute), 94
flexVnetModeOneDual
from_param (ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion
attribute), 95
flexVnetModeOneSingle
from_param (ics.structures.e_uart_port_t.e_uart_port_t
attribute), 95
flexVnetModeTwoSingle
from_param (ics.structures.ew_bms_instance_t.ew_bms_instance_t
attribute), 96
flexvnetz (ics.structures.global_settings.global_settings
from_param (ics.structures.ew_bms_manager_lock_state_t.ew_bms_man
attribute), 100
attribute), 97
attribute), 97
from_param (ics.structures.flex_vnet_mode.flex_vnet_mode
flexVnetzStatus (ics.structures.ics_device_status.ics_device_statttribute), 98
attribute), 102
from_param (ics.structures.op_eth_link_mode.op_eth_link_mode
flow_control (ics.structures.uart_settings.uart_settings
attribute), 114
attribute), 114
flowControlExtendedAddress
from_param (ics.structures.phy_error_type.phy_error_type
attribute), 202
attribute), 115
flowControlExtendedAddress
from_param (ics.structures.s_phy_reg_pkt_rw.s_phy_reg_pkt_rw
attribute), 111
attribute), 142
flowControlExtendedAddress
from_param (ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_status
attribute), 193
fs_timeout (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_
attribute), 193
attribute), 144

```

```

    attribute), 111
fs_timeout (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message
attribute), 194
37
fs_wait (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message
attribute), 111
get_backup_power_enabled() (in module ics.ics),
fs_wait (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message
attribute), 194
get_backup_power_ready() (in module ics.ics),
fullcbg (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params_s
attribute), 143
get_bus_voltage() (in module ics.ics), 38
functionError (ics.structures.generic_api_status.generic_api_status_component_versions
attribute), 98
get_component_versions() (class in
ics.structures.get_component_versions),
functionID (ics.structures.generic_api_selector.generic_api_selector
attribute), 98
get_component_versions_response (class in
ics.structures.get_component_versions_response),
99
G
gateway (ics.structures.ethernet10_g_settings.ethernet10_g_settings
attribute), 95
get_device_settings() (in module ics.ics), 38
get_device_status() (in module ics.ics), 38
gateway (ics.structures.ethernet_settings2.ethernet_settings2
attribute), 96
get_disk_details() (in module ics.ics), 39
get_disk_format_progress() (in module
ics.ics), 39
gateway (ics.structures.sradbms_settings.sradbms_settings
attribute), 189
get_dll_firmware_info() (in module ics.ics), 39
get_dll_version() (in module ics.ics), 39
gatewayAddress (ics.structures.start_dhcp_server_command.start_dhcp_server_command
attribute), 195
get_error_messages() (in module ics.ics), 40
General_Settings (ics.structures.hw_eth_settings.hw_eth_settings
attribute), 102
get_gtp_status() (in module ics.ics), 40
get_hw_firmware_info() (in module ics.ics), 40
generalParams (ics.structures.s_pluto_switch_settings.s_pluto_switch_settings
attribute), 150
get_library_path() (in module ics.ics), 40
get_messages() (in module ics.ics), 41
generic_api_data (class in
ics.structures.generic_api_data), 98
get_pcba_serial_number() (in module ics.ics), 41
GENERIC_API_DATA_BUFFER_SIZE (in module
ics.ics), 208
get_performance_parameters() (in module
ics.ics), 41
generic_api_data_old (class in
ics.structures.generic_api_data_old), 98
get_phy_firmware_version() (in module
ics.ics), 41
generic_api_get_status() (in module ics.ics), 36
get_rtc() (in module ics.ics), 42
generic_api_read_data() (in module ics.ics), 37
get_script_status() (in module ics.ics), 42
generic_api_selector (class in
ics.structures.generic_api_selector), 98
get_serial_number() (in module ics.ics), 42
GET_SUPPORTED_FEATURES_COMMAND_VERSION
(in module ics.ics), 208
generic_api_send_command() (in module
ics.ics), 37
get_supported_features_response (class in
ics.structures.get_supported_features_response),
99
generic_api_status (class in
ics.structures.generic_api_status), 98
get_timestamp_for_msg() (in module ics.ics), 42
generic_binary_status (class in
ics.structures.generic_binary_status), 98
GetActiveVNETChannel() (in module ics.ics), 22
GENERIC_BINARY_STATUS_ERROR_ANY_MASK (in
module ics.ics), 208
GetAllChipVersions() (in module ics.ics), 22
GetBackupPowerEnabled() (in module ics.ics), 22
GetBackupPowerReady() (in module ics.ics), 22
GetBusVoltage() (in module ics.ics), 22
GENERIC_BINARY_STATUS_ERROR_BINARY_EMPTY
(in module ics.ics), 208
GetDeviceSettings() (in module ics.ics), 22
GENERIC_BINARY_STATUS_ERROR_OVERSIZE (in
module ics.ics), 208
GetDeviceStatus() (in module ics.ics), 23
GetDLLFirmwareInfo() (in module ics.ics), 22
GetDLLVersion() (in module ics.ics), 22
GENERIC_BINARY_STATUS_ERROR_UNKNOWN_BINARY
(in module ics.ics), 208
GetErrorMessages() (in module ics.ics), 23
GenericAPIGetStatus() (in module ics.ics), 21
GetGTPStatus() (in module ics.ics), 23
GenericAPIReadData() (in module ics.ics), 21
GetHWFirmwareInfo() (in module ics.ics), 23

```

GetLastAPIError () (*in module ics.ics*), 23
 GetMessages () (*in module ics.ics*), 23
 GetPCBSerialNumber () (*in module ics.ics*), 23
 GetPerformanceParameters () (*in module ics.ics*), 23
 GetPhyFwVersion () (*in module ics.ics*), 24
 GetRTC () (*in module ics.ics*), 24
 GetSerialNumber () (*in module ics.ics*), 24
 GetTimeStampForMsg () (*in module ics.ics*), 24
 global_settings (*class in ics.structures.global_settings*), 99
 GLOBAL_SETTINGS_SIZE (*in module ics.ics*), 208
 gm_priority (*ics.structures.gptp_status.gptp_status attribute*), 101
 gps_interval_ms (*ics.structures.rad_reporting_setting attribute*), 116
 gPTP (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray attribute*), 124
 gPTP (*ics.structures.s_fire3_settings.s_fire3_settings attribute*), 128
 gPTP (*ics.structures.s_red2_settings.s_red2_settings attribute*), 153
 gPTP (*ics.structures.srad_comet_settings.srad_comet_settings attribute*), 169
 gPTP (*ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute*), 172
 gPTP (*ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute*), 178
 gPTP (*ics.structures.srad_gptp_and_tap_settings.s.srad_gptp_and_tap_attributes*), 168
 gPTP (*ics.structures.srad_star2_settings.srad_star2_settings attribute*), 185
 gPTP (*ics.structures.srad_super_moon_settings.srad_supermoon_attributes*), 186
 gPTP (*ics.structures.srada2_b_settings.srada2_b_settings attribute*), 188
 gptp_status (*class in ics.structures.gptp_status*), 101
 gptpEnabledPort (*ics.structures.srad_gptp_settings.s.srad_gptp_attributes*), 180
 gPTPportRole (*ics.structures.s_jupiter_ptp_params.s.s_jupiter_ptp_attributes*), 137
 gPTPportRole (*ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_attributes*), 149
 gPTPportRole (*ics.structures.srad_gptp_settings.s.srad_gptp_attributes*), 180
 GS_VERSION (*in module ics.ics*), 208

H

half_duplex (*ics.structures uart_settings.uart_settings attribute*), 203
 Handle (*ics.ics.NeoDevice attribute*), 18

HARDWARE_TIMESTAMP_ID_AVT_716 (*in module ics.ics*), 208
 HARDWARE_TIMESTAMP_ID_AVT_717 (*in module ics.ics*), 208
 HARDWARE_TIMESTAMP_ID_DOUBLE_SEC (*in module ics.ics*), 208
 HARDWARE_TIMESTAMP_ID_NEORED_10NS (*in module ics.ics*), 208
 HARDWARE_TIMESTAMP_ID_NEORED_10US (*in module ics.ics*), 208
 HARDWARE_TIMESTAMP_ID_NEORED_25NS (*in module ics.ics*), 208
 HARDWARE_TIMESTAMP_ID_NEOVI (*in module ics.ics*), 208

HARDWARE_TIMESTAMP_ID_NI_CAN (*in module ics.ics*), 208
HARDWARE_TIMESTAMP_ID_NONE (*in module ics.ics*), 208
 HARDWARE_TIMESTAMP_ID_VSI (*in module ics.ics*), 208

hcrc_lsbs (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flexray_attributes*), 106
 hcrc_msbs (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flexray_attributes*), 106

Header (*ics.ics.SpyMessageJ1850 attribute*), 19
 Header (*ics.structures.spy_filter_long.spy_filter_long attribute*), 167
 HeaderLength (*ics.structures.spy_filter_long.spy_filter_long attribute*), 168

HeaderMask (*ics.structures.spy_filter_long.spy_filter_long attribute*), 168

high_speed_auto_switch (*ics.structures.swcan_settings.swcan_settings attribute*), 200

hw_eth_settings (*class in ics.structures.hw_eth_settings*), 102
 HW_ETH_SETTINGS_SIZE (*in module ics.ics*), 208

hwComLatencyTestEn (*ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute*), 182
 hwComLatencyTestEn (*ics.structures.srad_star2_settings.srad_star2_settings attribute*), 185
 hwComLatencyTestEn (*ics.structures.srad_super_moon_settings.srad_super_moon_settings attribute*), 186

| *ics.structures.ics_spy_message_vsb), 109*

iAppMajor (*ics.structures.st_api_firmware_info.st_api_firmware_info.vcan4_device_status (class in ics.structures.ics_vcan4_device_status), 110*
attribute), 190

iAppMinor (*ics.structures.st_api_firmware_info.st_api_firmware_info.vcan4_industrial_device_status (class in ics.structures.ics_vcan4_industrial_device_status), 110*
attribute), 190

iBoardRevMajor (*ics.structures.st_api_firmware_info.st_api_firmware_info.neoClosePort () (in module ics.ics), 42*
attribute), 190

iBoardRevMinor (*ics.structures.st_api_firmware_info.st_api_firmware_info.neoEnableBusVoltageMonitor () (in module ics.ics), 42*
attribute), 190

iBootLoaderVersionMajor (*ics.structures.st_api_firmware_info.st_api_firmware_info.neoEnableDOIPLine () (in module ics.ics), 42*
attribute), 190

iBootLoaderVersionMinor (*ics.structures.st_api_firmware_info.st_api_firmware_info.neoEnableNetworkCom () (in module ics.ics), 43*
attribute), 190

ics.ics (*module*), 17

ics_device_status (*class in ics.structures.ics_device_status), 102*

ics_fire2_device_status (*class in ics.structures.ics_fire2_device_status), 102*

ics_fire2_vnet_device_status (*class in ics.structures.ics_fire2_vnet_device_status), 103*

ics_fire3_device_status (*class in ics.structures.ics_fire3_device_status), 103*

ics_flex_vnetz_device_status (*class in ics.structures.ics_flex_vnetz_device_status), 103*

ics_obd2_pro_device_status (*class in ics.structures.ics_obd2_pro_device_status), 103*

ics_rad_bms_device_status (*class in ics.structures.ics_rad_bms_device_status), 103*

ics_rad_epsilon_device_status (*class in ics.structures.ics_rad_epsilon_device_status), 104*

ics_rad_jupiter_device_status (*class in ics.structures.ics_rad_jupiter_device_status), 104*

ics_rad_moon_duo_device_status (*class in ics.structures.ics_rad_moon_duo_device_status), 104*

ics_rad_pluto_device_status (*class in ics.structures.ics_rad_pluto_device_status), 104*

ics_spy_message_flex_ray (*class in ics.structures.ics_spy_message_flex_ray), 104*

ics_spy_message_long (*class in ics.structures.ics_spy_message_long), 106*

ics_spy_message_mdio (*class in ics.structures.ics_spy_message_mdio), 107*

ics_spy_message_vsb (*class in ics.structures.ics_spy_message_vsb), 109*

icsneoClosePort () (*in module ics.ics*), 42

icsneoEnableBusVoltageMonitor () (*in module ics.ics*), 42

icsneoEnableDOIPLine () (*in module ics.ics*), 42

icsneoEnableNetworkCom () (*in module ics.ics*), 43

icsneoFindNeoDevices () (*in module ics.ics*), 43

icsneoFirmwareUpdateRequired () (*in module ics.ics*), 43

icsneoFlashPhyFirmware () (*in module ics.ics*), 43

icsneoForceFirmwareUpdate () (*in module ics.ics*), 43

icsneoGenericAPIGetStatus () (*in module ics.ics*), 43

icsneoGenericAPIReadData () (*in module ics.ics*), 43

icsneoGenericAPISendCommand () (*in module ics.ics*), 43

icsneoGetActiveVNETChannel () (*in module ics.ics*), 44

icsneoGetAllChipVersions () (*in module ics.ics*), 44

icsneoGetBackupPowerEnabled () (*in module ics.ics*), 44

icsneoGetBackupPowerReady () (*in module ics.ics*), 44

icsneoGetBusVoltage () (*in module ics.ics*), 44

icsneoGetDeviceSettings () (*in module ics.ics*), 44

icsneoGetDeviceStatus () (*in module ics.ics*), 45

icsneoGetDLLFirmwareInfo () (*in module ics.ics*), 44

icsneoGetDLLVersion () (*in module ics.ics*), 44

icsneoGetErrorMessages () (*in module ics.ics*), 45

icsneoGetGTPStatus () (*in module ics.ics*), 45

icsneoGetHWFirmwareInfo () (*in module ics.ics*), 45

icsneoGetLastError () (*in module ics.ics*), 45

icsneoGetMessages () (*in module ics.ics*), 45

icsneoGetPCBSerialNumber () (*in module ics.ics*), 45

icsneoGetPerformanceParameters () (*in module ics.ics*), 45

icsneoGetPhyFwVersion () (*in module ics.ics*), 46

icsneoGetRTC () (*in module ics.ics*), 46

icsneoGetSerialNumber () (*in module ics.ics*), 46

icsneoGetTimeStampForMsg() (in module `ics.ics`), 46
 icsneoIsDeviceFeatureSupported() (in module `ics.ics`), 47
 icsneoISO15765_DisableNetworks() (in module `ics.ics`), 46
 icsneoISO15765_EnableNetworks() (in module `ics.ics`), 46
 icsneoISO15765_ReceiveMessage() (in module `ics.ics`), 46
 icsneoISO15765_TransmitMessage() (in module `ics.ics`), 46
 icsneoLoadDefaultSettings() (in module `ics.ics`), 47
 icsneoOpenNeoDevice() (in module `ics.ics`), 47
 icsneoReadJupiterFirmware() (in module `ics.ics`), 47
 icsneoReadSDCard() (in module `ics.ics`), 47
 icsneoRequestDiskDetails() (in module `ics.ics`), 47
 icsneoRequestDiskFormat() (in module `ics.ics`), 47
 icsneoRequestDiskFormatCancel() (in module `ics.ics`), 47
 icsneoRequestDiskFormatProgress() (in module `ics.ics`), 48
 icsneoRequestEnterSleepMode() (in module `ics.ics`), 48
 icsneoScriptClear() (in module `ics.ics`), 48
 icsneoScriptGetFBlockStatus() (in module `ics.ics`), 48
 icsneoScriptGetScriptStatus() (in module `ics.ics`), 48
 icsneoScriptGetScriptStatusEx() (in module `ics.ics`), 48
 icsneoScriptLoad() (in module `ics.ics`), 48
 icsneoScriptReadAppSignal() (in module `ics.ics`), 48
 icsneoScriptReadRxMessage() (in module `ics.ics`), 49
 icsneoScriptReadTxMessage() (in module `ics.ics`), 49
 icsneoScriptStart() (in module `ics.ics`), 49
 icsneoScriptStartFBlock() (in module `ics.ics`), 49
 icsneoScriptStop() (in module `ics.ics`), 49
 icsneoScriptStopFBlock() (in module `ics.ics`), 49
 icsneoScriptWriteAppSignal() (in module `ics.ics`), 49
 icsneoScriptWriteRxMessage() (in module `ics.ics`), 49
 icsneoScriptWriteTxMessage() (in module `ics.ics`), 50
 icsneoSetActiveVNETChannel() (in module `ics.ics`), 50
 icsneoSetBackupPowerEnabled() (in module `ics.ics`), 50
 icsneoSetBitRate() (in module `ics.ics`), 50
 icsneoSetBitRateEx() (in module `ics.ics`), 50
 icsneoSetContext() (in module `ics.ics`), 50
 icsneoSetDeviceSettings() (in module `ics.ics`), 50
 icsneoSetFDBitRate() (in module `ics.ics`), 50
 icsneoSetLedProperty() (in module `ics.ics`), 51
 icsneoSetReflashDisplayCallbacks() (in module `ics.ics`), 51
 icsneoSetRTC() (in module `ics.ics`), 51
 icsneoStartDHCPServer() (in module `ics.ics`), 51
 icsneoStopDHCPServer() (in module `ics.ics`), 51
 icsneoTxMessages() (in module `ics.ics`), 51
 icsneoUartGetBaudrate() (in module `ics.ics`), 51
 icsneoUartRead() (in module `ics.ics`), 51
 icsneoUartSetBaudrate() (in module `ics.ics`), 51
 icsneoUartWrite() (in module `ics.ics`), 52
 icsneoValidateHObject() (in module `ics.ics`), 52
 icsneowBMSManagerReset() (in module `ics.ics`), 52
 icsneowBMSManagerWriteLock() (in module `ics.ics`), 52
 icsneoWriteJupiterFirmware() (in module `ics.ics`), 52
 icsneoWriteSDCard() (in module `ics.ics`), 52
 id(`ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray` attribute), 106
 id(`ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message` attribute), 111
 id(`ics.structures.scan_sleep_id.scan_sleep_id` attribute), 158
 id(`ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message` attribute), 193
 id(`ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message` attribute), 194
 id_29_bit_enable(`ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message` attribute), 111
 id_29_bit_enable(`ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message` attribute), 193
 id_29_bit_enable(`ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message` attribute), 194
 id_mask(`ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message` attribute), 193
 identifier(`ics.structures.version_report.version_report` attribute), 203
 idle_wakeup_network_enables_1(`ics.structures.s_cyan_settings.s_cyan_settings` attribute), 117
 idle_wakeup_network_enables_1(`ics.structures.sievb_settings.sievb_settings`

```

    attribute), 162
idle_wakeup_network_enables_1           ifg (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s
                                         attribute), 148
                                         (ics.structures.srad_galaxy_settings.srad_galaxy_settingattribute), 172
                                         attribute), 172
idle_wakeup_network_enables_1           iMainFirmChkSum (ics.structures.st_api_firmware_info.st_api_firmware
                                         (ics.structures.srad_gigalog_settings.srad_gigalog_settingsattribute), 190
                                         attribute), 190
idle_wakeup_network_enables_1           iMainFirmDateDay (ics.structures.st_api_firmware_info.st_api_firmware
                                         (ics.structures.srad_gigastar_settings.srad_gigastar_settingattribute), 178
                                         attribute), 178
idle_wakeup_network_enables_1           iMainFirmDateHour (ics.structures.st_api_firmware_info.st_api_firmware_info
                                         attribute), 190
idle_wakeup_network_enables_1           iMainFirmDateMin (ics.structures.st_api_firmware_info.st_api_firmware
                                         attribute), 190
idle_wakeup_network_enables_1           iMainFirmDateMonth
                                         (ics.structures.st_api_firmware_info.st_api_firmware_info
                                         attribute), 190
idle_wakeup_network_enables_1           iMainFirmDateSecond
                                         (ics.structures.st_api_firmware_info.st_api_firmware_info
                                         attribute), 190
idle_wakeup_network_enables_1           iMainFirmDateYear
                                         (ics.structures.st_api_firmware_info.st_api_firmware_info
                                         attribute), 190
idle_wakeup_network_enables_2           iMainVnetHWrevMajor
                                         (ics.structures.s_cyan_settings.s_cyan_settingsattribute), 117
idle_wakeup_network_enables_2           iMainVnetHWrevMinor
                                         (ics.structures.srad_gigalog_settings.srad_gigalog_settingsattribute), 176
idle_wakeup_network_enables_2           iMainVnetSRAMSize
                                         (ics.structures.srad_gigastar_settings.srad_gigastar_settingattribute), 178
idle_wakeup_network_enables_2           iManufactureDay (ics.structures.st_api_firmware_info.st_api_firmware
                                         (ics.structures.srad_star2_settings.srad_star2_settingsattribute), 190
                                         attribute), 185
idle_wakeup_network_enables_2           iManufactureMonth
                                         (ics.structures.st_api_firmware_info.st_api_firmware_info
                                         attribute), 190
idle_wakeup_network_enables_2           iManufactureYear (ics.structures.st_api_firmware_info.st_api_firmware
                                         attribute), 190
idle_wakeup_network_enables_3           incl_srcpt0 (ics.structures.s_pluto_general_params_s.s_pluto_general_
                                         attribute), 145
                                         (ics.structures.s_cyan_settings.s_cyan_settingsattribute), 117
idle_wakeup_network_enables_3           incl_srcpt1 (ics.structures.s_pluto_general_params_s.s_pluto_general_
                                         attribute), 145
                                         (ics.structures.srad_galaxy_settings.srad_galaxy_settingsattribute), 172
idle_wakeup_network_enables_3           index (ics.structures.generic_binary_status.generic_binary_status
                                         attribute), 98
idle_wakeup_network_enables_3           incl_srcpt0 (ics.structures.s_pluto_general_params_s.s_pluto_general_
                                         attribute), 146
                                         (ics.structures.srad_gigalog_settings.srad_gigalog_settingattribute), 176
idle_wakeup_network_enables_3           incl_srcpt1 (ics.structures.s_pluto_general_params_s.s_pluto_general_
                                         attribute), 148
                                         (ics.structures.srad_gigastar_settings.srad_gigastar_settingattribute), 188
idle_wakeup_network_enables_3           incl_srcpt0 (ics.structures.s_pluto_general_params_s.s_pluto_general_
                                         attribute), 150
                                         (ics.structures.srad_star2_settings.srad_star2_settingsattribute), 185
idle_wakeup_network_enables_3           incl_srcpt1 (ics.structures.s_pluto_general_params_s.s_pluto_general_
                                         attribute), 148
                                         (ics.structures.global_settings.global_settingsattribute), 100
ievb (ics.structures.global_settings.global_settings at- init_step_count (ics.structures.iso9141_keyword2000_settings.iso91
                                         attribute), 100                                         attribute), 112

```

```

init_steps (ics.structures.iso9141_keyword2000_settings.iso9141attribute2000_settings
            attribute), 112
initLogPDelayReqInterval
            (ics.structures.s_jupiter_ptp_params.s.s_jupiter_ptp_params.FeatureSupported() (in module
            attribute), 137
            attribute), 137
initLogSyncInterval
            (ics.structures.s_jupiter_ptp_params.s.s_jupiter_ptp_params.FeatureSupported() (in module
            attribute), 137
            attribute), 137
innerFrameDelay25us
            (ics.structures.can_settings.can_settings
            attribute), 90
instance (ics.structures.generic_api_selector.generic_api_selector208
            attribute), 98
intcydur (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s
            attribute), 143
inttosynch (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s
            attribute), 143
inttotenth (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s
            attribute), 143
invert_rx (ics.structures uart_settings.uart_settings
            attribute), 203
invert_tx (ics.structures uart_settings.uart_settings
            attribute), 203
io_interval_ms (ics.structures.rad_reporting_settings.rad_reporting_settings
            attribute), 116
ip_addr (ics.structures.ethernet10_g_settings.ethernet10_g_setting208
            attribute), 95
ip_addr (ics.structures.ethernet_settings2.ethernet_settings2
            attribute), 96
ipAddress (ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_converter_settings
            attribute), 115
ipcframesy (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s
            attribute), 143
ipGateway (ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_converter_settings
            attribute), 115
iPhySiliconRev (ics.structures.st_api_firmware_info.st_api_firmware_info
            attribute), 190
ipMask (ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_converter_settings
            attribute), 115
is_device_feature_supported() (in module
            ics.ics), 52
is_sync (ics.structures.gptp_status.gptp_status at-
            tribute), 101
is_syntonized (ics.structures.gptp_status.gptp_status
            attribute), 102
isBRSEnabled (ics.structures.iso15765_2015_tx_message.iso15765attribute2015_tx_message
            attribute), 111
isBRSEnabled (ics.structures.st_cm_iso15765_rx_message.st_cm_iso15765_rx_message.flexray_settings.s_fire3	flexray_settings
            attribute), 193
isBRSEnabled (ics.structures.st_cm_iso15765_tx_message.st_cm_iso15765_tx_message.fire3_settings
            attribute), 194
iscanFD (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message.attribute28
            attribute), 111
iscanFD (ics.structures.st_cm_iso15765_rx_message.st_cm_iso15765_rx_message.fire_settings.s_fire_settings
            attribute), 111
iscanFD (ics.structures.st_cm_iso15765_rx_message.st_cm_iso15765_rx_message.fire_settings.s_fire_settings
            attribute), 111
iscanFD (ics.structures.st_cm_iso15765_tx_message.st_cm_iso15765_tx_message.fire_settings.s_fire_settings
            attribute), 111
iso15765_2_NETWORK_HSCAN (in module ics.ics),
            208
ISO15765_2_NETWORK_HSCAN2 (in module ics.ics),
            111
ISO15765_2_NETWORK_HSCAN3 (in module ics.ics),
            208
ISO15765_2_NETWORK_HSCAN4 (in module ics.ics),
            208
ISO15765_2_NETWORK_HSCAN5 (in module ics.ics),
            208
ISO15765_2_NETWORK_HSCAN6 (in module ics.ics),
            208
ISO15765_2_NETWORK_HSCAN7 (in module ics.ics),
            208
ISO15765_2_NETWORK_MSCAN (in module ics.ics),
            208
ISO15765_2_NETWORK_SWCAN (in module ics.ics),
            208
ISO15765_DisableNetworks () (in module
            ics.ics), 24
ISO15765_EnableNetworks () (in module ics.ics),
            24
ISO15765_ReceiveMessage () (in module ics.ics),
            24
iso15765_separation_time_offset
            (ics.structures.s_cyan_settings.s_cyan_settings
            attribute), 117
iso15765_separation_time_offset
            (ics.structures.s_ether_badge_settings.s_ether_badge_settings
            attribute), 124
iso15765_separation_time_offset
            (ics.structures.s_fire3_settings.s_fire3_settings
            attribute), 128
iso15765_separation_time_offset
            (ics.structures.s_fire3_settings.s_fire3_settings
            attribute), 128
iso15765_separation_time_offset
            (ics.structures.s_fire_settings.s_fire_settings
            attribute), 128

```

<code>attribute), 131</code> <code>iso15765_separation_time_offset (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 134</code> <code>iso15765_separation_time_offset (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 136</code> <code>iso15765_separation_time_offset (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 138</code> <code>iso15765_separation_time_offset (ics.structures.s_pendant_settings.s_pendant_settings attribute), 139</code> <code>iso15765_separation_time_offset (ics.structures.s_red2_settings.s_red2_settings attribute), 153</code> <code>iso15765_separation_time_offset (ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute), 156</code> <code>iso15765_separation_time_offset (ics.structures.scan_hub_settings.scan_hub_settings attribute), 157</code> <code>iso15765_separation_time_offset (ics.structures.secu_avb_settings.secu_avb_settings attribute), 158</code> <code>iso15765_separation_time_offset (ics.structures.secu_settings.secu_settings attribute), 159</code> <code>iso15765_separation_time_offset (ics.structures.seevb_settings.seevb_settings attribute), 160</code> <code>iso15765_separation_time_offset (ics.structures.sievb_settings.sievb_settings attribute), 162</code> <code>iso15765_separation_time_offset (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 164</code> <code>iso15765_separation_time_offset (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 165</code> <code>iso15765_separation_time_offset (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 166</code> <code>iso15765_separation_time_offset (ics.structures.srad_comet_settings.srad_comet_settings attribute), 169</code> <code>iso15765_separation_time_offset (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 170</code> <code>iso15765_separation_time_offset (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 173</code> <code>iso15765_separation_time_offset (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 174</code>	<code>attribute), 176</code> <code>iso15765_separation_time_offset (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 178</code> <code>iso15765_separation_time_offset (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 181</code> <code>iso15765_separation_time_offset (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 184</code> <code>iso15765_separation_time_offset (ics.structures.srad_star2_settings.srad_star2_settings attribute), 185</code> <code>iso15765_separation_time_offset (ics.structures.srada2_b_settings.srada2_b_settings attribute), 188</code> <code>iso15765_separation_time_offset (ics.structures.srdbms_settings.srdbms_settings attribute), 189</code> <code>iso15765_separation_time_offset (ics.structures.svcan3_settings.svcan3_settings attribute), 195</code> <code>iso15765_separation_time_offset (ics.structures.svcan412_settings.svcan412_settings attribute), 196</code> <code>iso15765_separation_time_offset (ics.structures.svcan4_ind_settings.svcan4_ind_settings attribute), 197</code> <code>iso15765_separation_time_offset (ics.structures.svcan4_settings.svcan4_settings attribute), 198</code> <code>iso15765_separation_time_offset (ics.structures.svcanrf_settings.svcanrf_settings attribute), 199</code> <code>iso15765_transmit_message () (in module ics.ics), 53</code> <code>ISO15765_TransmitMessage () (in module ics.ics), 24</code> <code>ISO9141_KEYWORD2000_INIT_STEP_SIZE (in module ics.ics), 208</code> <code>iso9141_keyword2000_init_step (class in ics.structures.iso9141_keyword2000_init_step), 112</code> <code>iso9141_keyword2000_settings (class in ics.structures.iso9141_keyword2000_settings), 112</code> <code>ISO9141_KEYWORD2000_SETTINGS_SIZE (in module ics.ics), 208</code> <code>iso9141_kwp_enable_reserved (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 121</code> <code>iso9141_kwp_enable_reserved (ics.structures.s_fire_settings.s_fire_settings attribute), 131</code>
--	---

iso9141_kwp_enable_reserved (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute</i>), 134	iso9141_kwp_settings_1 (<i>ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute</i>), 124
iso9141_kwp_enable_reserved (<i>ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute</i>), 170	iso9141_kwp_settings_1 (<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 128
iso9141_kwp_enable_reserved (<i>ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute</i>), 181	iso9141_kwp_settings_1 (<i>ics.structures.s_red2_settings.s_red2_settings attribute</i>), 153
iso9141_kwp_enable_reserved (<i>ics.structures.srad_pluto_settings.srad_pluto_settings attribute</i>), 184	iso9141_kwp_settings_1 (<i>ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute</i>), 164
iso9141_kwp_enable_reserved (<i>ics.structures.svcancrf_settings.svcancrf_settings attribute</i>), 199	iso9141_kwp_settings_1 (<i>ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute</i>), 165
iso9141_kwp_settings (<i>ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute</i>), 121	iso9141_kwp_settings_1 (<i>ics.structures.srad_comet_settings.srad_comet_settings attribute</i>), 169
iso9141_kwp_settings (<i>ics.structures.s_fire_settings.s_fire_settings attribute</i>), 131	iso9141_kwp_settings_1 (<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute</i>), 173
iso9141_kwp_settings (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute</i>), 134	iso9141_kwp_settings_1 (<i>ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute</i>), 176
iso9141_kwp_settings (<i>ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute</i>), 138	iso9141_kwp_settings_1 (<i>ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute</i>), 178
iso9141_kwp_settings (<i>ics.structures.s_pendant_settings.s_pendant_settings attribute</i>), 139	iso9141_kwp_settings_1 (<i>ics.structures.srad_star2_settings.srad_star2_settings attribute</i>), 185
iso9141_kwp_settings (<i>ics.structures.secu_settings.secu_settings attribute</i>), 159	iso9141_kwp_settings_1 (<i>ics.structures.srada2_b_settings.srada2_b_settings attribute</i>), 188
iso9141_kwp_settings (<i>ics.structures.sievb_settings.sievb_settings attribute</i>), 162	iso9141_kwp_settings_1 (<i>ics.structures.svcanc4_settings.svcanc4_settings attribute</i>), 198
iso9141_kwp_settings (<i>ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute</i>), 170	iso9141_kwp_settings_2 (<i>ics.structures.s_cyan_settings.s_cyan_settings attribute</i>), 117
iso9141_kwp_settings (<i>ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute</i>), 181	iso9141_kwp_settings_2 (<i>ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute</i>), 124
iso9141_kwp_settings (<i>ics.structures.srad_pluto_settings.srad_pluto_settings attribute</i>), 184	iso9141_kwp_settings_2 (<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 128
iso9141_kwp_settings (<i>ics.structures.svcanc4_ind_settings.svcanc4_ind_settings attribute</i>), 197	iso9141_kwp_settings_2 (<i>ics.structures.s_fire_settings.s_fire_settings attribute</i>), 131
iso9141_kwp_settings (<i>ics.structures.svcancrf_settings.svcancrf_settings attribute</i>), 199	iso9141_kwp_settings_2 (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute</i>), 134
iso9141_kwp_settings_1 (<i>ics.structures.s_cyan_settings.s_cyan_settings attribute</i>), 117	iso9141_kwp_settings_2 (<i>ics.structures.s_pendant_settings.s_pendant_settings attribute</i>), 139

iso9141_kwp_settings_2
(*ics.structures.s_red2_settings.s_red2_settings*
attribute), 153

iso9141_kwp_settings_2
(*ics.structures.secu_settings.secu_settings*
attribute), 159

iso9141_kwp_settings_2
(*ics.structures.sievb_settings.sievb_settings*
attribute), 162

iso9141_kwp_settings_2
(*ics.structures.sobd2_pro_settings.sobd2_pro_settings*
attribute), 165

iso9141_kwp_settings_2
(*ics.structures.svcancrf_settings.svcancrf_settings*
attribute), 199

iso9141_kwp_settings_3
(*ics.structures.s_cyan_settings.s_cyan_settings*
attribute), 117

iso9141_kwp_settings_3
(*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*
attribute), 124

iso9141_kwp_settings_3
(*ics.structures.s_fire3_settings.s_fire3_settings*
attribute), 128

iso9141_kwp_settings_3
(*ics.structures.s_fire_settings.s_fire_settings*
attribute), 131

iso9141_kwp_settings_3
(*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
attribute), 134

iso9141_kwp_settings_4
(*ics.structures.s_cyan_settings.s_cyan_settings*
attribute), 118

iso9141_kwp_settings_4
(*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*
attribute), 124

iso9141_kwp_settings_4
(*ics.structures.s_fire3_settings.s_fire3_settings*
attribute), 128

iso9141_kwp_settings_4
(*ics.structures.s_fire_settings.s_fire_settings*
attribute), 131

iso9141_kwp_settings_4
(*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
attribute), 134

iso9141_kwp_settings_5
(*ics.structures.s_fire3_settings.s_fire3_settings*
attribute), 128

iso9141_kwp_settings_6
(*ics.structures.s_fire3_settings.s_fire3_settings*
attribute), 128

iso_9141_kwp_enable_reserved
(*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*
attribute), 138

iso_9141_kwp_enable_reserved
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings*
attribute), 173

iso_9141_kwp_enable_reserved
(*ics.structures.srad_gigalog_settings.srad_gigalog_settings*
attribute), 176

iso_9141_kwp_enable_reserved
(*ics.structures.srad_gigastar_settings.srad_gigastar_settings*
attribute), 178

iso_9141_kwp_enable_reserved
(*ics.structures.srad_star2_settings.srad_star2_settings*
attribute), 185

iso_9141_kwp_enable_reserved
(*ics.structures.svcanc4_settings.svcanc4_settings*
attribute), 198

iso_msg_termination
(*ics.structures.s_ether_badge_settings.s_ether_badge_settings*
attribute), 121

iso_msg_termination
(*ics.structures.s_fire_settings.s_fire_settings*
attribute), 131

iso_msg_termination
(*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
attribute), 134

iso_msg_termination
(*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*
attribute), 138

iso_msg_termination
(*ics.structures.s_pendant_settings.s_pendant_settings*
attribute), 139

iso_msg_termination
(*ics.structures.s_structures.secu_settings.secu_settings*
attribute), 159

iso_msg_termination
(*ics.structures.sievb_settings.sievb_settings*
attribute), 162

iso_msg_termination
(*ics.structures.srad_epsilon_settings.srad_epsilon_settings*
attribute), 170

iso_msg_termination
(*ics.structures.srad_jupiter_settings.srad_jupiter_settings*
attribute), 181

iso_msg_termination
(*ics.structures.srad_pluto_settings.srad_pluto_settings*
attribute), 184

iso_msg_termination
(*ics.structures.svcanc4_ind_settings.svcanc4_ind_settings*
attribute), 197

iso_msg_termination
(*ics.structures.svcancrf_settings.svcancrf_settings*
attribute), 199

iso_msg_termination_1 (<i>ics.structures.s_cyan_settings.s_cyan_settings attribute</i>), 118	iso_msg_termination_2 (<i>ics.structures.s_pendant_settings.s_pendant_settings attribute</i>), 140
iso_msg_termination_1 (<i>ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute</i>), 124	iso_msg_termination_2 (<i>ics.structures.s_red2_settings.s_red2_settings attribute</i>), 153
iso_msg_termination_1 (<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 128	iso_msg_termination_2 (<i>ics.structures.secu_settings.secu_settings attribute</i>), 159
iso_msg_termination_1 (<i>ics.structures.s_red2_settings.s_red2_settings attribute</i>), 153	iso_msg_termination_2 (<i>ics.structures.sievb_settings.sievb_settings attribute</i>), 162
iso_msg_termination_1 (<i>ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute</i>), 164	iso_msg_termination_2 (<i>ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute</i>), 165
iso_msg_termination_1 (<i>ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute</i>), 165	iso_msg_termination_2 (<i>ics.structures.svcnrf_settings.svcnrf_settings attribute</i>), 199
iso_msg_termination_1 (<i>ics.structures.srad_comet_settings.srad_comet_settings attribute</i>), 169	iso_msg_termination_3 (<i>ics.structures.s_cyan_settings.s_cyan_settings attribute</i>), 118
iso_msg_termination_1 (<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute</i>), 173	iso_msg_termination_3 (<i>ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute</i>), 124
iso_msg_termination_1 (<i>ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute</i>), 176	iso_msg_termination_3 (<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 128
iso_msg_termination_1 (<i>ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute</i>), 178	iso_msg_termination_3 (<i>ics.structures.s_fire_settings.s_fire_settings attribute</i>), 131
iso_msg_termination_1 (<i>ics.structures.srad_star2_settings.srad_star2_settings attribute</i>), 185	iso_msg_termination_3 (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute</i>), 134
iso_msg_termination_1 (<i>ics.structures.srada2_b_settings.srada2_b_settings attribute</i>), 188	iso_msg_termination_4 (<i>ics.structures.s_cyan_settings.s_cyan_settings attribute</i>), 118
iso_msg_termination_1 (<i>ics.structures.svcn4_settings.svcn4_settings attribute</i>), 198	iso_msg_termination_4 (<i>ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute</i>), 124
iso_msg_termination_2 (<i>ics.structures.s_cyan_settings.s_cyan_settings attribute</i>), 118	iso_msg_termination_4 (<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 128
iso_msg_termination_2 (<i>ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute</i>), 124	iso_msg_termination_4 (<i>ics.structures.s_fire_settings.s_fire_settings attribute</i>), 131
iso_msg_termination_2 (<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 128	iso_msg_termination_4 (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute</i>), 134
iso_msg_termination_2 (<i>ics.structures.s_fire_settings.s_fire_settings attribute</i>), 131	iso_msg_termination_5 (<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 128
iso_msg_termination_2 (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute</i>), 134	iso_msg_termination_6 (<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 128

iso_tester_pullup_enable
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute*), 134

iso_tester_pullup_enable
 (*ics.structures.s_red2_settings.s_red2_settings attribute*), 154

iso_tester_pullup_enable
 (*ics.structures.sievb_settings.sievb_settings attribute*), 162

iso_tester_pullup_enable
 (*ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute*), 170

iso_tester_pullup_enable
 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute*), 181

iso_tester_pullup_enable
 (*ics.structures.srad_pluto_settings.srad_pluto_settings attribute*), 184

iso_tester_pullup_enable
 (*ics.structures.svcnrf_settings.svcnrf_settings attribute*), 199

IsOpen (*ics.ics.NeoDevice attribute*), 18

iType (*ics.structures.st_api_firmware_info.st_api_firmware_info attribute*), 191

J

j1708_settings
 (class in *ics.structures.j1708_settings*), 112

J1708_SETTINGS_SIZE (in module *ics.ics*), 208

jitter (*ics.structures.s_pluto_vl_policing_entry.s_pluto_vl_policing_entry attribute*), 151

jupiter (*ics.structures.global_settings.global_settings attribute*), 100

JUPITER_PTP_ROLE_DISABLED (in module *ics.ics*), 208

JUPITER_PTP_ROLE_MASTER (in module *ics.ics*), 208

JUPITER_PTP_ROLE_SLAVE (in module *ics.ics*), 208

jupiter_versions (*ics.structures.st_chip_versions.st_chip_versions attribute*), 191

jupiterStatus (*ics.structures.ics_device_status.ics_device_status attribute*), 129

 (attribute), 102

K

k (*ics.structures.iso9141_keyword2000_init_step.iso9141_keyword2000_init_step attribute*), 112

L

l (*ics.structures.iso9141_keyword2000_init_step.iso9141_keyword2000_init_step attribute*), 112

12_addressLookupEntries
 (*ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute*), 150

 12_addressLookupParams
 (*ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute*), 150

 12_ForwardingEntries
 (*ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute*), 150

 12_forwardingParams
 (*ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute*), 150

 12_policing (*ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute*), 150

 learnedEntry (*ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry attribute*), 146

 Time (*ics.structures.start_dhcp_server_command.start_dhcp_server command attribute*), 195

 led_mode (*ics.structures.ethernet_settings.ethernet_settings attribute*), 96

 legacy (*ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings attribute*), 171

 len (*ics.structures.global_settings.global_settings attribute*), 100

 len (*ics.structures.s_extended_data_flash_header.s_extended_data_flash_header attribute*), 100

 len (*ics.structures.uart_port_data.uart_port_data attribute*), 202

 len (*ics.structures.uart_port_port_bytes.uart_port_port_bytes attribute*), 202

 length (*ics.structures.generic_api_data.generic_api_data attribute*), 98

 length (*ics.structures.s_ext_sub_cmd_hdr.s_ext_sub_cmd_hdr attribute*), 122

 lin1 (*ics.structures.s_cyan_settings.s_cyan_settings attribute*), 118

 lin1 (*ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute*), 121

 lin1 (*ics.structures.s_fire3 flexray_settings.s_fire3 flexray_settings attribute*), 125

 lin1 (*ics.structures.s_fire3_settings.s_fire3_settings attribute*), 125

 lin1 (*ics.structures.s_fire_settings.s_fire_settings attribute*), 132

 lin1 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute*), 134

 lin1 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute*), 138

 lin1 (*ics.structures.s_pendant_settings.s_pendant_settings attribute*), 140

 lin1 (*ics.structures.s_red2_settings.s_red2_settings attribute*), 154

 lin1 (*ics.structures.s_red_settings.s_red_settings attribute*), 155

 lin1 (*ics.structures.secu_settings.secu_settings attribute*), 155

```

    tribute), 159
lin1 (ics.structures.sievb_settings.sievb_settings at- lin3 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings
tribute), 162                                         attribute), 125
lin1 (ics.structures.sobd2_lc_settings.sobd2_lc_settings lin3 (ics.structures.s_fire3_settings.s_fire3_settings at-
attribute), 164                                         tribute), 129
lin1 (ics.structures.sobd2_pro_settings.sobd2_pro_setting lin3 (ics.structures.s_fire_settings.s_fire_settings
attribute), 165                                         attribute), 132
lin1 (ics.structures.srad_epsilon_settings.srad_epsilon_setting (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
attribute), 170                                         attribute), 134
lin1 (ics.structures.srad_galaxy_settings.srad_galaxy_setting (ics.structures.s_cyan_settings.s_cyan_settings at-
attribute), 173                                         tribute), 118
lin1 (ics.structures.srad_gigalog_settings.srad_gigalog_setting (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings
attribute), 176                                         attribute), 125
lin1 (ics.structures.srad_gigastar_settings.srad_gigastar_setting (ics.structures.s_fire3_settings.s_fire3_settings at-
attribute), 178                                         tribute), 129
lin1 (ics.structures.srad_jupiter_settings.srad_jupiter_setting (ics.structures.s_fire_settings.s_fire_settings
attribute), 181                                         attribute), 132
lin1 (ics.structures.srad_pluto_settings.srad_pluto_setting (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
attribute), 184                                         attribute), 134
lin1 (ics.structures.srad_star2_settings.srad_star2_setting (ics.structures.s_cyan_settings.s_cyan_settings at-
attribute), 185                                         tribute), 118
lin1 (ics.structures.srada2_b_settings.srada2_b_settings lin5 (ics.structures.s_fire3_settings.s_fire3_settings at-
attribute), 188                                         tribute), 129
lin1 (ics.structures.svcan4_ind_settings.svcan4_ind_setting (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
attribute), 197                                         attribute), 134
lin1 (ics.structures.svcan4_settings.svcan4_settings at- lin6 (ics.structures.s_cyan_settings.s_cyan_settings at-
tribute), 198                                         tribute), 118
lin1 (ics.structures.svcanrf_settings.svcanrf_settings lin6 (ics.structures.s_fire3_settings.s_fire3_settings at-
attribute), 199                                         tribute), 129
lin2 (ics.structures.s_cyan_settings.s_cyan_settings at- lin7 (ics.structures.s_fire3_settings.s_fire3_settings at-
tribute), 118                                         tribute), 129
lin2 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_setting (ics.structures.s_fire3_settings.s_fire3_settings at-
attribute), 125                                         tribute), 129
lin2 (ics.structures.s_fire3_settings.s_fire3_settings at- lin_settings (class in ics.structures.lin_settings),
tribute), 129                                         113
lin2 (ics.structures.s_fire_settings.s_fire_settings LIN_SETTINGS_SIZE (in module ics.ics), 209
attribute), 132                                         link_delay_ns (ics.structures.gptp_status.gptp_status
attribute), 102
lin2 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings link_spd (ics.structures.op_eth_settings.op_eth_settings
attribute), 134                                         attribute), 114
lin2 (ics.structures.s_pendant_settings.s_pendant_settings link_speed (ics.structures.ethernet10_g_settings.ethernet10_g_settings
attribute), 140                                         attribute), 95
lin2 (ics.structures.s_red2_settings.s_red2_settings link_speed (ics.structures.ethernet_settings.ethernet_settings
attribute), 154                                         attribute), 96
lin2 (ics.structures.s_red_settings.s_red_settings link_speed (ics.structures.ethernet_settings2.ethernet_settings2
attribute), 155                                         attribute), 96
lin2 (ics.structures.secu_settings.secu_settings link_status (ics.structures.gptp_status.gptp_status
attribute), 159                                         attribute), 102
lin2 (ics.structures.sievb_settings.sievb_settings linkFullDuplex (ics.structures.ethernet_network_status_t.ethernet_ne
attribute), 162                                         attribute), 95
lin2 (ics.structures.sobd2_pro_settings.sobd2_pro_settings linkMode (ics.structures.ethernet_network_status_t.ethernet_network_st
attribute), 166                                         attribute), 96
lin2 (ics.structures.svcanrf_settings.svcanrf_settings linkMode0 (ics.structures.rad_moon_duo_converter_settings.rad_moon_
attribute), 199                                         attribute), 115
lin3 (ics.structures.s_cyan_settings.s_cyan_settings at-
```

linkMode1 (*ics.structures.rad_moon_duo_converter_settings.rad_matributed_to_converter_settings*
attribute), 115
 linkSpeed (*ics.structures.ethernet_network_status_t.ethernet_networkstatus*), 140
attribute), 96
 linkStatus (*ics.structures.ethernet_network_status_t.ethernet_netwibitrate*), 159
attribute), 96
 LINUX_BOOT_ALLOWED (*in module ics.ics*), 209
 LINUX_CONFIG_PORT_ETH_01 (*in module ics.ics*), 209
 LINUX_CONFIG_PORT_ETH_02 (*in module ics.ics*), 209
 LINUX_CONFIG_PORT_NONE (*in module ics.ics*), 209
 LISTEN_ALL (*in module ics.ics*), 209
 LISTEN_ONLY (*in module ics.ics*), 209
 listentmout (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clocksyncparams_s*
attribute), 143
 load_default_settings () (*in module ics.ics*), 53
 LoadDefaultSettings () (*in module ics.ics*), 25
 local_id (*ics.structures.ethernet10_t1_s_settings.ethernet10_t1_s*
attribute), 95
 local_id_alternate
(ics.structures.ethernet10_t1_s_settings.ethernet10_t1_s_settings) (*ics.structures.secu_settings.secu_settings*
attribute), 95
 logAnnounceInterval
(ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params_s
attribute), 149
 logAnnounceInterval
(ics.structures.srad_gptp_settings.s.srad_gptp_settings_s
attribute), 180
 logger (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*), 170
attribute), 173
 logger (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*), 171
attribute), 176
 logger (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*), 178
attribute), 178
 logger (*ics.structures.srada2_b_settings.srada2_b_settings*), 188
attribute), 188
 logger_settings
(class ics.structures.logger_settings), 113
 LOGGER_SETTINGS_SIZE (*in module ics.ics*), 209
 logPDelayReqInterval
(ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params_s
attribute), 149
 logPDelayReqInterval
(ics.structures.srad_gptp_settings.s.srad_gptp_settings_s
attribute), 180
 logSyncInterval (*ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params_s*
attribute), 149
 logSyncInterval (*ics.structures.srad_gptp_settings.s.srad_gptp_settings_s*
attribute), 180
 LOOPBACK (*in module ics.ics*), 209
 lsftcan (*ics.structures.s_fire_settings.s.fire_settings*
attribute), 132
 lsftcan (*ics.structures.s_fire_vnet_settings.s.fire_vnet_settings*
attribute), 104
 lsftcan (*ics.structures.s_pendant_settings.s.pendant_settings*
attribute), 140
 lsftcan1 (*ics.structures.secu_settings.secu_settings*
attribute), 159
 lsftcan1 (*ics.structures.s_cyan_settings.s.cyan_settings*
attribute), 118
 lsftcan1 (*ics.structures.s_fire3_settings.s.fire3_settings*
attribute), 129
 lsftcan1 (*ics.structures.s_neo_ecu12_settings.s.neo_ecu12_settings*
attribute), 138
 lsftcan1 (*ics.structures.s_vivid_can_settings.s.vivid_can_settings*
attribute), 156
 lsftcan2 (*ics.structures.s_cyan_settings.s.cyan_settings*
attribute), 118
 lsftcan2 (*ics.structures.s_fire3_settings.s.fire3_settings*
attribute), 129
 lsftcan2 (*ics.structures.s_neo_ecu12_settings.s.neo_ecu12_settings*
attribute), 138
 lsftcan2 (*ics.structures.s_pendant_settings.s.pendant_settings*
attribute), 140
 mac_addr1 (*ics.structures.op_eth_settings.op_eth_settings*
attribute), 114
 mac_addr2 (*ics.structures.op_eth_settings.op_eth_settings*
attribute), 114
 mac_general10 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params*
attribute), 145
 mac_general11 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params*
attribute), 145
 mac_general0 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params*
attribute), 146
 mac_fltres1 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params*
attribute), 146
 mac_spoofing_en (*ics.structures.op_eth_settings.op_eth_settings*
attribute), 114
 mac_spoofing_isDstOrSrc
(ics.structures.op_eth_settings.op_eth_settings
attribute), 114
 macaddr (*ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_a*
attribute), 146
 macconfig (*ics.structures.s_pluto_switch_settings.s.s_pluto_switch_sett*
attribute), 150
 managerIndex (*ics.structures.w_bms_manager_reset.w.bms_manager_r*
attribute), 203
 managerIndex (*ics.structures.w_bms_manager_set_lock.w.bms_manager_s*
attribute), 203
 MasterEnable (*ics.structures.timesync_icshardware_settings.timesync_i*
attribute), 201

MasterNetwork (*ics.structures.timesync_icshardware_settings.time_constraint_icshardware_setBadge_settings.s_ether_badge_settings attribute*), 202
MasterResistor (*ics.structures.lin_settings.lin_settings.misc_io_analog_enable attribute*), 121
MasterResistor (*ics.structures.lin_settings.lin_settings.misic_io_analog_enable attribute*), 113
max_burst_count (*ics.structures.ethernet10_t1_s_settings.ethernet10_t1_s_attributes.settings attribute*), 125
max_dyncp (*ics.structures.s_pluto_l2_forwarding_params.s.s_pluto_l2_forwarding_params.fire3_flexray_settings.s_fire3_flexray_settings attribute*), 147
max_num_nodes (*ics.structures.ethernet10_t1_s_settings.ethernet10_t1_s_attributes.settings attribute*), 126
MAX_NUMBYTES_PHYSETTINGS (*in module ics.ics*), 209
MAX_PHY_REG_PKT_ENTRIES (*in module ics.ics*), 209
MAX_PHY_SETTINGS_STRUCT (*in module ics.ics*), 209
MAX_REPORTED VERSIONS (*in module ics.ics*), 209
MAX_VL_FORWARDING_ENTRIES (*in module ics.ics*), 209
MAX_VL_POLICING_ENTRIES (*in module ics.ics*), 209
maxage (*ics.structures.s_pluto_l2_address_lookup_params.s.s_pluto_id2_stale_relook2_pettings.s_red2_settings attribute*), 154
maxage (*ics.structures.s_pluto_mac_config.s.s_pluto_macconfig_attributes.settings attribute*), 148
MaxAllowedClients (*ics.ics.NeoDevice attribute*), 18
maxintegcy (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clocksync_attributes.settings.sievb_settings attribute*), 162
maxlen (*ics.structures.s_pluto_l2_policing.s.s_pluto_l2_policing_attributes.settings attribute*), 147
maxlen (*ics.structures.s_pluto_vl_policing_entry.s.s_pluto_vl_policing_attributes.settings attribute*), 151
maxtranspclk (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clocksync_attributes.settings.sobd2_sim_settings attribute*), 143
MessagePieceID (*ics.ics.SpyMessage attribute*), 18
MessagePieceID (*ics.ics.SpyMessageJ1850 attribute*), 19
MessagePieceID (*ics.structures.ics_spy_message_flex_attributes.settings attribute*), 104
MessagePieceID (*ics.structures.ics_spy_message_long.ics_spy_message_long attribute*), 107
MessagePieceID (*ics.structures.ics_spy_message_mdio.ics_spy_message_mdio_attributes.settings attribute*), 108
MessagePieceID (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb_attributes.settings attribute*), 109
mirr_port (*ics.structures.s_pluto_general_params.s.s_pluto_general_attributes.settings attribute*), 146
mirr_ptacu (*ics.structures.s_pluto_general_params.s.s_pluto_general_attributes.settings.srad_star2_settings.srad_star2_attributes.settings attribute*), 146
misc_io_analog_enable (*ics.structures.s_cyan_settings.s_cyan_settings attribute*), 118
misc_io_analog_enable (*ics.structures.s_cyan_settings.s_cyan_settings attribute*), 119
misc_io_analog_enable (*ics.structures.svcancrf_settings.svcancrf_settings attribute*), 199
misc_io_analog_enable (*ics.structures.svcancrf_settings.svcancrf_settings attribute*), 200

misc_io_initial_ddr
 (*ics.structures.sievb_settings.sievb_settings*
 attribute), 162
 misc_io_initial_ddr
 (*ics.structures.s_cyan_settings.s_cyan_settings*
 attribute), 118
 misc_io_initial_ddr
 (*ics.structures.s_ether_badge_settings.s_ether_badge_settings*
 attribute), 121
 misc_io_initial_ddr
 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*
 attribute), 125
 misc_io_initial_ddr
 (*ics.structures.s_fire3_settings.s_fire3_settings*
 attribute), 129
 misc_io_initial_ddr
 (*ics.structures.s_fire_settings.s_fire_settings*
 attribute), 132
 misc_io_initial_ddr
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
 attribute), 135
 misc_io_initial_ddr
 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*
 attribute), 138
 misc_io_initial_ddr
 (*ics.structures.s_pendant_settings.s_pendant_settings*
 attribute), 140
 misc_io_initial_ddr
 (*ics.structures.s_red2_settings.s_red2_settings*
 attribute), 154
 misc_io_initial_ddr
 (*ics.structures.secu_settings.secu_settings*
 attribute), 159
 misc_io_initial_ddr
 (*ics.structures.sievb_settings.sievb_settings*
 attribute), 163
 misc_io_initial_ddr
 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings*
 attribute), 166
 misc_io_initial_ddr
 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*
 attribute), 173
 misc_io_initial_ddr
 (*ics.structures.srad_star2_settings.srad_star2_settings*
 attribute), 185
 misc_io_initial_ddr
 (*ics.structures.svcanc3_settings.svcanc3_settings*
 attribute), 195
 misc_io_initial_ddr
 (*ics.structures.svcancrf_settings.svcancrf_settings*
 attribute), 199
 misc_io_initial_ddr
 (*ics.structures.s_cyan_settings.s_cyan_settings*
 attribute), 119
 misc_io_initial_latch
 (*ics.structures.s_ether_badge_settings.s_ether_badge_settings*
 attribute), 121
 misc_io_initial_latch
 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*
 attribute), 125
 misc_io_initial_latch
 (*ics.structures.s_fire3_settings.s_fire3_settings*
 attribute), 129
 misc_io_initial_latch
 (*ics.structures.s_fire_settings.s_fire_settings*
 attribute), 132
 misc_io_initial_latch
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
 attribute), 135
 misc_io_initial_latch
 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*
 attribute), 138
 misc_io_initial_latch
 (*ics.structures.s_pendant_settings.s_pendant_settings*
 attribute), 140
 misc_io_initial_latch
 (*ics.structures.s_red2_settings.s_red2_settings*
 attribute), 154
 misc_io_initial_latch
 (*ics.structures.secu_settings.secu_settings*
 attribute), 159
 misc_io_initial_latch
 (*ics.structures.sievb_settings.sievb_settings*
 attribute), 163
 misc_io_initial_latch
 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings*
 attribute), 166
 misc_io_initial_latch
 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*
 attribute), 173
 misc_io_initial_latch
 (*ics.structures.srad_star2_settings.srad_star2_settings*
 attribute), 185
 misc_io_initial_latch
 (*ics.structures.svcanc3_settings.svcanc3_settings*
 attribute), 195
 misc_io_initial_latch
 (*ics.structures.svcancrf_settings.svcancrf_settings*
 attribute), 199
 misc_io_on_report_events
 (*ics.structures.s_cyan_settings.s_cyan_settings*
 attribute), 119
 misc_io_on_report_events
 (*ics.structures.s_ether_badge_settings.s_ether_badge_settings*
 attribute), 121
 misc_io_on_report_events
 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*
 attribute), 125
 misc_io_on_report_events

(*ics.structures.s_fire3_settings.s_fire3_settings_attribute*), 129
misc_io_on_report_events (*ics.structures.s_fire_settings.s_fire_settings_attribute*), 132
misc_io_on_report_events (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings_attribute*), 135
misc_io_on_report_events (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings_attribute*), 136
misc_io_on_report_events (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings_attribute*), 138
misc_io_on_report_events (*ics.structures.s_pendant_settings.s_pendant_settings_attribute*), 140
misc_io_on_report_events (*ics.structures.s_red2_settings.s_red2_settings_attribute*), 154
misc_io_on_report_events (*ics.structures.secu_settings.secu_settings_attribute*), 159
misc_io_on_report_events (*ics.structures.sievb_settings.sievb_settings_attribute*), 163
misc_io_on_report_events (*ics.structures.sobd2_lc_settings.sobd2_lc_settings_attribute*), 164
misc_io_on_report_events (*ics.structures.sobd2_sim_settings.sobd2_sim_settings_attribute*), 167
misc_io_on_report_events (*ics.structures.srad_epsilon_settings.srad_epsilon_settings_attribute*), 170
misc_io_on_report_events (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 173
misc_io_on_report_events (*ics.structures.srad_star2_settings.srad_star2_settings_attribute*), 186
misc_io_on_report_events (*ics.structures.svcn3_settings.svcn3_settings_attribute*), 195
misc_io_on_report_events (*ics.structures.svcnrf_settings.svcnrf_settings_attribute*), 199
misc_io_report_period (*ics.structures.s_cyan_settings.s_cyan_settings_attribute*), 119
misc_io_report_period (*ics.structures.s_ether_badge_settings.s_ether_badge_settings_attribute*), 121
misc_io_report_period
 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings_attribute*), 125
 misc_io_report_period
 (*ics.structures.s_fire3_settings.s_fire3_settings_attribute*), 129
 misc_io_report_period
 (*ics.structures.s_fire_settings.s_fire_settings_attribute*), 132
 misc_io_report_period
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings_attribute*), 135
 misc_io_report_period
 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings_attribute*), 138
 misc_io_report_period
 (*ics.structures.s_pendant_settings.s_pendant_settings_attribute*), 140
 misc_io_report_period
 (*ics.structures.s_red2_settings.s_red2_settings_attribute*), 154
 misc_io_report_period
 (*ics.structures.secu_settings.secu_settings_attribute*), 159
 misc_io_report_period
 (*ics.structures.sievb_settings.sievb_settings_attribute*), 163
 misc_io_report_period
 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings_attribute*), 167
 misc_io_report_period
 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 173
 misc_io_report_period
 (*ics.structures.srad_star2_settings.srad_star2_settings_attribute*), 186
 misc_io_report_period
 (*ics.structures.svcn3_settings.svcn3_settings_attribute*), 195
 misc_io_report_period
 (*ics.structures.svcnrf_settings.svcnrf_settings_attribute*), 200
 MiscData (*ics.ics.SpyMessage attribute*), 18
 MiscData (*ics.ics.SpyMessageJ1850 attribute*), 19
 MiscData (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_attribute*), 104
 MiscData (*ics.structures.ics_spy_message_long.ics_spy_message_long_attribute*), 107
 MiscData (*ics.structures.ics_spy_message_mdio.ics_spy_message_mdio_attribute*), 108
 MiscData (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb_attribute*), 109
 MiscDataMask (*ics.structures.spy_filter_long.spy_filter_long_attribute*), 168
 MiscDataMask (*ics.structures.spy_filter_long.spy_filter_long_attribute*)

attribute), 168

`mod_id(ics.structures.serdesgen_settings.serdesgen_settings attribute), 161`

`Mode(ics.structures.can_settings.can_settings attribute), 90`

`Mode(ics.structures.lin_settings.lin_settings attribute), 113`

`mode(ics.structures.s_pluto_custom_params.s.s_pluto_custom_params attribute), 145`

`mode(ics.structures.serdescam_settings.serdescam_setting NEO_CFG_MPIC_HS_CAN_CNF1 (in module ics.ics), attribute), 161`

`mode(ics.structures.serdespoc_settings.serdespoc_settings NEO_CFG_MPIC_HS_CAN_CNF2 (in module ics.ics), attribute), 161`

`Mode(ics.structures.swcan_settings.swcan_settings attribute), 200`

`ms_offset_ns(ics.structures.gptp_status.gptp_status attribute), 102`

N

`Name(ics.ics.NeoDevice attribute), 18`

`Nameless11656(ics.structures.s_pluto_vl_lookup_entry_s.s_pluto_iq9_ip8d8k9p_entry_s attribute), 151`

`Nameless14996(ics.structures.op_eth_settings.op_eth_settings attribute), 114`

`Nameless18511(ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 107`

`Nameless18906(ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute), 108`

`Nameless19471(ics.structures.op_eth_general_settings.op_eth_general_settings attribute), 113`

`Nameless2284(ics.structures.uart_settings.uart_settings attribute), 202`

`Nameless23244(ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute), 141`

`Nameless43713(ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 111`

`Nameless45381(ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute), 108`

`Nameless5269(ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute), 141`

`Nameless54558(ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 109`

`Nameless59426(ics.structures.global_settings.global_settings attribute), 99`

`Nameless61974(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 192`

`Nameless9252(ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 193`

`Nameless9872(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 104`

`Nameless9992(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 104`

`nanoseconds(ics.structures.timestamp_timestamp_attribute), 201`

`neighborPropDelay(ics.structures.s_jupiter_ptp_params.s.s_jupiter_ptp_params_s attribute), 137`

`neighborPropDelayThresh(ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params_s attribute), 149`

`neighborPropDelayThresh(ics.structures.srad_gptp_settings.s.srad_gptp_settings_s attribute), 180`

`NEO_CFG_MPIC_HS_CAN_CNF1 (in module ics.ics), 211`

`NEO_CFG_MPIC_HS_CAN_CNF2 (in module ics.ics), 211`

`NEO_CFG_MPIC_HS_CAN_CNF3 (in module ics.ics), 211`

`NEO_CFG_MPIC_HS_CAN_MODE (in module ics.ics), 211`

`NEO_CFG_MPIC_LSFT_CAN_CNF1 (in module ics.ics), 211`

`NEO_CFG_MPIC_MS_CAN_CNF1 (in module ics.ics), 211`

`NEO_CFG_MPIC_MS_CAN_CNF2 (in module ics.ics), 211`

`NEO_CFG_MPIC_MS_CAN_CNF3 (in module ics.ics), 211`

`NEO_CFG_MPIC_SW_CAN_CNF1 (in module ics.ics), 212`

`NEO_CFG_MPIC_SW_CAN_CNF2 (in module ics.ics), 212`

`NEO_CFG_MPIC_SW_CAN_CNF3 (in module ics.ics), 212`

`NeoDevice (class in ics.ics), 18`

`NEODEVICE_ANONYTON (in module ics.ics), 209`

`NEODEVICE_ANY_PLASMA (in module ics.ics), 209`

`NEODEVICE_BLUE (in module ics.ics), 209`

`NEODEVICE_CMPROBE (in module ics.ics), 209`

`NEODEVICE_G3b_OBD (in module ics.ics), 209`

`NEODEVICE_DONT_REUSE0 (in module ics.ics), 209`

`NEODEVICE_DONT_REUSE1 (in module ics.ics), 209`

`NEODEVICE_DONT_REUSE2 (in module ics.ics), 209`

`NEODEVICE_DONT_REUSE3 (in module ics.ics), 209`

`NEODEVICE_DW_VCAN (in module ics.ics), 209`

`NEODEVICE_ECM_15765 (in module ics.ics), 209`

`NEODEVICE_ECU22 (in module ics.ics), 209`

`NEODEVICE_FCU_AVB (in module ics.ics), 209`

`NEODEVICE_ECUCHIP_UART (in module ics.ics), 209`

`NEODEVICE_FDV (in module ics.ics), 209`

`NEODEVICE_FLEXRAY (in module ics.ics), 209`

`NEODEVICE_Ether_Badge (in module ics.ics), 209`

`NEODEVICE_FIRE (in module ics.ics), 209`

`NEODEVICE_FIRE2 (in module ics.ics), 209`

NEODEVICE_FIRE2_REDLINE (*in module ics.ics*), 209
NEODEVICE_FIRE3 (*in module ics.ics*), 209
NEODEVICE_FIRE3_FLEXRAY (*in module ics.ics*), 210
NEODEVICE_FLEX (*in module ics.ics*), 210
NEODEVICE_GIGASTAR (*in module ics.ics*), 210
NEODEVICE_IEVB (*in module ics.ics*), 210
NEODEVICE_ION (*in module ics.ics*), 210
NEODEVICE_NEOANALOG (*in module ics.ics*), 210
NEODEVICE_NEOECU12 (*in module ics.ics*), 210
NEODEVICE_NEOECUCHIP (*in module ics.ics*), 210
NEODEVICE_NEW_DEVICE_58 (*in module ics.ics*), 210
NEODEVICE_NEW_DEVICE_59 (*in module ics.ics*), 210
NEODEVICE_OBD2_DEV (*in module ics.ics*), 210
NEODEVICE_OBD2_LC (*in module ics.ics*), 210
NEODEVICE_OBD2_PRO (*in module ics.ics*), 210
NEODEVICE_OBD2_SIM (*in module ics.ics*), 210
NEODEVICE_OBD2_SIM_DOIP (*in module ics.ics*), 210
NEODEVICE_PENDANT (*in module ics.ics*), 210
NEODEVICE_PLASMA (*in module ics.ics*), 210
NEODEVICE_RAD_A2B (*in module ics.ics*), 210
NEODEVICE_RAD_BMS (*in module ics.ics*), 210
NEODEVICE_RAD_MOONDUO (*in module ics.ics*), 210
NEODEVICE_RADCOMET (*in module ics.ics*), 210
NEODEVICE_RADEPSILON (*in module ics.ics*), 210
NEODEVICE_RADEPSILON_EXPRESS (*in module ics.ics*), 210
NEODEVICE_RADEPSILON_T (*in module ics.ics*), 210
NEODEVICE_RADGALAXY (*in module ics.ics*), 210
NEODEVICE_RADGIGALOG (*in module ics.ics*), 210
NEODEVICE_RADIO_CANHUB (*in module ics.ics*), 210
NEODEVICE_RADJUPITER (*in module ics.ics*), 210
NEODEVICE_RADMOON2 (*in module ics.ics*), 210
NEODEVICE_RADMOON3 (*in module ics.ics*), 210
NEODEVICE_RADPLUTO (*in module ics.ics*), 210
NEODEVICE_RADPROXIMA (*in module ics.ics*), 210
NEODEVICE_RADSTAR (*in module ics.ics*), 210
NEODEVICE_RADSTAR2 (*in module ics.ics*), 210
NEODEVICE_RADSUPERMOON (*in module ics.ics*), 210
NEODEVICE_RED (*in module ics.ics*), 210
NEODEVICE_RED2 (*in module ics.ics*), 211
NEODEVICE_RED2_OEM (*in module ics.ics*), 211
NEODEVICE_UNKNOWN (*in module ics.ics*), 211
NEODEVICE_VCAN3 (*in module ics.ics*), 211
NEODEVICE_VCAN41 (*in module ics.ics*), 211
NEODEVICE_VCAN42 (*in module ics.ics*), 211
NEODEVICE_VCAN42_EL (*in module ics.ics*), 211
NEODEVICE_VCAN44 (*in module ics.ics*), 211
NEODEVICE_VCAN4_IND (*in module ics.ics*), 211
NEODEVICE_VCANRF (*in module ics.ics*), 211
NEODEVICE_VIVIDCAN (*in module ics.ics*), 211
neoecu12 (*ics.structures.global_settings.global_settings attribute*), 100
neoecu_avb (*ics.structures.global_settings.global_settings attribute*), 100
neoecu_avb_versions
 (*ics.structures.st_chip_versions.st_chip_versions attribute*), 191
neoMostGateway (*ics.structures.s_fire_settings.s_fire_settings attribute*), 132
neoMostGateway (*ics.structures.s_fire_vnet_settings.s_fire_vnet_setting attribute*), 135
neoobd2_sim (*ics.structures.global_settings.global_settings attribute*), 100
NEOVI6_VCAN_TIMESTAMP_1 (*in module ics.ics*), 211
NEOVI6_VCAN_TIMESTAMP_2 (*in module ics.ics*), 211
NEOVI3G_MAX_SETTINGS_SIZE (*in module ics.ics*), 211
NEOVI_COMMTYPE_FIRE_USB (*in module ics.ics*), 211
NEOVI_COMMTYPE_RS232 (*in module ics.ics*), 211
NEOVI_COMMTYPE_TCPIP (*in module ics.ics*), 211
NEOVI_COMMTYPE_USB_BULK (*in module ics.ics*), 211
NEOVI_RED_TIMESTAMP_1_10NS (*in module ics.ics*), 211
NEOVI_RED_TIMESTAMP_1_25NS (*in module ics.ics*), 211
NEOVI_RED_TIMESTAMP_2_10NS (*in module ics.ics*), 211
NEOVI_RED_TIMESTAMP_2_25NS (*in module ics.ics*), 211
NEOVI_TIMESTAMP_1 (*in module ics.ics*), 211
NEOVI_TIMESTAMP_2 (*in module ics.ics*), 211
NEOVIPRO_VCAN_TIMESTAMP_1 (*in module ics.ics*), 211
NEOVIPRO_VCAN_TIMESTAMP_2 (*in module ics.ics*), 211
netId (*ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway attribute*), 139
NETID_3G_APP_SIGNAL_STATUS (*in module ics.ics*), 212
NETID_3G_FB_STATUS (*in module ics.ics*), 212
NETID_3G_LOGGING_OVERFLOW (*in module ics.ics*), 212
NETID_3G_READ_DATALINK_CM_RX_MSG (*in module ics.ics*), 212
NETID_3G_READ_DATALINK_CM_TX_MSG (*in module ics.ics*), 212
NETID_3G_READ_SETTINGS_EX (*in module ics.ics*), 212
NETID_3G_RESET_STATUS (*in module ics.ics*), 212

NETID_A2B_01 (*in module ics.ics*), 212
 NETID_A2B_02 (*in module ics.ics*), 212
 NETID_AUTOSAR (*in module ics.ics*), 212
 NETID_AUX (*in module ics.ics*), 212
 NETID_CAN_SWITCH (*in module ics.ics*), 212
 NETID_CGI (*in module ics.ics*), 212
 NETID_DATA_TO_HOST (*in module ics.ics*), 212
 NETID_DEVICE (*in module ics.ics*), 212
 NETID_DEVICE_STATUS (*in module ics.ics*), 212
 NETID_DWCAN_09 (*in module ics.ics*), 212
 NETID_DWCAN_10 (*in module ics.ics*), 212
 NETID_DWCAN_11 (*in module ics.ics*), 212
 NETID_DWCAN_12 (*in module ics.ics*), 212
 NETID_DWCAN_13 (*in module ics.ics*), 212
 NETID_DWCAN_14 (*in module ics.ics*), 212
 NETID_DWCAN_15 (*in module ics.ics*), 212
 NETID_DWCAN_16 (*in module ics.ics*), 212
 NETID_ETHERNET (*in module ics.ics*), 212
 NETID_ETHERNET2 (*in module ics.ics*), 212
 NETID_ETHERNET3 (*in module ics.ics*), 212
 NETID_ETHERNET_DAQ (*in module ics.ics*), 212
 NETID_ETHERNET_TX_WRAP (*in module ics.ics*), 212
 NETID_FLEXRAY (*in module ics.ics*), 212
 NETID_FLEXRAY1A (*in module ics.ics*), 212
 NETID_FLEXRAY1B (*in module ics.ics*), 212
 NETID_FLEXRAY2 (*in module ics.ics*), 212
 NETID_FLEXRAY2A (*in module ics.ics*), 213
 NETID_FLEXRAY2B (*in module ics.ics*), 213
 NETID_FORDSCP (*in module ics.ics*), 213
 NETID_FORWARDED_MESSAGE (*in module ics.ics*), 213
 NETID_GMFSA (*in module ics.ics*), 213
 NETID_HSCAN (*in module ics.ics*), 213
 NETID_HSCAN2 (*in module ics.ics*), 213
 NETID_HSCAN3 (*in module ics.ics*), 213
 NETID_HSCAN4 (*in module ics.ics*), 213
 NETID_HSCAN5 (*in module ics.ics*), 213
 NETID_HSCAN6 (*in module ics.ics*), 213
 NETID_HSCAN7 (*in module ics.ics*), 213
 NETID_HW_COM_LATENCY_TEST (*in module ics.ics*), 213
 NETID_I2C1 (*in module ics.ics*), 213
 NETID_I2C2 (*in module ics.ics*), 213
 NETID_I2C3 (*in module ics.ics*), 213
 NETID_I2C4 (*in module ics.ics*), 213
 NETID_INVALID (*in module ics.ics*), 213
 NETID_ISM_LOGGER (*in module ics.ics*), 213
 NETID_ISO (*in module ics.ics*), 213
 NETID_ISO14230 (*in module ics.ics*), 213
 NETID_ISO2 (*in module ics.ics*), 213
 NETID_ISO3 (*in module ics.ics*), 213
 NETID_ISO4 (*in module ics.ics*), 213
 NETID_ISOPIC (*in module ics.ics*), 213
 NETID_J1708 (*in module ics.ics*), 213
 NETID_JVPW (*in module ics.ics*), 213
 NETID_LIN (*in module ics.ics*), 213
 NETID_LIN2 (*in module ics.ics*), 213
 NETID_LIN3 (*in module ics.ics*), 213
 NETID_LIN4 (*in module ics.ics*), 213
 NETID_LIN5 (*in module ics.ics*), 213
 NETID_LIN6 (*in module ics.ics*), 213
 NETID_LIN_07 (*in module ics.ics*), 213
 NETID_LIN_08 (*in module ics.ics*), 213
 NETID_LSFTCAN (*in module ics.ics*), 213
 NETID_LSFTCAN2 (*in module ics.ics*), 214
 NETID_MAIN51 (*in module ics.ics*), 214
 NETID_MAX (*in module ics.ics*), 214
 NETID_MDIO_01 (*in module ics.ics*), 214
 NETID_MDIO_02 (*in module ics.ics*), 214
 NETID_MDIO_03 (*in module ics.ics*), 214
 NETID_MDIO_04 (*in module ics.ics*), 214
 NETID_MDIO_05 (*in module ics.ics*), 214
 NETID_MDIO_06 (*in module ics.ics*), 214
 NETID_MDIO_07 (*in module ics.ics*), 214
 NETID_MDIO_08 (*in module ics.ics*), 214
 NETID_MOST (*in module ics.ics*), 214
 NETID_MOST150 (*in module ics.ics*), 214
 NETID_MOST25 (*in module ics.ics*), 214
 NETID_MOST50 (*in module ics.ics*), 214
 NETID_MSCAN (*in module ics.ics*), 214
 NETID_OP_ETHERNET1 (*in module ics.ics*), 214
 NETID_OP_ETHERNET10 (*in module ics.ics*), 214
 NETID_OP_ETHERNET11 (*in module ics.ics*), 214
 NETID_OP_ETHERNET12 (*in module ics.ics*), 214
 NETID_OP_ETHERNET2 (*in module ics.ics*), 214
 NETID_OP_ETHERNET3 (*in module ics.ics*), 214
 NETID_OP_ETHERNET4 (*in module ics.ics*), 214
 NETID_OP_ETHERNET5 (*in module ics.ics*), 214
 NETID_OP_ETHERNET6 (*in module ics.ics*), 214
 NETID_OP_ETHERNET7 (*in module ics.ics*), 214
 NETID_OP_ETHERNET8 (*in module ics.ics*), 214
 NETID_OP_ETHERNET9 (*in module ics.ics*), 214
 NETID_RED (*in module ics.ics*), 214
 NETID_RED_APP_ERROR (*in module ics.ics*), 214
 NETID_RED_VBAT (*in module ics.ics*), 214
 NETID_RS232 (*in module ics.ics*), 214
 NETID_SCI (*in module ics.ics*), 214
 NETID_SPI1 (*in module ics.ics*), 214
 NETID_SPI2 (*in module ics.ics*), 214
 NETID_SWCAN (*in module ics.ics*), 214
 NETID_SWCAN2 (*in module ics.ics*), 215
 NETID_TCP (*in module ics.ics*), 215
 NETID_TEXTAPI_TO_HOST (*in module ics.ics*), 215
 NETID_UART (*in module ics.ics*), 215
 NETID_UART2 (*in module ics.ics*), 215
 NETID_UART3 (*in module ics.ics*), 215
 NETID_UART4 (*in module ics.ics*), 215
 NETID_UDP (*in module ics.ics*), 215

NETID_WBMS (*in module ics.ics*), 215
NETID_WBMS2 (*in module ics.ics*), 215
netmask (*ics.structures.ethernet10_g_settings.ethernet10_g_setting*~~s~~*attribute*), 160
 attribute, 95
netmask (*ics.structures.ethernet_settings2.ethernet_settings2*~~s~~*attribute*), 160
network_data_capture_config
 (*ics.structures.s_wil_connection_settings.s_wil_connection*~~s~~*settings*~~s~~*attribute*), 157
network_enabled_on_boot
 (*ics.structures.s_cm_probe_settings.s_cm_probe_settings*~~s~~*attribute*), 116
network_enabled_on_boot
 (*ics.structures.s_cyan_settings.s_cyan_settings*~~s~~*attribute*), 119
network_enabled_on_boot
 (*ics.structures.s_ether_badge_settings.s_ether_badge_settings*~~s~~*attribute*), 121
network_enabled_on_boot
 (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings*~~s~~*attribute*), 125
network_enabled_on_boot
 (*ics.structures.s_fire3_settings.s_fire3_settings*~~s~~*attribute*), 130
network_enabled_on_boot
 (*ics.structures.s_fire_settings.s_fire_settings*~~s~~*attribute*), 132
network_enabled_on_boot
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*~~s~~*attribute*), 135
network_enabled_on_boot
 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*~~s~~*attribute*), 136
network_enabled_on_boot
 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*~~s~~*attribute*), 138
network_enabled_on_boot
 (*ics.structures.s_pendant_settings.s_pendant_settings*~~s~~*attribute*), 140
network_enabled_on_boot
 (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo*~~s~~*settings*~~s~~*attribute*), 152
network_enabled_on_boot
 (*ics.structures.s_red2_settings.s_red2_settings*~~s~~*attribute*), 154
network_enabled_on_boot
 (*ics.structures.s_vivid_can_settings.s_vivid_can_settings*~~s~~*attribute*), 156
network_enabled_on_boot
 (*ics.structures.scan_hub_settings.scan_hub_settings*~~s~~*attribute*), 157
network_enabled_on_boot
 (*ics.structures.secu_avb_settings.secu_avb_settings*~~s~~*attribute*), 158
network_enabled_on_boot
 (*ics.structures.secu_settings.secu_settings*~~s~~*attribute*), 160
network_enabled_on_boot
 (*ics.structures.sobd2_lc_settings.sobd2_lc_settings*~~s~~*attribute*), 164
network_enabled_on_boot
 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings*~~s~~*attribute*), 166
network_enabled_on_boot
 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings*~~s~~*attribute*), 167
network_enabled_on_boot
 (*ics.structures.srad_comet_settings.srad_comet_settings*~~s~~*attribute*), 169
network_enabled_on_boot
 (*ics.structures.srad_epsilon_settings.srad_epsilon_settings*~~s~~*attribute*), 170
network_enabled_on_boot
 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*~~s~~*attribute*), 173
network_enabled_on_boot
 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*~~s~~*attribute*), 176
network_enabled_on_boot
 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*~~s~~*attribute*), 178
network_enabled_on_boot
 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings*~~s~~*attribute*), 181
network_enabled_on_boot
 (*ics.structures.srad_moon2_settings.srad_moon2_settings*~~s~~*attribute*), 182
network_enabled_on_boot
 (*ics.structures.srad_moon3_settings.srad_moon3_settings*~~s~~*attribute*), 183
network_enabled_on_boot
 (*ics.structures.srad_pluto_settings.srad_pluto_settings*~~s~~*attribute*), 184
network_enabled_on_boot
 (*ics.structures.srad_star2_settings.srad_star2_settings*~~s~~*attribute*), 186
network_enabled_on_boot
 (*ics.structures.srad_super_moon_settings.srad_super_moon_settings*~~s~~*attribute*), 187
network_enabled_on_boot
 (*ics.structures.srada2_b_settings.srada2_b_settings*~~s~~*attribute*), 188

network_enabled_on_boot
(ics.structures.srdbms_settings.srdbms_settings attribute), 189

network_enabled_on_boot
(ics.structures.svcn3_settings.svcn3_settings attribute), 195

network_enabled_on_boot
(ics.structures.svcn412_settings.svcn412_settings attribute), 196

network_enabled_on_boot
(ics.structures.svcn4_ind_settings.svcn4_ind_settings attribute), 197

network_enabled_on_boot
(ics.structures.svcn4_settings.svcn4_settings attribute), 198

network_enabled_on_boot
(ics.structures.svcnrf_settings.svcnrf_settings attribute), 200

network_enables (*ics.structures.s_cm_probe_settings.s_cm_probe_settings attribute*)
(ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 116

network_enables (*ics.structures.s_cyan_settings.s_cyan_settings attribute*)
(ics.structures.srad_moon2_settings.srad_moon2_settings attribute), 119

network_enables (*ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute*)
(ics.structures.srad_moon3_settings.srad_moon3_settings attribute), 121

network_enables (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute*)
(ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 125

network_enables (*ics.structures.s_fire3_settings.s_fire3_settings attribute*)
(ics.structures.srad_star2_settings.srad_star2_settings attribute), 130

network_enables (*ics.structures.s_fire_settings.s_fire_settings attribute*)
(ics.structures.srad_super_moon_settings.srad_super_moon_settings attribute), 132

network_enables (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute*)
(ics.structures.srada2_b_settings.srada2_b_settings attribute), 135

network_enables (*ics.structures.s_flex_vnet_settings.s_flex_vnet_settings attribute*)
(ics.structures.srdbms_settings.srdbms_settings attribute), 137

network_enables (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute*)
(ics.structures.svcn3_settings.svcn3_settings attribute), 138

network_enables (*ics.structures.s_pendant_settings.s_pendant_settings attribute*)
(ics.structures.svcn412_settings.svcn412_settings attribute), 140

network_enables (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings attribute*)
(ics.structures.svcn4_ind_settings.svcn4_ind_settings attribute), 152

network_enables (*ics.structures.s_red2_settings.s_red2_settings attribute*)
(ics.structures.svcn4_settings.svcn4_settings attribute), 154

network_enables (*ics.structures.s_text_api_settings.s_text_api_settings attribute*)
(ics.structures.svcnrf_settings.svcnrf_settings attribute), 156

network_enables (*ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute*)
(ics.structures.svcn4_settings.svcn4_settings attribute), 156

network_enables (*ics.structures.scan_hub_settings.scan_hub_settings attribute*)
(ics.structures.s_cyan_settings.s_cyan_settings attribute), 119

network_enables_2
(ics.structures.s_secu_avb_settings.secavb_attributes.s_secu_avb_attributes attribute), 158

network_enables_2
(ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 121

network_enables_2
(ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings attribute), 125

network_enables_2
(ics.structures.s_seebv_settings.seebv_attributes.s_seebv_attributes attribute), 160

(*ics.structures.s_fire3_settings.s_fire3_settings
attribute*), 130

network_enables_2
(*ics.structures.s_fire_settings.s_fire_settings
attribute*), 132

network_enables_2
(*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
attribute*), 135

network_enables_2
(*ics.structures.s_pendant_settings.s_pendant_settings
attribute*), 140

network_enables_2
(*ics.structures.secu_settings.secu_settings
attribute*), 160

network_enables_2
(*ics.structures.sievb_settings.sievb_settings
attribute*), 163

network_enables_2
(*ics.structures.srad_epsilon_settings.srad_epsilon_settings
attribute*), 170

network_enables_2
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings
attribute*), 173

network_enables_2
(*ics.structures.srad_gigalog_settings.srad_gigalog_settings
attribute*), 176

network_enables_2
(*ics.structures.srad_gigastar_settings.srad_gigastar_setting
attribute*), 178

network_enables_2
(*ics.structures.srad_moon2_settings.srad_moon2_settings
attribute*), 182

network_enables_2
(*ics.structures.srad_moon3_settings.srad_moon3_settings
attribute*), 183

network_enables_2
(*ics.structures.srad_pluto_settings.srad_pluto_settings
attribute*), 184

network_enables_2
(*ics.structures.srad_star2_settings.srad_star2_settings
attribute*), 186

network_enables_2
(*ics.structures.srad_super_moon_settings.srad_super_moon_setti
ngs*), 187

network_enables_2
(*ics.structures.sradbms_settings.sradbms_settings
attribute*), 189

network_enables_2
(*ics.structures.svcn4_settings.svcn4_settings
attribute*), 198

network_enables_2
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings
attribute*), 173

network_enables_2
(*ics.structures.srad_gigalog_settings.srad_gigalog_settings
attribute*), 176

network_enables_2
(*ics.structures.srad_gigastar_settings.srad_gigastar_settings
attribute*), 179

network_enables_2
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings
attribute*), 173

network_enables_3
(*ics.structures.s_cyan_settings.s_cyan_settings
attribute*), 119

network_enables_3
(*ics.structures.s_ether_badge_settings.s_ether_badge_settings
attribute*), 121

network_enables_3
(*ics.structures.srad_epsilon_settings.srad_epsilon_settings
attribute*), 170

network_enables_3
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings
attribute*), 173

network_enables_3
(*ics.structures.srad_gigalog_settings.srad_gigalog_settings
attribute*), 176

network_enables_3
(*ics.structures.srad_gigastar_settings.srad_gigastar_settings
attribute*), 178

network_enables_3
(*ics.structures.srad_jupiter_settings.srad_jupiter_settings
attribute*), 181

network_enables_3
(*ics.structures.srad_moon2_settings.srad_moon2_settings
attribute*), 182

network_enables_3
(*ics.structures.srad_moon3_settings.srad_moon3_settings
attribute*), 183

network_enables_3
(*ics.structures.srad_pluto_settings.srad_pluto_settings
attribute*), 184

network_enables_3
(*ics.structures.srad_star2_settings.srad_star2_settings
attribute*), 186

network_enables_3
(*ics.structures.srad_super_moon_settings.srad_super_moon_setti
ngs*), 187

network_enables_3
(*ics.structures.sradbms_settings.sradbms_settings
attribute*), 189

network_enables_3
(*ics.structures.svcn4_settings.svcn4_settings
attribute*), 198

network_enables_4
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings
attribute*), 173

network_enables_4
(*ics.structures.srad_gigalog_settings.srad_gigalog_settings
attribute*), 176

network_enables_4
(*ics.structures.srad_gigastar_settings.srad_gigastar_settings
attribute*), 179

network_enables_4

(*ics.structures.sradbms_settings.sradbms_settings*.NetworkID (*ics.structures.ics_spy_message_long.ics_spy_message_long*.attribute), 189
 network_enables_5 NetworkID (*ics.structures.ics_spy_message_mdio.ics_spy_message_mdio*.attribute), 107
attribute), 108
attribute), 169 NetworkID (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb*.attribute), 109
 network_enables_5 NetworkID (*ics.structures.srad_comet_settings.srad_comet_settings*.attribute), 108
attribute), 173 NetworkID (*ics.structures.spy_filter_long.spy_filter_long*.attribute), 168
 network_enables_5 networkId (*ics.structures.start_dhcp_server_command.start_dhcp_server*.attribute), 195
attribute), 176 networkId (*ics.structures.stop_dhcp_server_command.stop_dhcp_server*.attribute), 195
 network_enables_5 networkId2 (*ics.ics.SpyMessage*.attribute), 18
attribute), 179 NetworkID2 (*ics.ics.SpyMessageJ1850*.attribute), 19
 network_enables_5 NetworkID2 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray*.attribute), 104
attribute), 182 NetworkID2 (*ics.structures.ics_spy_message_long.ics_spy_message_long*.attribute), 107
 network_enables_5 networkID2 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*.attribute), 109
attribute), 176 networkTerminationDWCAN01
 network_enables_5 networkTerminationDWCAN02
attribute), 179 (*ics.structures.device_feature.device_feature*.attribute), 91
attribute), 187 networkTerminationDWCAN02
 network_enables_5 networkTerminationDWCAN03
attribute), 188 (*ics.structures.device_feature.device_feature*.attribute), 91
attribute), 189 networkTerminationDWCAN04
 networkDWCAN01 (*ics.structures.device_feature.device_feature*.attribute), 91 (*ics.structures.device_feature.device_feature*.attribute), 91
 networkDWCAN02 (*ics.structures.device_feature.device_feature*.attribute), 91 networkTerminationDWCAN05
attribute), 91 (*ics.structures.device_feature.device_feature*.attribute), 92
 networkDWCAN03 (*ics.structures.device_feature.device_feature*.attribute), 91 networkTerminationDWCAN06
attribute), 91 (*ics.structures.device_feature.device_feature*.attribute), 92
 networkDWCAN04 (*ics.structures.device_feature.device_feature*.attribute), 91 networkTerminationDWCAN07
attribute), 91 (*ics.structures.device_feature.device_feature*.attribute), 92
 networkDWCAN05 (*ics.structures.device_feature.device_feature*.attribute), 91 networkTerminationDWCAN07
attribute), 91 (*ics.structures.device_feature.device_feature*.attribute), 92
 networkDWCAN06 (*ics.structures.device_feature.device_feature*.attribute), 91 networkTerminationDWCAN08
attribute), 91 (*ics.structures.device_feature.device_feature*.attribute), 92
 networkDWCAN07 (*ics.structures.device_feature.device_feature*.attribute), 91 (*ics.structures.device_feature.device_feature*.attribute), 92
 networkDWCAN08 (*ics.structures.device_feature.device_feature*.attribute), 91 no_enf_hostprt (*ics.structures.s_pluto_l2_address_lookup_params_s*.attribute), 147
attribute), 91 NodeID (*ics.ics.SpyMessage*.attribute), 18
 NetworkID (*ics.ics.SpyMessage*.attribute), 18 no_mgmt_learn (*ics.structures.s_pluto_l2_address_lookup_params_s*.attribute), 147
 NetworkID (*ics.ics.SpyMessageJ1850*.attribute), 19 NodeID (*ics.ics.SpyMessageJ1850*.attribute), 18
 networkId (*ics.structures.ethernet_network_status_t.ethernet_networkstatus*.attribute), 147 NodeID (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray*.attribute), 19
attribute), 96 NodeID (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray*.attribute), 104

attribute), 105
 NodeID (*ics.structures.ics_spy_message_long.ics_spy_message_long.ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 107
 NodeID (*ics.structures.ics_spy_message_mdio.ics_spy_message_mdio.ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 108
 NodeID (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 110
 NodeID (*ics.structures.spy_filter_long.spy_filter_long attribute*), 168
 nodeType (*ics.structures.a2_b_monitor_settings.a2_b_monitor_settings attribute*), 89
 noExtraDataPtrCleanup (*ics.ics.SpyMessage attribute*), 19
 noExtraDataPtrCleanup (*ics.ics.SpyMessageJ1850 attribute*), 20
 NORMAL (in module *ics.ics*), 215
 NORMAL_MODE (in module *ics.ics*), 215
 null_frame (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 106
 num_bytes (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute*), 111
 num_bytes (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute*), 194
 NUM_DEVICE_FEATURE_BITFIELDS (in module *ics.ics*), 215
 NUM_VALID_DEVICE_FEATURES (*ics.structures.device_feature.device_feature attribute*), 91
 NUM_VALID_DEVICE_FEATURES (in module *ics.ics*), 215
 NumberBytesData (*ics.ics.SpyMessage attribute*), 18
 NumberBytesData (*ics.ics.SpyMessageJ1850 attribute*), 20
 NumberBytesData (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 105
 NumberBytesData (*ics.structures.ics_spy_message_long.ics_spy_message_long.ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 107
 NumberBytesData (*ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute*), 108
 NumberBytesData (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 110
 NumberBytesHeader (*ics.ics.SpyMessage attribute*), 18
 NumberBytesHeader (*ics.ics.SpyMessageJ1850 attribute*), 20
 NumberBytesHeader (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 105
 NumberBytesHeader (*ics.structures.ics_spy_message_long.ics_spy_message_long attribute*), 107
 NumberBytesHeader (*ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute*), 108
 NumberBytesHeader (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 110
 NumberBytesHeader
NumberBytesHeader (*ics.structures.op_eth_general_settings op_eth_general_settings attribute*), 113
NumberBytesHeader (*ics.structures.op_eth_link_mode op_eth_link_mode attribute*), 114
NumberBytesHeader (*ics.structures.op_eth_settings op_eth_settings attribute*), 114
NumberBytesHeader (*OP_ETH_SETTINGS_SIZE (in module ics.ics)*), 215
OpenDevice () (*in module ics.ics*), 53
OpenNeoDevice () (*in module ics.ics*), 25

operationLogPDelayReqInterval
 (*ics.structures.s_jupiter_ptp_params_s.s_jupiter_OPETH_LINK_AUTO* (*ics.structures.op_eth_link_mode.op_eth_link_mode_attribute*), 137)
 operationLogSyncInterval
 (*ics.structures.s_jupiter_ptp_params_s.s_jupiter_OPETH_LINK_MASTER*
 (*ics.structures.op_eth_link_mode.op_eth_link_mode_attribute*), 137)
 opEth1 (*ics.structures.srad_comet_settings.srad_comet_settings_attribute*), 114
 OPETH_LINK_MASTER (*in module ics.ics*), 215
 opEth1 (*ics.structures.srad_galaxy_settings.srad_galaxy_OPETH_LINK_SLAVE* (*ics.structures.op_eth_link_mode.op_eth_link_mode_attribute*), 173)
 opEth1 (*ics.structures.srad_gigastar_settings.srad_gigastar_OPETH_LINK_SLAVE* (*in module ics.ics*), 215
 (*attribute*), 179
 opEth1 (*ics.structures.srad_moon2_settings.srad_moon2_settings_attribute*), 215
 OPETH_MAC_SPOOF_DST_ADDR (*in module ics.ics*),
 (*attribute*), 182
 opEth1 (*ics.structures.srad_star2_settings.srad_star2_settings_attribute*), 215
 OPETH_MAC_SPOOF_SRC_ADDR (*in module ics.ics*),
 (*attribute*), 186
 opEth1 (*ics.structures.srad_super_moon_settings.srad_super_moon_attributes*), 169
 opEthGen (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 174
 opEth10 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 174
 opEthGen (*ics.structures.srad_gigastar_settings.srad_gigastar_settings_attribute*), 173
 opEth11 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 179
 opEthGen (*ics.structures.srad_moon2_settings.srad_moon2_settings_attribute*), 173
 opEth12 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 182
 opEthGen (*ics.structures.srad_star2_settings.srad_star2_settings_attribute*), 174
 opEth2 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 186
 opEthGen (*ics.structures.srad_super_moon_settings.srad_super_moon_attributes*), 174
 opEth2 (*ics.structures.srad_gigastar_settings.srad_gigastar_setting_attributes*), 187
 options (*ics.structures.s_disk_structure.s_disk_structure_attribute*), 120
 opEth2 (*ics.structures.srad_star2_settings.srad_star2_settings_attribute*), 186
 os_settings (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings_attribute*), 125
 opEth3 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 174
 os_settings (*ics.structures.s_fire3_settings.s_fire3_settings_attribute*), 174
 opEth4 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 130
 os_settings (*ics.structures.s_red2_settings.s_red2_settings_attribute*), 174
 opEth5 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 154
 override_library_name () (*in module ics.ics*), 54
 opEth6 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attributesideBlockSize*
 (*attribute*), 174
 opEth7 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 111
 overrideBlockSize
 opEth8 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attributesideSTmin* (*ics.structures.iso15765_2015_tx_message.st_cm_iso157652_tx_message.st_cm_iso157652_tx_attributes*), 194
 opEth9 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attributesideSTmin* (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_attributes*), 174
 OPETH_FUNC_MEDIA_CONVERTER (*in module ics.ics*), 215
 OPETH_FUNC_RAW_MEDIA_CONVERTER (*in module ics.ics*), 215
 OPETH_FUNC_RAW_MEDIA_CONVERTER2 (*in module ics.ics*), 215
 OPETH_FUNC_RAW_MEDIA_CONVERTER2_LOW_LATENCY
 (*in module ics.ics*), 215
 OPETH_FUNC_TAP (*in module ics.ics*), 215
 OPETH_FUNC_TAP_LOW_LATENCY
 (*in module ics.ics*), 215

P

p2_Y500us (*ics.structures.iso9141_keyword2000_settings.iso9141_keyword_attributes*), 112
 p3_500us (*ics.structures.iso9141_keyword2000_settings.iso9141_keyword_attributes*), 112

p4_500us (*ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings.pluto_vl_forwarding_entry.s.s_pluto_vl_for_attribute*), 112
pad (*ics.structures.s_pluto_custom_params.s.s_pluto_custom_params.s.s_pluto_vl_forwarding_params.s.s_pluto_vl_for_attribute*), 145
pad (*ics.structures.s_pluto_l2_address_lookup_params.s.s_pluto_l2_address_lookup_params.s.s_pluto_vl_forwarding_params.s.s_pluto_vl_for_attribute*), 147
pad (*ics.structures.s_pluto_l2_forwarding_entry.s.s_pluto_l2_forwarding_entry.s.s_pluto_l2_forwarding_entry.srad_moon2_settings.srad_moon2_settings_attribute*), 147
pad (*ics.structures.s_pluto_l2_forwarding_params.s.s_pluto_l2_forwarding_params.s.s_pluto_clock_sync_params.s.s_pluto_clock_sync_attribute*), 147
pad (*ics.structures.s_pluto_mac_config.s.s_pluto_mac_config.s.com_mode* (*ics.structures.srad_super_moon_settings.srad_super_moo_attribute*), 148
pad (*ics.structures.s_pluto_retagging_entry.s.s_pluto_retagging_entry.s.s_pluto_clock_sync_params.s.s_pluto_clock_sync_attribute*), 150
pad (*ics.structures.s_pluto_vl_forwarding_params.s.s_pluto_vl_forwarding_params.s.s_pluto_clock_sync_params.s.s_pluto_clock_sync_attribute*), 151
pad (*ics.structures.s_pluto_vlan_lookup.s.s_pluto_vlan_lookup.s.global_settings.global_settings_attribute*), 151
pad (*ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings.s_cyan_settings.s_cyan_settings_attribute*), 171
pad (*ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings.s.ether_badge_settings.s.ether_badge_settings_attribute*), 182
pad1 (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.s.fire3.flexray_settings.s.fire3.flexray_settings_attribute*), 143
pad1 (*ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry.s.fire3.settings.s.fire3.settings_attribute*), 146
pad2 (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.s.fire_settings.s.fire_settings_attribute*), 143
pad2 (*ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry.s.fire_vnet_settings.s.fire_vnet_settings_attribute*), 146
pad3 (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.s.flex_vnetz_settings.s.flex_vnetz_settings_attribute*), 143
pad3 (*ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry.s.neo_ecu12_settings.s.neo_ecu12_settings_attribute*), 146
padding (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message.srad_moon_duo_settings.s.rad_moon_duo_settings_attribute*), 112
padding (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message.red2_settings.s.red2_settings_attribute*), 193
padding (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message.vivid_can_settings.s.vivid_can_settings_attribute*), 194
paddingEnable (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message.secu_avb_settings.secu_avb_settings_attribute*), 112
paddingEnable (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message.seevb_settings.seevb_settings_attribute*), 193
paddingEnable (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message.sobd2_lc_settings.sobd2_lc_settings_attribute*), 194
page (*ics.structures.s_phy_reg_pkt_clause22.mess.s_phy_reg_pkt_clause22.sobd2_pro_settings.sobd2_pro_settings_attribute*), 141
parity (*ics.structures.uart_settings.uart_settings.at_perf_en* (*ics.structures.sobd2_sim_settings.sobd2_sim_settings_attribute*), 167
part_spc (*ics.structures.s_pluto_l2_forwarding_params.s.s_pluto_l2_forwarding_params.granulation.set_settings.srad_comet_settings_attribute*), 147
partition (*ics.structures.s_pluto_l2_policing.s.s_pluto_l2_policing.s.srd_epsilon_settings.srad_epsilon_settings_attribute*), 148
partition (*ics.structures.s_pluto_l2_policing.s.s_pluto_l2_policing.s.srd_epsilon_settings.srad_epsilon_settings_attribute*), 171

perf_en (*ics.structures.srad_galaxy_settings.srad_galaxyattribute*), 174
PhyFlashingReadError
attribute), 174
perf_en (*ics.structures.srad_gigalog_settings.srad_gigalog_settingattribute*), 115
PhyFlashingVerifyError
attribute), 176
perf_en (*ics.structures.srad_gigastar_settings.srad_gigastar_settingattribute*), 115
PhyFlashingWriteError
attribute), 179
perf_en (*ics.structures.srad_jupiter_settings.srad_jupiterattribute*), 181
PhyFlashingWriteError
attribute), 181
perf_en (*ics.structures.srad_moon2_settings.srad_moon2_settingsattribute*), 115
PhyGetVersionError
attribute), 183
perf_en (*ics.structures.srad_moon3_settings.srad_moon3_settingsattribute*), 115
PhyGetVersionError
attribute), 183
perf_en (*ics.structures.srad_pluto_settings.srad_pluto_settingattribute*), 115
PhyIndexError
attribute), 184
perf_en (*ics.structures.srad_star2_settings.srad_star2_settingsattribute*), 171
PhyMode (*ics.structures.srad_epsilon_switch_settings.srad_epsilon_switchattribute*), 171
perf_en (*ics.structures.srad_super_moon_settings.srad_spy(attribute)*), 182
PhyMode (*ics.structures.srad_jupiter_switch_settings.srad_jupiter_switchattribute*), 182
perf_en (*ics.structures.srada2_b_settings.srada2_b_settingsattribute*), 188
PhyOperationError
attribute), 188
perf_en (*ics.structures.sradbms_settings.sradbms_settingsattribute*), 115
PhyOperationSuccess
attribute), 189
perf_en (*ics.structures.svcn3_settings.svcn3_settingsattribute*), 115
PhyOperationSuccess
attribute), 196
perf_en (*ics.structures.svcn412_settings.svcn412_settingsattribute*), 142
PHYREG_BOTH (*ics.structures.s_phy_reg_pkt_rw.s_phy_reg_pkt_rwattribute*), 142
perf_en (*ics.structures.svcn4_ind_settings.svcn4_ind_settingsattribute*), 215
PHYREG_BOTH (*in module ics.ics*), 215
attribute), 197
PHYREG_FAILURE (*ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_statusattribute*), 142
perf_en (*ics.structures.svcn4_settings.svcn4_settingsattribute*), 215
PHYREG_FAILURE (*in module ics.ics*), 215
perf_en (*ics.structures.svcnrf_settings.svcnrf_settingsattribute*), 200
PHYREG_INVALID_MDIO_BUS_INDEX
attribute), 200
phy_error_type (*class ics.structures.phy_error_type*), 114
in attribute, 142
PHYREG_INVALID_MDIO_BUS_INDEX (*in module ics.ics*), 215
PHY_REG_PKT_VERSION (*in module ics.ics*), 216
PhyAddr (*ics.structures.ics_spy_message_mdio.ics_spy_messageattribute*), 108
VALID_PHY_ADDR
attribute), 108
PhyAddr (*ics.structures.s_phy_reg_pkt_clause22_messageattribute*), 214
mess
attribute), 141
PHYREG_INVALID_PHY_ADDR (*in module ics.ics*), 215
PhyFlashingDeinitError
(ics.structures.phy_error_type.phy_error_typeattribute), 114
attribute), 114
PHYREG_READ (*ics.structures.s_phy_reg_pkt_rw.s_phy_reg_pkt_rwattribute*), 142
PHYREG_READ (*in module ics.ics*), 215
PhyFlashingEraseError
(ics.structures.phy_error_type.phy_error_typeattribute), 114
attribute), 114
PHYREG_RESERVED1 (*ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkattribute*), 142
attribute), 142
PHYREG_RESERVED1 (*in module ics.ics*), 215
PhyFlashingInitError
(ics.structures.phy_error_type.phy_error_typeattribute), 114
attribute), 114
PHYREG_RESERVED2 (*in module ics.ics*), 215
PhyFlashingInvalidDataFile
(ics.structures.phy_error_type.phy_error_typeattribute), 114
attribute), 114
PHYREG_RESERVED3 (*ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkattribute*), 142
attribute), 142
PHYREG_RESERVED3 (*in module ics.ics*), 215
PhyFlashingInvalidHardware
(ics.structures.phy_error_type.phy_error_typeattribute), 114
attribute), 114
PHYREG_SUCCESS (*ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkattribute*), 142

PHYREG_SUCCESS (*in module* `ics.ics`), 216
 PHYREG_UNSUPPORTED_MDIO_CLAUSE
 (`ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_status` attribute), 142
 PHYREG_UNSUPPORTED_MDIO_CLAUSE (*in module* `ics.ics`), 216
 PHYREG_WRITE (`ics.structures.s_phy_reg_pkt_rw.s_phy_reg_pkt_rw` attribute), 142
 PHYREG_WRITE (*in module* `ics.ics`), 216
`plasma_fire_vnet` (`ics.structures.st_chip_versions.st_chip_versions` attribute), 191
 PLASMA_SLAVE1_OFFSET (*in module* `ics.ics`), 216
 PLASMA_SLAVE1_OFFSET_RANGE2 (*in module* `ics.ics`), 216
 PLASMA_SLAVE2_OFFSET (*in module* `ics.ics`), 216
 PLASMA_SLAVE2_OFFSET_RANGE2 (*in module* `ics.ics`), 216
 PLASMA_SLAVE3_OFFSET_RANGE2 (*in module* `ics.ics`), 216
 PLASMA_SLAVE_NUM (*in module* `ics.ics`), 216
`PlasmaIonVnetChannelA`
 (`ics.structures.e_plasma Ion_vnet_channel.t.e_plasma Ion_vnet_channel` attribute), 94
`PlasmaIonVnetChannelB`
 (`ics.structures.e_plasma Ion_vnet_channel.t.e_plasma Ion_vnet_channel` attribute), 94
`PlasmaIonVnetChannelMain`
 (`ics.structures.e_plasma Ion_vnet_channel.t.e_plasma Ion_vnet_channel` attribute), 94
`pluto` (`ics.structures.global_settings.global_settings` attribute), 100
 PLUTO_MAX_FORWARDING_ENTRIES (*in module* `ics.ics`), 216
 PLUTO_MAX_L2_ADDRESS_LOOKUP (*in module* `ics.ics`), 216
 PLUTO_MAX_L2_POLICING (*in module* `ics.ics`), 216
 PLUTO_MAX_MAC_CONFIG_ENTRIES (*in module* `ics.ics`), 216
 PLUTO_MAX RETAGGING_ENTRIES (*in module* `ics.ics`), 216
 PLUTO_MAX_VLAN_LOOKUP (*in module* `ics.ics`), 216
 PLUTO_NUM_PORTS (*in module* `ics.ics`), 216
 PLUTO_NUM_PRIORITY (*in module* `ics.ics`), 216
`pluto_versions` (`ics.structures.st_chip_versions.st_chip_versions` attribute), 191
`plutoStatus` (`ics.structures.ics_device_status.ics_device_status` attribute), 102
`poly` (`ics.structures.s_pluto_l2_address_lookup_params.s_pluto_l2_address_lookup_params` attribute), 147
`port` (`ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_Reg_pkt_clause45_mess` attribute), 142
`port` (`ics.structures.uart_port_config.uart_port_config` attribute), 202
`port` (`ics.structures.uart_port_data.uart_port_data` attribute), 202
 port (`ics.structures.uart_port_port_bytes.uart_port_port_bytes` attribute), 202
 port7Select (`ics.structures.srad_jupiter_switch_settings.srad_jupiter_s` attribute), 182
 port8Legacy (`ics.structures.srad_jupiter_switch_settings.srad_jupiter_s` attribute), 182
 port8Select (`ics.structures.srad_jupiter_switch_settings.srad_jupiter_s` attribute), 182
 port_a (`ics.structures.s_spi_port_settings.s_spi_port_settings` attribute), 155
 port_b (`ics.structures.s_spi_port_settings.s_spi_port_settings` attribute), 155
 port_identity (*class in* `ics.structures.port_identity`), 115
 port_number (`ics.structures.port_identity.port_identity` attribute), 115
 port_number (`ics.structures.priority_vector.priority_vector` attribute), 115
 portid (`ics.structures.priority_vector.priority_vector` attribute), 149
 preemption_en (`ics.structures.op_eth_settings.op_eth_settings` attribute), 114
 priority1 (`ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params` attribute), 149
 priority1 (`ics.structures.srad_gptp_settings.s.srad_gptp_settings` attribute), 180
 priority2 (`ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params` attribute), 149
 priority2 (`ics.structures.srad_gptp_settings.s.srad_gptp_settings` attribute), 180
 priority_1 (`ics.structures.system_identity.system_identity` attribute), 201
 priority_2 (`ics.structures.system_identity.system_identity` attribute), 201
 priority_vector (*class* in `ics.structures.priority_vector`), 115
 Protocol (`ics.ics.SpyMessageJ1850` attribute), 20
 Protocol (`ics.ics.SpyMessageJ455` attribute), 105
 Protocol (`ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex` attribute), 107
 Protocol (`ics.structures.ics_spy_message_long.ics_spy_message_long` attribute), 107
 Protocol (`ics.structures.ics_spy_message_mdio.ics_spy_message_mdio` attribute), 107

attribute), 108
*Protocol(ics.structures.ics_spy_message_vsb.ics_spy_message_vsb_enable(ics.structures.srad_gigastar_settings.srad_gigastar_s
attribute), 110*
attribute), 176
attribute), 179
*ptpParams(ics.structures.s_pluto_custom_params.s_pluto_custom_params(ics.structures.srad_jupiter_settings.srad_jupiter_setti
attribute), 145*
attribute), 181
*ptpParams_unused(ics.structures.srad_jupiter_switch_setting.srad_jupiter_is_in_the_star(ics.structures.srad_pluto_settings.srad_pluto_setting
attribute), 182*
attribute), 184
*pwm_man_timeout(ics.structures.s_fire_settings.s_fire_settingman_enable(ics.structures.srad_star2_settings.srad_star2_setting
attribute), 132*
attribute), 186
*pwm_man_timeout(ics.structures.s_fire_vnet_settings.s_fire_vnet_settingman_enable(ics.structures.srada2_b_settings.srada2_b_settings
attribute), 135*
attribute), 188
*pwr_man_enable(ics.structures.s_cyan_settings.s_cyan_settingman_enable(ics.structures.sradbms_settings.sradbms_settings
attribute), 119*
attribute), 189
*pwr_man_enable(ics.structures.s_ether_badge_settings.s_ether_badge_setting(ics.structures.svcan412_settings.svcan412_settings
attribute), 121*
attribute), 196
*pwr_man_enable(ics.structures.s_fire3_flexray_settings.s_fire3_flexray_setting(ics.structures.svcan4_ind_settings.svcan4_ind_setting
attribute), 125*
attribute), 197
*pwr_man_enable(ics.structures.s_fire3_settings.s_fire3_settingman_enable(ics.structures.svcan4_settings.svcan4_settings
attribute), 130*
attribute), 198
*pwr_man_enable(ics.structures.s_fire_settings.s_fire_settingman_enable(ics.structures.svcanrf_settings.svcanrf_settings
attribute), 132*
attribute), 200
*pwr_man_enable(ics.structures.s_fire_vnet_settings.s_fire_vnet_settingtimeout(ics.structures.s_cyan_settings.s_cyan_settings
attribute), 135*
attribute), 119
*pwr_man_enable(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settingtimeout(ics.structures.s_ether_badge_settings.s_ether_badg
attribute), 137*
attribute), 121
*pwr_man_enable(ics.structures.s_neo_ecu12_settings.s_neo_ecu2_setting(ics.structures.s_fire3_flexray_settings.s_fire3_flexra
attribute), 139*
attribute), 125
*pwr_man_enable(ics.structures.s_pendant_settings.s_pendant_settingtimeout(ics.structures.s_fire3_settings.s_fire3_settings
attribute), 140*
attribute), 130
*pwr_man_enable(ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_setting(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_set
attribute), 152*
attribute), 137
*pwr_man_enable(ics.structures.s_red2_settings.s_red2_settingtimeout(ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
attribute), 154*
attribute), 139
*pwr_man_enable(ics.structures.s_vivid_can_settings.s_vivid_can_settingtimeout(ics.structures.s_pendant_settings.s_pendant_setting
attribute), 156*
attribute), 140
*pwr_man_enable(ics.structures.scan_hub_settings.scanhub_settingtimeout(ics.structures.s_rad_moon_duo_settings.s_rad_moo
attribute), 157*
attribute), 152
*pwr_man_enable(ics.structures.secu_avb_settings.secu_avb_settingtimeout(ics.structures.s_red2_settings.s_red2_settings
attribute), 158*
attribute), 154
*pwr_man_enable(ics.structures.secu_settings.secu_settingpwr_man_timeout(ics.structures.s_vivid_can_settings.s_vivid_can_set
attribute), 160*
attribute), 156
*pwr_man_enable(ics.structures.sievb_settings.sievb_settingman_timeout(ics.structures.scan_hub_settings.scan_hub_settings
attribute), 163*
attribute), 158
*pwr_man_enable(ics.structures.sobd2_lc_settings.sobd2_lc_settingtimeout(ics.structures.secu_avb_settings.secu_avb_settings
attribute), 164*
attribute), 158
*pwr_man_enable(ics.structures.sobd2_pro_settings.sobd2_pro_settingtimeout(ics.structures.secu_settings.secu_settings
attribute), 166*
attribute), 160
*pwr_man_enable(ics.structures.srad_comet_settings.srad_comet_settingtimeout(ics.structures.sievb_settings.sievb_settings
attribute), 169*
attribute), 163
*pwr_man_enable(ics.structures.srad_epsilon_settings.srad_epsilon_settingtimeout(ics.structures.sobd2_lc_settings.sobd2_lc_settings
attribute), 171*
attribute), 164
*pwr_man_enable(ics.structures.srad_galaxy_settings.srad_galaxy_settingtimeout(ics.structures.sobd2_pro_settings.sobd2_pro_setting
attribute), 174*
attribute), 166
*pwr_man_enable(ics.structures.srad_gigalog_settings.srad_gigalog_settingtimeout(ics.structures.srad_comet_settings.srad_comet_setting
attribute), 177*
attribute), 163

attribute), 169
pwr_man_timeout (*ics.structures.srad_epsilon_settings.srad_epsilon_attributes*), 216
attribute), 171
pwr_man_timeout (*ics.structures.srad_galaxy_settings.srad_galaxy_attributes*), 216
attribute), 174
pwr_man_timeout (*ics.structures.srad_gigalog_settings.srad_gigalog_attributes*), 216
attribute), 176
pwr_man_timeout (*ics.structures.srad_gigastar_settings.srad_gigastar_attributes*), 216
attribute), 179
pwr_man_timeout (*ics.structures.srad_jupiter_settings.srad_jupiter_attributes*), 216
attribute), 181
pwr_man_timeout (*ics.structures.srad_pluto_settings.srad_pluto_attributes*), 216
attribute), 184
pwr_man_timeout (*ics.structures.srad_star2_settings.srad_star2_attributes*), 216
attribute), 186
pwr_man_timeout (*ics.structures.srada2_b_settings.srada2_b_attributes*), 216
attribute), 188
pwr_man_timeout (*ics.structures.sradbms_settings.sradbms_attributes*), 216
attribute), 189
pwr_man_timeout (*ics.structures.svcan412_settings.svcan412_attributes*), 216
attribute), 196
pwr_man_timeout (*ics.structures.svcan4_ind_settings.svcan4_ind_attributes*), 216
attribute), 197
pwr_man_timeout (*ics.structures.svcan4_settings.svcan4_attributes*), 216
attribute), 198
pwr_man_timeout (*ics.structures.svcanrf_settings.svcanrf_attributes*), 200
attribute), 200

Q

q2112_phy_mode (*ics.structures.op_eth_settings.op_eth_attributes*), 114

R

rad_a2b (*ics.structures.global_settings.global_attributes*), 100
rad_a2b_versions (*ics.structures.st_chip_versions.st_chip_attributes*), 191
rad_bms (*ics.structures.global_settings.global_attributes*), 100
rad_comet_versions (*ics.structures.st_chip_versions.st_chip_attributes*), 191
RAD_GPTP_AND_TAP_SETTINGS_SIZE (in module *ics.ics*), 216
RAD_GPTP_SETTINGS_SIZE (in module *ics.ics*), 216
rad_moon_duo_converter_settings (class in *ics.structures.rad_moon_duo_converter_settings*), 115
rad_moon_duo_versions (*ics.structures.st_chip_versions.st_chip_attributes*), 191
rad_reporting_settings (class in *ics.structures.rad_reporting_settings*), 115

RAD_REPORTING_SETTINGS_FLAG_AIN1 (in module *ics.ics*), 216
RAD_REPORTING_SETTINGS_FLAG_FAN_SPEED_ENABLE
RAD_REPORTING_SETTINGS_FLAG_INT_GPS_ENABLE
RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE
RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE2
RAD_REPORTING_SETTINGS_FLAG_MISC1_DIN
RAD_REPORTING_SETTINGS_FLAG_MISC1_PWMIN
RAD_REPORTING_SETTINGS_FLAG_MISC2_DIN
RAD_REPORTING_SETTINGS_FLAG_MISC2_PWMIN
RAD_REPORTING_SETTINGS_FLAG_SERDES_ENABLE
RAD_REPORTING_SETTINGS_FLAG_TEMP_ENABLE
RAD_REPORTING_SETTINGS_SIZE (in module *ics.ics*), 216
rad_wbms_versions

radBMSStatus (*ics.structures.ics_device_status.ics_device_status_attributes*), 102

RADEPSILON_MAX_PHY (in module *ics.ics*), 216
RADEPSILON_NUM_PORTS (in module *ics.ics*), 216

radgalaxy (*ics.structures.global_settings.global_attributes*), 100
radgalaxy_versions
radgalaxy_versions (*ics.structures.st_chip_versions.st_chip_attributes*), 191
radgigalog (*ics.structures.global_settings.global_attributes*), 100
radgigalog3_versions
radgigalog3_versions (*ics.structures.st_chip_versions.st_chip_attributes*), 191
radgigalog_versions
radgigalog_versions (*ics.structures.st_chip_versions.st_chip_attributes*), 192
radgigastar (*ics.structures.global_settings.global_attributes*), 101
radgigastar_usbz_versions
radgigastar_usbz_versions (*ics.structures.st_chip_versions.st_chip_attributes*), 192
radgigastar_versions
radgigastar_versions (*ics.structures.st_chip_versions.st_chip_attributes*), 192

RADJUPITER_NUM_PORTS (*in module ics.ics*), 216
radmoon2 (*ics.structures.global_settings.global_settings attribute*), 101
radmoon2_versions
 (*ics.structures.st_chip_versions.st_chip_versions attribute*), 192
radmoon2_z7010_versions
 (*ics.structures.st_chip_versions.st_chip_versions attribute*), 192
radmoon3 (*ics.structures.global_settings.global_settings attribute*), 101
radmoon3_versions
 (*ics.structures.st_chip_versions.st_chip_versions attribute*), 192
radmoonduo (*ics.structures.global_settings.global_settings attribute*), 101
RADMOONDUO_CONVERTER_SETTINGS_SIZE (*in module ics.ics*), 216
radMoonDuoStatus (*ics.structures.ics_device_status.ics_device_status attribute*), 102
radstar2 (*ics.structures.global_settings.global_settings attribute*), 101
radstar2_versions
 (*ics.structures.st_chip_versions.st_chip_versions attribute*), 192
radsupermoon (*ics.structures.global_settings.global_settings attribute*), 101
radsupermoon_versions
 (*ics.structures.st_chip_versions.st_chip_versions attribute*), 192
rate (*ics.structures.s_pluto_l2_policing_s.s_pluto_l2_policing attribute*), 148
reach_port (*ics.structures.s_pluto_l2_forwarding_entry.s_pluto_l2_forwarding_entry attribute*), 147
read_jupiter_firmware () (*in module ics.ics*), 54
read_sdcard () (*in module ics.ics*), 54
ReadJupiterFirmware () (*in module ics.ics*), 25
ReadSDCard () (*in module ics.ics*), 25
red (*ics.structures.global_settings.global_settings attribute*), 101
red2 (*ics.structures.global_settings.global_settings attribute*), 101
red2_versions (*ics.structures.st_chip_versions.st_chip_versions attribute*), 192
RegAddr (*ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute*), 108
regAddr (*ics.structures.s_phy_reg_pkt_clause22_mess.s_phy_reg_pkt_clause22_mess attribute*), 141
regAddr (*ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt_clause45_mess attribute*), 142
REGISTER_BY_SERIAL (*in module ics.ics*), 217
regVal (*ics.structures.s_phy_reg_pkt_clause22_mess.s_phy_reg_pkt_clause22_mess generic_binary_status generic_binary_status attribute*), 141
regVal (*ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt_clause45_mess generic_binary_status generic_binary_status attribute*), 141
attribute), 142
REPORT_ON_GPS (*in module ics.ics*), 217
REPORT_ON_KLINE (*in module ics.ics*), 217
REPORT_ON_LED1 (*in module ics.ics*), 217
REPORT_ON_LED2 (*in module ics.ics*), 217
REPORT_ON_MISC1 (*in module ics.ics*), 217
REPORT_ON_MISC2 (*in module ics.ics*), 217
REPORT_ON_MISC3 (*in module ics.ics*), 217
REPORT_ON_MISC3_AIN (*in module ics.ics*), 217
REPORT_ON_MISC4 (*in module ics.ics*), 217
REPORT_ON_MISC4_AIN (*in module ics.ics*), 217
REPORT_ON_MISC5 (*in module ics.ics*), 217
REPORT_ON_MISC5_AIN (*in module ics.ics*), 217
REPORT_ON_MISC6 (*in module ics.ics*), 217
REPORT_ON_PERIODIC (*in module ics.ics*), 217
REPORTING (*ics.structures.srad_comet_settings.srad_comet_settings attribute*), 169
request_enter_sleep_mode () (*in module ics.ics*), 55
RequestDiskDetails () (*in module ics.ics*), 25
RequestDiskFormat () (*in module ics.ics*), 25
RequestPlutoL2ForwardingEntry () (*in module ics.ics*), 25
RequestSleepMode () (*in module ics.ics*), 26
res1 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 106
res2 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 106
reserve (*ics.structures.uart_port_config.uart_port_config attribute*), 291mess
reserved (*ics.structures.a2_b_monitor_settings.a2_b_monitor_settings attribute*), 97
reserved (*ics.structures.canfd_settings.canfd_settings attribute*), 99
reserved (*ics.structures.fire3_linux_settings.fire3_linux_settings attribute*), 97
reserved (*ics.structures.canterm_settings.canterm_settings attribute*), 99
reserved (*ics.structures.fire3_linux_settings.fire3_linux_settings attribute*), 99
get_component_versions.get_component_version()

attribute), 99

reserved (ics.structures.gptp_status.gptp_status attribute), 102

Reserved(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray.attribute), 105

Reserved(ics.structures.ics_spy_message_long.ics_spy_message_long.attribute), 107

Reserved(ics.structures.ics_spy_message_mdio.ics_spy_message_mdio.attribute), 108

Reserved(ics.structures.ics_spy_message_vsb.ics_spy_message_vsb.attribute), 110

reserved(ics.structures.op_eth_settings.op_eth_settings.rsvd.attribute), 114

reserved(ics.structures.s_fire3_flexport_settings.s_fire3_flexport.attribute), 125

reserved(ics.structures.s_fire3_settings.s_fire3_settings.rsvd.attribute), 130

reserved(ics.structures.s_phy_reg_pkt.s_phy_reg_pkt.rsvd.attribute), 141

reserved(ics.structures.s_red2_settings.s_red2_settings.rsvd.attribute), 154

reserved(ics.structures.s_text_api_settings.s_text_api_settings.attribute), 156

reserved(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message.attribute), 193

RESERVED(ics.structures.swcan_settings.swcan_settings.rsvd.attribute), 200

Reserved(ics.structures.tag_options_find_neo_ex.tag_options_find_structures.srad_gptp_settings.srad_gptp_settings.attribute), 201

Reserved(ics.structures.tag_options_open_neo_ex.tag_options_open_structures.serdescam_settings.serdescam_settings.attribute), 201

reserved(ics.structures.version_report.version_report.rsvd1.attribute), 203

reserved(ics.structures.wbms_gateway_settings.wbms_gateway_settings.rsvd1.attribute), 204

reserved0(ics.structures.op_eth_general_settings.op_eth_general_settings.ethernet10_g_settings.ethernet10_g_settings.attribute), 113

reserved0(ics.structures.op_eth_settings.op_eth_settings.rsvd2.attribute), 114

reserved_1(ics.structures.sievb_settings.sievb_settings.rsvd2.attribute), 163

reserved_1(ics.structures.uart_settings.uart_settings.rsvd2.attribute), 203

reserved_2(ics.structures.sievb_settings.sievb_settings.RuntimeError, 18.attribute), 163

reserved_bits(ics.structures.uart_settings.uart_settings.rx_speed.attribute), 203

reserved_bits2(ics.structures.uart_settings.uart_settings.S.attribute), 203

s_cm_probe_settings (class in reserved_field(ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings.rsvd2.attribute), 116.attribute), 139

s_cyan_settings (class in reservedZero(ics.structures.svcancrf_settings.svcancrf_settings.rsvd2.attribute), 116.attribute), 200

s_device_settings (class in resHeight(ics.structures.serdescam_settings.serdescam_settings.ics.structures.s_device_settings), 119

s_disk_details	(class <i>ics.structures.s_disk_details</i>),	in	<i>ics.structures.s_pluto_custom_params_s</i> ,
s_disk_format_progress	(class <i>ics.structures.s_disk_format_progress</i>),	in	145 <i>ics.structures.s_pluto_general_params_s</i> (class in <i>ics.structures.s_pluto_general_params_s</i>),
s_disk_status	(class in <i>ics.structures.s_disk_status</i>),	120	145 <i>ics.structures.s_pluto_l2_address_lookup_entry_s</i> (class in <i>ics.structures.s_pluto_l2_address_lookup_entry_s</i>),
s_disk_structure	(class <i>ics.structures.s_disk_structure</i>),	120	146 <i>ics.structures.s_pluto_l2_address_lookup_params_s</i> (class in <i>ics.structures.s_pluto_l2_address_lookup_params_s</i>),
s_ether_badge_settings	(class <i>ics.structures.s_ether_badge_settings</i>),	120	147 <i>ics.structures.s_pluto_l2_forwarding_entry_s</i> (class in <i>ics.structures.s_pluto_l2_forwarding_entry_s</i>),
s_ext_sub_cmd_hdr	(class <i>ics.structures.s_ext_sub_cmd_hdr</i>),	122	147 <i>ics.structures.s_pluto_l2_forwarding_params_s</i> (class in <i>ics.structures.s_pluto_l2_forwarding_params_s</i>),
s_extended_data_flash_header	(class in <i>ics.structures.s_extended_data_flash_header</i>),	122	147 <i>ics.structures.s_pluto_l2_policing_s</i> (class in <i>ics.structures.s_pluto_l2_policing_s</i>),
s_fire3_flexray_settings	(class <i>ics.structures.s_fire3_flexray_settings</i>),	122	147 <i>ics.structures.s_pluto_mac_config_s</i> (class in <i>ics.structures.s_pluto_mac_config_s</i>),
s_fire3_settings	(class <i>ics.structures.s_fire3_settings</i>),	126	148 <i>ics.structures.s_pluto_ptp_params_s</i> (class in <i>ics.structures.s_pluto_ptp_params_s</i>),
s_fire_settings	(class <i>ics.structures.s_fire_settings</i>),	130	149 <i>ics.structures.s_pluto_retagging_entry_s</i> (class in <i>ics.structures.s_pluto_retagging_entry_s</i>),
s_fire_vnet_settings	(class <i>ics.structures.s_fire_vnet_settings</i>),	133	149 <i>ics.structures.s_pluto_switch_settings_s</i> (class in <i>ics.structures.s_pluto_switch_settings_s</i>),
s_flex_vnetz_settings	(class <i>ics.structures.s_flex_vnetz_settings</i>),	135	150 <i>ics.structures.s_pluto_vl_forwarding_entry_s</i> (class in <i>ics.structures.s_pluto_vl_forwarding_entry_s</i>),
s_jupiter_ptp_params_s	(class <i>ics.structures.s_jupiter_ptp_params_s</i>),	137	150 <i>ics.structures.s_pluto_vl_forwarding_params_s</i> (class in <i>ics.structures.s_pluto_vl_forwarding_params_s</i>),
s_neo_ecu12_settings	(class <i>ics.structures.s_neo_ecu12_settings</i>),	137	151 <i>ics.structures.s_pluto_vl_lookup_entry_s</i> (class in <i>ics.structures.s_pluto_vl_lookup_entry_s</i>),
s_neo_most_gateway_settings	(class in <i>ics.structures.s_neo_most_gateway_settings</i>),	139	151 <i>ics.structures.s_pluto_vl_policing_entry_s</i> (class in <i>ics.structures.s_pluto_vl_policing_entry_s</i>),
s_pendant_settings	(class <i>ics.structures.s_pendant_settings</i>),	139	151 <i>ics.structures.s_pluto_vlan_lookup_s</i> (class in <i>ics.structures.s_pluto_vlan_lookup_s</i>),
s_phy_reg_pkt	(class <i>ics.structures.s_phy_reg_pkt</i>),	141	151 <i>ics.structures.s_rad_moon_duo_settings</i> (class in <i>ics.structures.s_rad_moon_duo_settings</i>),
s_phy_reg_pkt_clause22_mess	(class in <i>ics.structures.s_phy_reg_pkt_clause22_mess</i>),	141	152 <i>ics.structures.s_red2_settings</i> (class in <i>ics.structures.s_red2_settings</i>),
s_phy_reg_pkt_clause45_mess	(class in <i>ics.structures.s_phy_reg_pkt_clause45_mess</i>),	141	152 <i>ics.structures.s_red_settings</i> (class in <i>ics.structures.s_red_settings</i>),
s_phy_reg_pkt_hdr	(class <i>ics.structures.s_phy_reg_pkt_hdr</i>),	142	155 <i>ics.structures.s_spi_port_setting</i> (class in <i>ics.structures.s_spi_port_setting</i>),
s_phy_reg_pkt_rw	(class <i>ics.structures.s_phy_reg_pkt_rw</i>),	142	155 <i>ics.structures.s_spi_port_settings</i> (class in <i>ics.structures.s_spi_port_settings</i>),
s_phy_reg_pkt_status	(class <i>ics.structures.s_phy_reg_pkt_status</i>),	142	155
s_pluto_avb_params_s	(class <i>ics.structures.s_pluto_avb_params_s</i>),	142	
s_pluto_clock_sync_params_s	(class in <i>ics.structures.s_pluto_clock_sync_params_s</i>),	143	
s_pluto_custom_params_s	(class <i>ics.structures.s_pluto_custom_params_s</i>),	in	

```

s_text_api_settings      (class      in      ics.structures.secu_avb_settings), 158
    ics.structures.s_text_api_settings), 155
s_vivid_can_settings    (class      in      seevb_settings      (class      in
    ics.structures.s_vivid_can_settings), 156
s_wil_bridge_config     (class      in      selectable_network_1
    ics.structures.s_wil_bridge_config), 156
s_wil_connection_settings (class      in      (ics.structures.s_fire3_settings.s_fire3_settings
    ics.structures.s_wil_connection_settings), 157
s_wil_fault_servicing_settings (class      in      attribute), 130
    ics.structures.s_wil_fault_servicing_settings), 157
s_wil_network_data_capture_settings
    (class in ics.structures.s_wil_network_data_capture_settings) selectable_network (ics.structures.secu_settings.secu_settings
    157                                         attribute), 160
scan_hub_settings        (class      in      selected_network (ics.structures.s_pendant_settings.s_pendant_setting
    ics.structures.scan_hub_settings), 157
scan_sleep_id            (class      in      attribute), 140
    ics.structures.scan_sleep_id), 158
SCRIPT_LOCATION_EMMC (in module ics.ics), 217
SCRIPT_LOCATION_FLASH_MEM (in module ics.ics),
    217
SCRIPT_LOCATION_INTERNAL_FLASH (in module
    ics.ics), 217
SCRIPT_LOCATION_SDCARD (in module ics.ics), 217
SCRIPT_LOCATION_VCAN3_MEM (in module ics.ics),
    217
SCRIPT_STATUS_RUNNING (in module ics.ics), 217
SCRIPT_STATUS_STOPPED (in module ics.ics), 217
ScriptClear () (in module ics.ics), 26
ScriptGetFBBlockStatus () (in module ics.ics), 26
ScriptGetScriptStatus () (in module ics.ics), 26
ScriptGetScriptStatusEx () (in module ics.ics),
    26
ScriptLoad () (in module ics.ics), 26
ScriptReadAppSignal () (in module ics.ics), 26
ScriptReadRxMessage () (in module ics.ics), 27
ScriptReadTxMessage () (in module ics.ics), 27
ScriptStart () (in module ics.ics), 27
ScriptStartFBBlock () (in module ics.ics), 27
ScriptStop () (in module ics.ics), 27
ScriptStopFBBlock () (in module ics.ics), 27
ScriptWriteAppSignal () (in module ics.ics), 27
ScriptWriteRxMessage () (in module ics.ics), 27
ScriptWriteTxMessage () (in module ics.ics), 28
seconds_lsb   (ics.structures.timestamp_timestamp_
    attribute), 201
seconds_msb   (ics.structures.timestamp_timestamp_
    attribute), 201
sectors (ics.structures.s_disk_status.s_disk_status attribute), 120
sectorsRemaining (ics.structures.s_disk_format_progress
    attribute), 120
secu_avb_settings      (class      in      SERDESCAM_MODE_PROGRESS_REPEAT
    ics.structures.secu_avb_settings), 158
    ics.structures.seevb_settings), 158
    ics.structures.selectable_network_1
    (ics.structures.s_fire3_settings.s_fire3_settings
    attribute), 130
    ics.structures.selectable_network_2
    (ics.structures.s_fire3_settings.s_fire3_settings
    attribute), 130
    ics.structures.selected_network (ics.structures.s_pendant_settings.s_pendant_setting
    attribute), 140
    ics.structures.selected_network (ics.structures.secu_settings.secu_settings
    attribute), 160
    ics.structures.selected_network (ics.structures.sievb_settings.sievb_settings
    attribute), 163
    ics.structures.selected_role (ics.structures.gptp_status.gptp_status
    attribute), 102
send_meta0 (ics.structures.s_pluto_general_params_s.s_pluto_general_
    attribute), 146
send_meta1 (ics.structures.s_pluto_general_params_s.s_pluto_general_
    attribute), 146
sensor_buffer_size
    (ics.structures.s_wil_connection_settings.s_wil_connection_setting
    attribute), 157
serdes_interval_ms
    (ics.structures.rad_reporting_settings.rad_reporting_setting
    attribute), 116
serdescam1 (ics.structures.srad_gigalog_settings.srad_gigalog_setting
    attribute), 177
serdescam1 (ics.structures.srad_gigastar_settings.srad_gigastar_setting
    attribute), 179
serdescam2 (ics.structures.srad_gigalog_settings.srad_gigalog_setting
    attribute), 177
serdescam2 (ics.structures.srad_gigastar_settings.srad_gigastar_setting
    attribute), 179
serdescam3 (ics.structures.srad_gigalog_settings.srad_gigalog_setting
    attribute), 177
serdescam3 (ics.structures.srad_gigastar_settings.srad_gigastar_setting
    attribute), 179
serdescam4 (ics.structures.srad_gigalog_settings.srad_gigalog_setting
    attribute), 177
serdescam4 (ics.structures.srad_gigastar_settings.srad_gigastar_setting
    attribute), 179
SERDESCAM_MODE_COUNT (in module ics.ics), 217
SERDESCAM_MODE_CUSTOM (in module ics.ics), 217
SERDESCAM_MODE_LOG_ONLY (in module ics.ics),
    217
SERDESCAM_MODE_SPLITTER (in module ics.ics),
    217
SERDESCAM_MODE_PROGRESS_REPEAT (in module
    ics.ics), 217
SERDESCAM_PIXEL_BIT_POS_0 (in module ics.ics),
    217

```

SERDESCAM_PIXEL_BIT_POS_1 (in module <code>ics.ics</code>), 217	(in module <code>ics.ics</code>), 218
SERDESCAM_PIXEL_BIT_POS_2 (in module <code>ics.ics</code>), 217	SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_16LE (in module <code>ics.ics</code>), 218
SERDESCAM_PIXEL_BIT_POS_3 (in module <code>ics.ics</code>), 217	SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_8 (in module <code>ics.ics</code>), 218
<code>serdescam_settings</code> (class in <code>ics.structures.serdescam_settings</code>), 161	SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_10LE_PACKED (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_FLAG_AUTO_DET_RES_ENABLE (in module <code>ics.ics</code>), 217	SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_12LE_PACKED (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_FLAG_CONFIG_ENABLE (in module <code>ics.ics</code>), 217	SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_16LE (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_FLAG_ENABLE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_8 (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_FLAG_LOGGING_ENABLE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_COUNT (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_FLAG_RTSP_ENABLE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_BGGR_10LE_PACKED (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_FLAG_TX0_ENABLE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_BGGR_12LE_PACKED (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_FLAG_TX1_ENABLE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_BGGR_8 (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_FLAG_TX2_ENABLE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_GBRG_10LE_PACKED (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_FLAG_TX3_ENABLE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_GBRG_12LE_PACKED (in module <code>ics.ics</code>), 218
SERDESCAM_SETTINGS_SIZE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_GBRG_8 (in module <code>ics.ics</code>), 218
SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_10LE_PACKED (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_GRBG_10LE_PACKED (in module <code>ics.ics</code>), 218
SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_12LE_PACKED (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_GRBG_12LE_PACKED (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16BE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_GRBG_8 (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16LE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_RGGB_10LE_PACKED (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_8 (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_RGGB_12LE_PACKED (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_10LE_PACKED (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_BAYER_RGGB_8 (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_12LE_PACKED (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_RAW_10 (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_16BE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_RAW_12 (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_16LE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_RAW_14 (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_8 (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_RAW_16 (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_10LE_PACKED (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_RAW_20 (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_12LE_PACKED (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_RAW_24 (in module <code>ics.ics</code>), 219
SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_16BE (in module <code>ics.ics</code>), 218	SERDESCAM_VIDEO_FORMAT_CSII_RAW_30 (in module <code>ics.ics</code>), 219

```

        module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_RAW_32 (in ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_RAW_36 (in ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_RAW_8 (in ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_RGB565 (in ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_RGB666 (in ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_RGB888 (in ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_10LE (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_12LE (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_8 (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_10LE (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_12LE (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_8 (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_10LE (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_12LE (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_8 (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_10LE (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_12LE (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_8 (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_JPEG (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_NONE (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_RAW_10 (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_RAW_12 (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_RAW_14 (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_RAW_16 (in module ics.ics), 219
SERDESCAM_VIDEO_FORMAT_RAW_20 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_RAW_24 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_RAW_30 (in module ics.ics), 220
ics.ics), 220
SERDESCAM_VIDEO_FORMAT_RAW_32 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_RAW_36 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_RAW_8 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_RGB565 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_RGB666 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_RGB888 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_UYVY_422_10LE_PACKED (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_UYVY_422_12LE_PACKED (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_UYVY_422_8 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_VYUY_422_10LE_PACKED (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_VYUY_422_12LE_PACKED (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_VYUY_422_8 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_YUV422_10LE_PLANAR (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_YUV422_16LE_PLANAR (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_YUYV_422_10LE_PACKED (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_YUYV_422_12LE_PACKED (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_YUYV_422_8 (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_YVYU_422_10LE_PACKED (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_YVYU_422_12LE_PACKED (in module ics.ics), 220
SERDESCAM_VIDEO_FORMAT_YVYU_422_8 (in module ics.ics), 220
serdesgen (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 177
serdesgen (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 179
SERDESGEN_MOD_ID_NONE (in module ics.ics), 220
SERDESGEN_MOD_ID_UNKNOWN (in module ics.ics), 220
serdesgen_settings (class in ics.structures.serdesgen_settings), 161
SERDESGEN_SETTINGS_FLAG_TX_PATGEN_ENABLE (in module ics.ics), 220
SERDESGEN_SETTINGS_SIZE (in module ics.ics), 220

```

serdespoc (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*.*s_pluto_vl_policing_entry_s.s_pluto_vl_policing_attribute*), 177
 serdespoc (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*.*s_pluto_vl_policing_entry_s.s_pluto_vl_policing_attribute*), 179
 serdespoc_settings (class in *ics.structures.serdespoc_settings*), 161
 SERDESPOC_SETTINGS_MODE_DISABLED (in module *ics.ics*), 220
 SERDESPOC_SETTINGS_MODE_SERIALIZER (in module *ics.ics*), 220
 SERDESPOC_SETTINGS_MODE_SUPPLY (in module *ics.ics*), 220
 SERDESPOC_SETTINGS_SIZE (in module *ics.ics*), 220
 SerialNumber (*ics.ics.NeoDevice* attribute), 18
 serverIpAddress (*ics.structures.start_dhcp_server_command.start_dhcp_server_command* attribute), 195
 set_active_vnet_channel () (in module *ics.ics*), 55
 set_backup_power_enabled () (in module *ics.ics*), 55
 set_bit_rate () (in module *ics.ics*), 55
 set_bit_rate_ex () (in module *ics.ics*), 55
 set_context () (in module *ics.ics*), 56
 set_device_settings () (in module *ics.ics*), 56
 set_fd_bit_rate () (in module *ics.ics*), 56
 set_led_property () (in module *ics.ics*), 56
 set_reflash_callback () (in module *ics.ics*), 57
 set_rtc () (in module *ics.ics*), 57
 SetActiveVNETChannel () (in module *ics.ics*), 28
 SetBackupPowerEnabled () (in module *ics.ics*), 28
 SetBaudrate (*ics.structures.can_settings.can_settings* attribute), 90
 SetBaudrate (*ics.structures.swcan_settings.swcan_settings* attribute), 200
 SetBitRate () (in module *ics.ics*), 28
 SetBitRateEx () (in module *ics.ics*), 28
 SetContext () (in module *ics.ics*), 28
 SetDeviceSettings () (in module *ics.ics*), 28
 SetFDBitRate () (in module *ics.ics*), 28
 SetLedProperty () (in module *ics.ics*), 29
 setLock (*ics.structures.w_bms_manager_set_lock.w_bms_manager_set_lock*.*spnmgkicsetlockres.iso9141_keyword2000_settings.iso9141_keyword2000_attribute*), 204
 SetReflashDisplayCallback () (in module *ics.ics*), 29
 SetRTC () (in module *ics.ics*), 29
 Settings (*ics.structures.s_device_settings.s_device_settings* attribute), 119
 settings (*ics.structures.s_disk_structure.s_disk_structure* attribute), 120
 shared_learn (*ics.structures.s_pluto_l2_address_lookup_params*.*attrpluto_l2address_lookup_params_s* attribute), 147
 sharindx (*ics.structures.s_pluto_l2_policing_s.s_pluto_l2_policing* attribute), 171
 size (*ics.structures.generic_binary_status.generic_binary_status* attribute), 99
 SLAVE_VNET_A (in module *ics.ics*), 220
 SLAVE_VNET_B (in module *ics.ics*), 220
 SlaveEnable (*ics.structures.timesync_icshardware_settings.timesync_icshardware_settings*.*timesync_icshardware_settings* attribute), 202
 SlaveNetwork (*ics.structures.timesync_icshardware_settings.timesync_icshardware_settings*.*timesync_icshardware_settings* attribute), 202
 slaveVnetA (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 119
 slaveVnetA (*ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings* attribute), 125
 slaveVnetA (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 130
 slaveVnetA (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 137
 slaveVnetA (*ics.structures.s_red2_settings.s_red2_settings* attribute), 154
 slaveVnetB (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 119
 slaveVnetB (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 137
 sleep_id (*ics.structures.scan_hub_settings.scan_hub_settings* attribute), 158
 SLEEP_MODE (in module *ics.ics*), 220
 SLOW_MODE (in module *ics.ics*), 220
 smax (*ics.structures.s_pluto_l2_policing_s.s_pluto_l2_policing* attribute), 148
 sobd2_lc_settings (class in *ics.structures.sobd2_lc_settings*), 163
 sobd2_pro_settings (class in *ics.structures.sobd2_pro_settings*), 165
 sobd2_sim_settings (class in *ics.structures.sobd2_sim_settings*), 166
 software_update_command (class in *ics.structures.software_update_command*), 167
 spbmgkicsetlockres.iso9141_keyword2000_settings.iso9141_keyword2000_attributes (attribute), 112
 spbmgkicsetlockres.iso9141_keyword2000_settings.iso9141_keyword2000_attributes (attribute), 113
 spbmgkicsetlockres.iso9141_keyword2000_settings.iso9141_keyword2000_attributes (attribute), 203
 speed (*ics.structures.s_pluto_custom_params.s.s_pluto_custom_params* attribute), 145
 speed (*ics.structures.s_pluto_mac_config.s.s_pluto_mac_config* s attribute), 145
 speed (*ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings*.*srad_epsilon_switch_settings* attribute), 128

attribute), 189
SPI_MODE_MASTER (*in module* `ics.ics`), 220
SPI_MODE_PMS_EMULATION (*in module* `ics.ics`), 221
SPI_MODE_SLAVE (*in module* `ics.ics`), 221
SPI_PORT_EXTERNAL (*in module* `ics.ics`), 221
SPI_PORT_ONBOARD (*in module* `ics.ics`), 221
SPI_TYPE_RAW (*in module* `ics.ics`), 221
SPI_TYPE_WIL (*in module* `ics.ics`), 221
spoofedMac (`ics.structures.srad_epsilon_switch_settings.SEND_EPDON_SWITCH_SETTINGS` *module* `ics.ics`), 222
attribute), 171
spoofedMac (`ics.structures.srad_jupiter_switch_settings.SEND_JUPITER_SWITCH_CHANGE_LINK_DATA` (*in module* `ics.ics`), 222
attribute), 182
spoofMacFlag (`ics.structures.srad_epsilon_switch_settings.SEND_EPDON_SWITCH_ISOLATING` *module* `ics.ics`), 222
attribute), 171
spoofMacFlag (`ics.structures.srad_jupiter_switch_settings.SEND_JUPITER_SWITCH_SWING_MESSAGE` (*in module* `ics.ics`), 222
attribute), 182
spy_filter_long (class *in* `ics.structures.spy_filter_long`), 167
SPY_PROTOCOL_A2B (*in module* `ics.ics`), 221
SPY_PROTOCOL_AUTOSAR (*in module* `ics.ics`), 221
SPY_PROTOCOL_BEAN (*in module* `ics.ics`), 221
SPY_PROTOCOL_CAN (*in module* `ics.ics`), 221
SPY_PROTOCOL_CANFD (*in module* `ics.ics`), 221
SPY_PROTOCOL_CGI (*in module* `ics.ics`), 221
SPY_PROTOCOL_CHRYSLER_CCD (*in module* `ics.ics`), 221
SPY_PROTOCOL_CHRYSLER_JVPW (*in module* `ics.ics`), 221
SPY_PROTOCOL_CHRYSLER_SCI (*in module* `ics.ics`), 221
SPY_PROTOCOL_CUSTOM (*in module* `ics.ics`), 221
SPY_PROTOCOL_DALLAS_1WIRE (*in module* `ics.ics`), 221
SPY_PROTOCOL_ETHERNET (*in module* `ics.ics`), 221
SPY_PROTOCOL_FLEXRAY (*in module* `ics.ics`), 221
SPY_PROTOCOL_FORD_UBP (*in module* `ics.ics`), 221
SPY_PROTOCOL_GENERIC_MANCHSESTER (*in module* `ics.ics`), 221
SPY_PROTOCOL_GENERIC_UART (*in module* `ics.ics`), 221
SPY_PROTOCOL_GM_ALDL_UART (*in module* `ics.ics`), 221
SPY_PROTOCOL_GME_CIM_SCL_KLINE (*in module* `ics.ics`), 221
SPY_PROTOCOL_GMFSA (*in module* `ics.ics`), 221
SPY_PROTOCOL_GMLAN (*in module* `ics.ics`), 221
SPY_PROTOCOL_I2C (*in module* `ics.ics`), 221
SPY_PROTOCOL_ISO9141 (*in module* `ics.ics`), 221
SPY_PROTOCOL_J1708 (*in module* `ics.ics`), 221
SPY_PROTOCOL_J1850PWM (*in module* `ics.ics`), 221
SPY_PROTOCOL_J1850VPW (*in module* `ics.ics`), 221
SPY_PROTOCOL_J1939 (*in module* `ics.ics`), 221
SPY_PROTOCOL_JTAG (*in module* `ics.ics`), 221
SPY_PROTOCOL_LIN (*in module* `ics.ics`), 221
SPY_PROTOCOL_MDIO (*in module* `ics.ics`), 221
SPY_PROTOCOL_MOST (*in module* `ics.ics`), 221
SPY_PROTOCOL_SENT_PROTOCOL (*in module* `ics.ics`), 222
SPY_PROTOCOL_SPI (*in module* `ics.ics`), 222
SPY_PROTOCOL_TCP (*in module* `ics.ics`), 222
SPY_PROTOCOL_UART (*in module* `ics.ics`), 222
SPY_PROTOCOL_UDP (*in module* `ics.ics`), 222
SPY_PROTOCOL_WBMS (*in module* `ics.ics`), 222
SPY_STATUS2_ERROR_FRAME (*in module* `ics.ics`), 222
SPY_STATUS2_ETHERNET_CRC_ERROR (*in module* `ics.ics`), 222
SPY_STATUS2_ETHERNET_FCS_VERIFIED (*in module* `ics.ics`), 222
SPY_STATUS2_ETHERNET_FRAME_TOO_SHORT (*in module* `ics.ics`), 222
SPY_STATUS2_ETHERNET_MANUALFCS_ENABLED (*in module* `ics.ics`), 222
SPY_STATUS2_ETHERNET_NO_PADDING (*in module* `ics.ics`), 222
SPY_STATUS2_ETHERNET_PREEMPTION_ENABLED (*in module* `ics.ics`), 222
SPY_STATUS2_ETHERNET_UPDATE_CHECKSUMS (*in module* `ics.ics`), 222
SPY_STATUS2_FLEXRAY_NO_CRC (*in module* `ics.ics`), 222
SPY_STATUS2_FLEXRAY_NO_HEADERCRC (*in module* `ics.ics`), 222
SPY_STATUS2_FLEXRAY_TX_AB (*in module* `ics.ics`), 222
SPY_STATUS2_FLEXRAY_TX_AB_NO_A (*in module* `ics.ics`), 222
SPY_STATUS2_FLEXRAY_TX_AB_NO_B (*in module* `ics.ics`), 222
SPY_STATUS2_FLEXRAY_TX_AB_NO_MATCH (*in module* `ics.ics`), 222
SPY_STATUS2_GLOBAL_CHANGE (*in module* `ics.ics`), 222
SPY_STATUS2_HAS_VALUE (*in module* `ics.ics`), 222
SPY_STATUS2_HIGH_VOLTAGE (*in module* `ics.ics`), 222
SPY_STATUS2_I2C_DIR_READ (*in module* `ics.ics`), 222
SPY_STATUS2_I2C_ERR_NACK (*in module* `ics.ics`), 222
SPY_STATUS2_I2C_ERR_TIMEOUT (*in module* `ics.ics`), 222

`ics.ics), 222`

`SPY_STATUS2_ISO_FRAME_ERROR (in module ics.ics), 222`

`SPY_STATUS2_ISO_OVERFLOW_ERROR (in module ics.ics), 222`

`SPY_STATUS2_ISO_PARITY_ERROR (in module ics.ics), 222`

`SPY_STATUS2_LIN_ERR_MSG_ID_PARITY (in module ics.ics), 222`

`SPY_STATUS2_LIN_ERR_RX_BREAK_NOT_0 (in module ics.ics), 222`

`SPY_STATUS2_LIN_ERR_RX_BREAK_TOO_SHORT (in module ics.ics), 222`

`SPY_STATUS2_LIN_ERR_RX_DATA_GREATER_8 (in module ics.ics), 223`

`SPY_STATUS2_LIN_ERR_RX_SYNC_NOT_55 (in module ics.ics), 223`

`SPY_STATUS2_LIN_ERR_TX_RX_MISMATCH (in module ics.ics), 223`

`SPY_STATUS2_LIN_ID_FRAME_ERROR (in module ics.ics), 223`

`SPY_STATUS2_LIN_NO_SLAVE_DATA (in module ics.ics), 223`

`SPY_STATUS2_LIN_SLAVE_BYTE_ERROR (in module ics.ics), 223`

`SPY_STATUS2_LIN_SYNC_FRAME_ERROR (in module ics.ics), 223`

`SPY_STATUS2_LONG_MESSAGE (in module ics.ics), 223`

`SPY_STATUS2_MDIO_CLAUSE45 (in module ics.ics), 223`

`SPY_STATUS2_MDIO_ERR_TIMEOUT (in module ics.ics), 223`

`SPY_STATUS2_MDIO_INVALID_BUS (in module ics.ics), 223`

`SPY_STATUS2_MDIO_INVALID_PHYADDR (in module ics.ics), 223`

`SPY_STATUS2_MDIO_INVALID_REGADDR (in module ics.ics), 223`

`SPY_STATUS2_MDIO_JOB_CANCELLED (in module ics.ics), 223`

`SPY_STATUS2_MDIO_OVERFLOW (in module ics.ics), 223`

`SPY_STATUS2_MDIO_READ (in module ics.ics), 223`

`SPY_STATUS2_MDIO_UNSUPPORTED_CLAUSE (in module ics.ics), 223`

`SPY_STATUS2_MDIO_UNSUPPORTED_OPCODE (in module ics.ics), 223`

`SPY_STATUS2_MOST_CHANGED_PAR (in module ics.ics), 223`

`SPY_STATUS2_MOST_CONTROL_DATA (in module ics.ics), 223`

`SPY_STATUS2_MOST_I2S_DUMP (in module ics.ics), 223`

`SPY_STATUS2_MOST_LOW_LEVEL (in module ics.ics), 223`

`SPY_STATUS2_MOST_MHP_CONTROL_DATA (in module ics.ics), 223`

`SPY_STATUS2_MOST_MHP_USER_DATA (in module ics.ics), 223`

`SPY_STATUS2_MOST_MOST150 (in module ics.ics), 223`

`SPY_STATUS2_MOST_MOST50 (in module ics.ics), 223`

`SPY_STATUS2_MOST_PACKET_DATA (in module ics.ics), 223`

`SPY_STATUS2_MOST_TOO_SHORT (in module ics.ics), 223`

`SPY_STATUS2_RX_TIMEOUT_ERROR (in module ics.ics), 223`

`SPY_STATUS2_VALUE_IS_BOOLEAN (in module ics.ics), 223`

`SPY_STATUS2_WBMS_API_IS_CALLBACK (in module ics.ics), 223`

`SPY_STATUS3_CANFD_BRS (in module ics.ics), 223`

`SPY_STATUS3_CANFD_ESI (in module ics.ics), 223`

`SPY_STATUS3_CANFD_FDF (in module ics.ics), 223`

`SPY_STATUS3_CANFD_IDE (in module ics.ics), 223`

`SPY_STATUS3_CANFD_RTR (in module ics.ics), 223`

`SPY_STATUS3_LIN_JUST_BREAK_SYNC (in module ics.ics), 224`

`SPY_STATUS3_LIN_ONLY_UPDATE_SLAVE_TABLE_ONCE (in module ics.ics), 224`

`SPY_STATUS3_LIN_SLAVE_DATA_TOO_SHORT (in module ics.ics), 224`

`SPY_STATUS_A2B_CONTROL (in module ics.ics), 224`

`SPY_STATUS_A2B_MONITOR (in module ics.ics), 224`

`SPY_STATUS_A2B_SCF_VALID_WAITING (in module ics.ics), 224`

`SPY_STATUS_A2B_UPSTREAM (in module ics.ics), 224`

`SPY_STATUS_ANALOG_DIGITAL_INPUT (in module ics.ics), 224`

`SPY_STATUS_AUDIO_COMMENT (in module ics.ics), 224`

`SPY_STATUS_AVSI_REC_OVERFLOW (in module ics.ics), 224`

`SPY_STATUS_BAD_MESSAGE_BIT_TIME_ERROR (in module ics.ics), 224`

`SPY_STATUS_BREAK (in module ics.ics), 224`

`SPY_STATUS_BUS_RECOVERED (in module ics.ics), 224`

`SPY_STATUS_BUS_SHORTED_GND (in module ics.ics), 224`

`SPY_STATUS_BUS_SHORTED_PLUS (in module ics.ics), 224`

`SPY_STATUS_CAN_BUS_OFF (in module ics.ics), 224`

`SPY_STATUS_CAN_ERROR_PASSIVE (in module ics.ics), 224`

```

    ics.ics), 224
SPY_STATUS_CANFD (in module ics.ics), 224
SPY_STATUS_CHECKSUM_ERROR (in module ics.ics), 224
SPY_STATUS_COMM_IN_OVERFLOW (in module ics.ics), 224
SPY_STATUS_CRC_ERROR (in module ics.ics), 224
SPY_STATUS_EXPECTED_LEN_MISMATCH (in module ics.ics), 224
SPY_STATUS_EXTENDED (in module ics.ics), 224
SPY_STATUS_FLEXRAY_PDU (in module ics.ics), 224
SPY_STATUS_FLEXRAY_PDU_NO_UPDATE_BIT (in module ics.ics), 224
SPY_STATUS_FLEXRAY_PDU_UPDATE_BIT_SET (in module ics.ics), 224
SPY_STATUS_GLOBAL_ERR (in module ics.ics), 224
SPY_STATUS_GPS_DATA (in module ics.ics), 224
SPY_STATUS_HEADERCRC_ERROR (in module ics.ics), 224
SPY_STATUS_HIGH_SPEED (in module ics.ics), 224
SPY_STATUS_INCOMPLETE_FRAME (in module ics.ics), 224
SPY_STATUS_INIT_MESSAGE (in module ics.ics), 224
SPY_STATUS_LIN_MASTER (in module ics.ics), 224
SPY_STATUS_LOST_ARBITRATION (in module ics.ics), 224
SPY_STATUS_MSG_NO_MATCH (in module ics.ics), 224
SPY_STATUS_NETWORK_MESSAGE_TYPE (in module ics.ics), 224
SPY_STATUS_PDU (in module ics.ics), 225
SPY_STATUS_REMOTE_FRAME (in module ics.ics), 225
SPY_STATUS_TEST_TRIGGER (in module ics.ics), 225
SPY_STATUS_TEXT_COMMENT (in module ics.ics), 225
SPY_STATUS_TX_MSG (in module ics.ics), 225
SPY_STATUS_TX_NOMATCH (in module ics.ics), 225
SPY_STATUS_UNDEFINED_ERROR (in module ics.ics), 225
SPY_STATUS_VSI_IFR_CRC_BIT (in module ics.ics), 225
SPY_STATUS_VSI_TX_UNDERRUN (in module ics.ics), 225
SPY_STATUS_XTD_FRAME (in module ics.ics), 225
SpyMessage (class in ics.ics), 18
SpyMessageJ1850 (class in ics.ics), 19
srad_comet_settings (class in ics.structures.srad_comet_settings), 168
srad_epsilon_settings (class in ics.structures.srad_epsilon_settings), 170
srad_epsilon_switch_settings (class in ics.structures.srad_epsilon_switch_settings), 171
srad_galaxy_settings (class in ics.structures.srad_galaxy_settings), 171
srad_gigalog_settings (class in ics.structures.srad_gigalog_settings), 174
srad_gigastar_settings (class in ics.structures.srad_gigastar_settings), 177
srad_gptp_and_tap_settings_s (class in ics.structures.srad_gptp_and_tap_settings_s), 179
srad_gptp_settings_s (class in ics.structures.srad_gptp_settings_s), 180
srad_jupiter_settings (class in ics.structures.srad_jupiter_settings), 180
srad_jupiter_switch_settings (class in ics.structures.srad_jupiter_switch_settings), 182
srad_moon2_settings (class in ics.structures.srad_moon2_settings), 182
srad_moon3_settings (class in ics.structures.srad_moon3_settings), 183
srad_pluto_settings (class in ics.structures.srad_pluto_settings), 183
srad_star2_settings (class in ics.structures.srad_star2_settings), 184
srad_super_moon_settings (class in ics.structures.srad_super_moon_settings), 186
srada2_b_settings (class in ics.structures.srada2_b_settings), 187
sradbms_settings (class in ics.structures.sradbms_settings), 188
srcmeta (ics.structures.s_pluto_avb_params_s.s_pluto_avb_params_s attribute), 142
srcport (ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_sync attribute), 144
st_api_firmware_info (class in ics.structures.st_api_firmware_info), 190
st_chip_versions (class in ics.structures.st_chip_versions), 191
st_cm_iso157652_rx_message (class in ics.structures.st_cm_iso157652_rx_message), 192
st_cm_iso157652_tx_message (class in ics.structures.st_cm_iso157652_tx_message), 193
stabasyen (ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_s attribute), 144
start_dhcp_server () (in module ics.ics), 57
start_dhcp_server_command (class in ics.structures.start_dhcp_server_command), 195
startAddress (ics.structures.start_dhcp_server_command.start_dhcp_s

```

attribute), 195
StartDHCPServer () (in module ics.ics), 29
startup (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray), 106
state (ics.structures.s_disk_format_progress.s_disk_format_progress), 120
status (ics.structures.generic_binary_status.generic_binary_status), 99
status (ics.structures.s_disk_details.s_disk_details attribute), 119
status (ics.structures.s_disk_status.s_disk_status attribute), 120
status (ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute), 141
Status2Mask (ics.structures.spy_filter_long.spy_filter_long attribute), 168
Status2Value (ics.structures.spy_filter_long.spy_filter_long attribute), 168
StatusBitField (ics.ics.SpyMessage attribute), 19
StatusBitField (ics.ics.SpyMessageJ1850 attribute), 20
StatusBitField (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 105
StatusBitField (ics.structures.ics_spy_message_long.ics_spy_message_long), 107
StatusBitField (ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute), 108
StatusBitField2 (ics.ics.SpyMessage attribute), 19
StatusBitField2 (ics.ics.SpyMessageJ1850 attribute), 20
StatusBitField2 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 105
StatusBitField2 (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 107
StatusBitField2 (ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute), 109
StatusBitField2 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 110
StatusBitField3 (ics.ics.SpyMessage attribute), 19
StatusBitField3 (ics.ics.SpyMessageJ1850 attribute), 20
StatusBitField3 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 105
StatusBitField3 (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 107
StatusBitField3 (ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute), 109
StatusBitField3 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 110
StatusBitField4 (ics.ics.SpyMessage attribute), 19
StatusBitField4 (ics.ics.SpyMessageJ1850 attribute), 20
StatusBitField4 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 105
StatusBitField4 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 107
StatusBitField4 (ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute), 109
StatusBitField4 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 110
StatusMask (ics.structures.spy_filter_long.spy_filter_long attribute), 168
StatusValue (ics.structures.spy_filter_long.spy_filter_long attribute), 168
steps_removed (ics.structures.priority_vector.priority_vector attribute), 115
stMin (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 112
stop_bits (ics.structures.uart_settings.uart_settings attribute), 194
stop_dhcp_server () (in module ics.ics), 58
stop_dhcp_server_command (class in ics.structures.stop_dhcp_server_command), 195
StopDHCPServer () (in module ics.ics), 29
subnetMask (ics.structures.start_dhcp_server_command.start_dhcp_server_command attribute), 105
supportedFeatureMax
svcan3_settings (class in ics.structures.svcancan3_settings), 195
svcan412_settings (class in ics.structures.svcancan412_settings), 196
svcan4_ind_settings (class in ics.structures.svcancan4_ind_settings), 196
svcan4_settings (class in ics.structures.svcancan4_settings), 197
svcanrf_settings (class in ics.structures.svcancanrf_settings), 198
swcan (ics.structures.s_fire_settings.s_fire_settings attribute), 199
swcan (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 135
swcan (ics.structures.s_pendant_settings.s_pendant_settings attribute), 140

swcan (ics.structures.secu_settings.secu_settings attribute), 160
 swcan1 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 119
 swcan1 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 130
 swcan1 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 139
 swcan1 (ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute), 156
 swcan1 (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 164
 swcan1 (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 166
 swcan1 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 174
 swcan2 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 119
 swcan2 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 130
 swcan2 (ics.structures.s_fire_ynet_settings.s_fire_ynet_settings attribute), 135
 swcan2 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 139
 swcan2 (ics.structures.s_pendant_settings.s_pendant_settings attribute), 140
 swcan2 (ics.structures.secu_settings.secu_settings attribute), 160
 swcan2 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 174
 SWCAN_AUTOSWITCH_DISABLED (in module ics.ics), 225
 SWCAN_AUTOSWITCH_DISABLED_RESISTOR_ENABLE (in module ics.ics), 225
 SWCAN_AUTOSWITCH_NO_RESISTOR (in module ics.ics), 225
 SWCAN_AUTOSWITCH_WITH_RESISTOR (in module ics.ics), 225
 swcan_settings (class in ics.structures.swcan_settings), 200
 SWCAN_SETTINGS_SIZE (in module ics.ics), 225
 switchid (ics.structures.s_pluto_general_params.s.s_pluto_general_params attribute), 146
 switchSettings (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 171
 switchSettings (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 181
 swmaster (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 144
 syasyen (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 144
 sydomain (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 144
 sync (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray REPORTED (in module ics.ics), 225

tdmMode (ics.structures.a2_b_monitor_settings.a2_b_monitor_setting.attribute), 89
tdmModeTDM12 (ics.structures.a2_btdm_mode.a2_btdm_mode.termination_enables.attribute), 89
tdmModeTDM16 (ics.structures.a2_btdm_mode.a2_btdm_mode.termination_enables.attribute), 89
tdmModeTDM2 (ics.structures.a2_btdm_mode.a2_btdm_mode.termination_enables.attribute), 89
tdmModeTDM20 (ics.structures.a2_btdm_mode.a2_btdm_mode.termination_enables.attribute), 90
tdmModeTDM24 (ics.structures.a2_btdm_mode.a2_btdm_mode.termination_enables.attribute), 90
tdmModeTDM32 (ics.structures.a2_btdm_mode.a2_btdm_mode.termination_enables.attribute), 90
tdmModeTDM4 (ics.structures.a2_btdm_mode.a2_btdm_mode.termination_enables.attribute), 90
tdmModeTDM8 (ics.structures.a2_btdm_mode.a2_btdm_mode.termination_enables.attribute), 90
temp_interval_ms (ics.structures.rad_reporting_settings.rad_reporting_settings.sradbms_settings.sradbms_settings.attribute), 116
tentSYRELEN (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params.attribute), 144
term_enabled (ics.structures.canterm_settings.canterm_settings.attribute), 196
term_network (ics.structures.canterm_settings.canterm_settings.attribute), 197
termination_enables (ics.structures.s_cyan_settings.s_cyan_settings.attribute), 119
termination_enables (ics.structures.s_ether_badge_settings.s_ether_badge_settings.attribute), 121
termination_enables (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings.attribute), 137
termination_enables (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings.attribute), 139
termination_enables (ics.structures.s_red2_settings.s_red2_settings.attribute), 154
termination_enables (ics.structures.s_vivid_can_settings.s_vivid_can_settings.attribute), 156
termination_enables (ics.structures.scan_hub_settings.scan_hub_setting.attribute), 158
termination_enables (ics.structures.secu_avb_settings.secu_avb_settings.attribute), 158
termination_enables (ics.structures.srad_comet_settings.srad_comet_settings.attribute), 169
termination_enables (ics.structures.srad_epsilon_settings.srad_epsilon_settings.attribute), 171
termination_enables (ics.structures.srad_gigalog_settings.srad_gigalog_settings.attribute), 177
termination_enables (ics.structures.srad_gigastar_settings.srad_gigastar_settings.attribute), 179
termination_enables (ics.structures.srad_jupiter_settings.srad_jupiter_settings.attribute), 181
termination_enables (ics.structures.srada2_b_settings.srada2_b_settings.attribute), 188
termination_enables (ics.structures.svcan412_settings.svcan412_settings.attribute), 189
termination_enables_1 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.attribute), 126
termination_enables_1 (ics.structures.s_fire3_settings.s_fire3_settings.attribute), 130
termination_enables_2 (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.attribute), 126
termination_enables_2 (ics.structures.s_fire3_settings.s_fire3_settings.attribute), 130
text_api (ics.structures.s_cyan_settings.s_cyan_settings.attribute), 119
text_api (ics.structures.s_ether_badge_settings.s_ether_badge_settings.attribute), 121
text_api (ics.structures.s_fire3_flexray_settings.s_fire3_flexray_settings.attribute), 126
text_api (ics.structures.s_fire3_settings.s_fire3_settings.attribute), 130
text_api (ics.structures.s_fire3_settings.s_fire3_settings.attribute), 130
text_api (ics.structures.s_fire_settings.s_fire_settings.attribute), 133
text_api (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings.attribute), 135
text_api (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings.attribute)

attribute), 137
text_api (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_setting attribute), 110
attribute), 139
TimeHardware2 (ics.ics.SpyMessage attribute), 19
text_api (ics.structures.s_pendant_settings.s_pendant_setting attribute), 140
TimeHardware2 (ics.ics.SpyMessageJ1850 attribute), 20
text_api (ics.structures.s_red2_settings.s_red2_settings TimeHardware2 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_ vsb.attribute), 154
attribute), 105
text_api (ics.structures.secu_avb_settings.secu_avb_setting TimeHardware2 (ics.structures.ics_spy_message_long.ics_spy_message_ vsb.attribute), 158
attribute), 107
text_api (ics.structures.secu_settings.secu_settings TimeHardware2 (ics.structures.ics_spy_message_mdio.ics_spy_message_ vsb.attribute), 160
attribute), 109
text_api (ics.structures.sievb_settings.sievb_settings TimeHardware2 (ics.structures.ics_spy_message_vsb.ics_spy_message_ vsb.attribute), 163
attribute), 110
text_api (ics.structures.sobd2_lc_settings.sobd2_lc_setting timestamp_(class in ics.structures.timestamp_), 201
attribute), 164
TimeStampHardwareID (ics.ics.SpyMessage attribute), 201
text_api (ics.structures.sobd2_pro_settings.sobd2_pro_setting tribute), 19
attribute), 166
TimeStampHardwareID (ics.ics.SpyMessageJ1850 attribute), 19
text_api (ics.structures.sobd2_sim_settings.sobd2_sim_setting attribute), 167
TimeStampHardwareID
text_api (ics.structures.srad_comet_settings.srad_comet_settings (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_r attribute), 169
attribute), 105
text_api (ics.structures.srad_epsilon_settings.srad_epsilon_setting TimeStampHardwareID
attribute), 171
TimeStampHardwareID (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 107
text_api (ics.structures.srad_galaxy_settings.srad_galaxy_setting attribute), 174
TimeStampHardwareID
text_api (ics.structures.srad_gigalog_settings.srad_gigalog_setting TimeStampHardwareID
attribute), 177
TimeStampHardwareID (ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute), 109
text_api (ics.structures.srad_gigastar_settings.srad_gigastar_setting TimeStampHardwareID
attribute), 179
TimeStampHardwareID (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 109
text_api (ics.structures.srad_jupiter_settings.srad_jupiter_setting attribute), 181
TimeStampSystemID (ics.ics.SpyMessage attribute), 181
text_api (ics.structures.srad_moon2_settings.srad_moon2_setting 19
attribute), 183
TimeStampSystemID (ics.ics.SpyMessageJ1850 attribute), 183
text_api (ics.structures.srad_pluto_settings.srad_pluto_setting attribute), 184
TimeStampSystemID
text_api (ics.structures.srad_star2_settings.srad_star2_setting (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_r attribute), 186
attribute), 105
text_api (ics.structures.srad_super_moon_settings.srad_super_moon_setting TimeStampSystemID
attribute), 187
TimeStampSystemID (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 107
text_api (ics.structures.svcan412_settings.svcan412_setting TimeStampSystemID
attribute), 196
TimeStampSystemID (ics.structures.ics_spy_message_mdio.ics_spy_message_mdio attribute), 109
text_api (ics.structures.svcan4_settings.svcan4_setting attribute), 198
attribute), 109
time_500us (ics.structures.iso9141_keyword2000_init_step iso9141_keyword2000_init_step
attribute), 112
TimeHardware (ics.ics.SpyMessage attribute), 19
TimeHardware (ics.ics.SpyMessageJ1850 attribute), 19
timeSync (ics.structures.s_cyan_settings.s_cyan_setting
attribute), 20
attribute), 119
TimeHardware (ics.structures.ics_spy_message_flex_ray.timeSync messageflexray.s_fire3 flexray_settings.s_fire3 flexray_settings
attribute), 105
attribute), 126
TimeHardware (ics.structures.ics_spy_message_long.ics_spy_message_long s_fire3 flexray_settings.s_fire3 flexray_settings
attribute), 107
attribute), 130
TimeHardware (ics.structures.ics_spy_message_mdio.ics_spy_message_mdio s_fire3 flex_vnetz_settings.s_fire3 flex_vnetz_settings
attribute), 109
attribute), 137

uart (*ics.structures.secu_settings.secu_settings* attribute), 160
 uart (*ics.structures.sievb_settings.sievb_settings* attribute), 163
 uart2 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 133
 uart2 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 135
 uart2 (*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 141
 uart2 (*ics.structures.secu_settings.secu_settings* attribute), 160
 uart2 (*ics.structures.sievb_settings.sievb_settings* attribute), 163
 uart_get_baudrate () (in module *ics.ics*), 58
 uart_port_config (class *ics.structures.uart_port_config*), 202
 uart_port_data (class *ics.structures.uart_port_data*), 202
 uart_port_port_bytes (class *ics.structures.uart_port_port_bytes*), 202
 uart_read () (in module *ics.ics*), 59
 uart_set_baudrate () (in module *ics.ics*), 59
 uart_settings (class in *ics.structures.uart_settings*), 202
 UART_SETTINGS_SIZE (in module *ics.ics*), 225
 uart_write () (in module *ics.ics*), 59
 UartGetBaudrate () (in module *ics.ics*), 29
 UartRead () (in module *ics.ics*), 29
 UartSetBaudrate () (in module *ics.ics*), 29
 UartWrite () (in module *ics.ics*), 30
 ucConfigMode (*ics.structures.op_eth_settings.op_eth_settings* attribute), 114
 ucInterfaceType (*ics.structures.op_eth_general_settings.op_eth_general_settings* attribute), 114
 uFlags (*ics.structures.op_eth_general_settings.op_eth_general_settings* attribute), 114
 unsytosyth (*ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params* attribute), 144
 unsytotsyth (*ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params* attribute), 144
 unused (*ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device_status* attribute), 103
 unused (*ics.structures.ics_flex_vnet_device_status.ics_flex_vnet_device_status* attribute), 103
 unused (*ics.structures.ics_vcan4_device_status.ics_vcan4_device_status* attribute), 110
 upstreamChannelOffset (*ics.structures.a2_b_monitor_settings.a2_b_monitor_settings* attribute), 89
 usbHostPowerEnabled (*ics.structures.ics_fire2_device_status.ics_fire2_device_status* attribute), 103
 usbSelect (*ics.structures.s_pluto_custom_params.s_pluto_custom_params_s* attribute), 145
 use_dest_ports (*ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s* attribute), 150
 USE_TQ (in module *ics.ics*), 225
 useExternalWifiAntenna (*ics.structures.fire3_linux_settings.fire3_linux_settings* attribute), 97
 using_port_a (*ics.structures.s_wil_connection_settings.s_wil_connection_settings* attribute), 157
 using_port_b (*ics.structures.s_wil_connection_settings.s_wil_connection_settings* attribute), 157

V

valid (*ics.structures.version_report.version_report* attribute), 203
 in validate_hobject () (in module *ics.ics*), 60
 ValidateHObject () (in module *ics.ics*), 30
 in vcan3 (*ics.structures.global_settings.global_settings* attribute), 101
 in vcan3_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 192
 vcan4 (*ics.structures.global_settings.global_settings* attribute), 101
 vcan412 (*ics.structures.global_settings.global_settings* attribute), 101
 vcan41_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 192
 vcan42_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 192
 vcan4_12 (*ics.structures.global_settings.global_settings* attribute), 101
 vcan4_41d (*ics.structures.global_settings.global_settings* attribute), 101
 see also *ics_device_status.ics_device_status* (*ics.structures.ics_device_status.ics_device_status* attribute), 102
 vcan4_41d (*ics.structures.global_settings.global_settings* attribute), 101
 vcan4_41d (*ics.structures.global_settings.global_settings* attribute), 101
 vs_s_pluto_clock_sync_params (*ics.structures.st_chip_versions.st_chip_versions* attribute), 192
 unused (*ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device_status* attribute), 151
 unused (*ics.structures.ics_flex_vnet_device_status.ics_flex_vnet_device_status* attribute), 101
 unused (*ics.structures.ics_vcan4_device_status.ics_vcan4_device_status* attribute), 122
 version (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt* attribute), 141
 version (*ics.structures.s_phy_reg_pkt_hdr.s_phy_reg_pkt_hdr* attribute), 142
 version (*ics.structures.version_report* class in *ics.structures.version_report*), 203

versions (`ics.structures.get_component_versions_response`) WGETCOMPONENTVERSIONRESPONSEMSGS (in module `ics.ics`), 225

videoFormat (`ics.structures.serdescam_settings.serdescam_SETTINGS_FEATURE_DISABLE_USB_CHECK`) (in module `ics.ics`), 225

ving_mirr (`ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_datatypes.serdespoc_settings.serdespoc_settings`) attribute), 162

vividcan (`ics.structures.global_settings.global_settings_vs_netid`) (`ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_attributes`) attribute), 112

vividcan_versions vs_netid (`ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_st_chip_versions.st_chip_versions`) attribute), 193

vlan_bc (`ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_attributes`) attribute), 194

vlan_egress (`ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s`) attribute), 150

vlan_ing (`ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s`) w_bms_manager_reset (class in `ics.structures.w_bms_manager_reset_attributes`), 203

vlan_LookupEntries w_bms_manager_set_lock (class in `ics.structures.w_bms_manager_set_lock_attributes`), 203

vlanID (`ics.structures.s_pluto_l2_address_lookup_entry_s.s_pluto_l2_address_lookup_entry_s`) waitthsync (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params`) attribute), 204

vlanid (`ics.structures.s_pluto_mac_config.s.s_pluto_mac_config`) wbms_gateway_settings (`ics.structures.wbms_gateway_settings.wbms_gateway_attributes`), 204

vlanid (`ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_attributes`) wbms1_canfd_enable (code in `ics.structures.wbms_gateway_settings.wbms_gateway_attributes`), 152

vlan prio (`ics.structures.s_pluto_mac_config.s.s_pluto_mac_config_attributes`) wbms2_network (`ics.structures.wbms_gateway_settings.wbms_gateway_attributes`), 204

vlidimnmin (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_attributes`) WBMS_GATEWAY_NETWORK_DWCAN_01 (in module `ics.ics`), 204

vlidinmax (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_attributes`) WBMS_GATEWAY_NETWORK_DWCAN_02 (in module `ics.ics`), 204

vlidout (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_attributes`) WBMS_GATEWAY_NETWORK_NONE (in module `ics.ics`), 204

vlidselect (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_attributes`) WBMS_GATEWAY_NETWORK_UDP_MULTICAST (in module `ics.ics`), 204

vllupformat (`ics.structures.s_pluto_general_params.s.s_pluto_general_params_attributes`) wbms_gateway_settings (class in `ics.ics`), 225

vllupformat0 (`ics.structures.s_pluto_vl_lookup_entry.s.s_pluto_vl_lookup_entry_attributes`) wbms_gateway_settings (`ics.structures.wbms_gateway_settings.wbms_gateway_attributes`), 204

vllupformat1 (`ics.structures.s_pluto_vl_lookup_entry.s.s_pluto_vl_lookup_entry_attributes`) wbms_manager_reset () (in module `ics.ics`), 60

vlmarker (`ics.structures.s_pluto_general_params.s.s_pluto_general_params_attributes`) WBMS_GATEWAY_WIRELESS_LOCK () (in module `ics.ics`), 60

vlmask (`ics.structures.s_pluto_general_params.s.s_pluto_general_params_attributes`) WBMS_MANAGER_RESET (code in `ics.structures.wbms_gateway_settings.wbms_gateway_attributes`), 189

vmemb_port (`ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_attributes`) WBMS_MANAGER_WRITELOCK (code in `ics.structures.wbms_gateway_settings.wbms_gateway_attributes`), 157

vnetBits (`ics.structures.s_fire_settings.s.fire_settings_attributes`) wBMSManagerReset () (in module `ics.ics`), 60

vnetBits (`ics.structures.s_fire_vnet_settings.s.fire_vnet_settings_attributes`) wBMSManagerWriteLock () (in module `ics.ics`), 60

WIFI_ANTENNA_EXTERNAL (*in module ics.ics*), 225
WIFI_ANTENNA_INTERNAL (*in module ics.ics*), 225
WIFI_CONNECTION (*in module ics.ics*), 225
will_nwk_metadata_buff_count
 (*ics.structures.sradbms_settings.sradbms_settings*
 attribute), 189
will_nwk_metadata_buff_count
 (*ics.structures.sradbms_settings.sradbms_settings*
 attribute), 189
will_config (*ics.structures.sradbms_settings.sradbms_settings*
 attribute), 189
word (*ics.structures.scan_sleep_id.scan_sleep_id*
 attribute), 158
write_jupiter_firmware () (*in module ics.ics*),
 61
write_sdcard () (*in module ics.ics*), 61
WriteEnable (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt*
 attribute), 141
WriteJupiterFirmware () (*in module ics.ics*), 30
WriteSDCard () (*in module ics.ics*), 30

Z

zero0 (*ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway_settings*
 attribute), 139