
python_ics Documentation

Release 912.4

David Rebbe

Aug 16, 2023

Contents

1	Whats New?	3
1.1	ISO 15765-2	3
1.2	Settings	4
1.3	PyInstaller	4
2	Versioning Information	7
2.1	v903	7
2.2	Older Versions:	7
3	Installation on Windows	9
3.1	Building from source	9
3.2	Intrepid icsneo40 Library	9
4	Installation on Linux	11
4.1	Fedora Dependencies (FC28)	11
4.2	Debian/Ubuntu Dependencies	11
4.3	libicsneo library	11
4.4	Others (Required dependencies)	11
4.5	Installation	12
5	Getting Started	13
6	Examples	15
6.1	Opening a device	15
6.2	Transmitting and Receiving a CAN message	15
6.3	ISO 15765-2 Example	15
6.4	Missing an example?	16
7	Module Documentation	17
8	Module Functions	61
9	Module Structures	87
10	Module Variables	191
	Python Module Index	211

Intrepid Control Systems, Inc. open source Python module for interfacing to Intrepid hardware. Basic knowledge of using and installing Python modules is assumed. Please see <https://docs.python.org/3/installing/index.html> for documentation on how to install Python modules.

This module is essentially just a wrapper around icsneo40.dll. For more documentation please visit neoVI DLL Documentation under <https://intrepidcs.com/support/support-resources/>

CHAPTER 1

Whats New?

v903+ is a new release that implements features that break existing API in some areas.

1.1 ISO 15765-2

old naming conventions have been updated to reflex closer to the actual codebase.

```
# Old:
tx_msg = ics.CmISO157652TxMessage()
rx_msg = ics.CmISO157652RxMessage()

# New:
tx_msg = ics.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message()
rx_msg = ics.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message()
```

`ics.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message()` data structure is now a `ctypes.c_ubyte` array instead of a python list.

```
# Old:
msg.data = [x for x in range(number_of_bytes)]

# New:
my_data = [x for x in range(number_of_bytes)]
msg.data = (ctypes.c_ubyte*len(msg.data))(*my_data)

>>> msg.data
<ics.structures.st_cm_iso157652_tx_message.c_ubyte_Array_4096 object at 0x0000023E534BE940>
```

1.2 Settings

v903 and up have converted over to a new auto generation of `icsnVC40.h`. This enables faster support for newer Intrepid devices and less error prone. With this switch we have moved to using `ics.s_device_settings`.

```
# Old behavior:
device = ics.open_device()
settings = ics.get_device_settings(device)
# settings is a Vcan3Settings type
settings.can1.Baudrate = 1
ics.set_device_settings(device, settings)

# New behavior
device = ics.open_device()
settings = ics.get_device_settings(device)
# settings is a s_device_settings type
settings.vcan3.can1.Baudrate = 1
ics.set_device_settings(device, settings)
```

1.3 PyInstaller

Due to the added complexity underneath when building PyInstaller `hidden_imports.py` should be used now in your spec script:

```
# -*- mode: python ; coding: utf-8 -*-

import ics

block_cipher = None

a = Analysis(['test.py'],
             pathex=['.'],
             binaries=[],
             datas=[],
             hiddenimports=ics.hiddenimports.hidden_imports,
             hookspath=[],
             runtime_hooks=[],
             excludes=[],
             win_no_prefer_redirects=False,
             win_private_assemblies=False,
             cipher=block_cipher,
             noarchive=False)
pyz = PYZ(a.pure, a.zipped_data,
          cipher=block_cipher)
exe = EXE(pyz,
          a.scripts,
          [],
          exclude_binaries=True,
          name='test',
          debug=False,
          bootloader_ignore_signals=False,
          strip=False,
          upx=True,
```

(continues on next page)

(continued from previous page)

```
        console=True )
coll = COLLECT(exe,
               a.binaries,
               a.zipfiles,
               a.datas,
               strip=False,
               upx=True,
               upx_exclude=[],
               name='test')
```

Versioning Information

Minor differences can occur between different icsnVC40.h versions. These differences are usually just structures and constant differences. Below is a list of how the python_ics version correlates to the icsnVC40.h version:

2.1 v903

Starting with 903, python_ics module will now match official upstream version releases.

```
pip install 'python_ics>=5.0,<904.0' --force-reinstall
```

Note: Refer to platform specific installation if not on Windows

2.2 Older Versions:

- **v802** `pip install 'python_ics>=2.0,<3.0' --force-reinstall`

Note: Refer to platform specific installation if not on Windows

- **v803** `pip install 'python_ics>=3.0,<4.0' --force-reinstall`

Note: Refer to platform specific installation if not on Windows

- **v900** `pip install 'python_ics>=4.0,<5.0' --force-reinstall`

Note: Refer to platform specific installation if not on Windows

Installation on Windows

PyPi provides binary packages for Windows. You can simply install the `python_ics` module by running the following command:

```
pip install python_ics
```

Note: `pip.exe` is usually located under the `Scripts` directory under the Python installation directory.

3.1 Building from source

Building from source on windows is not usually need so it won't really be covered here in detail. As a starting point you'll need to match the compiler version used to build the official Python binaries (MSVC). If the build environment is setup correctly, you should be able to run `python setup.py build` like usual.

3.2 Intrepid icsneo40 Library

`python_ics` module looks for `icsneo40.dll` in the normal windows DLL search paths. The module will throw an exception if its not found.

Installation on Linux

`python_ics` does not provide binaries for linux distributions so we will have to compile from source. This can be easily achieved by utilizing Python's PIP. First we need to make sure we have some base packages installed.

4.1 Fedora Dependencies (FC28)

```
sudo dnf install redhat-rpm-config gcc g++ python3-devel clang  
clang-tools-extra
```

4.2 Debian/Ubuntu Dependencies

```
sudo apt install build-essential python-dev clang-format
```

4.3 libicsneo library

The legacy version of libicsneo library (`libicsneolegacy.so`) is required, see the specific repo for details: <https://github.com/intrepidcs/libicsneo>

4.4 Others (Required dependencies)

- GCC
- G++
- Python Development packages (We Need to link to `Python.h`)
- Clang (llvm)
- clang-format

4.5 Installation

After dependencies are installed we can run the following pip command:

```
pip install python_ics
```

Note: A lot of distributions have Python 2 and 3 installed side by side. As of this writing without a version suffix the commands still default to version 2 of the Python binaries. In order to utilize the Python 3 binaries you must append a 3 after the binary names (python3 and pip3 instead of just python and pip).

CHAPTER 5

Getting Started

Please see https://github.com/intrepidcs/python_ics/tree/master/examples for simple examples on how to use this module. Most function documentation has a simple example on how its intended to be used. Every function was designed to be as close as possible to its C counterpart unless it was deemed to make the function more pythonic in nature.

For those experienced with the C API `ics.open_device (icsneoOpenNeoDevice())` behavior has been changed the most (no parameters makes it auto utilize `ics.find_devices (icsneoFindNeoDevices())` and open the first device). Also since python is a object oriented language the module utilizes this and auto cleans up device handles when going out of scope so there is usually no need to call `ics.close_device()`.

Examples can be found at https://github.com/intrepidcs/python_ics/tree/master/examples

For extra information on data structures and underlying functionality, please visit neoVI DLL Documentation under <https://intrepidcs.com/support/support-resources/>

6.1 Opening a device

The `open_device_example.py` example shows how to successfully open and close an Intrepid device.

6.2 Transmitting and Receiving a CAN message

The following examples show how to interact with CAN messages on an Intrepid device.

- `transmit_can_example.py`: Basic example showing how to transmit and receive standard CAN frame
- `transmit_can_xtd_example.py`: Builds off of the CAN example and adds extended Arbitration ID attributes
- `canfd_transmit_example.py`: Bare minimum example on how to transmit over CANFD.

6.3 ISO 15765-2 Example

The `iso15765_example.py` example shows how to setup basic ISO 15765-2 receive filters and transmitting an ISO 15765-2 message.

After opening an Intrepid device `ics.iso15765_enable_networks` should be called to enable ISO 15765-2.

Receive filtering can be established by passing a custom `ics.CmISO157652RxMessage()` to `ics.iso15765_receive_message()`.

Similarly transmitting an ISO 15765-2 frame can be accomplished by passing a custom `ics.CmISO157652TxMessage()` to `ics.iso15765_transmit_message()`.

6.4 Missing an example?

Need an example on something that isn't covered here? Please submit an issue on [github](#) or feel free to send over a Pull Request of your own.

Module Documentation

Python C Code module for interfacing to the icsneo40 dynamic library. Code tries to respect PEP 8 (<http://python.org/dev/peps/pep-0008>). Function naming convention does not follow the tradition c style icsneo40 naming convention as pyics module name acts as the namespace (icsneo portion of the function) and function names are suppose to be lowercase with underscores instead of mixedCase like icsneo API.

C API can be mimiced almost identically by doing the following:

```
>>> import ics as icsneo
>>> devices = icsneo.FindNeoDevices()
>>> for device in devices:
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

Recommended *Python* way by doing the following:

```
>>> import ics
>>> devices = ics.find_devices()
>>> for device in devices:
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

It should be noted that `ics.ics.NeoDevice` is used a little bit differently than the C API. `ics.ics.NeoDevice` contains two extra members: `ics.ics.NeoDevice.AutoHandleClose` and `ics.ics.NeoDevice._Handle`

The handle normally returned from `icsneoOpenNeoDevice()` is stored inside `_Handle` and setting `AutoHandleClose` to `True` (Default) will automatically close the handle when the `ics.ics.NeoDevice` goes out of scope.

Installation:

```
pip install python_ics
```

<https://pypi.python.org/pypi/python-ics>

exception ics.ics.ArgumentError

Bases: Exception

exception ics.ics.RuntimeError

Bases: Exception

class ics.ics.NeoDevice

Bases: object

NeoDevice object

AutoHandleClose

When NeoDevice is freed the handle will automatically be closed, if true.

DeviceType

Handle

IsOpen

This contains the handle returned from icsneoOpenDevice() API. If uncertain, don't use this.

MaxAllowedClients

Name

String describing DeviceType, extension to Python api only.

NumberOfClients

SerialNumber

class ics.ics.SpyMessage

Bases: object

SpyMessage object

AckBytes

ArbIDOrHeader

Data

DescriptionID

Not Used

ExtraDataPtr

ExtraDataPtrEnabled

MessagePieceID

Not Used

MiscData

NetworkID

This value is used to identify which network this message was received on.

NetworkID2

This value is used to identify which network this message was received on.

NodeID

Not Used

NumberBytesData

Holds the number of bytes in the Data(1 to 8) array or the number of bytes in a CAN remote frame (The DLC).

NumberBytesHeader

Used for J1850/ISO messages. It indicates how many bytes are stored in the Header(1 to 4) array.

Protocol

Valid values are SPY_PROTOCOL_CAN, SPY_PROTOCOL_J1850VPW, and SPY_PROTOCOL_ISO9141.

StatusBitField**StatusBitField2****StatusBitField3****StatusBitField4****TimeHardware**

Hardware time stamp. The TimeStamp is reset on device open

TimeHardware2

Hardware time stamp. The TimeStamp is reset on device open

TimeStampHardwareID

This is an identifier of what type of hardware timestamp is used. Since neoVI's timestamp is always the same, this doesn't change.

TimeStampSystemID

This is an identifier of what type of system timestamp is used. Since WIN32 neoVI's timestamp is always the same, from the timeGetTime API, this doesn't change.

TimeSystem

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

TimeSystem2

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

noExtraDataPtrCleanup

Tells Python to not clean up ExtraDataPtrMemory, If this is enabled. Ignore, if unsure.

class ics.ics.SpyMessageJ1850

Bases: object

SpyMessageJ1850 object

AckBytes**Data****DescriptionID**

Not Used

ExtraDataPtr**ExtraDataPtrEnabled****Header****MessagePieceID**

Not Used

MiscData**NetworkID**

This value is used to identify which network this message was received on.

NetworkID2

This value is used to identify which network this message was received on.

NodeID

Not Used

NumberBytesData

Holds the number of bytes in the Data(1 to 8) array or the number of bytes in a CAN remote frame (The DLC).

NumberBytesHeader

Used for J1850/ISO messages. It indicates how many bytes are stored in the Header(1 to 4) array.

Protocol

Valid values are SPY_PROTOCOL_CAN, SPY_PROTOCOL_J1850VPW, and SPY_PROTOCOL_ISO9141.

StatusBitField**StatusBitField2****StatusBitField3****StatusBitField4****TimeHardware**

Hardware time stamp. The TimeStamp is reset on device open

TimeHardware2

Hardware time stamp. The TimeStamp is reset on device open

TimeStampHardwareID

This is an identifier of what type of hardware timestamp is used. Since neoVI's timestamp is always the same, this doesn't change.

TimeStampSystemID

This is an identifier of what type of system timestamp is used. Since WIN32 neoVI's timestamp is always the same, from the timeGetTime API, this doesn't change.

TimeSystem

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

TimeSystem2

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

noExtraDataPtrCleanup

Tells Python to not clean up ExtraDataPtrMemory, If this is enabled. Ignore, if unsure.

```
ics.ics.ClosePort()
```

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.close_device()` method.

```
ics.ics.EnableBusVoltageMonitor()
```

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_bus_voltage_monitor()` method.

```
ics.ics.EnableDOIPLine()
```

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.enable_doip_line()* method.

`ics.ics.EnableNetworkCom()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.enable_network_com()* method.

`ics.ics.FindNeoDevices()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.find_devices()* method.

`ics.ics.FirmwareUpdateRequired()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.firmware_update_required()* method.

`ics.ics.ForceFirmwareUpdate()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.force_firmware_update()* method.

`ics.ics.GenericAPIGetStatus()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.generic_api_get_status()* method.

`ics.ics.GenericAPIReadData()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.generic_api_read_data()* method.

`ics.ics.GenericAPISendCommand()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.generic_api_send_command()* method.

`ics.ics.GetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_active_vnet_channel()` method.

`ics.ics.GetAllChipVersions()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_all_chip_versions()` method.

`ics.ics.GetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_enabled()` method.

`ics.ics.GetBackupPowerReady()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_ready()` method.

`ics.ics.GetBusVoltage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_bus_voltage()` method.

`ics.ics.GetDLLFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_firmware_info()` method.

`ics.ics.GetDLLVersion()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_version()` method.

`ics.ics.GetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_settings()` method.

`ics.ics.GetDeviceStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_status()` method.

`ics.ics.GetErrorMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_error_messages()` method.

`ics.ics.GetGPTPStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_gptp_status()` method.

`ics.ics.GetHWFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_hw_firmware_info()` method.

`ics.ics.GetLastAPIError()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_last_api_error()` method.

`ics.ics.GetMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_messages()` method.

`ics.ics.GetPCBSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_pcb_serial_number()` method.

`ics.ics.GetPerformanceParameters()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_performance_parameters()` method.

`ics.ics.GetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_rtc()` method.

`ics.ics.GetSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_serial_number()` method.

`ics.ics.GetTimeStampForMsg()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_timestamp_for_msg()` method.

`ics.ics.ISO15765_DisableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_disable_networks()` method.

`ics.ics.ISO15765_EnableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_enable_networks()` method.

`ics.ics.ISO15765_ReceiveMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.ics.ISO15765_TransmitMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.ics.IsDeviceFeatureSupported()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.is_device_feature_supported()` method.

`ics.ics.LoadDefaultSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.load_default_settings()`

method.

`ics.ics.OpenNeoDevice()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.open_device()` method.

`ics.ics.ReadJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_jupiter_firmware()` method.

`ics.ics.ReadSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_sdcard()` method.

`ics.ics.RequestDiskDetails()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_details()` method.

`ics.ics.RequestDiskFormat()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format()` method.

`ics.ics.RequestDiskFormatCancel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format_cancel()` method.

`ics.ics.RequestDiskFormatProgress()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_format_progress()` method.

`ics.ics.RequestEnterSleepMode()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.request_enter_sleep_mode()` method.

`ics.ics.ScriptClear()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_clear()` method.

`ics.ics.ScriptGetFBlockStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_fblock_status()` method.

`ics.ics.ScriptGetScriptStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_status()` method.

`ics.ics.ScriptGetScriptStatusEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_script_status()` method.

`ics.ics.ScriptLoad()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_load()` method.

`ics.ics.ScriptReadAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_app_signal()` method.

`ics.ics.ScriptReadRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_rx_message()` method.

`ics.ics.ScriptReadTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_tx_message()` method.

`ics.ics.ScriptStart()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start()` method.

`ics.ics.ScriptStartFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start_fblock()` method.

`ics.ics.ScriptStop()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop()` method.

`ics.ics.ScriptStopFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop_fblock()` method.

`ics.ics.ScriptWriteAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_app_signal()` method.

`ics.ics.ScriptWriteRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_rx_message()` method.

`ics.ics.ScriptWriteTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_tx_message()` method.

`ics.ics.SetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_active_vnet_channel()` method.

`ics.ics.SetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_backup_power_enabled()` method.

`ics.ics.SetBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate()` method.

`ics.ics.SetBitRateEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate_ex()` method.

`ics.ics.SetContext()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_context()` method.

`ics.ics.SetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_device_settings()` method.

`ics.ics.SetFDBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_fd_bit_rate()` method.

`ics.ics.SetLedProperty()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_led_property()` method.

`ics.ics.SetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_rtc()` method.

`ics.ics.SetReflashDisplayCallback()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_reflash_callback()` method.

`ics.ics.StartDHCPServer()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.start_dhcp_server()` method.

`ics.ics.StopDHCPServer()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.stop_dhcp_server()` method.

`ics.ics.TxMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.transmit_messages()` method.

`ics.ics.UartGetBaudrate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_get_baudrate()` method.

`ics.ics.UartRead()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_read()` method.

`ics.ics.UartSetBaudrate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_set_baudrate()` method.

`ics.ics.UartWrite()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_write()` method.

`ics.ics.ValidateHObject()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.validate_hobject()` method.

`ics.ics.WriteJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_jupiter_firmware()` method.

`ics.ics.WriteSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_sdcard()` method.

`ics.ics.base36enc(serial)`

Converts a decimal serial number to base36.

Args: serial (int): serial number.

Raises: `ics.ics.RuntimeError`

Returns: Str: Serial Number

```
>>> ics.base36enc(device.SerialNumber)
CY0024
```

`ics.ics.close_device(device)`

Closes the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Error Count (int)

```
>>> for device in ics.find_devices():
...     ics.open_device(device)
...     # Do something with the device...
...     ics.close_device(device)
... 
```

Note: `ics.ics.NeoDevice` will automatically close the device when it goes out of scope.

`ics.ics.coremini_clear(device, location)`

Clears the CoreMini into the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

location (int): Accepts `ics.ics.SCRIPT_LOCATION_FLASH_MEM`, `ics.ics.SCRIPT_LOCATION_SDCARD`, or `ics.ics.SCRIPT_LOCATION_VCAN3_MEM`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_clear(device, ics.SCRIPT_LOCATION_SDCARD)
```

`ics.ics.coremini_get_fblock_status(device, index)`

Gets the status of a Coremini Function Block at *index* on *device*.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

index (int): Index of the function block.

Raises: *ics.ics.RuntimeError*

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_get_fblock_status(device, 1)
True
```

ics.ics.coremini_get_status (device)

Gets the status of the CoreMini in the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: True if running, otherwise False.

```
>>> device = ics.open_device()
>>> ics.coremini_get_status(device)
>>>
```

ics.ics.coremini_load (device, coremini, location)

Loads the CoreMini into the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

coremini (str/tuple): Use string to load from file, Use Tuple if file data.

location (int): Accepts *ics.ics.SCRIPT_LOCATION_FLASH_MEM*, *ics.ics.SCRIPT_LOCATION_SDCARD*, or *ics.ics.SCRIPT_LOCATION_VCAN3_MEM*

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_load(device, 'cmvspy.vs3cmb', ics.SCRIPT_LOCATION_SDCARD)
```

ics.ics.coremini_read_app_signal (device, index)

Gets the value of a Coremini application signal at *index* on *device*.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

index (int): Index of the application signal.

Raises: *ics.ics.RuntimeError*

Returns: float on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_read_app_signal(device, 1)
52
```

ics.ics.coremini_read_rx_message (device, index, j1850=False)

Gets the value of a Coremini Message at *index* on *device*.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

index (int): Index of the application signal.

j1850 (bool): Use *ics.ics.SpyMessageJ1850* instead.

Raises: `ics.ics.RuntimeError`

Returns: `ics.ics.SpyMessage` Success.

```
>>> device = ics.open_device()
>>> msg = ics.coremini_read_tx_message(device, 0)
```

`ics.ics.coremini_read_tx_message(device, index, j1850=False)`

Gets the value of a Coremini Message at *index* on device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

index (int): Index of the application signal.

j1850 (bool): Use `ics.ics.SpyMessageJ1850` instead.

Raises: `ics.ics.RuntimeError`

Returns: `ics.ics.SpyMessage` Success.

```
>>> device = ics.open_device()
>>> msg = ics.coremini_read_tx_message(device, 0)
```

`ics.ics.coremini_start(device, location)`

Starts the CoreMini into the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

location (int): Accepts `ics.ics.SCRIPT_LOCATION_FLASH_MEM`, `ics.ics.SCRIPT_LOCATION_SDCARD`, or `ics.ics.SCRIPT_LOCATION_VCAN3_MEM`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_start(device, ics.SCRIPT_LOCATION_SDCARD)
```

`ics.ics.coremini_start_fblock(device, index)`

Starts a Coremini Function Block at *index* on device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

index (int): Index of the function block.

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_start_fblock(device, 1)
```

`ics.ics.coremini_stop(device)`

Stops the CoreMini into the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_stop(device)
```

`ics.ics.coremini_stop_fblock(device, index)`
 Stops a Coremini Function Block at *index* on *device*.

Args: *device* (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
index (int): Index of the function block.

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_stop_fblock(device, 1)
```

`ics.ics.coremini_write_app_signal(device, index, value)`
 Sets the value of a Coremini application signal at *index* on *device*.

Args: *device* (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
index (int): Index of the application signal.
value (float): New value of the application signal.

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_write_app_signal(device, 1, 52)
>>>
```

`ics.ics.coremini_write_rx_message(device, index, TODO)`
 TODO

`ics.ics.coremini_write_tx_message(device, index, msg)`
 TODO

`ics.ics.create_neovi_radio_message(Relay1, Relay2, Relay3, Relay4, Relay5, LED6, LED5, MSB_report_rate, LSB_report_rate, analog_change_report_rate, relay_timeout)`

Python API only. Generates data bytes for use with neoVI RADI/O CAN Messages

Kwargs: *Relay1* (boolean): Enable/Disable Relay1

Relay2 (boolean): Enable/Disable Relay2

Relay3 (boolean): Enable/Disable Relay3

Relay4 (boolean): Enable/Disable Relay4

Relay5 (boolean): Enable/Disable Relay5

LED5 (boolean): Enable/Disable LED5

LED6 (boolean): Enable/Disable LED6

MSB_report_rate (int): MSB Report Rate in ms (0-255)

LSB_report_rate (int): LSB Report Rate in ms (0-255)

analog_change_report_rate (int): Analog change report rate

relay_timeout (int): Relay Timeout (0-255)*255ms

Returns:

Tuple of data bytes for use with `ics.ics.SpyMessage`

Raises: `ics.ics.RuntimeError`

```
>>> msg = ics.SpyMessage()
>>> msg.Data = ics.create_neovi_radio_message(Relay1=True, Relay4=False,
↳ LED6=True, MSB_report_rate=10)
>>> msg.Data
(65, 10, 0, 0, 0)
```

`ics.ics.disk_format(device)`

Starts disk formatting on the device.

Args: `device` (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> details = ics.get_disk_details(d)
>>> details. = ics.get_disk_details(d)
>>> ics.disk_format(d, details)
>>>
```

`ics.ics.disk_format_cancel(device)`

Cancel in progress disk formatting on the device.

Args: `device` (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> ics.disk_format(d, details)
>>> ics.disk_format_cancel(d)
>>>
```

`ics.ics.enable_bus_voltage_monitor(device, enable, reserved)`

Enable or disable bus voltage monitoring.

Args: `device` (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

`enable` (bool): int

`reserved` (int): int: Optional. Should be set to zero. Don't set, if unsure.

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_bus_voltage_monitor(d, 1)
>>>
```

`ics.ics.enable_doip_line(device, enable)`

Activate or De-activate DOIP Line.

Args: `device` (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

`enable` (bool): bool

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_doip_line(d, True)
>>>
```

`ics.ics.enable_network_com(device, enable, net_id)`

Enable or disable network communication.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

enable (bool): bool

net_id (int): int: Optional. If left blank, disables/enables all networks.

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_network_com(d, True)
>>>
```

`ics.ics.find_devices(device_type=ics.ics.NEODEVICE_ALL)`

Finds all connected devices and returns a tuple of `ics.ics.NeoDevice` for use in `ics.ics.open_device()`

Args: device_type (int): Accepts `ics.ics.NEODEVICE_*` Macros

New in 3.0 (803):

device_types (List/Tuple): Accepts a Container of `ics.ics.NEODEVICE_*` Macros

network_id (int): OptionsFindNeoEx.CANOptions.iNetworkID. Usually `ics.NETID_CAN`, if needed

Raises: `ics.ics.RuntimeError`

Returns: Tuple of `ics.ics.NeoDevice` for use in `ics.ics.open_device()`

```
>>> for device in ics.find_devices():
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

New in 3.0 (803):

```
>>> for device in ics.find_devices([ics.NEODEVICE_FIRE, ics.NEODEVICE_VCAN3]):
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

`ics.ics.firmware_update_required(device)`

Determines if the device firmware needs flashing.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

```
>>> ics.force_firmware_update(device)
True
```

`ics.ics.force_firmware_update(device)`

Forces the device to flash firmware.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

```
>>> ics.force_firmware_update(device)
True
```

`ics.ics.generic_api_get_status(device, api_index, instance_index)`

Reads data in a generic way.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

api_index (int): api_index.

instance_index (int): instance_index.

Raises: *ics.ics.RuntimeError*

Returns: tuple of (int): (functionIndex, callbackError, finishedProcessing)

`ics.ics.generic_api_read_data(device, api_index, instance_index[, length])`

Reads data in a generic way.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

api_index (int): api_index.

instance_index (int): instance_index.

function_index (int): function_index.

length (int): (optional) Length of the data to read. defaults to *GENERIC_API_DATA_BUFFER_SIZE*

Raises: *ics.ics.RuntimeError*

Returns: tuple of (functionIndex, data)

`ics.ics.generic_api_send_command(device, api_index, instance_index, function_index, data)`

Sends a command in a generic way.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

api_index (int): api_index.

instance_index (int): instance_index.

function_index (int): function_index.

data (bytes): Data to be passed in.

Raises: *ics.ics.RuntimeError*

Returns: functionError(int): functionError.

`ics.ics.get_active_vnet_channel(device)`

Gets active vnet channel for the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: `ics.ics.RuntimeError`

Returns: Int: Returns active vnet channel.

`ics.ics.get_all_chip_versions(device, api_index, instance_index)`

Get all the chip (firmware) versions of the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: `ics.structures.st_chip_versions.st_chip_versions` (`ics.structures.st_chip_versions.st_chip_versions`)

`ics.ics.get_backup_power_enabled(device)`

Returns the device backup power enabled for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.get_backup_power_ready(device)`

Returns the device backup power is ready for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.get_bus_voltage(device, reserved)`

Reads bus voltage. (`ics.ics.enable_bus_voltage_monitor`) needs to be called first.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

reserved (int): int: Optional. Should be set to zero. Don't set, if unsure.

Raises: `ics.ics.RuntimeError`

Returns: Int: value returned is in mV.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_bus_voltage_monitor(d, 1)
>>> ics.get_bus_voltage(d)
12000
>>>
```

`ics.ics.get_device_settings(device, device_type, vnet_slot)`

Gets the settings in the device. vnet_slot defaults to `ics.ics.PlasmaIonVnetChannelMain`

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

device_type (EDeviceSettingsType): Optional: Overrides default device settings type. Defaults to '-1'

vnet_slot (PlasmaIonVnetChannelMain): Optional: Defaults to PlasmaIonVnetChannelMain, Used only for PLASMA/ION Devices.

Raises: `ics.ics.RuntimeError`

Returns: `ics.ics.device_settings`

```
>>> d = ics.open_device()
>>> d.Name
'neoVI ION'
>>> d.SerialNumber
404444
>>> s = ics.get_device_settings(d)
>>> s.DeviceSettingType
2
>>> s.cyan
<ics.CyanSettings object at 0x01E61B40>
>>> s.cyan.canfd1.FDMode
4
>>> s2.cyan
<ics.CyanSettings object at 0x02B113C8>
>>> s2 = ics.get_device_settings(d, -1, ics.PlasmaIonVnetChannelA)
>>> s2.DeviceSettingType
2
>>> s2.cyan.canfd1.FDMode
4
```

ics.ics.get_device_status (*device*)

Returns the device status.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: (ics.ics.ics_device_status).

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.get_device_status(d)
>>> status.fire2Status.ethernetActivationLineEnabled
0
```

ics.ics.get_disk_details (*device*)

Returns the device disk details.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: (ics.ics.srad_gigalog_disk_details).

```
>>> import ics
>>> d = ics.open_device()
>>> details = ics.get_disk_details(d)
>>> details.structure.options
>>>
```

ics.ics.get_disk_format_progress (*device*)

Returns the device disk formatting progress.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: (ics.ics.srad_gigalog_disk_format_progress).

```
>>> import ics
>>> d = ics.open_device()
>>> d = ics.disk_format(d, details)
>>> progress = ics.get_disk_format_progress(d)
>>> progress.sectorsRemaining
>>>
```

`ics.ics.get_dll_firmware_info(device)`

Returns the DLL firmware info for the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: (*ics.ics.st_api_firmware_info*)

```
>>> device = ics.open_device()
>>> info = ics.get_dll_firmware_info(device)
>>> info.iAppMajor
7
>>> info.iAppMinor
55
>>>
```

`ics.ics.get_dll_version(device)`

Gets the DLL version.

Args: None

Raises: *ics.ics.RuntimeError*

Returns: Int: DLL Version

```
>>> ics.get_dll_version()
700
```

`ics.ics.get_error_messages(device[, j1850, timeout])`

Gets the error message(s) on the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: list of tuple`s. :class:`tuple` contents: (error_number, description_short, description_long, severity, restart_needed)

```
>>> device = ics.open_device()
>>> errors = ics.get_error_messages(device)
```

`ics.ics.get_gptp_status(device)`

Gets the gPTP Status from the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: *ics.structures.gptp_status.gptp_status* (*ics.structures.gptp_status.gptp_status*)

`ics.ics.get_hw_firmware_info(device)`

Returns the device firmware info for the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: (*ics.ics.st_api_firmware_info*)

```
>>> device = ics.open_device()
>>> info = ics.get_hw_firmware_info(device)
>>> info.iAppMajor
7
>>> info.iAppMinor
55
>>>
```

ics.ics.get_last_api_error (*device*)

Gets the error message from the last API call.

Args: *device* (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Tuple: (error, description short, description long, severity, restart needed)

```
>>> device = ics.open_device()
>>> try:
...     msg = ics.coremini_read_tx_message(device, 0)
... except ics.RuntimeError as ex:
...     print(ex)
...     print(ics.get_last_api_error(device))
...
Error: coremini_read_tx_message(): icsneoScriptReadTxMessage() Failed
(224, 'Invalid Message Index for script.', 'Invalid Message Index for script.
↳', 16, 0)
```

ics.ics.get_library_path ()

ics.ics.get_messages (*device* [, *j1850*, *timeout*])

Gets the message(s) on the device.

Args: *device* (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

j1850 (bool): Return *ics.ics.SpyMessageJ1850* instead.

timeout (float): Optional timeout to wait for messages in seconds (0.1 = 100ms).

Raises: *ics.ics.RuntimeError*

Returns: tuple of two items. First item is a tuple of *ics.ics.SpyMessage* and second is the error count.

```
>>> device = ics.open_device()
>>> messages, errors = ics.get_messages(device)
>>> len(messages)
14
>>> hex(messages[0].ArbIDOrHeader)
'0x160'
>>> messages[0].Data
(36, 11, 11, 177, 37, 3, 11, 199)
>>> errors
0
```

ics.ics.get_pcb_serial_number (*device*)

Gets the unique PCB serial number of the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: (str): PCB Serial Number

```
>>> import ics
>>> d = ics.open_device()
>>> pcb_sn = ics.get_pcb_serial_number(d)
>>>
```

ics.ics.get_performance_parameters (device)

Gets the Performance Parameters on *device*.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Tuple on Success: (buffer count, buffer max, overflow count, reserved, reserved, reserved, reserved, reserved)

```
>>> device = ics.open_device()
>>> ics.get_performance_parameters(device)
(0, 24576, 0, 0, 0, 0, 0, 0)
```

ics.ics.get_rtc (device)

Gets the Real-Time Clock of the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Tuple: (datetime.datetime object, offset in seconds)

```
>>> device = ics.open_device()
>>> ics.get_rtc(device)
(datetime.datetime(2014, 9, 10, 17, 45, 45), 3)
```

ics.ics.get_script_status ()

Accepts a *ics.ics.NeoDevice*, exception on error. Returns a list of values of what ulParameters would hold

ics.ics.get_serial_number (device)

Gets the serial number out of the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Int: Serial Number Version

```
>>> ics.get_serial_number(device)
53123
```

ics.ics.get_timestamp_for_msg (device, msg)

Calculates the timestamp for a message.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

msg (*ics.ics.SpyMessage*): *ics.ics.SpyMessage*

Raises: *ics.ics.RuntimeError*

Returns: Float: Timestamp for the message.

```
>>> import ics
>>> d = ics.open_device()
>>> msgs, error_count = ics.get_messages(d)
>>> ics.get_timestamp_for_msg(d, msgs[0])
354577568.9145524
```

`ics.ics.icsneoClosePort()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.close_device()` method.

`ics.ics.icsneoEnableBusVoltageMonitor()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_bus_voltage_monitor()` method.

`ics.ics.icsneoEnableDOIPLine()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_doip_line()` method.

`ics.ics.icsneoEnableNetworkCom()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_network_com()` method.

`ics.ics.icsneoFindNeoDevices()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.find_devices()` method.

`ics.ics.icsneoFirmwareUpdateRequired()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.firmware_update_required()` method.

`ics.ics.icsneoForceFirmwareUpdate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.force_firmware_update()` method.

`ics.ics.icsneoGenericAPIGetStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.generic_api_get_status()` method.

`ics.ics.icsneoGenericAPIReadData()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.generic_api_read_data()` method.

`ics.ics.icsneoGenericAPISendCommand()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.generic_api_send_command()` method.

`ics.ics.icsneoGetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_active_vnet_channel()` method.

`ics.ics.icsneoGetAllChipVersions()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_all_chip_versions()` method.

`ics.ics.icsneoGetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_enabled()` method.

`ics.ics.icsneoGetBackupPowerReady()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_ready()` method.

`ics.ics.icsneoGetBusVoltage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_bus_voltage()` method.

`ics.ics.icsneoGetDLLFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_firmware_info()` method.

`ics.ics.icsneoGetDLLVersion()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_version()` method.

`ics.ics.icsneoGetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_settings()` method.

`ics.ics.icsneoGetDeviceStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_status()` method.

`ics.ics.icsneoGetErrorMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_error_messages()` method.

`ics.ics.icsneoGetGPTPStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_gptp_status()` method.

`ics.ics.icsneoGetHWFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_hw_firmware_info()` method.

`ics.ics.icsneoGetLastError()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_last_api_error()` method.

`ics.ics.icsneoGetMessages()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_messages()* method.

`ics.ics.icsneoGetPCBSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_pcb_serial_number()* method.

`ics.ics.icsneoGetPerformanceParameters()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_performance_parameters()* method.

`ics.ics.icsneoGetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_rtc()* method.

`ics.ics.icsneoGetSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_serial_number()* method.

`ics.ics.icsneoGetTimeStampForMsg()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_timestamp_for_msg()* method.

`ics.ics.icsneoISO15765_DisableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.iso15765_disable_networks()* method.

`ics.ics.icsneoISO15765_EnableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.iso15765_enable_networks()* method.

`ics.ics.icsneoISO15765_ReceiveMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.ics.icsneoISO15765_TransmitMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.ics.icsneoIsDeviceFeatureSupported()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.is_device_feature_supported()` method.

`ics.ics.icsneoLoadDefaultSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.load_default_settings()` method.

`ics.ics.icsneoOpenNeoDevice()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.open_device()` method.

`ics.ics.icsneoReadJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_jupiter_firmware()` method.

`ics.ics.icsneoReadSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_sdcard()` method.

`ics.ics.icsneoRequestDiskDetails()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_details()` method.

`ics.ics.icsneoRequestDiskFormat()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.disk_format()* method.

`ics.ics.icsneoRequestDiskFormatCancel()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.disk_format_cancel()* method.

`ics.ics.icsneoRequestDiskFormatProgress()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_disk_format_progress()* method.

`ics.ics.icsneoRequestEnterSleepMode()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.request_enter_sleep_mode()* method.

`ics.ics.icsneoScriptClear()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.coremini_clear()* method.

`ics.ics.icsneoScriptGetFBlockStatus()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.coremini_get_fblock_status()* method.

`ics.ics.icsneoScriptGetScriptStatus()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.coremini_get_status()* method.

`ics.ics.icsneoScriptGetScriptStatusEx()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_script_status()* method.

`ics.ics.icsneoScriptLoad()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_load()` method.

`ics.ics.icsneoScriptReadAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_app_signal()` method.

`ics.ics.icsneoScriptReadRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_rx_message()` method.

`ics.ics.icsneoScriptReadTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_tx_message()` method.

`ics.ics.icsneoScriptStart()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start()` method.

`ics.ics.icsneoScriptStartFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start_fblock()` method.

`ics.ics.icsneoScriptStop()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop()` method.

`ics.ics.icsneoScriptStopFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop_fblock()` method.

`ics.ics.icsneoScriptWriteAppSignal()`

Note:	Compatibility	Function:	Identical	to	PEP8	compliant	<i>ics.ics.</i>
		<i>coremini_write_app_signal()</i>					method.

`ics.ics.icsneoScriptWriteRxMessage()`

Note:	Compatibility	Function:	Identical	to	PEP8	compliant	<i>ics.ics.</i>
		<i>coremini_write_rx_message()</i>					method.

`ics.ics.icsneoScriptWriteTxMessage()`

Note:	Compatibility	Function:	Identical	to	PEP8	compliant	<i>ics.ics.</i>
		<i>coremini_write_tx_message()</i>					method.

`ics.ics.icsneoSetActiveVNETChannel()`

Note:	Compatibility	Function:	Identical	to	PEP8	compliant	<i>ics.ics.set_active_vnet_channel()</i>
		method.					

`ics.ics.icsneoSetBackupPowerEnabled()`

Note:	Compatibility	Function:	Identical	to	PEP8	compliant	<i>ics.ics.set_backup_power_enabled()</i>
		method.					

`ics.ics.icsneoSetBitRate()`

Note:	Compatibility	Function:	Identical	to	PEP8	compliant	<i>ics.ics.set_bit_rate()</i>
		method.					

`ics.ics.icsneoSetBitRateEx()`

Note:	Compatibility	Function:	Identical	to	PEP8	compliant	<i>ics.ics.set_bit_rate_ex()</i>
		method.					

`ics.ics.icsneoSetContext()`

Note:	Compatibility	Function:	Identical	to	PEP8	compliant	<i>ics.ics.set_context()</i>
		method.					

`ics.ics.icsneoSetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_device_settings()` method.

`ics.ics.icsneoSetFDBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_fd_bit_rate()` method.

`ics.ics.icsneoSetLedProperty()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_led_property()` method.

`ics.ics.icsneoSetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_rtc()` method.

`ics.ics.icsneoSetReflashDisplayCallbacks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_reflash_callback()` method.

`ics.ics.icsneoStartDHCPServer()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.start_dhcp_server()` method.

`ics.ics.icsneoStopDHCPServer()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.stop_dhcp_server()` method.

`ics.ics.icsneoTxMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.transmit_messages()` method.

`ics.ics.icsneoUartGetBaudrate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.uart_get_baudrate()` method.

```
ics.ics.icsneoUartRead()
```

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.uart_read()* method.

```
ics.ics.icsneoUartSetBaudrate()
```

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.uart_set_baudrate()* method.

```
ics.ics.icsneoUartWrite()
```

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.uart_write()* method.

```
ics.ics.icsneoValidateHObject()
```

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.validate_hobject()* method.

```
ics.ics.icsneoWriteJupiterFirmware()
```

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.write_jupiter_firmware()* method.

```
ics.ics.icsneoWriteSDCard()
```

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.write_sdcard()* method.

```
ics.ics.icsneowBMSManagerReset()
```

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.wbms_manager_reset()* method.

```
ics.ics.icsneowBMSManagerWriteLock()
```

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.wbms_manager_write_lock()* method.

```
ics.ics.is_device_feature_supported(device, feature)
```

Polls firmware in device to see if the feature is supported. As of 908 only ValueCAN4-2EL, ValueCAN4-4 and ValueCAN4-Industrial are supported.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

enable (DeviceFeature): DeviceFeature

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> from ics.structures.device_feature import DeviceFeature
>>> d = ics.open_device()
>>> supported = ics.is_device_feature_supported(d, DeviceFeature.
↳ networkTerminationDWCAN01)
>>>
```

ics.ics.iso15765_disable_networks (device)

Disables ISO15765 networks.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: None

ics.ics.iso15765_enable_networks (device, networks)

Enables ISO15765 networks.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: None

ics.ics.iso15765_receive_message (device, netid, rx_msg)

Setup rx ISO15765 Message.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

prx_msg (ics.ics.st_cm_iso157652_rx_message): ics.ics.
st_cm_iso157652_rx_message

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

ics.ics.iso15765_transmit_message (device, ulNetworkID, pMsg, ulBlockingTimeout)

Transmits an ISO15765 Message.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

pMsg (ics.ics.st_cm_iso157652_tx_message): ics.ics.
st_cm_iso157652_tx_message

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

ics.ics.load_default_settings (device)

Load the default settings in the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: None.


```
>>> device = ics.open_device()
>>> ics.load_default_settings(device)
>>>
```

`ics.ics.open_device(device)`

Opens the device. *device* can be omitted to return a `ics.ics.NeoDevice` of the first free available device, a `ics.ics.NeoDevice`, or a serial number of the device.

Args: *device* (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

device (int): Serial Number of the device

network_ids (List/Tuple): This is an array of number IDs which specify the NetworkID parameter of each network. This allows you to assign a custom network ID to each network. Normally, you will assign consecutive IDs to each of the networks. See NetworkIDList for a list of current network ID's. You may also set this parameter to NULL (zero) and the default network ID's will be used.

config_read (int): Specifies whether the DLL should read the neoVI's device configuration before enabling the device. It is recommended that this value be set to 1.

options (int): `DEVICE_OPTION_*` defines

network_id (int): `OptionsFindNeoEx.CANOptions.iNetworkID`. Usually `ics.NETID_CAN`, if needed

use_server (int): Defaults to False, Setting to True allows opening the same device more than once.

Raises: `ics.ics.RuntimeError`

Returns: If `ics.ics.NeoDevice` is passed as a parameter, None. If serial number is passed as a parameter, a `ics.ics.NeoDevice` will be returned. If *device* parameter is omitted, a `ics.ics.NeoDevice` will be returned with the first available free device.

```
>>> for device in ics.find_devices():
...     ics.open_device(device)
... 
```

Note: `ics.ics.NeoDevice` will automatically close the device when it goes out of scope.

`ics.ics.override_library_name(new_name)`

Overrides the default search for loading the icsneo40 library

Args: *name*: Absolute path or relative path including filename.

Raises: `ics.ics.RuntimeError`

Returns: None

```
>>> import ics
>>> ics.find_devices()
Traceback (most recent call last):
  File "<stdin>", line 1, in <module>
ics.RuntimeError: Error: find_devices(): Failed to open library: 'icsneo40.dll
↳ ' with error code: #126
>>> ics.override_library_name(r"C:\Windows\SysWOW64\icsneo40-different.dll")
>>> ics.find_devices()
(<ics.NeoDevice object at 0x00284C50>, <ics.NeoDevice object at 0x007C9A10>)
```

`ics.ics.read_jupiter_firmware(device, size[, vnetChannel])`

Reads firmware binary from a RAD-Jupiter. If not sure, don't use this method

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

size (int): int: size of the bytes to read of the firmware binary.

vnetChannel (int): int: Optional. Don't set, if unsure.

Raises: *ics.ics.RuntimeError*

Returns: None

`ics.ics.read_sdcard()`

`icsneoReadSDCard()`, Accepts a `ics.ics.NeoDevice` and sector index. Returns a bytearray of 512 bytes max. Exception on error.

`ics.ics.request_enter_sleep_mode(device, timeout_ms, mode, reserved_zero)`

Signal neoVI to immediate go to sleep. Currently only supported by FIREVNET/PLASMA. If using over USB this will likely return true but never cause PLASMA to sleep since USB insertion keeps it alive. This API allows Android/Linux applications to invoke power management.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

timeout_ms (int): 16bit word for how long to wait on idle bus before going to sleep. If caller does not want to change it pass in 65535 (0xFFFF) and it will stay whatever it was set to in explorer/coremini.

mode (int): 16bit word for power mode to enter. If caller does not want to change it pass in 65535 (0xFFFF) and it will stay whatever it was set to in explorer/coremini. If it is zero then neoVI will do 'normal sleep'. 0 - power mode off but calling this function will do 'normal sleep'. 1 - normal sleep. 2 - instant sleep. 3 - comatose sleep.

reserved_zero (int): Reserved, Keep as zero.

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

```
>>> ics.request_enter_sleep_mode(device, 1, 0)
True
```

`ics.ics.set_active_vnet_channel(device, channel)`

Sets active vnet channel for the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

`ics.ics.set_backup_power_enabled(device, enable)`

Sets the device backup power enabled for the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

`ics.ics.set_bit_rate(device, BitRate, NetworkID)`

Specifies bit rate setting. Valid values depend on the network specified.

For the networks NETID_HSCAN, NETID_MSCAN, NETID_SWCAN, NETID_FIRE_HSCAN2, NETID_HSCAN3, NETID_LSFTCAN, valid bit rates are 2000, 33333, 50000, 62500, 83333, 100000, 125000, 250000, 500000, 800000, 1000000

For the networks NETID_LIN, NETID_ISO2, NETID_FIRE_LIN2, NETID_FIRE_LIN3, NETID_FIRE_LIN4, valid bit rates are

For the network NETID_FIRE_CGI valid bit rates are 625000 and 115200

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Int: None.

ics.ics.set_bit_rate_ex (*device, BitRate, NetworkID, iOptions*)

Sets the bitrate for a given Network ID on the device with extended options.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Int: None.

ics.ics.set_context (*device*)

Sets the “context” of how icsneoFindNeoDevices(Ex) and icsneoOpenNeoDevice(Ex) function. If the context is 0 (null) than icsneoFindNeoDevices(Ex) will be system wide, searching USB and other supported computer interfaces. icsneoFindNeoDevices can then be used to connect to devices found in this manner. If the context is a handle to connected CAN tool than icsneoFindNeoDevices(Ex) will search a specific CAN bus for supported IntrepidCS CAN Nodes. Again icsneoOpenNeoDevice(Ex) would be used create logical connections to found CAN Nodes.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True on success, False on failure.

```
>>> ics.set_context(device)
True
```

ics.ics.set_device_settings (*device, settings, save_to_eeprom, vnet_slot*)

Sets the settings in the device. vnet_slot defaults to ics.ics.PlasmaIonVnetChannelMain

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

settings (*ics.ics.device_settings*): *ics.ics.device_settings*

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> d = ics.open_device()
>>> d.Name
'neoVI ION'
>>> d.SerialNumber
404444
>>> s = ics.get_device_settings(d, ics.PlasmaIonVnetChannelA) # Get Slave_
↪ settings, channel selection not needed if not a Plasma/Ion
>>> s.DeviceSettingType
2
>>> s.cyan.can_switch_mode
1
>>> s.cyan.can_switch_mode = 2
>>> ics.set_device_settings(d, s, True, ics.PlasmaIonVnetChannelA)
>>>
```

ics.ics.set_fd_bit_rate (*device, BitRate, NetworkID*)

Sets the FD bitrate for a given Network ID on the device..

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: `ics.ics.RuntimeError`

Returns: Int: None.

`ics.ics.set_led_property(device, led, prop, value)`

Sets the LED property on the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

led (int): Index or position of the LED

prop (int): Property of the LED

value (int): Value of the LED Property

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> ics.set_led_property(d, TODO, TODO, TODO)
>>>
```

`ics.ics.set_reflash_callback(callback)`

Sets the reflash display callback.

Args: callback (function): Must be a callable Python function (*def callback(msg, progress)*)

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> def callback(msg, progress):
...     print(msg, progress)
...
>>> ics.set_reflash_callback(callback)
>>>
```

`ics.ics.set_rtc(device[, time])`

Sets the Real-Time Clock of the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

time (datetime.datetime): Optional. Sets to current time, if omitted.

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.set_rtc(device)
```

`ics.ics.start_dhcp_server(device, network_id, device_ip_address, subnet_mask, gateway, start_address, end_address, overwrite_dhcp_settings, lease_time, reserved)`

Starts a DHCP Server.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

network_id (int): NetworkID

device_ip_address (str): Device IP Address

subnet_mask (str): Subnet Mask

gateway (str): Gateway
 start_address (str): Start Address
 end_address (str): End Address
 overwrite_dhcp_settings (bool): Overwrite DHCP Settings
 lease_time (int): Lease time
 reserved (int): (Optional) Reserved, set to 0

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> ics.start_dhcp_server(d, TODO)
>>>
```

ics.ics.stop_dhcp_server (*device, network_id*)

Stops the DHCP Server

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

network_id (int): NetworkID

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> ics.stop_dhcp_server(d, TODO)
>>>
```

ics.ics.transmit_messages (*device, messages*)

Transmits message(s) on the device. *messages* can be a tuple of *ics.ics.SpyMessage*

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

messages (*ics.ics.SpyMessage*): *ics.ics.SpyMessage*

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> device = ics.open_device()
>>> msg = ics.SpyMessage()
>>> msg.ArbIDOrHeader = 0xFF
>>> msg.NetworkID = ics.NETID_HSCAN
>>> msg.Data = (0,1,2,3,4,5,6,7)
>>> ics.transmit_messages(device, msg)
>>>
```

ics.ics.uart_get_baudrate (*device, port*)

Gets the UART baudrate on the given port.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

port (*ics.ics.structures.e_uart_port_t.e_uart_port_t*): *ics.ics.structures.e_uart_port_t.e_uart_port_t*

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> from ics.structures.e_uart_port_t import e_uart_port_t
>>> d = ics.open_device()
>>> baudrate = ics.uart_set_baudrate(d, e_uart_port_t.eUART0)
>>>
```

`ics.ics.uart_read(device, port, bytes_to_read, flags)`

Reads UART on the given port.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

port (*ics.ics.structures.e_uart_port_t.e_uart_port_t*): *ics.ics.structures.e_uart_port_t.e_uart_port_t*

bytes_to_read (int): Optional. How many bytes to read from the UART, 256 if omitted.

flags (int): Optional. Flags to be used. Don't use if unsure.

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> from ics.structures.e_uart_port_t import e_uart_port_t
>>> d = ics.open_device()
>>> data = ics.uart_read(d, e_uart_port_t.eUART0)
>>> print(f"Read {len(data)} bytes: {data}")
>>>
```

`ics.ics.uart_set_baudrate(device, port, baudrate)`

Sets the UART baudrate on the given port.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

port (*ics.ics.structures.e_uart_port_t.e_uart_port_t*): *ics.ics.structures.e_uart_port_t.e_uart_port_t*

baudrate (int): Baudrate of the UART to set.

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> from ics.structures.e_uart_port_t import e_uart_port_t
>>> d = ics.open_device()
>>> ics.uart_set_baudrate(d, e_uart_port_t.eUART0, 115200)
>>> print(f"Read {len(data)} bytes: {data}")
>>>
```

`ics.ics.uart_write(device, port, data, flags)`

Writes UART on the given port

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

port (*ics.ics.structures.e_uart_port_t.e_uart_port_t*): *ics.ics.structures.e_uart_port_t.e_uart_port_t*

data (bytes): bytes

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> from ics.structures.e_uart_port_t import e_uart_port_t
>>> d = ics.open_device()
>>> ics.uart_write(d, e_uart_port_t.eUART0, b'my uart data goes here')
>>>
```

`ics.ics.validate_hobject(device)`

Validates the handle is valid for a *device*. Handles are only valid when the device is open.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

or:

device (int): c style integer handle to the device.

Raises: *ics.ics.RuntimeError*

Returns: Boolean: True if valid, false otherwise.

```
>>> device = ics.open_device()
>>> ics.validate_hobject(device)
1
>>> ics.validate_hobject(device._Handle)
1
```

`ics.ics.wBMSManagerReset()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.wbms_manager_reset()* method.

`ics.ics.wBMSManagerWriteLock()`

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.wbms_manager_write_lock()* method.

`ics.ics.wbms_manager_reset(device, manager)`

Resets the manager

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

manager (*ics.ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t*):
ics.ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> from ics.structures.ew_bms_manager_port_t import ew_bms_manager_port_t
>>> d = ics.open_device()
>>> ics.wbms_manager_reset(d, ew_bms_manager_port_t.eManagerPortA.value)
>>>
```

`ics.ics.wbms_manager_write_lock(device, manager, lock_state)`

Sets the lock state on the manager

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

manager (*ics.ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t*):
ics.ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t

lock_state (*ics.ics.structures.ew_bms_manager_lock_state_t.ew_bms_manager_lock_state_t*):
ics.ics.structures.ew_bms_manager_lock_state_t.ew_bms_manager_lock_state_t

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> import ics
>>> from ics.structures.ew_bms_manager_port_t import ew_bms_manager_port_t
>>> from ics.structures.ew_bms_manager_lock_state_t import ew_bms_manager_
↪lock_state_t
>>> d = ics.open_device()
>>> ics.wbms_manager_write_lock(d, ew_bms_manager_port_t.eManagerPortA.value, ↪
↪ew_bms_manager_lock_state_t.eLockManager.value)
>>>
```

ics.ics.write_jupiter_firmware (device, bytes[, vnetChannel])

Writes firmware binary to a RAD-Jupiter. If not sure, don't use this method

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

bytes (bytes): bytes: bytes of the firmware binary.

vnetChannel (int): int: Optional. Don't set, if unsure.

Raises: *ics.ics.RuntimeError*

Returns: None

ics.ics.write_sdcard()

icsneoReadSDCard(), Accepts a *ics.ics.NeoDevice*, sector index, and a bytearray of 512 bytes. Exception on error.

CHAPTER 8

Module Functions

`ics.ISO15765_DisableNetworks`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_disable_networks()` method.

`ics.ISO15765_EnableNetworks`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_enable_networks()` method.

`ics.ISO15765_ReceiveMessage`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.ISO15765_TransmitMessage`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.close_device(device)`

Closes the device.

`ics.coremini_clear(device, location)`

Clears the CoreMini into the device.

Continued on next page

Table 1 – continued from previous page

<code>ics.coremini_get_fblock_status(device, index)</code>	Gets the status of a Coremini Function Block at <i>index</i> on <i>device</i> .
<code>ics.coremini_get_status(device)</code>	Gets the status of the CoreMini in the device.
<code>ics.coremini_load(device, coremini, location)</code>	Loads the CoreMini into the device.
<code>ics.coremini_read_app_signal(device, index)</code>	Gets the value of a Coremini application signal at <i>index</i> on <i>device</i> .
<code>ics.coremini_read_rx_message(device, index)</code>	Gets the value of a Coremini Message at <i>index</i> on <i>device</i> .
<code>ics.coremini_read_tx_message(device, index)</code>	Gets the value of a Coremini Message at <i>index</i> on <i>device</i> .
<code>ics.coremini_start(device, location)</code>	Starts the CoreMini into the device.
<code>ics.coremini_start_fblock(device, index)</code>	Starts a Coremini Function Block at <i>index</i> on <i>device</i> .
<code>ics.coremini_stop(device)</code>	Stops the CoreMini into the device.
<code>ics.coremini_stop_fblock(device, index)</code>	Stops a Coremini Function Block at <i>index</i> on <i>device</i> .
<code>ics.coremini_write_app_signal(device, index, ...)</code>	Sets the value of a Coremini application signal at <i>index</i> on <i>device</i> .
<code>ics.coremini_write_rx_message(device, index, ...)</code>	TODO
<code>ics.coremini_write_tx_message(device, index, msg)</code>	TODO
<code>ics.create_neovi_radio_message(Relay1, ...)</code>	Python API only.
<code>ics.disk_format(device)</code>	Starts disk formatting on the device.
<code>ics.disk_format_cancel(device)</code>	Cancel in progress disk formatting on the device.
<code>ics.enable_bus_voltage_monitor(device, ...)</code>	Enable or disable bus voltage monitoring.
<code>ics.enable_doip_line(device, enable)</code>	Activate or De-activate DOIP Line.
<code>ics.enable_network_com(device, enable, net_id)</code>	Enable or disable network communication.
<code>ics.find_devices([device_type])</code>	Finds all connected devices and returns a tuple of <code>ics.ics.NeoDevice</code> for use in <code>ics.ics.open_device()</code>
<code>ics.firmware_update_required(device)</code>	Determines if the device firmware needs flashing.
<code>ics.force_firmware_update(device)</code>	Forces the device to flash firmware.
<code>ics.generic_api_get_status(device, ...)</code>	Reads data in a generic way.
<code>ics.generic_api_read_data(device, api_index, ...)</code>	Reads data in a generic way.
<code>ics.generic_api_send_command(device, ...)</code>	Sends a command in a generic way.
<code>ics.get_active_vnet_channel(device)</code>	Gets active vnet channel for the device.
<code>ics.get_all_chip_versions(device, api_index, ...)</code>	Get all the chip (firmware) versions of the device.
<code>ics.get_backup_power_enabled(device)</code>	Returns the device backup power enabled for the device.
<code>ics.get_backup_power_ready(device)</code>	Returns the device backup power is ready for the device.
<code>ics.get_bus_voltage(device, reserved)</code>	Reads bus voltage.
<code>ics.get_device_settings(device, device_type, ...)</code>	Gets the settings in the device.
<code>ics.get_device_status(device)</code>	Returns the device status.
<code>ics.get_disk_details(device)</code>	Returns the device disk details.
<code>ics.get_disk_format_progress(device)</code>	Returns the device disk formatting progress.
<code>ics.get_dll_firmware_info(device)</code>	Returns the DLL firmware info for the device.
<code>ics.get_dll_version(device)</code>	Gets the DLL version.

Continued on next page

Table 1 – continued from previous page

<code>ics.get_error_messages(device[, j1850, timeout])</code>	Gets the error message(s) on the device.
<code>ics.get_gptp_status(device)</code>	Gets the gPTP Status from the device.
<code>ics.get_hw_firmware_info(device)</code>	Returns the device firmware info for the device.
<code>ics.get_last_api_error(device)</code>	Gets the error message from the last API call.
<code>ics.get_library_path</code>	
<code>ics.get_messages(device[, j1850, timeout])</code>	Gets the message(s) on the device.
<code>ics.get_pcb_serial_number(device)</code>	Gets the unique PCB serial number of the device.
<code>ics.get_performance_parameters(device)</code>	Gets the Performance Parameters on <i>device</i> .
<code>ics.get_rtc(device)</code>	Gets the Real-Time Clock of the device.
<code>ics.get_script_status</code>	Accepts a <code>ics.ics.NeoDevice</code> , exception on error.
<code>ics.get_serial_number(device)</code>	Gets the serial number out of the device.
<code>ics.get_timestamp_for_msg(device, msg)</code>	Calculates the timestamp for a message.
<code>ics.is_device_feature_supported(device, feature)</code>	Polls firmware in device to see if the feature is supported.
<code>ics.iso15765_disable_networks(device)</code>	Disables ISO15765 networks.
<code>ics.iso15765_enable_networks(device, networks)</code>	Enables ISO15765 networks.
<code>ics.iso15765_receive_message(device, netid, ...)</code>	Setup rx ISO15765 Message.
<code>ics.iso15765_transmit_message(device, ...)</code>	Transmits an ISO15765 Message.
<code>ics.load_default_settings(device)</code>	Load the default settings in the device.
<code>ics.open_device(device)</code>	Opens the device.
<code>ics.override_library_name(new_name)</code>	Overrides the default search for loading the <code>icsneo40</code> library
<code>ics.read_jupiter_firmware(device, size, ...)</code>	Reads firmware binary from a RAD-Jupiter.
<code>ics.read_sdcard</code>	<code>icsneoReadSDCard()</code> , Accepts a <code>ics.ics.NeoDevice</code> and sector index.
<code>ics.request_enter_sleep_mode(device, ...)</code>	Signal neoVI to immediate go to sleep.
<code>ics.set_active_vnet_channel(device, channel)</code>	Sets active vnet channel for the device.
<code>ics.set_backup_power_enabled(device, enable)</code>	Sets the device backup power enabled for the device.
<code>ics.set_bit_rate(device, BitRate, NetworkID)</code>	Specifies bit rate setting.
<code>ics.set_bit_rate_ex(device, BitRate, ...)</code>	Sets the bitrate for a given Network ID on the device with extended options.
<code>ics.set_context(device)</code>	Sets the “context” of how <code>icsneoFindNeoDevices(Ex)</code> and <code>icsneoOpenNeoDevice(Ex)</code> function.
<code>ics.set_device_settings(device, settings, ...)</code>	Sets the settings in the device.
<code>ics.set_fd_bit_rate(device, BitRate, NetworkID)</code>	Sets the FD bitrate for a given Network ID on the device..
<code>ics.set_led_property(device, led, prop, value)</code>	Sets the LED property on the device.
<code>ics.set_reflash_callback(callback)</code>	Sets the reflash display callback.
<code>ics.set_rtc(device[, time])</code>	Sets the Real-Time Clock of the device.
<code>ics.start_dhcp_server(device, network_id, ...)</code>	Starts a DHCP Server.
<code>ics.stop_dhcp_server(device, network_id)</code>	Stops the DHCP Server
<code>ics.transmit_messages(device, messages)</code>	Transmits message(s) on the device.
<code>ics.uart_get_baudrate(device, port)</code>	Gets the UART baudrate on the given port.
<code>ics.uart_read(device, port, bytes_to_read, flags)</code>	Reads UART on the given port.

Continued on next page

Table 1 – continued from previous page

<code>ics.uart_set_baudrate(device, port, baudrate)</code>	Sets the UART baudrate on the given port.
<code>ics.uart_write(device, port, data, flags)</code>	Writes UART on the given port
<code>ics.validate_hobject(device)</code>	Validates the handle is valid for a <i>device</i> .
<code>ics.wbms_manager_reset(device, manager)</code>	Resets the manager
<code>ics.wbms_manager_write_lock(device, manager, ...)</code>	Sets the lock state on the manager
<code>ics.write_jupiter_firmware(device, bytes, ...)</code>	Writes firmware binary to a RAD-Jupiter.
<code>ics.write_sdcard</code>	<code>icsneoReadSDCard()</code> , Accepts a <code>ics.ics.NeoDevice</code> , sector index, and a bytearray of 512 bytes.
<code>ics.ClosePort</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.close_device()</code> method.
<code>ics.EnableBusVoltageMonitor</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_bus_voltage_monitor()</code> method.
<code>ics.EnabledDOIPLine</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_doip_line()</code> method.
<code>ics.EnableNetworkCom</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_network_com()</code> method.
<code>ics.FindNeoDevices</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.find_devices()</code> method.
<code>ics.FirmwareUpdateRequired</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.firmware_update_required()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.ForceFirmwareUpdate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.force_firmware_update()</code> method.
<code>ics.GenericAPIGetStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_get_status()</code> method.
<code>ics.GenericAPIReadData</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_read_data()</code> method.
<code>ics.GenericAPISendCommand</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_send_command()</code> method.
<code>ics.GetActiveVNETChannel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_active_vnet_channel()</code> method.
<code>ics.GetAllChipVersions</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_all_chip_versions()</code> method.
<code>ics.GetBackupPowerEnabled</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_enabled()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.GetBackupPowerReady</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_ready()</code> method. <hr/>
<code>ics.GetBusVoltage</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_bus_voltage()</code> method. <hr/>
<code>ics.GetDLLFirmwareInfo</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_firmware_info()</code> method. <hr/>
<code>ics.GetDLLVersion</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_version()</code> method. <hr/>
<code>ics.GetDeviceSettings</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_settings()</code> method. <hr/>
<code>ics.GetDeviceStatus</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_status()</code> method. <hr/>
<code>ics.GetErrorMessages</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_error_messages()</code> method. <hr/>
<code>ics.GetGPTPStatus</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_gptp_status()</code> method. <hr/>

Continued on next page

Table 1 – continued from previous page

<code>ics.GetHWFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_hw_firmware_info()</code> method.
<code>ics.GetLastError</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_last_api_error()</code> method.
<code>ics.GetMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_messages()</code> method.
<code>ics.GetPCBSerialNumber</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_pcb_serial_number()</code> method.
<code>ics.GetPerformanceParameters</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_performance_parameters()</code> method.
<code>ics.GetRTC</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_rtc()</code> method.
<code>ics.GetSerialNumber</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_serial_number()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.GetTimeStampForMsg</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_timestamp_for_msg()</code> method.
<hr/>	
<code>ics.IsDeviceFeatureSupported</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.is_device_feature_supported()</code> method.
<hr/>	
<code>ics.LoadDefaultSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.load_default_settings()</code> method.
<hr/>	
<code>ics.OpenNeoDevice</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.open_device()</code> method.
<hr/>	
<code>ics.ReadJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_jupiter_firmware()</code> method.
<hr/>	
<code>ics.ReadSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_sdcard()</code> method.
<hr/>	
<code>ics.RequestDiskDetails</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_details()</code> method.
<hr/>	
<code>ics.RequestDiskFormat</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.RequestDiskFormatCancel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format_cancel()</code> method.
<code>ics.RequestDiskFormatProgress</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_format_progress()</code> method.
<code>ics.RequestEnterSleepMode</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.request_enter_sleep_mode()</code> method.
<code>ics.ScriptClear</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_clear()</code> method.
<code>ics.ScriptGetFBlockStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_fblock_status()</code> method.
<code>ics.ScriptGetScriptStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_status()</code> method.
<code>ics.ScriptGetScriptStatusEx</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_script_status()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.ScriptLoad</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_load()</code> method. <hr/>
<code>ics.ScriptReadAppSignal</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_app_signal()</code> method. <hr/>
<code>ics.ScriptReadRxMessage</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_rx_message()</code> method. <hr/>
<code>ics.ScriptReadTxMessage</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_tx_message()</code> method. <hr/>
<code>ics.ScriptStart</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start()</code> method. <hr/>
<code>ics.ScriptStartFBlock</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start_fblock()</code> method. <hr/>
<code>ics.ScriptStop</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop()</code> method. <hr/>

Continued on next page

Table 1 – continued from previous page

<code>ics.ScriptStopFBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop_fblock()</code> method.
<code>ics.ScriptWriteAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_app_signal()</code> method.
<code>ics.ScriptWriteRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_rx_message()</code> method.
<code>ics.ScriptWriteTxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_tx_message()</code> method.
<code>ics.SetActiveVNETChannel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_active_vnet_channel()</code> method.
<code>ics.SetBackupPowerEnabled</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_backup_power_enabled()</code> method.
<code>ics.SetBitRate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_bit_rate()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.SetBitRateEx</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_bit_rate_ex()</code> method. <hr/>
<code>ics.SetContext</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_context()</code> method. <hr/>
<code>ics.SetDeviceSettings</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_device_settings()</code> method. <hr/>
<code>ics.SetFDBitRate</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_fd_bit_rate()</code> method. <hr/>
<code>ics.SetLedProperty</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_led_property()</code> method. <hr/>
<code>ics.SetRTC</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_rtc()</code> method. <hr/>
<code>ics.SetReflashDisplayCallback</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_reflash_callback()</code> method. <hr/>
<code>ics.StartDHCPserver</code>	<hr/> Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.start_dhcp_server()</code> method. <hr/>

Continued on next page

Table 1 – continued from previous page

<code>ics.StopDHCP Server</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.stop_dhcp_server()</code> method.
<code>ics.TxMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.transmit_messages()</code> method.
<code>ics.UartGetBaudrate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_get_baudrate()</code> method.
<code>ics.UartRead</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_read()</code> method.
<code>ics.UartSetBaudrate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_set_baudrate()</code> method.
<code>ics.UartWrite</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_write()</code> method.
<code>ics.ValidateHObject</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.validate_hobject()</code> method.
<code>ics.WriteJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.write_jupiter_firmware()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.WriteSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.write_sdcard()</code> method.
<code>ics.base36enc(serial)</code>	Converts a decimal serial number to base36.
<code>ics.wBMSManagerReset</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.wbms_manager_reset()</code> method.
<code>ics.wBMSManagerWriteLock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.wbms_manager_write_lock()</code> method.
<code>ics.icsneoClosePort</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.close_device()</code> method.
<code>ics.icsneoEnableBusVoltageMonitor</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_bus_voltage_monitor()</code> method.
<code>ics.icsneoEnableDOIPLine</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_doip_line()</code> method.
<code>ics.icsneoEnableNetworkCom</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_network_com()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoFindNeoDevices</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.find_devices()</code> method.
<code>ics.icsneoFirmwareUpdateRequired</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.firmware_update_required()</code> method.
<code>ics.icsneoForceFirmwareUpdate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.force_firmware_update()</code> method.
<code>ics.icsneoGenericAPIGetStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_get_status()</code> method.
<code>ics.icsneoGenericAPIReadData</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_read_data()</code> method.
<code>ics.icsneoGenericAPISendCommand</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.generic_api_send_command()</code> method.
<code>ics.icsneoGetActiveVNETChannel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_active_vnet_channel()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoGetAllChipVersions</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_all_chip_versions()</code> method.
<code>ics.icsneoGetBackupPowerEnabled</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_enabled()</code> method.
<code>ics.icsneoGetBackupPowerReady</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_ready()</code> method.
<code>ics.icsneoGetBusVoltage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_bus_voltage()</code> method.
<code>ics.icsneoGetDLLFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_firmware_info()</code> method.
<code>ics.icsneoGetDLLVersion</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_version()</code> method.
<code>ics.icsneoGetDeviceSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_settings()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoGetDeviceStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_status()</code> method.
<code>ics.icsneoGetErrorMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_error_messages()</code> method.
<code>ics.icsneoGetGPTPStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_gptp_status()</code> method.
<code>ics.icsneoGetHWFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_hw_firmware_info()</code> method.
<code>ics.icsneoGetLastAPIError</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_last_api_error()</code> method.
<code>ics.icsneoGetMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_messages()</code> method.
<code>ics.icsneoGetPCBSerialNumber</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_pcb_serial_number()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoGetPerformanceParameters</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_performance_parameters()</code> method.
<code>ics.icsneoGetRTC</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_rtc()</code> method.
<code>ics.icsneoGetSerialNumber</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_serial_number()</code> method.
<code>ics.icsneoGetTimeStampForMsg</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_timestamp_for_msg()</code> method.
<code>ics.icsneoISO15765_DisableNetworks</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.iso15765_disable_networks()</code> method.
<code>ics.icsneoISO15765_EnableNetworks</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.iso15765_enable_networks()</code> method.
<code>ics.icsneoISO15765_ReceiveMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.iso15765_receive_message()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoISO15765_TransmitMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.iso15765_transmit_message()</code> method.
<code>ics.icsneoIsDeviceFeatureSupported</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.is_device_feature_supported()</code> method.
<code>ics.icsneoLoadDefaultSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.load_default_settings()</code> method.
<code>ics.icsneoOpenNeoDevice</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.open_device()</code> method.
<code>ics.icsneoReadJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_jupiter_firmware()</code> method.
<code>ics.icsneoReadSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_sdcard()</code> method.
<code>ics.icsneoRequestDiskDetails</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_details()</code> method.
<code>ics.icsneoRequestDiskFormat</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoRequestDiskFormatCancel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format_cancel()</code> method.
<code>ics.icsneoRequestDiskFormatProgress</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_format_progress()</code> method.
<code>ics.icsneoRequestEnterSleepMode</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.request_enter_sleep_mode()</code> method.
<code>ics.icsneoScriptClear</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_clear()</code> method.
<code>ics.icsneoScriptGetFBlockStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_fblock_status()</code> method.
<code>ics.icsneoScriptGetScriptStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_status()</code> method.
<code>ics.icsneoScriptGetScriptStatusEx</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_script_status()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoScriptLoad</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_load()</code> method.
<code>ics.icsneoScriptReadAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_app_signal()</code> method.
<code>ics.icsneoScriptReadRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_rx_message()</code> method.
<code>ics.icsneoScriptReadTxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_tx_message()</code> method.
<code>ics.icsneoScriptStart</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start()</code> method.
<code>ics.icsneoScriptStartFBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start_fblock()</code> method.
<code>ics.icsneoScriptStop</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoScriptStopFBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop_fblock()</code> method.
<code>ics.icsneoScriptWriteAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_app_signal()</code> method.
<code>ics.icsneoScriptWriteRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_rx_message()</code> method.
<code>ics.icsneoScriptWriteTxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_tx_message()</code> method.
<code>ics.icsneoSetActiveVNETChannel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_active_vnet_channel()</code> method.
<code>ics.icsneoSetBackupPowerEnabled</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_backup_power_enabled()</code> method.
<code>ics.icsneoSetBitRate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_bit_rate()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoSetBitRateEx</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_bit_rate_ex()</code> method.
<code>ics.icsneoSetContext</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_context()</code> method.
<code>ics.icsneoSetDeviceSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_device_settings()</code> method.
<code>ics.icsneoSetFDBitRate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_fd_bit_rate()</code> method.
<code>ics.icsneoSetLedProperty</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_led_property()</code> method.
<code>ics.icsneoSetRTC</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_rtc()</code> method.
<code>ics.icsneoSetReflashDisplayCallbacks</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_reflash_callback()</code> method.
<code>ics.icsneoStartDHCP Server</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.start_dhcp_server()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoStopDHCP</code> <code>Server</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.stop_dhcp_server()</code> method.
<code>ics.icsneoTxMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.transmit_messages()</code> method.
<code>ics.icsneoUartGetBaudrate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_get_baudrate()</code> method.
<code>ics.icsneoUartRead</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_read()</code> method.
<code>ics.icsneoUartSetBaudrate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_set_baudrate()</code> method.
<code>ics.icsneoUartWrite</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.uart_write()</code> method.
<code>ics.icsneoValidateHObject</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.validate_hobject()</code> method.
<code>ics.icsneoWriteJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.write_jupiter_firmware()</code> method.

Continued on next page

Table 1 – continued from previous page

`ics.icsneoWriteSDCard`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_sdcard()` method.

`ics.icsneowBMSManagerReset`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.wbms_manager_reset()` method.

`ics.icsneowBMSManagerWriteLock`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.wbms_manager_write_lock()` method.

CHAPTER 9

Module Structures

```
class ics.structures.a2_b_monitor_settings.a2_b_monitor_settings

    downstreamChannelOffset
        Structure/Union member

    flags
        Structure/Union member

    nodeType
        Structure/Union member

    reserved
        Structure/Union member

    tdmMode
        Structure/Union member

    upstreamChannelOffset
        Structure/Union member

class ics.structures.a2_b_node_type.a2_b_node_type
    A ctypes-compatible IntEnum superclass.

    a2bNodeTypeMaster = 1
    a2bNodeTypeMonitor = 0
    a2bNodeTypeSlave = 2

    from_param = <bound method a2_b_node_type.from_param of <enum 'a2_b_node_type'>>

class ics.structures.a2_btdm_mode.a2_btdm_mode
    A ctypes-compatible IntEnum superclass.

    from_param = <bound method a2_btdm_mode.from_param of <enum 'a2_btdm_mode'>>

    tdmModeTDM12 = 3
    tdmModeTDM16 = 4
```

```
tdmModeTDM2 = 0
tdmModeTDM20 = 5
tdmModeTDM24 = 6
tdmModeTDM32 = 7
tdmModeTDM4 = 1
tdmModeTDM8 = 2
```

```
class ics.structures.can_settings.can_settings
```

```
BRP
    Structure/Union member

Baudrate
    Structure/Union member

Mode
    Structure/Union member

SetBaudrate
    Structure/Union member

TqProp
    Structure/Union member

TqSeg1
    Structure/Union member

TqSeg2
    Structure/Union member

TqSync
    Structure/Union member

auto_baud
    Structure/Union member

innerFrameDelay25us
    Structure/Union member

transceiver_mode
    Structure/Union member
```

```
class ics.structures.canfd_settings.canfd_settings
```

```
FDBRP
    Structure/Union member

FDBaudrate
    Structure/Union member

FDMode
    Structure/Union member

FDTDC
    Structure/Union member

FDTqProp
    Structure/Union member
```

FDTqSeg1
Structure/Union member

FDTqSeg2
Structure/Union member

FDTqSync
Structure/Union member

reserved
Structure/Union member

class ics.structures.canterm_settings.canterm_settings

reserved
Structure/Union member

term_enabled
Structure/Union member

term_network
Structure/Union member

class ics.structures.clock_quality_.clock_quality_

clock_accuracy
Structure/Union member

clock_class
Structure/Union member

offset_scaled_log_variance
Structure/Union member

class ics.structures.device_feature.device_feature

A ctypes-compatible IntEnum superclass.

NUM_VALID_DEVICE_FEATURES = 17

enhancedFlashDriver = 16

from_param = <bound method device_feature.from_param of <enum 'device_feature'>>

networkDWCAN01 = 0

networkDWCAN02 = 1

networkDWCAN03 = 2

networkDWCAN04 = 3

networkDWCAN05 = 4

networkDWCAN06 = 5

networkDWCAN07 = 6

networkDWCAN08 = 7

networkTerminationDWCAN01 = 8

networkTerminationDWCAN02 = 9

networkTerminationDWCAN03 = 10

```
networkTerminationDWCAN04 = 11
networkTerminationDWCAN05 = 12
networkTerminationDWCAN06 = 13
networkTerminationDWCAN07 = 14
networkTerminationDWCAN08 = 15
supportedFeatureMax = 65535
class ics.structures.disk_settings.disk_settings

    disk_enables
        Structure/Union member

    disk_format
        Structure/Union member

    disk_layout
        Structure/Union member

    rsvd
        Structure/Union member

class ics.structures.e_device_settings_type.e_device_settings_type
    A ctypes-compatible IntEnum superclass.

    DeviceCANHUBSettingsType = 19
    DeviceCMPProbeSettingsType = 22
    DeviceECU_AVBSettingsType = 9
    DeviceEEVBSSettingsType = 15
    DeviceEtherBadgeSettingsType = 30
    DeviceFire2SettingsType = 2
    DeviceFire3FlexraySettingsType = 37
    DeviceFire3SettingsType = 36
    DeviceFireSettingsType = 0
    DeviceFireVnetSettingsType = 1
    DeviceFlexVnetzSettingsType = 18
    DeviceIEVBSSettingsType = 20
    DeviceNeoECU12SettingsType = 17
    DeviceOBD2LCSettingsType = 33
    DeviceOBD2ProSettingsType = 23
    DeviceOBD2SimSettingsType = 21
    DeviceRADA2BSettingsType = 31
    DeviceRADBMSSettingsType = 34
    DeviceRADEpsilonSettingsType = 32
    DeviceRADGalaxySettingsType = 4
```

```

DeviceRADGigalogSettingsType = 13
DeviceRADGigastarSettingsType = 26
DeviceRADJupiterSettingsType = 27
DeviceRADMoon2SettingsType = 11
DeviceRADMoon3SettingsType = 35
DeviceRADPlutoSettingsType = 12
DeviceRADPlutoSwitchSettingsType = 25
DeviceRADStar2SettingsType = 5
DeviceRADSuperMoonSettingsType = 10
DeviceRadMoonDuoSettingsType = 29
DeviceRed2SettingsType = 28
DeviceRedSettingsType = 24
DeviceSettingsNone = 4294967295
DeviceSettingsTypeMax = 38
DeviceVCAN3SettingsType = 3
DeviceVCAN412SettingsType = 7
DeviceVCAN4IndSettingsType = 16
DeviceVCAN4SettingsType = 6
DeviceVCANRFSettingsType = 14
DeviceVividCANSettingsType = 8
    from_param = <bound method e_device_settings_type.from_param of <enum 'e_device_set
class ics.structures.e_disk_format.e_disk_format
    A ctypes-compatible IntEnum superclass.
    DiskFormatFAT32 = 1
    DiskFormatUnknown = 0
    DiskFormatexFAT = 2
    from_param = <bound method e_disk_format.from_param of <enum 'e_disk_format'>>
class ics.structures.e_disk_layout.e_disk_layout
    A ctypes-compatible IntEnum superclass.
    DiskLayoutIndividual = 4
    DiskLayoutRAID0 = 1
    DiskLayoutRAID1 = 2
    DiskLayoutRAID5 = 3
    DiskLayoutSpanned = 0
    from_param = <bound method e_disk_layout.from_param of <enum 'e_disk_layout'>>
class ics.structures.e_generic_api_options.e_generic_api_options
    A ctypes-compatible IntEnum superclass.

```

```
eADI_WIL_API = 1
eGENERIC_API = 0

from_param = <bound method e_generic_api_options.from_param of <enum 'e_generic_api_options'>>

class ics.structures.e_gptp_port.e_gptp_port
    A ctypes-compatible IntEnum superclass.

    ePortDisabled = 0
    ePortOpEth1 = 1
    ePortOpEth10 = 10
    ePortOpEth11 = 11
    ePortOpEth12 = 12
    ePortOpEth2 = 2
    ePortOpEth3 = 3
    ePortOpEth4 = 4
    ePortOpEth5 = 5
    ePortOpEth6 = 6
    ePortOpEth7 = 7
    ePortOpEth8 = 8
    ePortOpEth9 = 9
    ePortStdEth1 = 13
    ePortStdEth2 = 14

    from_param = <bound method e_gptp_port.from_param of <enum 'e_gptp_port'>>

class ics.structures.e_gptp_role.e_gptp_role
    A ctypes-compatible IntEnum superclass.

    eRoleDisabled = 0
    eRoleMaster = 2
    eRolePassive = 1
    eRoleSlave = 3

    from_param = <bound method e_gptp_role.from_param of <enum 'e_gptp_role'>>

class ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet_channel_t
    A ctypes-compatible IntEnum superclass.

    PlasmaIonVnetChannelA = 1
    PlasmaIonVnetChannelB = 2
    PlasmaIonVnetChannelMain = 0
    eFpgaStatusResp = 4
    eSoftCore = 3

    from_param = <bound method e_plasma_ion_vnet_channel_t.from_param of <enum 'e_plasma_ion_vnet_channel_t'>>
```



```
class ics.structures.e_uart_port_t.e_uart_port_t
    A ctypes-compatible IntEnum superclass.

    eUART0 = 0
    eUART1 = 1

    from_param = <bound method e_uart_port_t.from_param of <enum 'e_uart_port_t'>>

class ics.structures.ethernet10_g_settings.ethernet10_g_settings

    flags
        Structure/Union member

    gateway
        Structure/Union member

    ip_addr
        Structure/Union member

    link_speed
        Structure/Union member

    netmask
        Structure/Union member

    rsvd2
        Structure/Union member

class ics.structures.ethernet_network_status_t.ethernet_network_status_t

    linkFullDuplex
        Structure/Union member

    linkMode
        Structure/Union member

    linkSpeed
        Structure/Union member

    linkStatus
        Structure/Union member

    networkId
        Structure/Union member

class ics.structures.ethernet_settings.ethernet_settings

    auto_neg
        Structure/Union member

    duplex
        Structure/Union member

    led_mode
        Structure/Union member

    link_speed
        Structure/Union member

    rsvd
        Structure/Union member
```

```
class ics.structures.ethernet_settings2.ethernet_settings2

    flags
        Structure/Union member

    flags2
        Structure/Union member

    gateway
        Structure/Union member

    ip_addr
        Structure/Union member

    link_speed
        Structure/Union member

    netmask
        Structure/Union member

    rsvd
        Structure/Union member

class ics.structures.ew_bms_instance_t.ew_bms_instance_t
    A ctypes-compatible IntEnum superclass.

    ewBMSInstance0 = 0
    ewBMSInstance1 = 1

    from_param = <bound method ew_bms_instance_t.from_param of <enum 'ew_bms_instance_t'>

class ics.structures.ew_bms_manager_lock_state_t.ew_bms_manager_lock_state_t
    A ctypes-compatible IntEnum superclass.

    eLockManager = 0
    eUnlockManager = 1

    from_param = <bound method ew_bms_manager_lock_state_t.from_param of <enum 'ew_bms_manager_lock_state_t'>

class ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t
    A ctypes-compatible IntEnum superclass.

    eManagerPortA = 0
    eManagerPortB = 1

    from_param = <bound method ew_bms_manager_port_t.from_param of <enum 'ew_bms_manager_port_t'>

class ics.structures.extended_response_code.extended_response_code
    A ctypes-compatible IntEnum superclass.

    EXTENDED_RESPONSE_INVALID_COMMAND = -1
    EXTENDED_RESPONSE_INVALID_PARAMETER = -5
    EXTENDED_RESPONSE_INVALID_STATE = -2
    EXTENDED_RESPONSE_OK = 0
    EXTENDED_RESPONSE_OPERATION_FAILED = -3
    EXTENDED_RESPONSE_OPERATION_PENDING = -4

    from_param = <bound method extended_response_code.from_param of <enum 'extended_response_code'>
```

```
class ics.structures.extended_response_generic.extended_response_generic
```

```
    commandType  
        Structure/Union member
```

```
    returnCode  
        Structure/Union member
```

```
class ics.structures.fire3_linux_settings.fire3_linux_settings
```

```
    allowBoot  
        Structure/Union member
```

```
    ethConfigurationPort  
        Structure/Union member
```

```
    reserved  
        Structure/Union member
```

```
    useExternalWifiAntenna  
        Structure/Union member
```

```
class ics.structures.flex_vnet_mode.flex_vnet_mode
```

```
    A ctypes-compatible IntEnum superclass.
```

```
    flexVnetModeColdStart = 4
```

```
    flexVnetModeDisabled = 0
```

```
    flexVnetModeOneDual = 2
```

```
    flexVnetModeOneSingle = 1
```

```
    flexVnetModeTwoSingle = 3
```

```
    from_param = <bound method flex_vnet_mode.from_param of <enum 'flex_vnet_mode'>>
```

```
class ics.structures.generic_api_data.generic_api_data
```

```
    api  
        Structure/Union member
```

```
    bData  
        Structure/Union member
```

```
    length  
        Structure/Union member
```

```
class ics.structures.generic_api_selector.generic_api_selector
```

```
    apiIndex  
        Structure/Union member
```

```
    functionID  
        Structure/Union member
```

```
    instance  
        Structure/Union member
```

```
class ics.structures.generic_api_status.generic_api_status
```

```
api
    Structure/Union member

callbackError
    Structure/Union member

finishedProcessing
    Structure/Union member

functionError
    Structure/Union member

class ics.structures.get_component_versions.get_component_versions

    reserved
        Structure/Union member

class ics.structures.get_component_versions_response.get_component_versions_response

    numVersions
        Structure/Union member

    versions
        Structure/Union member

class ics.structures.get_supported_features_response.get_supported_features_response

    cmdVersion
        Structure/Union member

    featureBitFields
        Structure/Union member

    numValidBits
        Structure/Union member

class ics.structures.global_settings.global_settings

    Nameless32656
        Structure/Union member

    canhub
        Structure/Union member

    chksum
        Structure/Union member

    cmprobe
        Structure/Union member

    cyan
        Structure/Union member

    ecu
        Structure/Union member

    eevb
        Structure/Union member
```

epsilon
Structure/Union member

etherBadge
Structure/Union member

fire
Structure/Union member

fire3
Structure/Union member

fire3fr
Structure/Union member

firevnet
Structure/Union member

flexvnetz
Structure/Union member

ievb
Structure/Union member

jupiter
Structure/Union member

len
Structure/Union member

neoecu12
Structure/Union member

neoecu_avb
Structure/Union member

neoobd2_sim
Structure/Union member

obd21c
Structure/Union member

obd2pro
Structure/Union member

pendant
Structure/Union member

pluto
Structure/Union member

rad_a2b
Structure/Union member

rad_bms
Structure/Union member

radgalaxy
Structure/Union member

radgigalog
Structure/Union member

radgigastar
Structure/Union member

radmoon2
Structure/Union member

radmoon3
Structure/Union member

radmoonduo
Structure/Union member

radstar2
Structure/Union member

radsupermoon
Structure/Union member

red
Structure/Union member

red2
Structure/Union member

vcan3
Structure/Union member

vcan4
Structure/Union member

vcan412
Structure/Union member

vcan4_12
Structure/Union member

vcan4_ind
Structure/Union member

vcanrf
Structure/Union member

version
Structure/Union member

vividcan
Structure/Union member

class ics.structures.gptp_status.gptp_status

as_capable
Structure/Union member

current_time
Structure/Union member

gm_priority
Structure/Union member

is_sync
Structure/Union member

is_syntonized
Structure/Union member

link_delay_ns
Structure/Union member

link_status
Structure/Union member

ms_offset_ns
Structure/Union member

reserved
Structure/Union member

selected_role
Structure/Union member

class ics.structures.hw_eth_settings.**hw_eth_settings**

General_Settings
Structure/Union member

class ics.structures.ics_device_status.**ics_device_status**

fire2Status
Structure/Union member

fire3Status
Structure/Union member

flexVnetzStatus
Structure/Union member

jupiterStatus
Structure/Union member

obd2proStatus
Structure/Union member

plutoStatus
Structure/Union member

radBMSStatus
Structure/Union member

radMoonDuoStatus
Structure/Union member

vcan4Status
Structure/Union member

vcan4indStatus
Structure/Union member

class ics.structures.ics_fire2_device_status.**ics_fire2_device_status**

backupPowerEnabled
Structure/Union member

backupPowerGood
Structure/Union member

ethernetActivationLineEnabled
Structure/Union member

ethernetStatus
Structure/Union member

usbHostPowerEnabled
Structure/Union member

class ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device_status

ethernetActivationLineEnabled
Structure/Union member

ethernetStatus
Structure/Union member

unused
Structure/Union member

class ics.structures.ics_fire3_device_status.ics_fire3_device_status

ethernetActivationLineEnabled
Structure/Union member

ethernetActivationLineEnabled_2
Structure/Union member

ethernetStatus
Structure/Union member

class ics.structures.ics_flex_vnetz_device_status.ics_flex_vnetz_device_status

ethernetActivationLineEnabled
Structure/Union member

ethernetStatus
Structure/Union member

unused
Structure/Union member

class ics.structures.ics_obd2_pro_device_status.ics_obd2_pro_device_status

ethernetStatus
Structure/Union member

class ics.structures.ics_rad_bms_device_status.ics_rad_bms_device_status

ethernetStatus
Structure/Union member

class ics.structures.ics_rad_epsilon_device_status.ics_rad_epsilon_device_status

ethernetStatus

Structure/Union member

```
class ics.structures.ics_rad_jupiter_device_status.ics_rad_jupiter_device_status
```

ethernetStatus

Structure/Union member

```
class ics.structures.ics_rad_moon_duo_device_status.ics_rad_moon_duo_device_status
```

ethernetStatus

Structure/Union member

```
class ics.structures.ics_rad_pluto_device_status.ics_rad_pluto_device_status
```

ethernetStatus

Structure/Union member

```
class ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray
```

AckBytes

Structure/Union member

ArbIDOrHeader

Structure/Union member

Data

Structure/Union member

DescriptionID

Structure/Union member

ExtraDataPtr

Structure/Union member

ExtraDataPtrEnabled

Structure/Union member

MessagePieceID

Structure/Union member

MiscData

Structure/Union member

Nameless21903

Structure/Union member

Nameless65087

Structure/Union member

NetworkID

Structure/Union member

NetworkID2

Structure/Union member

NodeID

Structure/Union member

NumberBytesData
Structure/Union member

NumberBytesHeader
Structure/Union member

Protocol
Structure/Union member

Reserved
Structure/Union member

StatusBitField
Structure/Union member

StatusBitField2
Structure/Union member

StatusBitField3
Structure/Union member

StatusBitField4
Structure/Union member

TimeHardware
Structure/Union member

TimeHardware2
Structure/Union member

TimeStampHardwareID
Structure/Union member

TimeStampSystemID
Structure/Union member

TimeSystem
Structure/Union member

TimeSystem2
Structure/Union member

chA
Structure/Union member

chB
Structure/Union member

cycle
Structure/Union member

dynamic
Structure/Union member

fcrc0
Structure/Union member

fcrc1
Structure/Union member

fcrc2
Structure/Union member

frame_len_12_5ns
Structure/Union member

frame_reserved
Structure/Union member

hcrc_lsbs
Structure/Union member

hcrc_msbs
Structure/Union member

id
Structure/Union member

null_frame
Structure/Union member

payload_preamble
Structure/Union member

res1
Structure/Union member

res2
Structure/Union member

startup
Structure/Union member

sync
Structure/Union member

tss_len_12_5ns
Structure/Union member

class ics.structures.ics_spy_message_long.ics_spy_message_long

AckBytes
Structure/Union member

ArbIDOrHeader
Structure/Union member

DataLsb
Structure/Union member

DataMsb
Structure/Union member

DescriptionID
Structure/Union member

ExtraDataPtr
Structure/Union member

ExtraDataPtrEnabled
Structure/Union member

MessagePieceID
Structure/Union member

MiscData
Structure/Union member

Nameless9872
Structure/Union member

NetworkID
Structure/Union member

NetworkID2
Structure/Union member

NodeID
Structure/Union member

NumberBytesData
Structure/Union member

NumberBytesHeader
Structure/Union member

Protocol
Structure/Union member

Reserved
Structure/Union member

StatusBitField
Structure/Union member

StatusBitField2
Structure/Union member

StatusBitField3
Structure/Union member

StatusBitField4
Structure/Union member

TimeHardware
Structure/Union member

TimeHardware2
Structure/Union member

TimeStampHardwareID
Structure/Union member

TimeStampSystemID
Structure/Union member

TimeSystem
Structure/Union member

TimeSystem2
Structure/Union member

class ics.structures.ics_spy_message_vsb.ics_spy_message_vsb

AckBytes
Structure/Union member

ArbIDOrHeader
Structure/Union member

Data
Structure/Union member

DescriptionID
Structure/Union member

ExtraDataPtr
Structure/Union member

ExtraDataPtrEnabled
Structure/Union member

MessagePieceID
Structure/Union member

MiscData
Structure/Union member

Nameless45381
Structure/Union member

NetworkID
Structure/Union member

NetworkID2
Structure/Union member

NodeID
Structure/Union member

NumberBytesData
Structure/Union member

NumberBytesHeader
Structure/Union member

Protocol
Structure/Union member

Reserved
Structure/Union member

StatusBitField
Structure/Union member

StatusBitField2
Structure/Union member

StatusBitField3
Structure/Union member

StatusBitField4
Structure/Union member

TimeHardware
Structure/Union member

TimeHardware2
Structure/Union member

TimeStampHardwareID
Structure/Union member

TimeStampSystemID
Structure/Union member

TimeSystem
Structure/Union member

TimeSystem2
Structure/Union member

class ics.structures.ics_vcan4_device_status.**ics_vcan4_device_status**

ethernetActivationLineEnabled
Structure/Union member

ethernetStatus
Structure/Union member

unused
Structure/Union member

class ics.structures.ics_vcan4_industrial_device_status.**ics_vcan4_industrial_device_status**

ethernetStatus
Structure/Union member

class ics.structures.iso15765_2015_tx_message.**iso15765_2015_tx_message**

Nameless9252
Structure/Union member

blockSize
Structure/Union member

data
Structure/Union member

ext_address_enable
Structure/Union member

extendedAddress
Structure/Union member

fc_ext_address_enable
Structure/Union member

fc_id
Structure/Union member

fc_id_29_bit_enable
Structure/Union member

fc_id_mask
Structure/Union member

flags
Structure/Union member

flowControlExtendedAddress
Structure/Union member

fs_timeout
Structure/Union member

fs_wait
Structure/Union member

id
Structure/Union member

id_29_bit_enable
Structure/Union member

isBRSEnabled
Structure/Union member

iscanFD
Structure/Union member

num_bytes
Structure/Union member

overrideBlockSize
Structure/Union member

overrideSTmin
Structure/Union member

padding
Structure/Union member

paddingEnable
Structure/Union member

stMin
Structure/Union member

tx_dl
Structure/Union member

tx_index
Structure/Union member

vs_netid
Structure/Union member

class ics.structures.iso9141_keyword2000_init_step.**iso9141_keyword2000_init_step**

k
Structure/Union member

l
Structure/Union member

time_500us
Structure/Union member

class ics.structures.iso9141_keyword2000_settings.**iso9141_keyword2000_settings**

Baudrate
Structure/Union member

brgh
Structure/Union member

chksum_enabled
Structure/Union member

init_step_count
Structure/Union member

init_steps
Structure/Union member

p2_500us
Structure/Union member

p3_500us
Structure/Union member

p4_500us
Structure/Union member

spbrg
Structure/Union member

class ics.structures.j1708_settings.j1708_settings

enable_convert_mode
Structure/Union member

class ics.structures.lin_settings.lin_settings

Baudrate
Structure/Union member

MasterResistor
Structure/Union member

Mode
Structure/Union member

brgh
Structure/Union member

numBitsDelay
Structure/Union member

spbrg
Structure/Union member

class ics.structures.logger_settings.logger_settings

extraction_timeout
Structure/Union member

rsvd
Structure/Union member


```
class ics.structures.op_eth_general_settings.op_eth_general_settings
```

```
    Nameless19471
```

```
        Structure/Union member
```

```
    flags
```

```
        Structure/Union member
```

```
    reserved0
```

```
        Structure/Union member
```

```
    tapPair0
```

```
        Structure/Union member
```

```
    tapPair1
```

```
        Structure/Union member
```

```
    tapPair2
```

```
        Structure/Union member
```

```
    tapPair3
```

```
        Structure/Union member
```

```
    tapPair4
```

```
        Structure/Union member
```

```
    tapPair5
```

```
        Structure/Union member
```

```
    uFlags
```

```
        Structure/Union member
```

```
    ucInterfaceType
```

```
        Structure/Union member
```

```
class ics.structures.op_eth_link_mode.op_eth_link_mode
```

```
    A ctypes-compatible IntEnum superclass.
```

```
    OPETH_LINK_AUTO = 0
```

```
    OPETH_LINK_MASTER = 1
```

```
    OPETH_LINK_SLAVE = 2
```

```
    from_param = <bound method op_eth_link_mode.from_param of <enum 'op_eth_link_mode'>
```

```
class ics.structures.op_eth_settings.op_eth_settings
```

```
    Nameless14996
```

```
        Structure/Union member
```

```
    link_spd
```

```
        Structure/Union member
```

```
    mac_addr1
```

```
        Structure/Union member
```

```
    mac_addr2
```

```
        Structure/Union member
```

```
    mac_spoofing_en
```

```
        Structure/Union member
```

```
mac_spoofing_isDstOrSrc
    Structure/Union member

preemption_en
    Structure/Union member

q2112_phy_mode
    Structure/Union member

reserved
    Structure/Union member

reserved0
    Structure/Union member

ucConfigMode
    Structure/Union member

class ics.structures.port_identity.port_identity

    clock_identity
        Structure/Union member

    port_number
        Structure/Union member

class ics.structures.priority_vector.priority_vector

    port_number
        Structure/Union member

    portid
        Structure/Union member

    steps_removed
        Structure/Union member

    sysid
        Structure/Union member

class ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_converter_settings

    converter1Mode
        Structure/Union member

    ipAddress
        Structure/Union member

    ipGateway
        Structure/Union member

    ipMask
        Structure/Union member

    linkMode0
        Structure/Union member

    linkMode1
        Structure/Union member
```

```
class ics.structures.rad_reporting_settings.rad_reporting_settings
```

```
    fan_speed_interval_ms
```

```
        Structure/Union member
```

```
    flags
```

```
        Structure/Union member
```

```
    gps_interval_ms
```

```
        Structure/Union member
```

```
    io_interval_ms
```

```
        Structure/Union member
```

```
    rsvd
```

```
        Structure/Union member
```

```
    serdes_interval_ms
```

```
        Structure/Union member
```

```
    temp_interval_ms
```

```
        Structure/Union member
```

```
class ics.structures.s_cm_probe_settings.s_cm_probe_settings
```

```
    network_enabled_on_boot
```

```
        Structure/Union member
```

```
    network_enables
```

```
        Structure/Union member
```

```
class ics.structures.s_cyan_settings.s_cyan_settings
```

```
    ain_sample_period
```

```
        Structure/Union member
```

```
    ain_threshold
```

```
        Structure/Union member
```

```
    can1
```

```
        Structure/Union member
```

```
    can2
```

```
        Structure/Union member
```

```
    can3
```

```
        Structure/Union member
```

```
    can4
```

```
        Structure/Union member
```

```
    can5
```

```
        Structure/Union member
```

```
    can6
```

```
        Structure/Union member
```

```
    can7
```

```
        Structure/Union member
```

can8
Structure/Union member

can_switch_mode
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

digitalIoThresholdEnable
Structure/Union member

digitalIoThresholdTicks
Structure/Union member

disk
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

idle_wakeup_network_enables_3
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso9141_kwp_settings_3
Structure/Union member

iso9141_kwp_settings_4
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_msg_termination_3
Structure/Union member

iso_msg_termination_4
Structure/Union member

iso_parity_1
Structure/Union member

iso_parity_2
Structure/Union member

iso_parity_3
Structure/Union member

iso_parity_4
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

lin3
Structure/Union member

lin4
Structure/Union member

lin5
Structure/Union member

lin6
Structure/Union member

lsftcan1
Structure/Union member

lsftcan2
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

slaveVnetA
Structure/Union member

slaveVnetB
Structure/Union member

swcan1
Structure/Union member

swcan2
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

timeSync
Structure/Union member

class ics.structures.s_device_settings.**s_device_settings**

DeviceSettingType
Structure/Union member

Settings
Structure/Union member

```
class ics.structures.s_disk_details.s_disk_details
```

```
    status  
        Structure/Union member
```

```
    structure  
        Structure/Union member
```

```
class ics.structures.s_disk_format_progress.s_disk_format_progress
```

```
    sectorsRemaining  
        Structure/Union member
```

```
    state  
        Structure/Union member
```

```
class ics.structures.s_disk_status.s_disk_status
```

```
    bytesPerSector  
        Structure/Union member
```

```
    sectors  
        Structure/Union member
```

```
    status  
        Structure/Union member
```

```
class ics.structures.s_disk_structure.s_disk_structure
```

```
    options  
        Structure/Union member
```

```
    settings  
        Structure/Union member
```

```
class ics.structures.s_ether_badge_settings.s_ether_badge_settings
```

```
    ain_sample_period  
        Structure/Union member
```

```
    ain_threshold  
        Structure/Union member
```

```
    can1  
        Structure/Union member
```

```
    can2  
        Structure/Union member
```

```
    canfd1  
        Structure/Union member
```

```
    canfd2  
        Structure/Union member
```

```
    ethernet  
        Structure/Union member
```

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_enable_reserved
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso_msg_termination
Structure/Union member

iso_parity
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

class ics.structures.s_ext_sub_cmd_comm.s_ext_sub_cmd_comm

extension
Structure/Union member

header
Structure/Union member

class ics.structures.s_ext_sub_cmd_hdr.s_ext_sub_cmd_hdr

command
Structure/Union member

length
Structure/Union member

class ics.structures.s_extended_data_flash_header.s_extended_data_flash_header

chksum
Structure/Union member

len
Structure/Union member

version
Structure/Union member

class ics.structures.s_fire3_settings.s_fire3_settings

ain_threshold
Structure/Union member

can1
Structure/Union member

can10
Structure/Union member

can11
Structure/Union member

can12
Structure/Union member

can13
Structure/Union member

can14
Structure/Union member

can15
Structure/Union member

can16
Structure/Union member

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

can5
Structure/Union member

can6
Structure/Union member

can7
Structure/Union member

can8
Structure/Union member

can9
Structure/Union member

canfd1
Structure/Union member

canfd10
Structure/Union member

canfd11
Structure/Union member

canfd12
Structure/Union member

canfd13
Structure/Union member

canfd14
Structure/Union member

canfd15
Structure/Union member

canfd16
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

canfd9
Structure/Union member

digitalIoThresholdEnable
Structure/Union member

digitalIoThresholdTicks
Structure/Union member

disk
Structure/Union member

ethernet2_1
Structure/Union member

ethernet2_2
Structure/Union member

ethernet2_3
Structure/Union member

ethernet_1
Structure/Union member

ethernet_2
Structure/Union member

ethernet_3
Structure/Union member

flags
Structure/Union member

gPTP
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso9141_kwp_settings_3
Structure/Union member

iso9141_kwp_settings_4
Structure/Union member

iso9141_kwp_settings_5
Structure/Union member

iso9141_kwp_settings_6
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_msg_termination_3
Structure/Union member

iso_msg_termination_4
Structure/Union member

iso_msg_termination_5
Structure/Union member

iso_msg_termination_6
Structure/Union member

iso_parity_1
Structure/Union member

iso_parity_2
Structure/Union member

iso_parity_3
Structure/Union member

iso_parity_4
Structure/Union member

iso_parity_5
Structure/Union member

iso_parity_6
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

lin3
Structure/Union member

lin4
Structure/Union member

lin5
Structure/Union member

lin6
Structure/Union member

lin7
Structure/Union member

lin8
Structure/Union member

lsftcan1
Structure/Union member

lsftcan2
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

os_settings
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reserved
Structure/Union member

selectable_network_1
Structure/Union member

selectable_network_2
Structure/Union member

slaveVnetA
Structure/Union member

swcan1
Structure/Union member

swcan2
Structure/Union member

termination_enables_1
Structure/Union member

termination_enables_2

Structure/Union member

text_api

Structure/Union member

timeSync

Structure/Union member

class ics.structures.s_fire_settings.s_fire_settings

ain_sample_period

Structure/Union member

ain_threshold

Structure/Union member

can1

Structure/Union member

can2

Structure/Union member

can3

Structure/Union member

can4

Structure/Union member

cgi_baud

Structure/Union member

cgi_chksum_enable

Structure/Union member

cgi_enable_reserved

Structure/Union member

cgi_rx_ifs_bit_times

Structure/Union member

cgi_tx_ifs_bit_times

Structure/Union member

fast_init_network_enables_1

Structure/Union member

fast_init_network_enables_2

Structure/Union member

iso15765_separation_time_offset

Structure/Union member

iso9141_kwp_enable_reserved

Structure/Union member

iso9141_kwp_settings

Structure/Union member

iso9141_kwp_settings_2

Structure/Union member

iso9141_kwp_settings_3
Structure/Union member

iso9141_kwp_settings_4
Structure/Union member

iso_msg_termination
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_msg_termination_3
Structure/Union member

iso_msg_termination_4
Structure/Union member

iso_parity
Structure/Union member

iso_parity_2
Structure/Union member

iso_parity_3
Structure/Union member

iso_parity_4
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

lin3
Structure/Union member

lin4
Structure/Union member

lsftcan
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

neoMostGateway

Structure/Union member

network_enabled_on_boot

Structure/Union member

network_enables

Structure/Union member

network_enables_2

Structure/Union member

perf_en

Structure/Union member

pwm_man_timeout

Structure/Union member

pwr_man_enable

Structure/Union member

swcan

Structure/Union member

text_api

Structure/Union member

uart

Structure/Union member

uart2

Structure/Union member

vnetBits

Structure/Union member

class ics.structures.s_fire_vnet_settings.s_fire_vnet_settings

ain_sample_period

Structure/Union member

ain_threshold

Structure/Union member

can1

Structure/Union member

can2

Structure/Union member

can3

Structure/Union member

can4

Structure/Union member

can5

Structure/Union member

can6

Structure/Union member

cgi_baud
Structure/Union member

cgi_chksum_enable
Structure/Union member

cgi_enable_reserved
Structure/Union member

cgi_rx_ifs_bit_times
Structure/Union member

cgi_tx_ifs_bit_times
Structure/Union member

fast_init_network_enables_1
Structure/Union member

fast_init_network_enables_2
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_enable_reserved
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso9141_kwp_settings_3
Structure/Union member

iso9141_kwp_settings_4
Structure/Union member

iso_msg_termination
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_msg_termination_3
Structure/Union member

iso_msg_termination_4
Structure/Union member

iso_parity
Structure/Union member

iso_parity_2
Structure/Union member

iso_parity_3
Structure/Union member

iso_parity_4
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

lin3
Structure/Union member

lin4
Structure/Union member

lin5
Structure/Union member

lsftcan
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

neoMostGateway
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

perf_en
Structure/Union member

pwm_man_timeout
Structure/Union member

pwr_man_enable
Structure/Union member

swcan
Structure/Union member

swcan2
Structure/Union member

text_api
Structure/Union member

uart
Structure/Union member

uart2
Structure/Union member

vnetBits
Structure/Union member

class ics.structures.s_flex_vnetz_settings.**s_flex_vnetz_settings**

can1
Structure/Union member

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

can5
Structure/Union member

can6
Structure/Union member

can7
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

disk
Structure/Union member

ethernet
Structure/Union member

ethernet2

Structure/Union member

flags

Structure/Union member

flex_mode

Structure/Union member

flex_termination

Structure/Union member

iso15765_separation_time_offset

Structure/Union member

misc_io_on_report_events

Structure/Union member

network_enabled_on_boot

Structure/Union member

network_enables

Structure/Union member

perf_en

Structure/Union member

pwr_man_enable

Structure/Union member

pwr_man_timeout

Structure/Union member

slaveVnetA

Structure/Union member

slaveVnetB

Structure/Union member

termination_enables

Structure/Union member

text_api

Structure/Union member

timeSync

Structure/Union member

class ics.structures.s_jupiter_ptp_params_s.s_jupiter_ptp_params_s

gPTPportRole

Structure/Union member

initLogPDelayReqInterval

Structure/Union member

initLogSyncInterval

Structure/Union member

neighborPropDelay

Structure/Union member

operationLogPDelayReqInterval

Structure/Union member

operationLogSyncInterval

Structure/Union member

class ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings

ain_sample_period

Structure/Union member

ain_threshold

Structure/Union member

can1

Structure/Union member

can2

Structure/Union member

can_switch_mode

Structure/Union member

canfd1

Structure/Union member

canfd2

Structure/Union member

ecu_id

Structure/Union member

flags

Structure/Union member

iso15765_separation_time_offset

Structure/Union member

iso9141_kwp_settings

Structure/Union member

iso_9141_kwp_enable_reserved

Structure/Union member

iso_msg_termination

Structure/Union member

iso_parity

Structure/Union member

lin1

Structure/Union member

lsftcan1

Structure/Union member

lsftcan2

Structure/Union member

misc_io_analog_enable

Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reserved_field
Structure/Union member

swcan1
Structure/Union member

swcan2
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

class ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway_settings

Config
Structure/Union member

netId
Structure/Union member

zero0
Structure/Union member

class ics.structures.s_pendant_settings.s_pendant_settings

ain_sample_period
Structure/Union member

ain_threshold
Structure/Union member

can1
Structure/Union member

can2
Structure/Union member

ecu_id
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso_msg_termination
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_parity
Structure/Union member

iso_parity_2
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

lsftcan
Structure/Union member

lsftcan2
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

selected_network
Structure/Union member

swcan
Structure/Union member

swcan2
Structure/Union member

text_api
Structure/Union member

uart
Structure/Union member

uart2
Structure/Union member

class ics.structures.s_phy_reg_pkt.s_phy_reg_pkt

BusIndex
Structure/Union member

Clause45Enable
Structure/Union member

Enabled
Structure/Union member

Nameless18511
Structure/Union member

Nameless40028
Structure/Union member

WriteEnable
Structure/Union member

clause22
Structure/Union member

clause45
Structure/Union member

flags
Structure/Union member

reserved
Structure/Union member

status
Structure/Union member


```
version
    Structure/Union member

class ics.structures.s_phy_reg_pkt_clause22_mess.s_phy_reg_pkt_clause22_mess

    page
        Structure/Union member

    phyAddr
        Structure/Union member

    regAddr
        Structure/Union member

    regVal
        Structure/Union member

class ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt_clause45_mess

    device
        Structure/Union member

    port
        Structure/Union member

    regAddr
        Structure/Union member

    regVal
        Structure/Union member

class ics.structures.s_phy_reg_pkt_hdr.s_phy_reg_pkt_hdr

    entryBytes
        Structure/Union member

    numEntries
        Structure/Union member

    version
        Structure/Union member

class ics.structures.s_phy_reg_pkt_rw.s_phy_reg_pkt_rw
    A ctypes-compatible IntEnum superclass.

    PHYREG_BOTH = 2

    PHYREG_READ = 0

    PHYREG_WRITE = 1

    from_param = <bound method s_phy_reg_pkt_rw.from_param of <enum 's_phy_reg_pkt_rw'>

class ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_status
    A ctypes-compatible IntEnum superclass.

    PHYREG_FAILURE = 1

    PHYREG_INVALID_MDIO_BUS_INDEX = 2

    PHYREG_INVALID_PHY_ADDR = 3

    PHYREG_RESERVED1 = 5
```

```
PHYREG_RESERVED2 = 6
PHYREG_RESERVED3 = 7
PHYREG_SUCCESS = 0
PHYREG_UNSUPPORTED_MDIO_CLAUSE = 4

from_param = <bound method s_phy_reg_pkt_status.from_param of <enum 's_phy_reg_pkt_
class ics.structures.s_pluto_avb_params_s.s_pluto_avb_params_s

    destmeta
        Structure/Union member

    srcmeta
        Structure/Union member

class ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_sync_params_s

    accdevwin
        Structure/Union member

    asyten syen
        Structure/Union member

    caentmout
        Structure/Union member

    etssrcpcf
        Structure/Union member

    fullcbg
        Structure/Union member

    intcydur
        Structure/Union member

    inttosyncth
        Structure/Union member

    inttotenth
        Structure/Union member

    ipcframesy
        Structure/Union member

    listentmout
        Structure/Union member

    maxintegcy
        Structure/Union member

    maxtranspc1k
        Structure/Union member

    numstbcy
        Structure/Union member

    numunstbcy
        Structure/Union member
```

obvwinsz
Structure/Union member

pad1
Structure/Union member

pad2
Structure/Union member

pad3
Structure/Union member

pcfpriority
Structure/Union member

pcfsze
Structure/Union member

srcport
Structure/Union member

stabasyen
Structure/Union member

stth
Structure/Union member

sttointth
Structure/Union member

swmaster
Structure/Union member

syasyen
Structure/Union member

sydomain
Structure/Union member

sypriority
Structure/Union member

syrelen
Structure/Union member

sysyen
Structure/Union member

syth
Structure/Union member

sytostben
Structure/Union member

sytousyth
Structure/Union member

tentsyrelen
Structure/Union member

tsyth
Structure/Union member

tsytesyth
Structure/Union member

tsytousyth
Structure/Union member

unsytesyth
Structure/Union member

unsytotsyth
Structure/Union member

vlidimnmin
Structure/Union member

vlidinmax
Structure/Union member

vlidout
Structure/Union member

vlidselect
Structure/Union member

waitthsync
Structure/Union member

wfintmout
Structure/Union member

class ics.structures.s_pluto_custom_params_s.s_pluto_custom_params_s

ae1Select
Structure/Union member

enablePhy
Structure/Union member

mode
Structure/Union member

pad
Structure/Union member

ptpParams
Structure/Union member

speed
Structure/Union member

usbSelect
Structure/Union member

class ics.structures.s_pluto_general_params_s.s_pluto_general_params_s

casc_port
Structure/Union member

host_port
Structure/Union member

hostprio
Structure/Union member

ignore2stf
Structure/Union member

incl_srcpt0
Structure/Union member

incl_srcpt1
Structure/Union member

macflt0
Structure/Union member

macflt1
Structure/Union member

macfltres0
Structure/Union member

macfltres1
Structure/Union member

mirr_port
Structure/Union member

mirr_ptacu
Structure/Union member

send_meta0
Structure/Union member

send_meta1
Structure/Union member

switchid
Structure/Union member

tpid
Structure/Union member

tpid2
Structure/Union member

vllupformat
Structure/Union member

vlmarker
Structure/Union member

vlmask
Structure/Union member

class ics.structures.s_pluto_l2_address_lookup_entry_s.s_pluto_l2_address_lookup_entry

destports
Structure/Union member

enfport
Structure/Union member

index
Structure/Union member

learnedEntry
Structure/Union member

macaddr
Structure/Union member

pad1
Structure/Union member

pad2
Structure/Union member

pad3
Structure/Union member

vlanID
Structure/Union member

class ics.structures.s_pluto_l2_address_lookup_params_s.s_pluto_l2_address_lookup_params_s

dyn_tbsz
Structure/Union member

maxage
Structure/Union member

no_enf_hostprt
Structure/Union member

no_mgmt_learn
Structure/Union member

pad
Structure/Union member

poly
Structure/Union member

shared_learn
Structure/Union member

class ics.structures.s_pluto_l2_forwarding_entry_s.s_pluto_l2_forwarding_entry_s

bc_domain
Structure/Union member

fl_domain
Structure/Union member

pad
Structure/Union member

reach_port
Structure/Union member

vlan_pmap
Structure/Union member

```
class ics.structures.s_pluto_l2_forwarding_params_s.s_pluto_l2_forwarding_params_s
```

```
    max_dynp  
        Structure/Union member
```

```
    pad  
        Structure/Union member
```

```
    part_spc  
        Structure/Union member
```

```
class ics.structures.s_pluto_l2_policing_s.s_pluto_l2_policing_s
```

```
    maxlen  
        Structure/Union member
```

```
    partition  
        Structure/Union member
```

```
    rate  
        Structure/Union member
```

```
    sharindx  
        Structure/Union member
```

```
    smax  
        Structure/Union member
```

```
class ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s
```

```
    base  
        Structure/Union member
```

```
    drpdtag  
        Structure/Union member
```

```
    drpnona664  
        Structure/Union member
```

```
    drpuntag  
        Structure/Union member
```

```
    dyn_learn  
        Structure/Union member
```

```
    egr_mirr  
        Structure/Union member
```

```
    egress  
        Structure/Union member
```

```
    enabled  
        Structure/Union member
```

```
    ifg  
        Structure/Union member
```

```
    ing_mirr  
        Structure/Union member
```

ingress
Structure/Union member

maxage
Structure/Union member

pad
Structure/Union member

retag
Structure/Union member

speed
Structure/Union member

top
Structure/Union member

tp_delin
Structure/Union member

tp_delout
Structure/Union member

vlanid
Structure/Union member

vlanprio
Structure/Union member

class ics.structures.s_pluto_ptp_params_s.s_pluto_ptp_params_s

clockaccuracy
Structure/Union member

clockclass
Structure/Union member

gPTPportRole
Structure/Union member

logAnnounceInterval
Structure/Union member

logPDelayReqInterval
Structure/Union member

logSyncInterval
Structure/Union member

neighborPropDelayThresh
Structure/Union member

offset_scaled_log_variance
Structure/Union member

portEnable
Structure/Union member

priority1
Structure/Union member

priority2
Structure/Union member

profile
Structure/Union member

sys_phc_sync_interval
Structure/Union member

class ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s

destports
Structure/Union member

do_not_learn
Structure/Union member

egr_port
Structure/Union member

ing_port
Structure/Union member

pad
Structure/Union member

use_dest_ports
Structure/Union member

vlan_egr
Structure/Union member

vlan_ing
Structure/Union member

class ics.structures.s_pluto_switch_settings_s.s_pluto_switch_settings_s

flashHeader
Structure/Union member

generalParams
Structure/Union member

12_ForwardingEntries
Structure/Union member

12_addressLookupEntries
Structure/Union member

12_addressLookupParams
Structure/Union member

12_forwardingParams
Structure/Union member

12_policing
Structure/Union member

macConfig
Structure/Union member

```
    retagging
        Structure/Union member

    vlan_LookupEntries
        Structure/Union member

class ics.structures.s_pluto_vl_forwarding_entry_s.s_pluto_vl_forwarding_entry_s

    destports
        Structure/Union member

    partition
        Structure/Union member

    priority
        Structure/Union member

    type
        Structure/Union member

class ics.structures.s_pluto_vl_forwarding_params_s.s_pluto_vl_forwarding_params_s

    debugen
        Structure/Union member

    pad
        Structure/Union member

    partspc
        Structure/Union member

class ics.structures.s_pluto_vl_lookup_entry_s.s_pluto_vl_lookup_entry_s

    Nameless11656
        Structure/Union member

    vllupformat0
        Structure/Union member

    vllupformat1
        Structure/Union member

class ics.structures.s_pluto_vl_policing_entry_s.s_pluto_vl_policing_entry_s

    bag
        Structure/Union member

    jitter
        Structure/Union member

    maxlen
        Structure/Union member

    sharindx
        Structure/Union member

    type
        Structure/Union member
```

```
class ics.structures.s_pluto_vlan_lookup.s_s_pluto_vlan_lookup_s
```

```
    pad  
        Structure/Union member
```

```
    tag_port  
        Structure/Union member
```

```
    vegr_mirr  
        Structure/Union member
```

```
    ving_mirr  
        Structure/Union member
```

```
    vlan_bc  
        Structure/Union member
```

```
    vlanid  
        Structure/Union member
```

```
    vmemb_port  
        Structure/Union member
```

```
class ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings
```

```
    converter  
        Structure/Union member
```

```
    flags  
        Structure/Union member
```

```
    network_enabled_on_boot  
        Structure/Union member
```

```
    network_enables  
        Structure/Union member
```

```
    perf_en  
        Structure/Union member
```

```
    pwr_man_enable  
        Structure/Union member
```

```
    pwr_man_timeout  
        Structure/Union member
```

```
class ics.structures.s_red_settings.s_red_settings
```

```
    can1  
        Structure/Union member
```

```
    can2  
        Structure/Union member
```

```
    lin1  
        Structure/Union member
```

```
    lin2  
        Structure/Union member
```

```
class ics.structures.s_spi_port_settings.s_spi_port_settings
```

```
    port_a
        Structure/Union member
```

```
    port_b
        Structure/Union member
```

```
class ics.structures.s_text_api_settings.s_text_api_settings
```

```
    can1_options
        Structure/Union member
```

```
    can1_rx_id
        Structure/Union member
```

```
    can1_tx_id
        Structure/Union member
```

```
    can2_options
        Structure/Union member
```

```
    can2_rx_id
        Structure/Union member
```

```
    can2_tx_id
        Structure/Union member
```

```
    can3_options
        Structure/Union member
```

```
    can3_rx_id
        Structure/Union member
```

```
    can3_tx_id
        Structure/Union member
```

```
    can4_options
        Structure/Union member
```

```
    can4_rx_id
        Structure/Union member
```

```
    can4_tx_id
        Structure/Union member
```

```
    network_enables
        Structure/Union member
```

```
    reserved
        Structure/Union member
```

```
class ics.structures.s_vivid_can_settings.s_vivid_can_settings
```

```
    can1
        Structure/Union member
```

```
    can_switch_mode
        Structure/Union member
```

ecu_id
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

lsftcan1
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

swcan1
Structure/Union member

termination_enables
Structure/Union member

class ics.structures.s_wil_bridge_config.s_wil_bridge_config

config
Structure/Union member

dword
Structure/Union member

class ics.structures.s_wil_connection_settings.s_wil_connection_settings

attemptConnect
Structure/Union member

fault_servicing_config
Structure/Union member

network_data_capture_config
Structure/Union member

sensor_buffer_size
Structure/Union member

using_port_a
Structure/Union member

using_port_b
Structure/Union member

```
class ics.structures.s_wil_fault_servicing_settings.s_wil_fault_servicing_settings
```

```
    enabled  
        Structure/Union member
```

```
    wBMSDeviceID  
        Structure/Union member
```

```
class ics.structures.s_wil_network_data_capture_settings.s_wil_network_data_capture_se
```

```
    enabled  
        Structure/Union member
```

```
class ics.structures.scan_hub_settings.scan_hub_settings
```

```
    can1  
        Structure/Union member
```

```
    canfd1  
        Structure/Union member
```

```
    ecu_id  
        Structure/Union member
```

```
    iso15765_separation_time_offset  
        Structure/Union member
```

```
    network_enabled_on_boot  
        Structure/Union member
```

```
    network_enables  
        Structure/Union member
```

```
    pwr_man_enable  
        Structure/Union member
```

```
    pwr_man_timeout  
        Structure/Union member
```

```
    sleep_id  
        Structure/Union member
```

```
    termination_enables  
        Structure/Union member
```

```
class ics.structures.scan_sleep_id.scan_sleep_id
```

```
    id  
        Structure/Union member
```

```
    word  
        Structure/Union member
```

```
class ics.structures.secu_avb_settings.secu_avb_settings
```

```
    can1  
        Structure/Union member
```

can2
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

class ics.structures.secu_settings.secu_settings

ain_sample_period
Structure/Union member

ain_threshold
Structure/Union member

can1
Structure/Union member

can2
Structure/Union member

ecu_id
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso_msg_termination
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_parity
Structure/Union member

iso_parity_2
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

lsftcan
Structure/Union member

lsftcan2
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

selected_network
Structure/Union member

swcan
Structure/Union member

swcan2
Structure/Union member

text_api
Structure/Union member

uart
Structure/Union member

uart2
Structure/Union member

class ics.structures.seevb_settings.seevb_settings

ain_sample_period
Structure/Union member

ain_threshold
Structure/Union member

can1
Structure/Union member

ecu_id
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

rsvd
Structure/Union member

class ics.structures.serdescam_settings.serdescam_settings

bitPos
Structure/Union member

flags
Structure/Union member

frameSkip
Structure/Union member

mode
Structure/Union member

resHeight
Structure/Union member

resWidth
Structure/Union member

rsvd1
Structure/Union member

```
rsvd2
    Structure/Union member

videoFormat
    Structure/Union member

class ics.structures.serdesgen_settings.serdesgen_settings

    flags
        Structure/Union member

    mod_id
        Structure/Union member

    rsvd1
        Structure/Union member

    rsvd2
        Structure/Union member

    rx_speed
        Structure/Union member

    tx_speed
        Structure/Union member

class ics.structures.serdespoc_settings.serdespoc_settings

    chksum
        Structure/Union member

    mode
        Structure/Union member

    rsvd
        Structure/Union member

    voltage
        Structure/Union member

class ics.structures.sievb_settings.sievb_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    ecu_id
        Structure/Union member

    idle_wakeup_network_enables_1
        Structure/Union member
```

idle_wakeup_network_enables_2
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso_msg_termination
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_parity
Structure/Union member

iso_parity_2
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_analog_enable_2
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

pwr_man_enable
Structure/Union member

```
pwr_man_timeout
    Structure/Union member

reserved_1
    Structure/Union member

reserved_2
    Structure/Union member

selected_network
    Structure/Union member

text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

class ics.structures.sobd2_lc_settings.sobd2_lc_settings

    can1
        Structure/Union member

    can2
        Structure/Union member

    can3
        Structure/Union member

    can4
        Structure/Union member

    can_switch_mode
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    canfd3
        Structure/Union member

    canfd4
        Structure/Union member

    disk
        Structure/Union member

    ethernet
        Structure/Union member

    ethernet2
        Structure/Union member

    flags
        Structure/Union member
```

iso15765_separation_time_offset

Structure/Union member

iso9141_kwp_settings_1

Structure/Union member

iso_msg_termination_1

Structure/Union member

iso_parity_1

Structure/Union member

lin1

Structure/Union member

misc_io_on_report_events

Structure/Union member

network_enabled_on_boot

Structure/Union member

network_enables

Structure/Union member

perf_en

Structure/Union member

pwr_man_enable

Structure/Union member

pwr_man_timeout

Structure/Union member

swcan1

Structure/Union member

text_api

Structure/Union member

class ics.structures.sobd2_pro_settings.sobd2_pro_settings

can1

Structure/Union member

can2

Structure/Union member

can3

Structure/Union member

can4

Structure/Union member

can_switch_mode

Structure/Union member

canfd1

Structure/Union member

canfd2

Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_parity_1
Structure/Union member

iso_parity_2
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

misc_io_analog_enable
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

swcan1
Structure/Union member

text_api
Structure/Union member

class ics.structures.sobd2_sim_settings.sobd2_sim_settings

ain_sample_period
Structure/Union member

ain_threshold
Structure/Union member

can1
Structure/Union member

can2
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

text_api
Structure/Union member

class ics.structures.software_update_command.software_update_command

commandData
Structure/Union member

commandSizeOrProgress

Structure/Union member

commandType

Structure/Union member

componentIdentifier

Structure/Union member

offset

Structure/Union member

class ics.structures.spy_filter_long.spy_filter_long

ByteDataLSB

Structure/Union member

ByteDataLength

Structure/Union member

ByteDataMSB

Structure/Union member

ByteDataMaskLSB

Structure/Union member

ByteDataMaskMSB

Structure/Union member

ExpectedLength

Structure/Union member

FrameMaster

Structure/Union member

Header

Structure/Union member

HeaderLength

Structure/Union member

HeaderMask

Structure/Union member

MiscData

Structure/Union member

MiscDataMask

Structure/Union member

NetworkID

Structure/Union member

NodeID

Structure/Union member

Status2Mask

Structure/Union member

Status2Value

Structure/Union member

StatusMask
Structure/Union member

StatusValue
Structure/Union member

bStuff2
Structure/Union member

bUseArbIdRangeFilter
Structure/Union member

class ics.structures.srad_epsilon_settings.srad_epsilon_settings

can1
Structure/Union member

can2
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_enable_reserved
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso_msg_termination
Structure/Union member

iso_parity
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

misc_io_analog_enable
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

switchSettings
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

class ics.structures.srad_epsilon_switch_settings.**srad_epsilon_switch_settings**

enablePhy
Structure/Union member

legacy
Structure/Union member

pad
Structure/Union member

phyMode
Structure/Union member

speed
Structure/Union member

spoofMacFlag
Structure/Union member

spoofedMac
Structure/Union member

class ics.structures.srad_galaxy_settings.**srad_galaxy_settings**

ain_sample_period
Structure/Union member

ain_threshold
Structure/Union member

can1
Structure/Union member

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

can5
Structure/Union member

can6
Structure/Union member

can7
Structure/Union member

can8
Structure/Union member

can_switch_mode
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

disk
Structure/Union member

ethernet1
Structure/Union member

ethernet2
Structure/Union member

gPTP
Structure/Union member

hwComLatencyTestEn
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

idle_wakeup_network_enables_3
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

logger
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

network_enables_4
Structure/Union member

opEth1
Structure/Union member

opEth10
Structure/Union member

opEth11
Structure/Union member

opEth12
Structure/Union member

opEth2
Structure/Union member

opEth3
Structure/Union member

opEth4
Structure/Union member

opEth5
Structure/Union member

opEth6
Structure/Union member

opEth7
Structure/Union member

opEth8
Structure/Union member

opEth9
Structure/Union member

opEthGen
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reporting
Structure/Union member

swcan1
Structure/Union member

swcan2
Structure/Union member

text_api
Structure/Union member

timeSyncSettings
Structure/Union member

class ics.structures.srad_gigalog_settings.**srad_gigalog_settings**

can1
Structure/Union member

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

can5
Structure/Union member

can6
Structure/Union member

can7
Structure/Union member

can8
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

disk
Structure/Union member

ecu_id
Structure/Union member

ethernet
Structure/Union member

ethernet10g
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

idle_wakeup_network_enables_3
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

logger
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

network_enables_4
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reporting
Structure/Union member

rsvd1
Structure/Union member

rsvd2
Structure/Union member

serdescam1
Structure/Union member

serdescam2
Structure/Union member

serdescam3
Structure/Union member

serdescam4
Structure/Union member

serdesgen
Structure/Union member

serdespoc
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

timeSyncSettings
Structure/Union member

class ics.structures.srad_gigastar_settings.**srad_gigastar_settings**

can1
Structure/Union member

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

can5
Structure/Union member

can6
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

disk
Structure/Union member

ecu_id
Structure/Union member

ethernet1
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

gPTP
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

idle_wakeup_network_enables_3
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

logger
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

network_enables_4
Structure/Union member

opEth1
Structure/Union member

opEth2
Structure/Union member

opEthGen
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reporting
Structure/Union member

serdescam1
Structure/Union member

serdescam2
Structure/Union member

serdescam3
Structure/Union member

serdescam4
Structure/Union member

serdesgen
Structure/Union member

serdespoc
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

timeSyncSettings
Structure/Union member

class ics.structures.srad_gptp_and_tap_settings_s.**srad_gptp_and_tap_settings_s**

gPTP
Structure/Union member

tap
Structure/Union member

```
class ics.structures.srad_gtp_settings_s.srad_gtp_settings_s
```

```
    clockaccuracy  
        Structure/Union member  
  
    clockclass  
        Structure/Union member  
  
    enableClockSyntonization  
        Structure/Union member  
  
    gPTPportRole  
        Structure/Union member  
  
    gptpEnabledPort  
        Structure/Union member  
  
    logAnnounceInterval  
        Structure/Union member  
  
    logPDelayReqInterval  
        Structure/Union member  
  
    logSyncInterval  
        Structure/Union member  
  
    neighborPropDelayThresh  
        Structure/Union member  
  
    offset_scaled_log_variance  
        Structure/Union member  
  
    priority1  
        Structure/Union member  
  
    priority2  
        Structure/Union member  
  
    profile  
        Structure/Union member  
  
    rsvd  
        Structure/Union member  
  
    sys_phc_sync_interval  
        Structure/Union member
```

```
class ics.structures.srad_jupiter_settings.srad_jupiter_settings
```

```
    can1  
        Structure/Union member  
  
    can2  
        Structure/Union member  
  
    canfd1  
        Structure/Union member  
  
    canfd2  
        Structure/Union member
```

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_enable_reserved
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso_msg_termination
Structure/Union member

iso_parity
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

misc_io_analog_enable
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

switchSettings
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

```
class ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings
```

```
    enablePhy  
        Structure/Union member
```

```
    pad  
        Structure/Union member
```

```
    phyMode  
        Structure/Union member
```

```
    port7Select  
        Structure/Union member
```

```
    port8Legacy  
        Structure/Union member
```

```
    port8Select  
        Structure/Union member
```

```
    port8Speed  
        Structure/Union member
```

```
    ptpParams  
        Structure/Union member
```

```
    spoofMacFlag  
        Structure/Union member
```

```
    spoofedMac  
        Structure/Union member
```

```
class ics.structures.srad_moon2_settings.srad_moon2_settings
```

```
    gPTP  
        Structure/Union member
```

```
    hwComLatencyTestEn  
        Structure/Union member
```

```
    network_enabled_on_boot  
        Structure/Union member
```

```
    network_enables  
        Structure/Union member
```

```
    network_enables_2  
        Structure/Union member
```

```
    network_enables_3  
        Structure/Union member
```

```
    opEth1  
        Structure/Union member
```

```
    opEthGen  
        Structure/Union member
```

```
    pc_com_mode  
        Structure/Union member
```

perf_en
Structure/Union member

text_api
Structure/Union member

timeSyncSettings
Structure/Union member

class ics.structures.srad_moon3_settings.srad_moon3_settings

autoEth10g
Structure/Union member

eth10g
Structure/Union member

flags
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

perf_en
Structure/Union member

class ics.structures.srad_pluto_settings.srad_pluto_settings

can1
Structure/Union member

can2
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

custom
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset

Structure/Union member

iso9141_kwp_enable_reserved

Structure/Union member

iso9141_kwp_settings

Structure/Union member

iso_msg_termination

Structure/Union member

iso_parity

Structure/Union member

iso_tester_pullup_enable

Structure/Union member

lin1

Structure/Union member

misc_io_analog_enable

Structure/Union member

network_enabled_on_boot

Structure/Union member

network_enables

Structure/Union member

network_enables_2

Structure/Union member

network_enables_3

Structure/Union member

perf_en

Structure/Union member

pwr_man_enable

Structure/Union member

pwr_man_timeout

Structure/Union member

termination_enables

Structure/Union member

text_api

Structure/Union member

class ics.structures.srad_star2_settings.**srad_star2_settings**

ain_sample_period

Structure/Union member

ain_threshold

Structure/Union member

can1

Structure/Union member

can2
Structure/Union member

can_switch_mode
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

ethernet
Structure/Union member

gPTP
Structure/Union member

hwComLatencyTestEn
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

idle_wakeup_network_enables_3
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot

Structure/Union member

network_enables

Structure/Union member

network_enables_2

Structure/Union member

network_enables_3

Structure/Union member

opEth1

Structure/Union member

opEth2

Structure/Union member

opEthGen

Structure/Union member

pc_com_mode

Structure/Union member

perf_en

Structure/Union member

pwr_man_enable

Structure/Union member

pwr_man_timeout

Structure/Union member

reporting

Structure/Union member

text_api

Structure/Union member

timeSyncSettings

Structure/Union member

class ics.structures.srad_super_moon_settings.srad_super_moon_settings

Eth2

Structure/Union member

gPTP

Structure/Union member

hwComLatencyTestEn

Structure/Union member

network_enabled_on_boot

Structure/Union member

network_enables

Structure/Union member

network_enables_2

Structure/Union member

network_enables_3
Structure/Union member

opEth1
Structure/Union member

opEthGen
Structure/Union member

pc_com_mode
Structure/Union member

perf_en
Structure/Union member

text_api
Structure/Union member

timeSyncSettings
Structure/Union member

class ics.structures.srada2_b_settings.srada2_b_settings

a2b_monitor
Structure/Union member

a2b_node
Structure/Union member

can1
Structure/Union member

can2
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

disk
Structure/Union member

ethernet
Structure/Union member

flags
Structure/Union member

gPTP
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

logger
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reporting
Structure/Union member

termination_enables
Structure/Union member

timeSyncSettings
Structure/Union member

class ics.structures.sradbms_settings.sradbms_settings

can1
Structure/Union member

can2
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

spi_config
Structure/Union member

termination_enables
Structure/Union member

wbms_wil_1
Structure/Union member

wbms_wil_2
Structure/Union member

wil1_nwk_metadata_buff_count
Structure/Union member

wil2_nwk_metadata_buff_count
Structure/Union member

wil_config
Structure/Union member

class ics.structures.st_api_firmware_info.st_api_firmware_info

iAppMajor
Structure/Union member

iAppMinor
Structure/Union member

iBoardRevMajor
Structure/Union member

iBoardRevMinor
Structure/Union member

iBootLoaderVersionMajor
Structure/Union member

iBootLoaderVersionMinor
Structure/Union member

iMainFirmChkSum
Structure/Union member

iMainFirmDateDay
Structure/Union member

iMainFirmDateHour
Structure/Union member

iMainFirmDateMin
Structure/Union member

iMainFirmDateMonth
Structure/Union member

iMainFirmDateSecond
Structure/Union member

iMainFirmDateYear
Structure/Union member

iMainVnetHWrevMajor
Structure/Union member

iMainVnetHWrevMinor
Structure/Union member

iMainVnetSRAMSize
Structure/Union member

iManufactureDay
Structure/Union member

iManufactureMonth
Structure/Union member

iManufactureYear
Structure/Union member

iPhySiliconRev
Structure/Union member

iType
Structure/Union member

class ics.structures.st_chip_versions.st_chip_versions

cmprobe_versions
Structure/Union member

epsilon_versions
Structure/Union member

ether_badge_versions
Structure/Union member

fire3_flexray_versions
Structure/Union member

fire3_versions
Structure/Union member

fire_versions
Structure/Union member

jupiter_versions
Structure/Union member

neoecu_avb_versions
Structure/Union member

obd2dev_versions
Structure/Union member

obd2lc_versions
Structure/Union member

obd2pro_versions
Structure/Union member

plasma_fire_vnet
Structure/Union member

pluto_versions
Structure/Union member

rad_a2b_versions
Structure/Union member

rad_moon_duo_versions
Structure/Union member

radgalaxy_versions
Structure/Union member

radgigalog3_versions
Structure/Union member

radgigalog_versions
Structure/Union member

radgigastar_usbz_versions
Structure/Union member

radgigastar_versions
Structure/Union member

radmoon2_versions
Structure/Union member

radmoon2_z7010_versions
Structure/Union member

radmoon3_versions
Structure/Union member

radstar2_versions
Structure/Union member

radsupermoon_versions
Structure/Union member

red2_versions
Structure/Union member

vcan3_versions
Structure/Union member

vcan41_versions

Structure/Union member

vcan42_versions

Structure/Union member

vcanrf_versions

Structure/Union member

vividcan_versions

Structure/Union member

class ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message

Nameless43713

Structure/Union member

blockSize

Structure/Union member

cf_timeout

Structure/Union member

enableFlowControlTransmission

Structure/Union member

ext_address_enable

Structure/Union member

extendedAddress

Structure/Union member

fc_ext_address_enable

Structure/Union member

fc_id

Structure/Union member

fc_id_29_bit_enable

Structure/Union member

flags

Structure/Union member

flowControlExtendedAddress

Structure/Union member

id

Structure/Union member

id_29_bit_enable

Structure/Union member

id_mask

Structure/Union member

isBRSEnabled

Structure/Union member

iscanFD

Structure/Union member

padding
Structure/Union member

paddingEnable
Structure/Union member

reserved
Structure/Union member

stMin
Structure/Union member

vs_netid
Structure/Union member

class ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message

Nameless59426
Structure/Union member

blockSize
Structure/Union member

data
Structure/Union member

ext_address_enable
Structure/Union member

extendedAddress
Structure/Union member

fc_ext_address_enable
Structure/Union member

fc_id
Structure/Union member

fc_id_29_bit_enable
Structure/Union member

fc_id_mask
Structure/Union member

flags
Structure/Union member

flowControlExtendedAddress
Structure/Union member

fs_timeout
Structure/Union member

fs_wait
Structure/Union member

id
Structure/Union member

id_29_bit_enable
Structure/Union member

isBRSEnabled
Structure/Union member

iscanFD
Structure/Union member

num_bytes
Structure/Union member

overrideBlockSize
Structure/Union member

overrideSTmin
Structure/Union member

padding
Structure/Union member

paddingEnable
Structure/Union member

stMin
Structure/Union member

tx_dl
Structure/Union member

tx_index
Structure/Union member

vs_netid
Structure/Union member

class ics.structures.start_dhcp_server_command.start_dhcp_server_command

endAddress
Structure/Union member

gatewayAddress
Structure/Union member

leaseTime
Structure/Union member

networkId
Structure/Union member

overwrite
Structure/Union member

serverIpAddress
Structure/Union member

startAddress
Structure/Union member

subnetMask
Structure/Union member

class ics.structures.stop_dhcp_server_command.stop_dhcp_server_command

networkId
Structure/Union member

class ics.structures.svcan3_settings.svcan3_settings

can1
Structure/Union member

can2
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

class ics.structures.svcan412_settings.svcan412_settings

can1
Structure/Union member

can2
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

termination_enables
Structure/Union member

text_api
Structure/Union member

class ics.structures.svcan4_ind_settings.svcan4_ind_settings

can1
Structure/Union member

can2
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso_msg_termination
Structure/Union member

iso_parity
Structure/Union member

lin1
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

termination_enables
Structure/Union member

class ics.structures.svcan4_settings.svcan4_settings

can1
Structure/Union member

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

network_enabled_on_boot

Structure/Union member

network_enables

Structure/Union member

network_enables_2

Structure/Union member

network_enables_3

Structure/Union member

perf_en

Structure/Union member

pwr_man_enable

Structure/Union member

pwr_man_timeout

Structure/Union member

termination_enables

Structure/Union member

text_api

Structure/Union member

class ics.structures.svcanrf_settings.svcanrf_settings

can1

Structure/Union member

can2

Structure/Union member

can3

Structure/Union member

can4

Structure/Union member

disableFwLEDs

Structure/Union member

idle_wakeup_network_enables_1

Structure/Union member

idle_wakeup_network_enables_2

Structure/Union member

iso15765_separation_time_offset

Structure/Union member

iso9141_kwp_enable_reserved

Structure/Union member

iso9141_kwp_settings

Structure/Union member

iso9141_kwp_settings_2

Structure/Union member

iso_msg_termination
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_parity
Structure/Union member

iso_parity_2
Structure/Union member

iso_tester_pullup_enable
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reservedZero
Structure/Union member

class ics.structures.swcan_settings.swcan_settings

BRP
Structure/Union member

Baudrate
Structure/Union member

Mode
Structure/Union member

RESERVED
Structure/Union member

SetBaudrate
Structure/Union member

TqProp
Structure/Union member

TqSeg1
Structure/Union member

TqSeg2
Structure/Union member

TqSync
Structure/Union member

auto_baud
Structure/Union member

high_speed_auto_switch
Structure/Union member

transceiver_mode
Structure/Union member

class ics.structures.system_identity.system_identity

clock_identity
Structure/Union member

clock_quality
Structure/Union member

priority_1
Structure/Union member

priority_2
Structure/Union member

class ics.structures.tag_options_find_neo_ex.tag_options_find_neo_ex

CANOptions
Structure/Union member

Reserved
Structure/Union member

class ics.structures.tag_options_open_neo_ex.tag_options_open_neo_ex

CANOptions
Structure/Union member

Reserved

Structure/Union member

class ics.structures.tagicsneo_vi_command.tagicsneo_vi_command**CommandByteLength**

Structure/Union member

CommandType

Structure/Union member

Data

Structure/Union member

class ics.structures.timestamp_.timestamp_**nanoseconds**

Structure/Union member

seconds_lsb

Structure/Union member

seconds_msb

Structure/Union member

class ics.structures.timesync_icshardware_settings.timesync_icshardware_settings**MasterEnable**

Structure/Union member

MasterNetwork

Structure/Union member

SlaveEnable

Structure/Union member

SlaveNetwork

Structure/Union member

class ics.structures.uart_port_config.uart_port_config**baudrate**

Structure/Union member

port

Structure/Union member

reserve

Structure/Union member

class ics.structures.uart_port_data.uart_port_data**bData**

Structure/Union member

len

Structure/Union member

port
Structure/Union member

class ics.structures.uart_port_port_bytes.uart_port_port_bytes

flag
Structure/Union member

len
Structure/Union member

port
Structure/Union member

class ics.structures.uart_settings.uart_settings

Baudrate
Structure/Union member

Nameless2284
Structure/Union member

bOptions
Structure/Union member

brgh
Structure/Union member

flow_control
Structure/Union member

half_duplex
Structure/Union member

invert_rx
Structure/Union member

invert_tx
Structure/Union member

parity
Structure/Union member

reserved_1
Structure/Union member

reserved_bits
Structure/Union member

reserved_bits2
Structure/Union member

spbrg
Structure/Union member

stop_bits
Structure/Union member

class ics.structures.version_report.version_report

commitHash
Structure/Union member

componentInfo
Structure/Union member

dotVersion
Structure/Union member

expansionSlot
Structure/Union member

identifier
Structure/Union member

reserved
Structure/Union member

valid
Structure/Union member

class ics.structures.w_bms_manager_reset.w_bms_manager_reset

managerIndex
Structure/Union member

class ics.structures.w_bms_manager_set_lock.w_bms_manager_set_lock

managerIndex
Structure/Union member

setLock
Structure/Union member

CHAPTER 10

Module Variables

```
ics.ics.A2B_SETTINGS_FLAG_16BIT = 1
ics.ics.AUTO = 0
ics.ics.BPS100 = 5
ics.ics.BPS1000 = 10
ics.ics.BPS100000 = 7
ics.ics.BPS10400 = 1
ics.ics.BPS117647 = 8
ics.ics.BPS125 = 6
ics.ics.BPS20 = 0
ics.ics.BPS2000 = 12
ics.ics.BPS250 = 7
ics.ics.BPS33 = 1
ics.ics.BPS33333 = 2
ics.ics.BPS4000 = 13
ics.ics.BPS50 = 2
ics.ics.BPS500 = 8
ics.ics.BPS5000 = 0
ics.ics.BPS50000 = 3
ics.ics.BPS62 = 3
ics.ics.BPS62500 = 4
ics.ics.BPS666 = 11
ics.ics.BPS71429 = 5
```

```
ics.ics.BPS800 = 9
ics.ics.BPS83 = 4
ics.ics.BPS83333 = 6
ics.ics.BUILD_DATETIME = Apr 3 2023 12:37:17
ics.ics.CANFD_BRS_ENABLED = 2
ics.ics.CANFD_BRS_ENABLED_ISO = 4
ics.ics.CANFD_ENABLED = 1
ics.ics.CANFD_ENABLED_ISO = 3
ics.ics.CANFD_SETTINGS_SIZE = 10
ics.ics.CANNODE_STATUS_COREMINI_IS_RUNNING = 1
ics.ics.CANNODE_STATUS_IN_BOOTLOADER = 2
ics.ics.CANTERM_SETTINGS_SIZE = 6
ics.ics.CAN_BPS10000 = 17
ics.ics.CAN_BPS5000 = 14
ics.ics.CAN_BPS6667 = 15
ics.ics.CAN_BPS8000 = 16
ics.ics.CAN_SETTINGS_SIZE = 12
ics.ics.DEVICECOUNT_FOR_EXPLORER = 43
ics.ics.DISABLE = 1
ics.ics.DISK_SETTINGS_SIZE = 14
ics.ics.DISK_STATUS_FLAG_INITIALIZED = 2
ics.ics.DISK_STATUS_FLAG_PRESENT = 1
ics.ics.DISK_STRUCTURE_FLAG_FULL_FORMAT = 1
ics.ics.ETHERNET10G_SETTINGS_SIZE = 24
ics.ics.ETHERNET_SETTINGS10G_FLAG_AUTO_NEG = 2
ics.ics.ETHERNET_SETTINGS10G_FLAG_COMM_IN_USE = -2147483648
ics.ics.ETHERNET_SETTINGS10G_FLAG_CONFIG_NOT_ALLOWED = 32
ics.ics.ETHERNET_SETTINGS10G_FLAG_DEVICE_HOSTING_ENABLE = 16
ics.ics.ETHERNET_SETTINGS10G_FLAG_FULL_DUPLEX = 1
ics.ics.ETHERNET_SETTINGS10G_FLAG_ICS_SFP = 64
ics.ics.ETHERNET_SETTINGS10G_FLAG_LINK_MODE = 128
ics.ics.ETHERNET_SETTINGS10G_FLAG_LINK_MODE_AUTO = 512
ics.ics.ETHERNET_SETTINGS10G_FLAG_PHY_MODE = 256
ics.ics.ETHERNET_SETTINGS10G_FLAG_RTSP_ENABLE = 8
ics.ics.ETHERNET_SETTINGS10G_FLAG_TCPIP_ENABLE = 4
ics.ics.ETHERNET_SETTINGS2_FLAG2_LINK_MODE = 1
```

```
ics.ics.ETHERNET_SETTINGS2_FLAG2_LINK_MODE_AUTO = 4
ics.ics.ETHERNET_SETTINGS2_FLAG2_PHY_MODE = 2
ics.ics.ETHERNET_SETTINGS2_FLAG_AUTO_NEG = 2
ics.ics.ETHERNET_SETTINGS2_FLAG_COMM_IN_USE = 128
ics.ics.ETHERNET_SETTINGS2_FLAG_CONFIG_NOT_ALLOWED = 32
ics.ics.ETHERNET_SETTINGS2_FLAG_DEVICE_HOSTING_ENABLE = 16
ics.ics.ETHERNET_SETTINGS2_FLAG_FULL_DUPLEX = 1
ics.ics.ETHERNET_SETTINGS2_FLAG_ICS_SFP = 64
ics.ics.ETHERNET_SETTINGS2_FLAG_RTSP_ENABLE = 8
ics.ics.ETHERNET_SETTINGS2_FLAG_TCPIP_ENABLE = 4
ics.ics.ETHERNET_SETTINGS2_SIZE = 16
ics.ics.ETHERNET_SETTINGS_SIZE = 8
ics.ics.EXTENDED_RESPONSE_INVALID_COMMAND = -1
ics.ics.EXTENDED_RESPONSE_INVALID_PARAMETER = -5
ics.ics.EXTENDED_RESPONSE_INVALID_STATE = -2
ics.ics.EXTENDED_RESPONSE_OK = 0
ics.ics.EXTENDED_RESPONSE_OPERATION_FAILED = -3
ics.ics.EXTENDED_RESPONSE_OPERATION_PENDING = -4
ics.ics.FAST_MODE = 3
ics.ics.GENERIC_API_DATA_BUFFER_SIZE = 513
ics.ics.GET_SUPPORTED_FEATURES_COMMAND_VERSION = 1
ics.ics.GLOBAL_SETTINGS_SIZE = 942
ics.ics.GS_VERSION = 5
ics.ics.HARDWARE_TIMESTAMP_ID_AVT_716 = 2
ics.ics.HARDWARE_TIMESTAMP_ID_AVT_717 = 5
ics.ics.HARDWARE_TIMESTAMP_ID_DOUBLE_SEC = 7
ics.ics.HARDWARE_TIMESTAMP_ID_NEORED_10NS = 10
ics.ics.HARDWARE_TIMESTAMP_ID_NEORED_10US = 8
ics.ics.HARDWARE_TIMESTAMP_ID_NEORED_25NS = 9
ics.ics.HARDWARE_TIMESTAMP_ID_NEOVI = 4
ics.ics.HARDWARE_TIMESTAMP_ID_NI_CAN = 3
ics.ics.HARDWARE_TIMESTAMP_ID_NONE = 0
ics.ics.HARDWARE_TIMESTAMP_ID_VSI = 1
ics.ics.HW_ETH_SETTINGS_SIZE = 20
ics.ics.ISO15765_2_NETWORK_HSCAN = 1
ics.ics.ISO15765_2_NETWORK_HSCAN2 = 4
```

```
ics.ics.ISO15765_2_NETWORK_HSCAN3 = 8
ics.ics.ISO15765_2_NETWORK_HSCAN4 = 20
ics.ics.ISO15765_2_NETWORK_HSCAN5 = 24
ics.ics.ISO15765_2_NETWORK_HSCAN6 = 28
ics.ics.ISO15765_2_NETWORK_HSCAN7 = 32
ics.ics.ISO15765_2_NETWORK_MSCAN = 2
ics.ics.ISO15765_2_NETWORK_SWCAN = 16
ics.ics.ISO15765_2_NETWORK_SWCAN2 = 36
ics.ics.ISO9141_KEYWORD2000_SETTINGS_SIZE = 114
ics.ics.ISO9141_KEYWORD2000__INIT_STEP_SIZE = 6
ics.ics.J1708_SETTINGS_SIZE = 2
ics.ics.JUPITER_PTP_ROLE_DISABLED = 0
ics.ics.JUPITER_PTP_ROLE_MASTER = 1
ics.ics.JUPITER_PTP_ROLE_SLAVE = 2
ics.ics.LINUX_BOOT_ALLOWED = 1
ics.ics.LINUX_CONFIG_PORT_ETH_01 = 1
ics.ics.LINUX_CONFIG_PORT_ETH_02 = 2
ics.ics.LINUX_CONFIG_PORT_NONE = 0
ics.ics.LIN_SETTINGS_SIZE = 10
ics.ics.LISTEN_ALL = 7
ics.ics.LISTEN_ONLY = 3
ics.ics.LOGGER_SETTINGS_SIZE = 4
ics.ics.LOOPBACK = 2
ics.ics.MAIN_VNET = 1
ics.ics.MAX_NUMBYTES_PHYSETTINGS = 512
ics.ics.MAX_PHY_REG_PKT_ENTRIES = 128
ics.ics.MAX_PHY_SETTINGS_STRUCT = 128
ics.ics.MAX_REPORTED_VERSIONS = 16
ics.ics.MAX_VL_FORWARDING_ENTRIES = 1024
ics.ics.MAX_VL_POLICING_ENTRIES = 1024
ics.ics.NEODEVICE_ANY_ION = 262144
ics.ics.NEODEVICE_ANY_PLASMA = 4096
ics.ics.NEODEVICE_BLUE = 1
ics.ics.NEODEVICE_CMPROBE = 8388608
ics.ics.NEODEVICE_CT_OBD = 32768
ics.ics.NEODEVICE_DONT_REUSE0 = 8192
```

```
ics.ics.NEODEVICE_DONT_REUSE1 = 65536
ics.ics.NEODEVICE_DONT_REUSE2 = 131072
ics.ics.NEODEVICE_DONT_REUSE3 = 1048576
ics.ics.NEODEVICE_DW_VCAN = 4
ics.ics.NEODEVICE_ECU = 128
ics.ics.NEODEVICE_ECU22 = 27
ics.ics.NEODEVICE_ECUCHIP_UART = 2048
ics.ics.NEODEVICE_ECU_AVB = 2
ics.ics.NEODEVICE_EEVB = 16777216
ics.ics.NEODEVICE_ETHER_BADGE = 22
ics.ics.NEODEVICE_FIRE = 8
ics.ics.NEODEVICE_FIRE2 = 67108864
ics.ics.NEODEVICE_FIRE2_REDLINE = 21
ics.ics.NEODEVICE_FIRE3 = 15
ics.ics.NEODEVICE_FLEX = 134217728
ics.ics.NEODEVICE_GIGASTAR = 19
ics.ics.NEODEVICE_IEVB = 256
ics.ics.NEODEVICE_ION = 262144
ics.ics.NEODEVICE_NEOANALOG = 16384
ics.ics.NEODEVICE_NEOECU12 = 12
ics.ics.NEODEVICE_NEOECUCHIP = 256
ics.ics.NEODEVICE_NEW_DEVICE_58 = 31
ics.ics.NEODEVICE_NEW_DEVICE_59 = 33
ics.ics.NEODEVICE_NEW_DEVICE_FF = 37
ics.ics.NEODEVICE_OBD2_DEV = 26
ics.ics.NEODEVICE_OBD2_LC = 13
ics.ics.NEODEVICE_OBD2_PRO = 1024
ics.ics.NEODEVICE_OBD2_SIM = -2147483648
ics.ics.NEODEVICE_OBD2_SIM_DOIP = 25
ics.ics.NEODEVICE_PENDANT = 512
ics.ics.NEODEVICE_PLASMA = 4096
ics.ics.NEODEVICE_RADCOMET = 36
ics.ics.NEODEVICE_RADEPSILON = 24
ics.ics.NEODEVICE_RADEPSILON_EXPRESS = 29
ics.ics.NEODEVICE_RADEPSILON_T = 28
ics.ics.NEODEVICE_RADGALAXY = 268435456
```

```
ics.ics.NEODEVICE_RADGIGALOG = 6
ics.ics.NEODEVICE_RADIO_CANHUB = 11
ics.ics.NEODEVICE_RADJUPITER = 17
ics.ics.NEODEVICE_RADMOON2 = 5
ics.ics.NEODEVICE_RADMOON3 = 35
ics.ics.NEODEVICE_RADPLUTO = 9
ics.ics.NEODEVICE_RADPROXIMA = 30
ics.ics.NEODEVICE_RADSTAR = 524288
ics.ics.NEODEVICE_RADSTAR2 = 536870912
ics.ics.NEODEVICE_RADSUPERMOON = 3
ics.ics.NEODEVICE_RAD_A2B = 23
ics.ics.NEODEVICE_RAD_BMS = 34
ics.ics.NEODEVICE_RAD_MOON_DUO = 14
ics.ics.NEODEVICE_RED = 64
ics.ics.NEODEVICE_RED2 = 20
ics.ics.NEODEVICE_UNKNOWN = 0
ics.ics.NEODEVICE_VCAN3 = 16
ics.ics.NEODEVICE_VCAN41 = 7
ics.ics.NEODEVICE_VCAN42 = 4194304
ics.ics.NEODEVICE_VCAN42_EL = 10
ics.ics.NEODEVICE_VCAN44 = 2097152
ics.ics.NEODEVICE_VCAN4_IND = 18
ics.ics.NEODEVICE_VCANRF = 33554432
ics.ics.NEODEVICE_VIVIDCAN = 1073741824
ics.ics.NEOVI6_VCAN_TIMESTAMP_1 = 1e-06
ics.ics.NEOVI6_VCAN_TIMESTAMP_2 = 0.065536
ics.ics.NEOVIPRO_VCAN_TIMESTAMP_1 = 1e-06
ics.ics.NEOVIPRO_VCAN_TIMESTAMP_2 = 0.065536
ics.ics.NEOVI_3G_MAX_SETTINGS_SIZE = 942
ics.ics.NEOVI_COMMTYPE_FIRE_USB = 5
ics.ics.NEOVI_COMMTYPE_RS232 = 0
ics.ics.NEOVI_COMMTYPE_TCPIP = 3
ics.ics.NEOVI_COMMTYPE_USB_BULK = 1
ics.ics.NEOVI_RED_TIMESTAMP_1_10NS = 1e-08
ics.ics.NEOVI_RED_TIMESTAMP_1_25NS = 2.5e-08
ics.ics.NEOVI_RED_TIMESTAMP_2_10NS = 429.4967296
```



```
ics.ics.NEOVI_RED_TIMESTAMP_2_25NS = 107.3741824
ics.ics.NEOVI_TIMESTAMP_1 = 1.6e-06
ics.ics.NEOVI_TIMESTAMP_2 = 0.1048576
ics.ics.NEO_CFG_MPIC_HS_CAN_CNF1 = 522
ics.ics.NEO_CFG_MPIC_HS_CAN_CNF2 = 521
ics.ics.NEO_CFG_MPIC_HS_CAN_CNF3 = 520
ics.ics.NEO_CFG_MPIC_HS_CAN_MODE = 566
ics.ics.NEO_CFG_MPIC_LSFT_CAN_CNF1 = 558
ics.ics.NEO_CFG_MPIC_LSFT_CAN_CNF2 = 557
ics.ics.NEO_CFG_MPIC_LSFT_CAN_CNF3 = 556
ics.ics.NEO_CFG_MPIC_MS_CAN_CNF1 = 534
ics.ics.NEO_CFG_MPIC_MS_CAN_CNF2 = 533
ics.ics.NEO_CFG_MPIC_MS_CAN_CNF3 = 532
ics.ics.NEO_CFG_MPIC_SW_CAN_CNF1 = 546
ics.ics.NEO_CFG_MPIC_SW_CAN_CNF2 = 545
ics.ics.NEO_CFG_MPIC_SW_CAN_CNF3 = 544
ics.ics.NETID_3G_APP_SIGNAL_STATUS = 56
ics.ics.NETID_3G_FB_STATUS = 55
ics.ics.NETID_3G_LOGGING_OVERFLOW = 59
ics.ics.NETID_3G_READ_DATA LINK_CM_RX_MSG = 58
ics.ics.NETID_3G_READ_DATA LINK_CM_TX_MSG = 57
ics.ics.NETID_3G_READ_SETTINGS_EX = 60
ics.ics.NETID_3G_RESET_STATUS = 54
ics.ics.NETID_A2B_01 = 522
ics.ics.NETID_A2B_02 = 523
ics.ics.NETID_AUTOSAR = 515
ics.ics.NETID_AUX = 7
ics.ics.NETID_CAN_SWITCH = 526
ics.ics.NETID_CGI = 53
ics.ics.NETID_DATA_TO_HOST = 70
ics.ics.NETID_DEVICE = 0
ics.ics.NETID_DEVICE_STATUS = 513
ics.ics.NETID_ETHERNET = 93
ics.ics.NETID_ETHERNET2 = 520
ics.ics.NETID_ETHERNET3 = 524
ics.ics.NETID_ETHERNET_DAQ = 69
```

```
ics.ics.NETID_ETHERNET_TX_WRAP = 521
ics.ics.NETID_FLEXRAY = 85
ics.ics.NETID_FLEXRAY1A = 80
ics.ics.NETID_FLEXRAY1B = 81
ics.ics.NETID_FLEXRAY2 = 86
ics.ics.NETID_FLEXRAY2A = 82
ics.ics.NETID_FLEXRAY2B = 83
ics.ics.NETID_FORDSCP = 5
ics.ics.NETID_FORWARDED_MESSAGE = 516
ics.ics.NETID_GMFSA = 94
ics.ics.NETID_HSCAN = 1
ics.ics.NETID_HSCAN2 = 42
ics.ics.NETID_HSCAN3 = 44
ics.ics.NETID_HSCAN4 = 61
ics.ics.NETID_HSCAN5 = 62
ics.ics.NETID_HSCAN6 = 96
ics.ics.NETID_HSCAN7 = 97
ics.ics.NETID_HW_COM_LATENCY_TEST = 512
ics.ics.NETID_I2C1 = 88
ics.ics.NETID_I2C2 = 517
ics.ics.NETID_I2C3 = 518
ics.ics.NETID_I2C4 = 519
ics.ics.NETID_INVALID = 65535
ics.ics.NETID_ISM_LOGGER = 525
ics.ics.NETID_ISO = 9
ics.ics.NETID_ISO14230 = 15
ics.ics.NETID_ISO2 = 14
ics.ics.NETID_ISO3 = 41
ics.ics.NETID_ISO4 = 47
ics.ics.NETID_ISOPIC = 10
ics.ics.NETID_J1708 = 6
ics.ics.NETID_JVPW = 8
ics.ics.NETID_LIN = 16
ics.ics.NETID_LIN2 = 48
ics.ics.NETID_LIN3 = 49
ics.ics.NETID_LIN4 = 50
```

```
ics.ics.NETID_LIN5 = 84
ics.ics.NETID_LIN6 = 98
ics.ics.NETID_LSFTCAN = 4
ics.ics.NETID_LSFTCAN2 = 99
ics.ics.NETID_MAIN51 = 11
ics.ics.NETID_MAX = 100
ics.ics.NETID_MOST = 51
ics.ics.NETID_MOST150 = 92
ics.ics.NETID_MOST25 = 90
ics.ics.NETID_MOST50 = 91
ics.ics.NETID_MSCAN = 2
ics.ics.NETID_OP_ETHERNET1 = 17
ics.ics.NETID_OP_ETHERNET10 = 78
ics.ics.NETID_OP_ETHERNET11 = 79
ics.ics.NETID_OP_ETHERNET12 = 87
ics.ics.NETID_OP_ETHERNET2 = 18
ics.ics.NETID_OP_ETHERNET3 = 19
ics.ics.NETID_OP_ETHERNET4 = 45
ics.ics.NETID_OP_ETHERNET5 = 46
ics.ics.NETID_OP_ETHERNET6 = 73
ics.ics.NETID_OP_ETHERNET7 = 75
ics.ics.NETID_OP_ETHERNET8 = 76
ics.ics.NETID_OP_ETHERNET9 = 77
ics.ics.NETID_RED = 12
ics.ics.NETID_RED_APP_ERROR = 52
ics.ics.NETID_RED_VBAT = 74
ics.ics.NETID_RS232 = 63
ics.ics.NETID_SCI = 13
ics.ics.NETID_SPI1 = 72
ics.ics.NETID_SWCAN = 3
ics.ics.NETID_SWCAN2 = 68
ics.ics.NETID_TCP = 95
ics.ics.NETID_TEXTAPI_TO_HOST = 71
ics.ics.NETID_UART = 64
ics.ics.NETID_UART2 = 65
ics.ics.NETID_UART3 = 66
```

```
ics.ics.NETID_UART4 = 67
ics.ics.NETID_UDP = 514
ics.ics.NETID_WBMS = 532
ics.ics.NORMAL = 0
ics.ics.NORMAL_MODE = 2
ics.ics.NO_CANFD = 0
ics.ics.NUM_DEVICE_FEATURE_BITFIELDS = 1
ics.ics.NUM_VALID_DEVICE_FEATURES = 17
ics.ics.OPETH_FUNC_MEDIACONVERTER = 1
ics.ics.OPETH_FUNC_RAW_MEDIA_CONVERTER = 3
ics.ics.OPETH_FUNC_RAW_MEDIA_CONVERTER2 = 4
ics.ics.OPETH_FUNC_RAW_MEDIA_CONVERTER2_LOW_LATENCY = 5
ics.ics.OPETH_FUNC_TAP = 0
ics.ics.OPETH_FUNC_TAP_LOW_LATENCY = 2
ics.ics.OPETH_LINK_AUTO = 0
ics.ics.OPETH_LINK_MASTER = 1
ics.ics.OPETH_LINK_SLAVE = 2
ics.ics.OPETH_MAC_SPOOF_DST_ADDR = 0
ics.ics.OPETH_MAC_SPOOF_SRC_ADDR = 1
ics.ics.OP_ETH_GENERAL_SETTINGS_SIZE = 20
ics.ics.OP_ETH_SETTINGS_SIZE = 16
ics.ics.PHYREG_BOTH = 2
ics.ics.PHYREG_FAILURE = 1
ics.ics.PHYREG_INVALID_MDIO_BUS_INDEX = 2
ics.ics.PHYREG_INVALID_PHY_ADDR = 3
ics.ics.PHYREG_READ = 0
ics.ics.PHYREG_RESERVED1 = 5
ics.ics.PHYREG_RESERVED2 = 6
ics.ics.PHYREG_RESERVED3 = 7
ics.ics.PHYREG_SUCCESS = 0
ics.ics.PHYREG_UNSUPPORTED_MDIO_CLAUSE = 4
ics.ics.PHYREG_WRITE = 1
ics.ics.PHY_REG_PKT_VERSION = 1
ics.ics.PLASMA_SLAVE1_OFFSET = 100
ics.ics.PLASMA_SLAVE1_OFFSET_RANGE2 = 4608
ics.ics.PLASMA_SLAVE2_OFFSET = 200
```

```
ics.ics.PLASMA_SLAVE2_OFFSET_RANGE2 = 8704
ics.ics.PLASMA_SLAVE3_OFFSET_RANGE2 = 12800
ics.ics.PLASMA_SLAVE_NUM = 51
ics.ics.PLUTO_MAX_FORWARDING_ENTRIES = 13
ics.ics.PLUTO_MAX_L2_ADDRESS_LOOKUP = 1024
ics.ics.PLUTO_MAX_L2_POLICING = 45
ics.ics.PLUTO_MAX_MAC_CONFIG_ENTRIES = 5
ics.ics.PLUTO_MAX_RETAGGING_ENTRIES = 32
ics.ics.PLUTO_MAX_VLAN_LOOKUP = 4096
ics.ics.PLUTO_NUM_PORTS = 5
ics.ics.PLUTO_NUM_PRIORITY = 8
ics.ics.RADEPSILON_MAX_PHY = 18
ics.ics.RADJUPITER_NUM_PORTS = 8
ics.ics.RADMOONDUO_CONVERTER_SETTINGS_SIZE = 16
ics.ics.RAD_GPTP_AND_TAP_SETTINGS_SIZE = 40
ics.ics.RAD_GPTP_SETTINGS_SIZE = 36
ics.ics.RAD_REPORTING_SETTINGS_FLAG_AIN1 = 256
ics.ics.RAD_REPORTING_SETTINGS_FLAG_FAN_SPEED_ENABLE = 1024
ics.ics.RAD_REPORTING_SETTINGS_FLAG_INT_GPS_ENABLE = 4
ics.ics.RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE = 2
ics.ics.RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE2 = 8
ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC1_DIN = 16
ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC1_PWMIN = 64
ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC2_DIN = 32
ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC2_PWMIN = 128
ics.ics.RAD_REPORTING_SETTINGS_FLAG_SERDES_ENABLE = 512
ics.ics.RAD_REPORTING_SETTINGS_FLAG_TEMP_ENABLE = 1
ics.ics.RAD_REPORTING_SETTINGS_SIZE = 16
ics.ics.REGISTER_BY_SERIAL = 16
ics.ics.REPORT_ON_GPS = 15
ics.ics.REPORT_ON_KLINE = 9
ics.ics.REPORT_ON_LED1 = 7
ics.ics.REPORT_ON_LED2 = 8
ics.ics.REPORT_ON_MISC1 = 1
ics.ics.REPORT_ON_MISC2 = 2
ics.ics.REPORT_ON_MISC3 = 3
```

```
ics.ics.REPORT_ON_MISC3_AIN = 10
ics.ics.REPORT_ON_MISC4 = 4
ics.ics.REPORT_ON_MISC4_AIN = 11
ics.ics.REPORT_ON_MISC5 = 5
ics.ics.REPORT_ON_MISC5_AIN = 12
ics.ics.REPORT_ON_MISC6 = 6
ics.ics.REPORT_ON_MISC6_AIN = 13
ics.ics.REPORT_ON_PERIODIC = 0
ics.ics.RESISTOR_OFF = 1
ics.ics.RESISTOR_ON = 0
ics.ics.SCRIPT_LOCATION_EMMC = 6
ics.ics.SCRIPT_LOCATION_FLASH_MEM = 0
ics.ics.SCRIPT_LOCATION_INTERNAL_FLASH = 2
ics.ics.SCRIPT_LOCATION_SDCARD = 1
ics.ics.SCRIPT_LOCATION_VCAN3_MEM = 4
ics.ics.SCRIPT_STATUS_RUNNING = 1
ics.ics.SCRIPT_STATUS_STOPPED = 0
ics.ics.SERDESCAM_MODE_COUNT = 4
ics.ics.SERDESCAM_MODE_CUSTOM = 3
ics.ics.SERDESCAM_MODE_LOG_ONLY = 2
ics.ics.SERDESCAM_MODE_SPLITTER = 1
ics.ics.SERDESCAM_MODE_TAP_REPEATER = 0
ics.ics.SERDESCAM_PIXEL_BIT_POS_0 = 0
ics.ics.SERDESCAM_PIXEL_BIT_POS_1 = 1
ics.ics.SERDESCAM_PIXEL_BIT_POS_2 = 2
ics.ics.SERDESCAM_PIXEL_BIT_POS_3 = 3
ics.ics.SERDESCAM_SETTINGS_FLAG_AUTO_DET_RES_ENABLE = 4
ics.ics.SERDESCAM_SETTINGS_FLAG_CONFIG_ENABLE = 8
ics.ics.SERDESCAM_SETTINGS_FLAG_ENABLE = 1
ics.ics.SERDESCAM_SETTINGS_FLAG_LOGGING_ENABLE = 16
ics.ics.SERDESCAM_SETTINGS_FLAG_RTSP_ENABLE = 2
ics.ics.SERDESCAM_SETTINGS_FLAG_TX0_ENABLE = 32
ics.ics.SERDESCAM_SETTINGS_FLAG_TX1_ENABLE = 64
ics.ics.SERDESCAM_SETTINGS_FLAG_TX2_ENABLE = 128
ics.ics.SERDESCAM_SETTINGS_FLAG_TX3_ENABLE = 256
ics.ics.SERDESCAM_SETTINGS_SIZE = 32
```

```
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_10LE_PACKED = 19
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_12LE_PACKED = 20
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16BE = 22
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16LE = 21
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_8 = 4
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_10LE_PACKED = 74
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_12LE_PACKED = 75
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_16BE = 77
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_16LE = 76
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_8 = 73
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_10LE_PACKED = 82
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_12LE_PACKED = 83
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_16BE = 85
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_16LE = 84
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_8 = 81
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_10LE_PACKED = 66
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_12LE_PACKED = 67
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_16BE = 69
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_16LE = 68
ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_8 = 65
ics.ics.SERDESCAM_VIDEO_FORMAT_COUNT = 89
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_10LE_PACKED = 51
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_12LE_PACKED = 52
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_8 = 50
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GBRG_10LE_PACKED = 79
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GBRG_12LE_PACKED = 80
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GBRG_8 = 78
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GRBG_10LE_PACKED = 87
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GRBG_12LE_PACKED = 88
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GRBG_8 = 86
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_RGGB_10LE_PACKED = 71
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_RGGB_12LE_PACKED = 72
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_RGGB_8 = 70
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_10 = 54
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_12 = 56
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_14 = 58
```

```
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_16 = 59
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_20 = 60
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_24 = 61
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_30 = 62
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_32 = 63
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_36 = 64
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_8 = 53
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RGB565 = 47
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RGB666 = 48
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RGB888 = 49
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_10LE_PACKED = 39
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_12LE_PACKED = 43
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_8 = 35
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_10LE_PACKED = 42
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_12LE_PACKED = 46
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_8 = 38
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_10LE_PACKED = 40
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_12LE_PACKED = 44
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_8 = 36
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_10LE_PACKED = 41
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_12LE_PACKED = 45
ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_8 = 37
ics.ics.SERDESCAM_VIDEO_FORMAT_JPEG = 23
ics.ics.SERDESCAM_VIDEO_FORMAT_NONE = -1
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_10 = 6
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_12 = 7
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_14 = 34
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_16 = 8
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_20 = 9
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_24 = 10
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_30 = 11
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_32 = 12
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_36 = 13
ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_8 = 5
ics.ics.SERDESCAM_VIDEO_FORMAT_RGB565 = 30
ics.ics.SERDESCAM_VIDEO_FORMAT_RGB666 = 31
```



```
ics.ics.SERDESCAM_VIDEO_FORMAT_RGB888 = 14
ics.ics.SERDESCAM_VIDEO_FORMAT_UYVY_422_10LE_PACKED = 15
ics.ics.SERDESCAM_VIDEO_FORMAT_UYVY_422_12LE_PACKED = 24
ics.ics.SERDESCAM_VIDEO_FORMAT_UYVY_422_8 = 0
ics.ics.SERDESCAM_VIDEO_FORMAT_VYUY_422_10LE_PACKED = 18
ics.ics.SERDESCAM_VIDEO_FORMAT_VYUY_422_12LE_PACKED = 27
ics.ics.SERDESCAM_VIDEO_FORMAT_VYUY_422_8 = 3
ics.ics.SERDESCAM_VIDEO_FORMAT_YUV422_10LE_PLANAR = 28
ics.ics.SERDESCAM_VIDEO_FORMAT_YUV422_16LE_PLANAR = 29
ics.ics.SERDESCAM_VIDEO_FORMAT_YUYV_422_10LE_PACKED = 16
ics.ics.SERDESCAM_VIDEO_FORMAT_YUYV_422_12LE_PACKED = 25
ics.ics.SERDESCAM_VIDEO_FORMAT_YUYV_422_8 = 1
ics.ics.SERDESCAM_VIDEO_FORMAT_YVYU_422_10LE_PACKED = 17
ics.ics.SERDESCAM_VIDEO_FORMAT_YVYU_422_12LE_PACKED = 26
ics.ics.SERDESCAM_VIDEO_FORMAT_YVYU_422_8 = 2
ics.ics.SERDESGEN_MOD_ID_NONE = 0
ics.ics.SERDESGEN_MOD_ID_UNKNOWN = -1
ics.ics.SERDESGEN_SETTINGS_FLAG_TX_PATGEN_ENABLE = 1
ics.ics.SERDESGEN_SETTINGS_SIZE = 32
ics.ics.SERDESPOC_SETTINGS_MODE_DISABLED = 0
ics.ics.SERDESPOC_SETTINGS_MODE_SERIALIZER = 2
ics.ics.SERDESPOC_SETTINGS_MODE_SUPPLY = 1
ics.ics.SERDESPOC_SETTINGS_SIZE = 10
ics.ics.SLAVE_VNET_A = 2
ics.ics.SLAVE_VNET_B = 4
ics.ics.SLEEP_MODE = 0
ics.ics.SLOW_MODE = 1
ics.ics.SPI_PORT_EXTERNAL = 1
ics.ics.SPI_PORT_ONBOARD = 0
ics.ics.SPY_PROTOCOL_A2B = 35
ics.ics.SPY_PROTOCOL_AUTOSAR = 34
ics.ics.SPY_PROTOCOL_BEAN = 11
ics.ics.SPY_PROTOCOL_CAN = 1
ics.ics.SPY_PROTOCOL_CANFD = 30
ics.ics.SPY_PROTOCOL_CGI = 18
ics.ics.SPY_PROTOCOL_CHRYSLER_CCD = 8
```

```
ics.ics.SPY_PROTOCOL_CHRYSLER_JVPW = 14
ics.ics.SPY_PROTOCOL_CHRYSLER_SCI = 9
ics.ics.SPY_PROTOCOL_CUSTOM = 0
ics.ics.SPY_PROTOCOL_DALLAS_1WIRE = 25
ics.ics.SPY_PROTOCOL_ETHERNET = 29
ics.ics.SPY_PROTOCOL_FLEXRAY = 16
ics.ics.SPY_PROTOCOL_FORD_UBP = 10
ics.ics.SPY_PROTOCOL_GENERIC_MANCHSESTER = 26
ics.ics.SPY_PROTOCOL_GENERIC_UART = 22
ics.ics.SPY_PROTOCOL_GME_CIM_SCL_KLINE = 19
ics.ics.SPY_PROTOCOL_GMFSA = 31
ics.ics.SPY_PROTOCOL_GMLAN = 2
ics.ics.SPY_PROTOCOL_GM_ALDL_UART = 7
ics.ics.SPY_PROTOCOL_I2C = 21
ics.ics.SPY_PROTOCOL_ISO9141 = 5
ics.ics.SPY_PROTOCOL_J1708 = 13
ics.ics.SPY_PROTOCOL_J1850PWM = 4
ics.ics.SPY_PROTOCOL_J1850VPW = 3
ics.ics.SPY_PROTOCOL_J1939 = 15
ics.ics.SPY_PROTOCOL_JTAG = 23
ics.ics.SPY_PROTOCOL_LIN = 12
ics.ics.SPY_PROTOCOL_MOST = 17
ics.ics.SPY_PROTOCOL_SENT_PROTOCOL = 27
ics.ics.SPY_PROTOCOL_SPI = 20
ics.ics.SPY_PROTOCOL_TCP = 32
ics.ics.SPY_PROTOCOL_UART = 28
ics.ics.SPY_PROTOCOL_UDP = 33
ics.ics.SPY_PROTOCOL_UNIO = 24
ics.ics.SPY_PROTOCOL_WBMS = 36
ics.ics.SPY_STATUS2_CAN_HAVE_LINK_DATA = 4194304
ics.ics.SPY_STATUS2_CAN_ISO15765_LOGICAL_FRAME = 2097152
ics.ics.SPY_STATUS2_END_OF_LONG_MESSAGE = 1048576
ics.ics.SPY_STATUS2_ERROR_FRAME = 131072
ics.ics.SPY_STATUS2_ETHERNET_CRC_ERROR = 2097152
ics.ics.SPY_STATUS2_ETHERNET_FCS_VERIFIED = 268435456
ics.ics.SPY_STATUS2_ETHERNET_FRAME_TOO_SHORT = 4194304
```

```
ics.ics.SPY_STATUS2_ETHERNET_MANUALFCS_ENABLED = 134217728
ics.ics.SPY_STATUS2_ETHERNET_NO_PADDING = 16777216
ics.ics.SPY_STATUS2_ETHERNET_PREEMPTION_ENABLED = 33554432
ics.ics.SPY_STATUS2_ETHERNET_UPDATE_CHECKSUMS = 67108864
ics.ics.SPY_STATUS2_FLEXRAY_NO_CRC = 33554432
ics.ics.SPY_STATUS2_FLEXRAY_NO_HEADERCRC = 67108864
ics.ics.SPY_STATUS2_FLEXRAY_TX_AB = 2097152
ics.ics.SPY_STATUS2_FLEXRAY_TX_AB_NO_A = 4194304
ics.ics.SPY_STATUS2_FLEXRAY_TX_AB_NO_B = 8388608
ics.ics.SPY_STATUS2_FLEXRAY_TX_AB_NO_MATCH = 16777216
ics.ics.SPY_STATUS2_GLOBAL_CHANGE = 65536
ics.ics.SPY_STATUS2_HAS_VALUE = 1
ics.ics.SPY_STATUS2_HIGH_VOLTAGE = 4
ics.ics.SPY_STATUS2_I2C_DIR_READ = 8388608
ics.ics.SPY_STATUS2_I2C_ERR_NACK = 4194304
ics.ics.SPY_STATUS2_I2C_ERR_TIMEOUT = 2097152
ics.ics.SPY_STATUS2_I2C_NODE_FAULT = 4194304
ics.ics.SPY_STATUS2_ISO_FRAME_ERROR = 134217728
ics.ics.SPY_STATUS2_ISO_OVERFLOW_ERROR = 268435456
ics.ics.SPY_STATUS2_ISO_PARITY_ERROR = 536870912
ics.ics.SPY_STATUS2_LIN_ERR_MSG_ID_PARITY = 67108864
ics.ics.SPY_STATUS2_LIN_ERR_RX_BREAK_NOT_0 = 2097152
ics.ics.SPY_STATUS2_LIN_ERR_RX_BREAK_TOO_SHORT = 4194304
ics.ics.SPY_STATUS2_LIN_ERR_RX_DATA_GREATER_8 = 16777216
ics.ics.SPY_STATUS2_LIN_ERR_RX_SYNC_NOT_55 = 8388608
ics.ics.SPY_STATUS2_LIN_ERR_TX_RX_MISMATCH = 33554432
ics.ics.SPY_STATUS2_LIN_ID_FRAME_ERROR = 268435456
ics.ics.SPY_STATUS2_LIN_NO_SLAVE_DATA = -2147483648
ics.ics.SPY_STATUS2_LIN_SLAVE_BYTE_ERROR = 536870912
ics.ics.SPY_STATUS2_LIN_SYNC_FRAME_ERROR = 134217728
ics.ics.SPY_STATUS2_LONG_MESSAGE = 8
ics.ics.SPY_STATUS2_MOST_CHANGED_PAR = -2147483648
ics.ics.SPY_STATUS2_MOST_CONTROL_DATA = 16777216
ics.ics.SPY_STATUS2_MOST_I2S_DUMP = 134217728
ics.ics.SPY_STATUS2_MOST_LOW_LEVEL = 8388608
ics.ics.SPY_STATUS2_MOST_MHP_CONTROL_DATA = 67108864
```

```
ics.ics.SPY_STATUS2_MOST_MHP_USER_DATA = 33554432
ics.ics.SPY_STATUS2_MOST_MOST150 = 1073741824
ics.ics.SPY_STATUS2_MOST_MOST50 = 536870912
ics.ics.SPY_STATUS2_MOST_PACKET_DATA = 2097152
ics.ics.SPY_STATUS2_MOST_STATUS = 4194304
ics.ics.SPY_STATUS2_MOST_TOO_SHORT = 268435456
ics.ics.SPY_STATUS2_RX_TIMEOUT_ERROR = 1073741824
ics.ics.SPY_STATUS2_VALUE_IS_BOOLEAN = 2
ics.ics.SPY_STATUS2_WBMS_NODE_DISCONNECTED = 2097152
ics.ics.SPY_STATUS3_CANFD_BRS = 16
ics.ics.SPY_STATUS3_CANFD_ESI = 1
ics.ics.SPY_STATUS3_CANFD_FDF = 8
ics.ics.SPY_STATUS3_CANFD_IDE = 2
ics.ics.SPY_STATUS3_CANFD_RTR = 4
ics.ics.SPY_STATUS3_LIN_JUST_BREAK_SYNC = 1
ics.ics.SPY_STATUS3_LIN_ONLY_UPDATE_SLAVE_TABLE_ONCE = 4
ics.ics.SPY_STATUS3_LIN_SLAVE_DATA_TOO_SHORT = 2
ics.ics.SPY_STATUS_A2B_CONTROL = 524288
ics.ics.SPY_STATUS_A2B_MONITOR = 536870912
ics.ics.SPY_STATUS_A2B_SCF_VALID_WAITING = 8
ics.ics.SPY_STATUS_A2B_UPSTREAM = 1073741824
ics.ics.SPY_STATUS_ANALOG_DIGITAL_INPUT = 16777216
ics.ics.SPY_STATUS_AUDIO_COMMENT = 4194304
ics.ics.SPY_STATUS_AVSI_REC_OVERFLOW = 1048576
ics.ics.SPY_STATUS_BAD_MESSAGE_BIT_TIME_ERROR = 16384
ics.ics.SPY_STATUS_BREAK = 524288
ics.ics.SPY_STATUS_BUS_RECOVERED = 1024
ics.ics.SPY_STATUS_BUS_SHORTED_GND = 4096
ics.ics.SPY_STATUS_BUS_SHORTED_PLUS = 2048
ics.ics.SPY_STATUS_CANFD = 536870912
ics.ics.SPY_STATUS_CAN_BUS_OFF = 512
ics.ics.SPY_STATUS_CAN_ERROR_PASSIVE = 32
ics.ics.SPY_STATUS_CHECKSUM_ERROR = 8192
ics.ics.SPY_STATUS_COMM_IN_OVERFLOW = 65536
ics.ics.SPY_STATUS_CRC_ERROR = 16
ics.ics.SPY_STATUS_EXPECTED_LEN_MISMATCH = 131072
```

```
ics.ics.SPY_STATUS_EXTENDED = -2147483648
ics.ics.SPY_STATUS_FLEXRAY_PDU = 268435456
ics.ics.SPY_STATUS_FLEXRAY_PDU_NO_UPDATE_BIT = 8
ics.ics.SPY_STATUS_FLEXRAY_PDU_UPDATE_BIT_SET = 1073741824
ics.ics.SPY_STATUS_GLOBAL_ERR = 1
ics.ics.SPY_STATUS_GPS_DATA = 8388608
ics.ics.SPY_STATUS_HEADERCRC_ERROR = 32
ics.ics.SPY_STATUS_HIGH_SPEED = 1073741824
ics.ics.SPY_STATUS_INCOMPLETE_FRAME = 64
ics.ics.SPY_STATUS_INIT_MESSAGE = 536870912
ics.ics.SPY_STATUS_LIN_MASTER = 536870912
ics.ics.SPY_STATUS_LOST_ARBITRATION = 128
ics.ics.SPY_STATUS_MSG_NO_MATCH = 262144
ics.ics.SPY_STATUS_NETWORK_MESSAGE_TYPE = 67108864
ics.ics.SPY_STATUS_PDU = 268435456
ics.ics.SPY_STATUS_REMOTE_FRAME = 8
ics.ics.SPY_STATUS_TEST_TRIGGER = 2097152
ics.ics.SPY_STATUS_TEXT_COMMENT = 33554432
ics.ics.SPY_STATUS_TX_MSG = 2
ics.ics.SPY_STATUS_TX_NOMATCH = 32768
ics.ics.SPY_STATUS_UNDEFINED_ERROR = 256
ics.ics.SPY_STATUS_VSI_IFR_CRC_BIT = 268435456
ics.ics.SPY_STATUS_VSI_TX_UNDERRUN = 134217728
ics.ics.SPY_STATUS_XTD_FRAME = 4
ics.ics.SWCAN_AUTOSWITCH_DISABLED = 0
ics.ics.SWCAN_AUTOSWITCH_DISABLED_RESISTOR_ENABLED = 3
ics.ics.SWCAN_AUTOSWITCH_NO_RESISTOR = 1
ics.ics.SWCAN_AUTOSWITCH_WITH_RESISTOR = 2
ics.ics.SWCAN_SETTINGS_SIZE = 14
ics.ics.TIMESYNC_ICSHARDWARE_SETTINGS_SIZE = 4
ics.ics.UART_SETTINGS_SIZE = 16
ics.ics.USE_TQ = 1
ics.ics.VNETBITS_FEATURE_ANDROID_MSGS = 1
ics.ics.VNETBITS_FEATURE_DISABLE_USB_CHECK = 2
ics.ics.WIFI_ANTENNA_EXTERNAL = 1
ics.ics.WIFI_ANTENNA_INTERNAL = 0
```

```
ics.ics.WIFI_CONNECTION = 8
```

i

`ics.ics`, [17](#)

A

a2_b_monitor_settings (class in *ics.structures.a2_b_monitor_settings*), 87
 a2_b_node_type (class in *ics.structures.a2_b_node_type*), 87
 a2_btdm_mode (class in *ics.structures.a2_btdm_mode*), 87
 a2b_monitor (*ics.structures.srada2_b_settings.srada2_b_settings* attribute), 174
 a2b_node (*ics.structures.srada2_b_settings.srada2_b_settings* attribute), 174
 A2B_SETTINGS_FLAG_16BIT (in module *ics.ics*), 191
 a2bNodeTypeMaster (*ics.structures.a2_b_node_type.a2_b_node_type* attribute), 87
 a2bNodeTypeMonitor (*ics.structures.a2_b_node_type.a2_b_node_type* attribute), 87
 a2bNodeTypeSlave (*ics.structures.a2_b_node_type.a2_b_node_type* attribute), 87
 accdevwin (*ics.structures.s_pluto_clock_sync_params.s.pluto_clock_sync_params* attribute), 134
 AckBytes (*ics.ics.SpyMessage* attribute), 18
 AckBytes (*ics.ics.SpyMessageJ1850* attribute), 19
 AckBytes (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray* attribute), 101
 AckBytes (*ics.structures.ics_spy_message_long.ics_spy_message_long* attribute), 103
 AckBytes (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb* attribute), 104
 aelSelect (*ics.structures.s_pluto_custom_params.s.pluto_custom_params* attribute), 136
 ain_sample_period (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 111
 ain_sample_period (*ics.structures.s_ether_badge_settings.s_ether_badge_settings* attribute), 115
 ain_sample_period (*ics.structures.s_fire_settings.s_fire_settings* attribute), 122
 ain_sample_period (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 124
 ain_sample_period (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings* attribute), 129
 ain_sample_period (*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 130
 ain_sample_period (*ics.structures.secu_settings.secu_settings* attribute), 147
 ain_sample_period (*ics.structures.seevb_settings.seevb_settings* attribute), 149
 ain_sample_period (*ics.structures.sievb_settings.sievb_settings* attribute), 150
 ain_sample_period (*ics.structures.sobd2_sim_settings.sobd2_sim_settings* attribute), 155
 ain_sample_period (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 158
 ain_sample_period (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 171
 ain_threshold (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 111
 ain_threshold (*ics.structures.s_ether_badge_settings.s_ether_badge_settings* attribute), 115
 ain_threshold (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 117
 ain_threshold (*ics.structures.s_fire_settings.s_fire_settings* attribute), 122
 ain_threshold (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 124

ain_threshold(*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings* attribute), 129
 ain_threshold(*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 130
 ain_threshold(*ics.structures.secu_settings.secu_settings* attribute), 147
 ain_threshold(*ics.structures.seevb_settings.seevb_settings* attribute), 149
 ain_threshold(*ics.structures.sievb_settings.sievb_settings* attribute), 150
 ain_threshold(*ics.structures.sobd2_sim_settings.sobd2_sim_settings* attribute), 155
 ain_threshold(*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 158
 ain_threshold(*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 171
 allowBoot(*ics.structures.fire3_linux_settings.fire3_linux_settings* attribute), 95
 api(*ics.structures.generic_api_data.generic_api_data* attribute), 95
 api(*ics.structures.generic_api_status.generic_api_status* attribute), 95
 apiIndex(*ics.structures.generic_api_selector.generic_api_selector* attribute), 95
 ArbIDOrHeader(*ics.ics.SpyMessage* attribute), 18
 ArbIDOrHeader(*ics.structures.ics_spy_message_flex_raw_ics_spy_message_flex_raw* attribute), 101
 ArbIDOrHeader(*ics.structures.ics_spy_message_long_ics_spy_message_long* attribute), 103
 ArbIDOrHeader(*ics.structures.ics_spy_message_vsb_ics_spy_message_vsb* attribute), 104
 ArgumentError, 17
 as_capable(*ics.structures.gptp_status.gptp_status* attribute), 98
 asytensyen(*ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params* attribute), 134
 attemptConnect(*ics.structures.s_wil_connection_settings.s_wil_connection_settings* attribute), 145
 AUTO (in module *ics.ics*), 191
 auto_baud(*ics.structures.can_settings.can_settings* attribute), 88
 auto_baud(*ics.structures.swcan_settings.swcan_settings* attribute), 187
 auto_neg(*ics.structures.ethernet_settings.ethernet_settings* attribute), 93
 autoEth10g(*ics.structures.srad_moon3_settings.srad_moon3_settings* attribute), 170
 AutoHandleClose(*ics.ics.NeoDevice* attribute), 18
B
 backupPowerEnabled(*ics.structures.ics_fire2_device_status.ics_fire2_device_status* attribute), 99
 baudrate36enc() (in module *ics.ics*), 30
 Baudrate(*ics.structures.can_settings.can_settings* attribute), 88
 Baudrate(*ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings* attribute), 107
 Baudrate(*ics.structures.lin_settings.lin_settings* attribute), 108
 Baudrate(*ics.structures.swcan_settings.swcan_settings* attribute), 186
 baudrate(*ics.structures.uart_port_config.uart_port_config* attribute), 188
 Baudrate(*ics.structures.uart_settings.uart_settings* attribute), 189
 bc_domain(*ics.structures.s_pluto_l2_forwarding_entry.s_pluto_l2_forwarding_entry* attribute), 138
 bData(*ics.structures.generic_api_data.generic_api_data* attribute), 95
 bData(*ics.structures.uart_port_data.uart_port_data* attribute), 188
 bcsTargetFlexRaw(*ics.structures.serdescam_settings.serdescam_settings* attribute), 149
 bcsTargetFlexRaw(*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message* attribute), 106
 bcsTargetFlexRaw(*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message* attribute), 179
 blockSize(*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message* attribute), 180
 bOptions(*ics.structures.uart_settings.uart_settings* attribute), 189
 BPS100 (in module *ics.ics*), 191
 BPS100000 (in module *ics.ics*), 191
 BPS10400 (in module *ics.ics*), 191
 BPS117647 (in module *ics.ics*), 191
 BPS125 (in module *ics.ics*), 191
 BPS20 (in module *ics.ics*), 191
 BPS2000 (in module *ics.ics*), 191
 BPS250 (in module *ics.ics*), 191
 BPS33 (in module *ics.ics*), 191
 BPS333 (in module *ics.ics*), 191
 BPS4000 (in module *ics.ics*), 191
 BPS50 (in module *ics.ics*), 191
 BPS500 (in module *ics.ics*), 191
 BPS5000 (in module *ics.ics*), 191
 BPS50000 (in module *ics.ics*), 191
 BPS62 (in module *ics.ics*), 191
 BPS62500 (in module *ics.ics*), 191
 BPS666 (in module *ics.ics*), 191

- BPS71429 (in module ics.ics), 191
- BPS800 (in module ics.ics), 191
- BPS83 (in module ics.ics), 192
- BPS83333 (in module ics.ics), 192
- brgh (ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings attribute), 108
- brgh (ics.structures.lin_settings.lin_settings attribute), 108
- brgh (ics.structures.uart_settings.uart_settings attribute), 189
- BRP (ics.structures.can_settings.can_settings attribute), 88
- BRP (ics.structures.swcan_settings.swcan_settings attribute), 186
- bStuff2 (ics.structures.spy_filter_long.spy_filter_long attribute), 157
- BUILD_DATETIME (in module ics.ics), 192
- bUseArbIdRangeFilter (ics.structures.spy_filter_long.spy_filter_long attribute), 157
- BusIndex (ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute), 132
- ByteDataLength (ics.structures.spy_filter_long.spy_filter_long attribute), 156
- ByteDataLSB (ics.structures.spy_filter_long.spy_filter_long attribute), 156
- ByteDataMaskLSB (ics.structures.spy_filter_long.spy_filter_long attribute), 156
- ByteDataMaskMSB (ics.structures.spy_filter_long.spy_filter_long attribute), 156
- ByteDataMSB (ics.structures.spy_filter_long.spy_filter_long attribute), 156
- bytesPerSector (ics.structures.s_disk_status.s_disk_status attribute), 115
- can1 (ics.structures.s_pendant_settings.s_pendant_settings attribute), 130
- can1 (ics.structures.s_red_settings.s_red_settings attribute), 143
- can1 (ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute), 144
- can1 (ics.structures.scan_hub_settings.scan_hub_settings attribute), 146
- can1 (ics.structures.secu_avb_settings.secu_avb_settings attribute), 146
- can1 (ics.structures.secu_settings.secu_settings attribute), 147
- can1 (ics.structures.seevb_settings.seevb_settings attribute), 149
- can1 (ics.structures.sievb_settings.sievb_settings attribute), 150
- can1 (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 152
- can1 (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 153
- can1 (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 155
- can1 (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 157
- can1 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 158
- can1 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 161
- can1 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 164
- can1 (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 167
- can1 (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 170
- can1 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 171
- can1 (ics.structures.srada2_b_settings.srada2_b_settings attribute), 174
- can1 (ics.structures.sradbms_settings.sradbms_settings attribute), 175
- can1 (ics.structures.svcn3_settings.svcn3_settings attribute), 182
- can1 (ics.structures.svcn412_settings.svcn412_settings attribute), 182
- can1 (ics.structures.svcn4_ind_settings.svcn4_ind_settings attribute), 183
- can1 (ics.structures.svcn4_settings.svcn4_settings attribute), 184
- can1 (ics.structures.svcnrf_settings.svcnrf_settings attribute), 185
- can10 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 117
- can11 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 117
- can11 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 129

C

- caentmout (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params attribute), 134
- callbackError (ics.structures.generic_api_status.generic_api_status attribute), 96
- can1 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 111
- can1 (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 115
- can1 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 117
- can1 (ics.structures.s_fire_settings.s_fire_settings attribute), 122
- can1 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 124
- can1 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 127
- can1 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 129

can12 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 117
 can13 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 117
 can14 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 117
 can15 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 117
 can16 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 117
 can1_options (ics.structures.s_text_api_settings.s_text_api_settings attribute), 144
 can1_rx_id (ics.structures.s_text_api_settings.s_text_api_settings attribute), 144
 can1_tx_id (ics.structures.s_text_api_settings.s_text_api_settings attribute), 144
 can2 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 111
 can2 (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 115
 can2 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118
 can2 (ics.structures.s_fire_settings.s_fire_settings attribute), 122
 can2 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 124
 can2 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 127
 can2 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 129
 can2 (ics.structures.s_pendant_settings.s_pendant_settings attribute), 131
 can2 (ics.structures.s_red_settings.s_red_settings attribute), 143
 can2 (ics.structures.secu_avb_settings.secu_avb_settings attribute), 146
 can2 (ics.structures.secu_settings.secu_settings attribute), 147
 can2 (ics.structures.sievb_settings.sievb_settings attribute), 150
 can2 (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 152
 can2 (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 153
 can2 (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 155
 can2 (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 157
 can2 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 158
 can2 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 162
 can2 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 164
 can2 (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 167
 can2 (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 170
 can2 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 171
 can2 (ics.structures.srada2_b_settings.srada2_b_settings attribute), 174
 can2 (ics.structures.sradbms_settings.sradbms_settings attribute), 175
 can2 (ics.structures.svcn3_settings.svcn3_settings attribute), 182
 can2 (ics.structures.svcn412_settings.svcn412_settings attribute), 182
 can2 (ics.structures.svcn4_ind_settings.svcn4_ind_settings attribute), 183
 can2 (ics.structures.svcn4_settings.svcn4_settings attribute), 184
 can2 (ics.structures.svcanrf_settings.svcanrf_settings attribute), 185
 can2_options (ics.structures.s_text_api_settings.s_text_api_settings attribute), 144
 can2_rx_id (ics.structures.s_text_api_settings.s_text_api_settings attribute), 144
 can2_tx_id (ics.structures.s_text_api_settings.s_text_api_settings attribute), 144
 can3 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 111
 can3 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118
 can3 (ics.structures.s_fire_settings.s_fire_settings attribute), 122
 can3 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 124
 can3 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 127
 can3 (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 152
 can3 (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 153
 can3 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 159
 can3 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 162
 can3 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 164
 can3 (ics.structures.svcn4_settings.svcn4_settings attribute), 184
 can3 (ics.structures.svcanrf_settings.svcanrf_settings attribute), 185
 can3_options (ics.structures.s_text_api_settings.s_text_api_settings attribute), 144
 can3_rx_id (ics.structures.s_text_api_settings.s_text_api_settings attribute), 144

attribute), 127

canfd1 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 129

canfd1 (ics.structures.scan_hub_settings.scan_hub_settings attribute), 146

canfd1 (ics.structures.secu_avb_settings.secu_avb_settings attribute), 147

canfd1 (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 152

canfd1 (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 153

canfd1 (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 155

canfd1 (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 157

canfd1 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 159

canfd1 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 162

canfd1 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 164

canfd1 (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 167

canfd1 (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 170

canfd1 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 172

canfd1 (ics.structures.srada2_b_settings.srada2_b_settings attribute), 174

canfd1 (ics.structures.sradbms_settings.sradbms_settings attribute), 175

canfd1 (ics.structures.svcan412_settings.svcan412_settings attribute), 182

canfd1 (ics.structures.svcan4_ind_settings.svcan4_ind_settings attribute), 183

canfd1 (ics.structures.svcan4_settings.svcan4_settings attribute), 184

canfd10 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118

canfd11 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118

canfd12 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118

canfd13 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118

canfd14 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118

canfd15 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118

canfd16 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118

canfd2 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 112

canfd2 (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 115

canfd2 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118

canfd2 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 127

canfd2 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 129

canfd2 (ics.structures.secu_avb_settings.secu_avb_settings attribute), 147

canfd2 (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 152

canfd2 (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 153

canfd2 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 159

canfd2 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 162

canfd2 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 164

canfd2 (ics.structures.svcan4_ind_settings.svcan4_ind_settings attribute), 183

canfd2 (ics.structures.svcan4_settings.svcan4_settings attribute), 184

canfd3 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 112

canfd3 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 118

canfd3 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 127

canfd3 (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 152

canfd3 (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 153

canfd3 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 159

canfd3 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 162

canfd3 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 164

- [attribute\), 164](#)
- [canfd3 \(ics.structures.svcan4_settings.svcan4_settings attribute\), 184](#)
- [canfd4 \(ics.structures.s_cyan_settings.s_cyan_settings attribute\), 112](#)
- [canfd4 \(ics.structures.s_fire3_settings.s_fire3_settings attribute\), 118](#)
- [canfd4 \(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute\), 127](#)
- [canfd4 \(ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute\), 152](#)
- [canfd4 \(ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute\), 154](#)
- [canfd4 \(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute\), 159](#)
- [canfd4 \(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute\), 162](#)
- [canfd4 \(ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute\), 164](#)
- [canfd4 \(ics.structures.svcan4_settings.svcan4_settings attribute\), 184](#)
- [canfd5 \(ics.structures.s_cyan_settings.s_cyan_settings attribute\), 112](#)
- [canfd5 \(ics.structures.s_fire3_settings.s_fire3_settings attribute\), 118](#)
- [canfd5 \(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute\), 127](#)
- [canfd5 \(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute\), 159](#)
- [canfd5 \(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute\), 162](#)
- [canfd5 \(ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute\), 164](#)
- [canfd6 \(ics.structures.s_cyan_settings.s_cyan_settings attribute\), 112](#)
- [canfd6 \(ics.structures.s_fire3_settings.s_fire3_settings attribute\), 118](#)
- [canfd6 \(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute\), 127](#)
- [canfd6 \(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute\), 159](#)
- [canfd6 \(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute\), 162](#)
- [canfd6 \(ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute\), 165](#)
- [canfd7 \(ics.structures.s_cyan_settings.s_cyan_settings attribute\), 112](#)
- [canfd7 \(ics.structures.s_fire3_settings.s_fire3_settings attribute\), 119](#)
- [canfd7 \(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute\), 127](#)
- [canfd7 \(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute\), 159](#)
- [canfd7 \(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute\), 122](#)
- [attribute\), 162](#)
- [canfd8 \(ics.structures.s_cyan_settings.s_cyan_settings attribute\), 112](#)
- [canfd8 \(ics.structures.s_fire3_settings.s_fire3_settings attribute\), 119](#)
- [canfd8 \(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute\), 159](#)
- [canfd8 \(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute\), 162](#)
- [canfd9 \(ics.structures.s_fire3_settings.s_fire3_settings attribute\), 119](#)
- [CANFD_BRS_ENABLED \(in module ics.ics\), 192](#)
- [CANFD_BRS_ENABLED_ISO \(in module ics.ics\), 192](#)
- [CANFD_ENABLED \(in module ics.ics\), 192](#)
- [CANFD_ENABLED_ISO \(in module ics.ics\), 192](#)
- [canfd_settings \(class in ics.structures.canfd_settings\), 88](#)
- [CANFD_SETTINGS_SIZE \(in module ics.ics\), 192](#)
- [canhub \(ics.structures.global_settings.global_settings attribute\), 96](#)
- [CANNODE_STATUS_COREMINI_IS_RUNNING \(in module ics.ics\), 192](#)
- [CANNODE_STATUS_IN_BOOTLOADER \(in module ics.ics\), 192](#)
- [CANOptions \(ics.structures.tag_options_find_neo_ex.tag_options_find_neo_ex attribute\), 187](#)
- [CANOptions \(ics.structures.tag_options_open_neo_ex.tag_options_open_neo_ex attribute\), 187](#)
- [canterm_settings \(class in ics.structures.canterm_settings\), 89](#)
- [CANTERM_SETTINGS_SIZE \(in module ics.ics\), 192](#)
- [cantransport \(ics.structures.s_pluto_general_params.s_pluto_general_params attribute\), 136](#)
- [cf_timeout \(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute\), 179](#)
- [cgi_baud \(ics.structures.s_fire_settings.s_fire_settings attribute\), 122](#)
- [cgi_baud \(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute\), 124](#)
- [cgi_checksum_enable \(ics.structures.s_fire_settings.s_fire_settings attribute\), 122](#)
- [cgi_checksum_enable \(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute\), 125](#)
- [cgi_enable_reserved \(ics.structures.s_fire_settings.s_fire_settings attribute\), 122](#)
- [cgi_enable_reserved \(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute\), 125](#)
- [cgi_ifs_bit_times \(ics.structures.s_fire_settings.s_fire_settings attribute\), 122](#)

`ics.ics`), 33
`current_time` (`ics.structures.gptp_status.gptp_status`
`attribute`), 98
`custom` (`ics.structures.srad_pluto_settings.srad_pluto_settings`
`attribute`), 170
`cyan` (`ics.structures.global_settings.global_settings` `at-`
`tribute`), 96
`cycle` (`ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray`
`attribute`), 102

D

`Data` (`ics.ics.SpyMessage` `attribute`), 18
`Data` (`ics.ics.SpyMessageJ1850` `attribute`), 19
`Data` (`ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray`
`attribute`), 101
`Data` (`ics.structures.ics_spy_message_vsb.ics_spy_message_vsb`
`attribute`), 105
`data` (`ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message`
`attribute`), 106
`data` (`ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message`
`attribute`), 180
`Data` (`ics.structures.tagicsneo_vi_command.tagicsneo_vi_command`
`attribute`), 188
`DataLsb` (`ics.structures.ics_spy_message_long.ics_spy_message_long`
`attribute`), 103
`DataMsb` (`ics.structures.ics_spy_message_long.ics_spy_message_long`
`attribute`), 103
`debugen` (`ics.structures.s_pluto_vl_forwarding_params.s.s_pluto_vl_forwarding_params`
`attribute`), 142
`DescriptionID` (`ics.ics.SpyMessage` `attribute`), 18
`DescriptionID` (`ics.ics.SpyMessageJ1850` `attribute`),
19
`DescriptionID` (`ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray`
`attribute`), 101
`DescriptionID` (`ics.structures.ics_spy_message_long.ics_spy_message_long`
`attribute`), 103
`DescriptionID` (`ics.structures.ics_spy_message_vsb.ics_spy_message_vsb`
`attribute`), 105
`destmeta` (`ics.structures.s_pluto_avb_params.s.s_pluto_avb_params`
`attribute`), 134
`destports` (`ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry_s`
`attribute`), 137
`destports` (`ics.structures.s_pluto_retagging_entry.s.s_pluto_retagging_entry_s`
`attribute`), 141
`destports` (`ics.structures.s_pluto_vl_forwarding_entry.s.s_pluto_vl_forwarding_entry_s`
`attribute`), 142
`device` (`ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt_clause45_mess`
`attribute`), 133
`device_feature` (class in `ics.structures.device_feature`), 89
`DeviceCANHUBSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceCMPProbeSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DEVICECOUNT_FOR_EXPLORER` (in module `ics.ics`),
192
`DeviceECU_AVBSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceEEVBSSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceEtherBadgeSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceFire2SettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceFire2FlexraySettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceFire3SettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceFireSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceFireVnetSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceFlexVnetzSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceLEVBSSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceNeoECU12SettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceOBD2LCSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceOBD2ProSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceOBD2SimSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceRADA2BSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceRADBMSSettingsType`
(`ics.structures.e_device_settings_type.e_device_settings_type`
`attribute`), 90
`DeviceRADEpsilonSettingsType`

(ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 90

DeviceRADGalaxySettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 90

DeviceRADGigalogSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 90

DeviceRADGigastarSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRADJupiterSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRADMoon2SettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRADMoon3SettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRadMoonDuoSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRADPlutoSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRADPlutoSwitchSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRADStar2SettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRADSuperMoonSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRed2SettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceRedSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceSettingsNone
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceSettingsTypeMax
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceSettingType
 (ics.structures.s_device_settings.s_device_settings
 attribute), 114

DeviceType (ics.ics.NeoDevice attribute), 18

DeviceVCAN3SettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceVCAN412SettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceVCAN4IndSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceVCAN4SettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceVCANRFSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceVidCANSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type
 attribute), 91

DeviceVidIoThresholdEnable
 (ics.structures.s_cyan_settings.s_cyan_settings
 attribute), 112

DeviceVidIoThresholdEnable
 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 119

DeviceVidIoThresholdTicks
 (ics.structures.s_cyan_settings.s_cyan_settings
 attribute), 112

DeviceVidIoThresholdTicks
 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 119

DeviceVidIoType (in module ics.ics), 192

disableFwLEDs (ics.structures.svcanrf_settings.svcanrf_settings
 attribute), 185

disableFwLEDs (ics.structures.s_cyan_settings.s_cyan_settings at-
 tribute), 112

disk (ics.structures.s_fire3_settings.s_fire3_settings at-
 tribute), 119

disk (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings
 attribute), 127

disk (ics.structures.sobd2_lc_settings.sobd2_lc_settings
 attribute), 152

disk (ics.structures.srad_galaxy_settings.srad_galaxy_settings
 attribute), 159

disk (ics.structures.srad_gigalog_settings.srad_gigalog_settings
 attribute), 162

disk (ics.structures.srad_gigastar_settings.srad_gigastar_settings
 attribute), 165

disk (ics.structures.srada2_b_settings.srada2_b_settings
 attribute), 174

disk_enables (ics.structures.disk_settings.disk_settings
 attribute), 90

disk_format (ics.structures.disk_settings.disk_settings
 attribute), 90

disk_format () (in module ics.ics), 34

disk_format_cancel () (in module ics.ics), 34

disk_out (ics.structures.disk_settings.disk_settings
 attribute), 90

disk_settings (class in ics.structures.disk_settings), 90
 DISK_SETTINGS_SIZE (in module ics.ics), 192
 DISK_STATUS_FLAG_INITIALIZED (in module ics.ics), 192
 DISK_STATUS_FLAG_PRESENT (in module ics.ics), 192
 DISK_STRUCTURE_FLAG_FULL_FORMAT (in module ics.ics), 192
 DiskFormatexFAT (ics.structures.e_disk_format.e_disk_format attribute), 91
 DiskFormatFAT32 (ics.structures.e_disk_format.e_disk_format attribute), 91
 DiskFormatUnknown (ics.structures.e_disk_format.e_disk_format attribute), 91
 DiskLayoutIndividual (ics.structures.e_disk_layout.e_disk_layout attribute), 91
 DiskLayoutRAID0 (ics.structures.e_disk_layout.e_disk_layout attribute), 91
 DiskLayoutRAID1 (ics.structures.e_disk_layout.e_disk_layout attribute), 91
 DiskLayoutRAID5 (ics.structures.e_disk_layout.e_disk_layout attribute), 91
 DiskLayoutSpanned (ics.structures.e_disk_layout.e_disk_layout attribute), 91
 do_not_learn (ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s attribute), 141
 dotVersion (ics.structures.version_report.version_report attribute), 190
 downstreamChannelOffset (ics.structures.a2_b_monitor_settings.a2_b_monitor_settings attribute), 87
 drpdttag (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute), 139
 drpnona664 (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute), 139
 drpntag (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute), 139
 duplex (ics.structures.ethernet_settings.ethernet_settings attribute), 93
 dword (ics.structures.s_wil_bridge_config_s.wil_bridge_config_s attribute), 145
 dyn_learn (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute), 139
 dyn_tbsz (ics.structures.s_pluto_l2_address_lookup_params_s.s_pluto_l2_address_lookup_params_s attribute), 138
 dynamic (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 102
 e_device_settings_type (class in ics.structures.e_device_settings_type), 90
 e_disk_format (class in ics.structures.e_disk_format), 91
 e_disk_layout (class in ics.structures.e_disk_layout), 91
 e_generic_api_options (class in ics.structures.e_generic_api_options), 91
 e_gptp_port (class in ics.structures.e_gptp_port), 92
 e_gptp_role (class in ics.structures.e_gptp_role), 92
 e_plasma_ion_vnet_channel_t (class in ics.structures.e_plasma_ion_vnet_channel_t), 92
 e_uart_port_t (class in ics.structures.e_uart_port_t), 92
 eADI_WIL_API (ics.structures.e_generic_api_options.e_generic_api_options attribute), 91
 ecu (ics.structures.global_settings.global_settings attribute), 96
 ecu_id (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 129
 ecu_id (ics.structures.s_pendant_settings.s_pendant_settings attribute), 131
 ecu_id (ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute), 144
 ecu_id (ics.structures.scan_hub_settings.scan_hub_settings attribute), 146
 ecu_id (ics.structures.secu_settings.secu_settings attribute), 147
 ecu_id (ics.structures.sievb_settings.sievb_settings attribute), 150
 ecu_id (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 162
 ecu_id (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 165
 eevb (ics.structures.global_settings.global_settings attribute), 96
 eFpgaStatusResp (ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet_channel_t attribute), 92
 eGENERIC_API (ics.structures.e_generic_api_options.e_generic_api_options attribute), 92
 egr_mirr (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute), 139
 egr_port (ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s attribute), 141
 egress (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute), 141
 eLockManager (ics.structures.ew_bms_manager_lock_state_t.ew_bms_manager_lock_state_t attribute), 94
 eManagerPortA (ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t attribute), 94
 eManagerPortB (ics.structures.ew_bms_manager_port_t.ew_bms_manager_port_t attribute), 94

E

enable_bus_voltage_monitor() (in module ics.ics), 34	ePortOpEth4 (ics.structures.e_gtp_port.e_gtp_port attribute), 92
enable_convert_mode (ics.structures.j1708_settings.j1708_settings attribute), 108	ePortOpEth5 (ics.structures.e_gtp_port.e_gtp_port attribute), 92
enable_doip_line() (in module ics.ics), 34	ePortOpEth6 (ics.structures.e_gtp_port.e_gtp_port attribute), 92
enable_network_com() (in module ics.ics), 35	ePortOpEth7 (ics.structures.e_gtp_port.e_gtp_port attribute), 92
EnableBusVoltageMonitor() (in module ics.ics), 20	ePortOpEth8 (ics.structures.e_gtp_port.e_gtp_port attribute), 92
enableClockSyntonization (ics.structures.srad_gtp_settings.srad_gtp_settings attribute), 167	ePortOpEth9 (ics.structures.e_gtp_port.e_gtp_port attribute), 92
Enabled (ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute), 132	ePortStdEth1 (ics.structures.e_gtp_port.e_gtp_port attribute), 92
enabled (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config attribute), 139	ePortStdEth2 (ics.structures.e_gtp_port.e_gtp_port attribute), 92
enabled (ics.structures.s_wil_fault_servicing_settings.s_wil_fault_servicing_settings attribute), 146	enableGlobalSettings (ics.structures.global_settings.global_settings attribute), 96
enabled (ics.structures.s_wil_network_data_capture_settings.s_wil_network_data_capture_settings attribute), 146	enableIcsSettings (ics.structures.ics_settings.ics_settings attribute), 177
EnableDOIPLine() (in module ics.ics), 20	eRoleDisabled (ics.structures.e_gtp_role.e_gtp_role attribute), 92
enableFlowControlTransmission (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 179	eRolePassive (ics.structures.e_gtp_role.e_gtp_role attribute), 92
EnableNetworkCom() (in module ics.ics), 21	eRoleSlave (ics.structures.e_gtp_role.e_gtp_role attribute), 92
enablePhy (ics.structures.s_pluto_custom_params.s.s_pluto_custom_params attribute), 136	eSoftCore (ics.structures.e_plasma_ion_vnet_channel.t.e_plasma_ion_vnet_channel attribute), 92
enablePhy (ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings attribute), 158	eth10g (ics.structures.srad_moon3_settings.srad_moon3_settings attribute), 92
enablePhy (ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings attribute), 169	eth2 (ics.structures.srad_super_moon_settings.srad_super_moon_settings attribute), 92
endAddress (ics.structures.start_dhcp_server_command.start_dhcp_server_command attribute), 181	ethConfigurationPort (ics.structures.fire3_linux_settings.fire3_linux_settings attribute), 95
enfport (ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry attribute), 137	ether_badge_versions
enhancedFlashDriver (ics.structures.device_feature.device_feature attribute), 89	etherBadge (ics.structures.global_settings.global_settings attribute), 97
entryBytes (ics.structures.s_phy_reg_pkt_hdr.s_phy_reg_pkt_hdr attribute), 133	ethernet (ics.structures.s_cyan_settings.s_cyan_settings attribute), 112
ePortDisabled (ics.structures.e_gtp_port.e_gtp_port attribute), 92	ethernet (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 115
ePortOpEth1 (ics.structures.e_gtp_port.e_gtp_port attribute), 92	ethernet (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 127
ePortOpEth10 (ics.structures.e_gtp_port.e_gtp_port attribute), 92	ethernet (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 152
ePortOpEth11 (ics.structures.e_gtp_port.e_gtp_port attribute), 92	ethernet (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 154
ePortOpEth12 (ics.structures.e_gtp_port.e_gtp_port attribute), 92	ethernet (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 157
ePortOpEth2 (ics.structures.e_gtp_port.e_gtp_port attribute), 92	
ePortOpEth3 (ics.structures.e_gtp_port.e_gtp_port attribute), 92	

(in module `ics.ics`), 193

`ETHERNET_SETTINGS2_FLAG_FULL_DUPLEX` (in module `ics.ics`), 193

`ETHERNET_SETTINGS2_FLAG_ICS_SFP` (in module `ics.ics`), 193

`ETHERNET_SETTINGS2_FLAG_RTSP_ENABLE` (in module `ics.ics`), 193

`ETHERNET_SETTINGS2_FLAG_TCPIP_ENABLE` (in module `ics.ics`), 193

`ETHERNET_SETTINGS2_SIZE` (in module `ics.ics`), 193

`ETHERNET_SETTINGS_SIZE` (in module `ics.ics`), 193

`ethernetActivationLineEnabled` (`ics.structures.ics_fire2_device_status.ics_fire2_device_status` attribute), 100

`ethernetActivationLineEnabled` (`ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device_status` attribute), 100

`ethernetActivationLineEnabled` (`ics.structures.ics_fire3_device_status.ics_fire3_device_status` attribute), 100

`ethernetActivationLineEnabled` (`ics.structures.ics_flex_vnetz_device_status.ics_flex_vnetz_device_status` attribute), 100

`ethernetActivationLineEnabled` (`ics.structures.ics_vcan4_device_status.ics_vcan4_device_status` attribute), 106

`ethernetActivationLineEnabled_2` (`ics.structures.ics_fire3_device_status.ics_fire3_device_status` attribute), 100

`ethernetStatus` (`ics.structures.ics_fire2_device_status.ics_fire2_device_status` attribute), 100

`ethernetStatus` (`ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device_status` attribute), 100

`ethernetStatus` (`ics.structures.ics_fire3_device_status.ics_fire3_device_status` attribute), 100

`ethernetStatus` (`ics.structures.ics_flex_vnetz_device_status.ics_flex_vnetz_device_status` attribute), 100

`ethernetStatus` (`ics.structures.ics_obd2_pro_device_status.ics_obd2_pro_device_status` attribute), 100

`ethernetStatus` (`ics.structures.ics_rad_bms_device_status.ics_rad_bms_device_status` attribute), 100

`ethernetStatus` (`ics.structures.ics_rad_epsilon_device_status.ics_rad_epsilon_device_status` attribute), 100

`ethernetStatus` (`ics.structures.ics_rad_jupiter_device_status.ics_rad_jupiter_device_status` attribute), 101

`ethernetStatus` (`ics.structures.ics_rad_moon_duo_device_status.ics_rad_moon_duo_device_status` attribute), 101

`ethernetStatus` (`ics.structures.ics_rad_pluto_device_status.ics_rad_pluto_device_status` attribute), 101

`ethernetStatus` (`ics.structures.ics_vcan4_device_status.ics_vcan4_device_status` attribute), 106

`ethernetStatus` (`ics.structures.ics_vcan4_industrial_device_status.ics_vcan4_industrial_device_status` attribute), 106

`etssrcpcf` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 134

`eUART0` (`ics.structures.e_uart_port_t.e_uart_port_t` attribute), 93

`eUART1` (`ics.structures.e_uart_port_t.e_uart_port_t` attribute), 93

`eUnlockManager` (`ics.structures.ew_bms_manager_lock_state_t.ew_bms_manager_lock_state_t` attribute), 94

`ew_bms_instance_t` (class in `ics.structures.ew_bms_instance_t`), 94

`ew_bms_manager_lock_state_t` (class in `ics.structures.ew_bms_manager_lock_state_t`), 94

`ew_bms_manager_port_t` (class in `ics.structures.ew_bms_manager_port_t`), 94

`ewBMSInstance1` (`ics.structures.ew_bms_instance_t.ew_bms_instance_t` attribute), 94

`expansionSlot` (`ics.structures.version_report.version_report` attribute), 190

`expansionSlot` (`ics.structures.spy_filter_long.spy_filter_long` attribute), 156

`ext_address_enable` (`ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message` attribute), 106

`ext_address_enable` (`ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message` attribute), 179

`ext_address_enable` (`ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message` attribute), 180

`extended_response_code` (class in `ics.structures.extended_response_code`), 94

`extended_response_code` (class in `ics.structures.extended_response_generic`), 94

`EXTENDED_RESPONSE_INVALID_COMMAND` (in module `ics.ics`), 193

`EXTENDED_RESPONSE_INVALID_PARAMETER` (in module `ics.ics`), 193

`EXTENDED_RESPONSE_INVALID_STATE` (in module `ics.ics`), 193

EXTENDED_RESPONSE_OK (ics.structures.extended_response_code.extended_response_code attribute), 94

EXTENDED_RESPONSE_OK (in module ics.ics), 193

EXTENDED_RESPONSE_OPERATION_FAILED (ics.structures.extended_response_code.extended_response_code attribute), 94

EXTENDED_RESPONSE_OPERATION_FAILED (in module ics.ics), 193

EXTENDED_RESPONSE_OPERATION_PENDING (ics.structures.extended_response_code.extended_response_code attribute), 94

EXTENDED_RESPONSE_OPERATION_PENDING (in module ics.ics), 193

extendedAddress (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 106

extendedAddress (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 179

extendedAddress (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 180

extension (ics.structures.s_ext_sub_cmd_comm.s_ext_sub_cmd_comm attribute), 117

extraction_timeout (ics.structures.logger_settings.logger_settings attribute), 108

ExtraDataPtr (ics.ics.SpyMessage attribute), 18

ExtraDataPtr (ics.ics.SpyMessageJ1850 attribute), 19

ExtraDataPtr (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 101

ExtraDataPtr (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 103

ExtraDataPtr (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 105

ExtraDataPtrEnabled (ics.ics.SpyMessage attribute), 18

ExtraDataPtrEnabled (ics.ics.SpyMessageJ1850 attribute), 19

ExtraDataPtrEnabled (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 101

ExtraDataPtrEnabled (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 103

ExtraDataPtrEnabled (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 105

F

fan_speed_interval_ms (ics.structures.rad_reporting_settings.rad_reporting_settings attribute), 111

fast_init_network_enables_1 (ics.structures.s_fire_settings.s_fire_settings attribute), 122

fast_init_network_enables_2 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 125

fast_init_network_enables_2 (ics.structures.s_fire_settings.s_fire_settings attribute), 122

fast_init_network_enables_2 (in module ics.ics), 193

fast_init_network_enables_2 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 125

fast_init_network_enables_2 (ics.structures.s_wil_connection_settings.s_wil_connection_settings attribute), 145

fc_ext_address_enable (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 179

fc_ext_address_enable (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 180

fc_id (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 106

fc_id (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 179

fc_id (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 180

fc_id_29_bit_enable (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 106

fc_id_29_bit_enable (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 179

fc_id_29_bit_enable (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 180

fc_id_mask (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 106

fc_id_mask (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 180

fcrc1 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 102

fcrc2 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 102

FDBaudrate (ics.structures.canfd_settings.canfd_settings attribute), 88

FDBDP (ics.structures.canfd_settings.canfd_settings attribute), 88

FDMODE (ics.structures.canfd_settings.canfd_settings attribute), 88

- FDTDC (*ics.structures.canfd_settings.canfd_settings* attribute), 88
- FDTqProp (*ics.structures.canfd_settings.canfd_settings* attribute), 88
- FDTqSeg1 (*ics.structures.canfd_settings.canfd_settings* attribute), 88
- FDTqSeg2 (*ics.structures.canfd_settings.canfd_settings* attribute), 89
- FDTqSync (*ics.structures.canfd_settings.canfd_settings* attribute), 89
- featureBitfields (*ics.structures.get_supported_features* attribute), 96
- find_devices() (in module *ics.ics*), 35
- FindNeoDevices() (in module *ics.ics*), 21
- finishedProcessing (*ics.structures.generic_api_status.generic_api_status* attribute), 96
- fire (*ics.structures.global_settings.global_settings* attribute), 97
- fire2Status (*ics.structures.ics_device_status.ics_device_status* attribute), 99
- fire3 (*ics.structures.global_settings.global_settings* attribute), 97
- fire3_flexray_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 177
- fire3_linux_settings (class in *ics.structures.fire3_linux_settings*), 95
- fire3_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 177
- fire3fr (*ics.structures.global_settings.global_settings* attribute), 97
- fire3Status (*ics.structures.ics_device_status.ics_device_status* attribute), 99
- fire_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 177
- firevnet (*ics.structures.global_settings.global_settings* attribute), 97
- firmware_update_required() (in module *ics.ics*), 35
- FirmwareUpdateRequired() (in module *ics.ics*), 21
- fl_domain (*ics.structures.s_pluto_l2_forwarding_entry_sfl_plus* attribute), 138
- flag (*ics.structures.uart_port_port_bytes.uart_port_port_bytes* attribute), 189
- flags (*ics.structures.a2_b_monitor_settings.a2_b_monitor_settings* attribute), 87
- flags (*ics.structures.ethernet10_g_settings.ethernet10_g_settings* attribute), 93
- flags (*ics.structures.ethernet_settings2.ethernet_settings2* attribute), 94
- flags (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message* attribute), 106
- flags (*ics.structures.op_eth_general_settings.op_eth_general_settings* attribute), 109
- flags (*ics.structures.rad_reporting_settings.rad_reporting_settings* attribute), 111
- flags (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 112
- flags (*ics.structures.s_ether_badge_settings.s_ether_badge_settings* attribute), 116
- flags (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 119
- flags (*ics.structures.s_flexray_settings.s_flexray_settings* attribute), 128
- flags (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings* attribute), 129
- flags (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt* attribute), 132
- flags (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings* attribute), 143
- flags (*ics.structures.s_vivid_can_settings.s_vivid_can_settings* attribute), 145
- flags (*ics.structures.secu_avb_settings.secu_avb_settings* attribute), 147
- flags (*ics.structures.serdescam_settings.serdescam_settings* attribute), 149
- flags (*ics.structures.serdesgen_settings.serdesgen_settings* attribute), 150
- flags (*ics.structures.sobd2_lc_settings.sobd2_lc_settings* attribute), 152
- flags (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 154
- flags (*ics.structures.sobd2_sim_settings.sobd2_sim_settings* attribute), 155
- flags (*ics.structures.srad_epsilon_settings.srad_epsilon_settings* attribute), 157
- flags (*ics.structures.srad_gigalog_settings.srad_gigalog_settings* attribute), 162
- flags (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 165
- flags (*ics.structures.srad_jupiter_settings.srad_jupiter_settings* attribute), 168
- flags (*ics.structures.srad_moon3_settings.srad_moon3_settings* attribute), 170
- flags (*ics.structures.srad_pluto_settings.srad_pluto_settings* attribute), 170
- flags (*ics.structures.srada2_b_settings.srada2_b_settings* attribute), 174
- flags (*ics.structures.sradbms_settings.sradbms_settings* attribute), 175
- flags (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message* attribute), 179
- flags (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message* attribute), 180
- flags (*ics.structures.svc412_settings.svc412_settings* attribute), 182

flags (ics.structures.svcan4_ind_settings.svcan4_ind_settings	from_param(ics.structures.a2_b_node_type.a2_b_node_type
attribute), 183	attribute), 87
flags (ics.structures.svcan4_settings.svcan4_settings	from_param(ics.structures.a2_btdm_mode.a2_btdm_mode
attribute), 184	attribute), 87
flags2 (ics.structures.ethernet_settings2.ethernet_settings2	from_param(ics.structures.device_feature.device_feature
attribute), 94	attribute), 89
flashHeader (ics.structures.s_pluto_switch_settings.s_s_pluto_switch_settings	from_param(ics.structures.e_device_settings_type.e_device_settings_type
attribute), 141	attribute), 91
flex_mode (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings	from_param(ics.structures.e_disk_format.e_disk_format
attribute), 128	attribute), 91
flex_termination (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings	from_param(ics.structures.e_disk_layout.e_disk_layout
attribute), 128	attribute), 91
flex_vnet_mode (class in ics.structures.flex_vnet_mode), 95	from_param(ics.structures.e_generic_api_options.e_generic_api_options
	attribute), 92
flexVnetModeColdStart (ics.structures.flex_vnet_mode.flex_vnet_mode	from_param(ics.structures.e_gptp_port.e_gptp_port
attribute), 95	attribute), 92
flexVnetModeDisabled (ics.structures.flex_vnet_mode.flex_vnet_mode	from_param(ics.structures.e_gptp_role.e_gptp_role
attribute), 95	attribute), 92
flexVnetModeOneDual (ics.structures.flex_vnet_mode.flex_vnet_mode	from_param(ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion
attribute), 95	attribute), 92
flexVnetModeOneSingle (ics.structures.flex_vnet_mode.flex_vnet_mode	from_param(ics.structures.e_uart_port_t.e_uart_port_t
attribute), 95	attribute), 93
flexVnetModeOneSingle (ics.structures.flex_vnet_mode.flex_vnet_mode	from_param(ics.structures.ew_bms_instance_t.ew_bms_instance_t
attribute), 95	attribute), 94
flexVnetModeOneSingle (ics.structures.flex_vnet_mode.flex_vnet_mode	from_param(ics.structures.ew_bms_manager_lock_state_t.ew_bms_man
attribute), 95	attribute), 94
flexVnetModeTwoSingle (ics.structures.flex_vnet_mode.flex_vnet_mode	from_param(ics.structures.ew_bms_manager_port_t.ew_bms_manager
attribute), 95	attribute), 94
flexvnetz (ics.structures.global_settings.global_settings	from_param(ics.structures.extended_response_code.extended_response
attribute), 97	attribute), 94
flexVnetzStatus (ics.structures.ics_device_status.ics_device_status	from_param(ics.structures.flex_vnet_mode.flex_vnet_mode
attribute), 99	attribute), 95
flow_control (ics.structures.uart_settings.uart_settings	from_param(ics.structures.op_eth_link_mode.op_eth_link_mode
attribute), 189	attribute), 109
flowControlExtendedAddress (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message	from_param(ics.structures.s_phy_reg_pkt_rw.s_phy_reg_pkt_rw
attribute), 106	attribute), 133
flowControlExtendedAddress (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message	from_param(ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_status
attribute), 106	attribute), 134
flowControlExtendedAddress (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message	fs_timeout(ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_m
attribute), 179	attribute), 187
flowControlExtendedAddress (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message	fs_timeout(ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_m
attribute), 180	attribute), 180
flowControlExtendedAddress (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message	fs_timeout(ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_m
attribute), 180	attribute), 107
force_firmware_update() (in module ics.ics), 36	fs_wait(ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_m
ForceFirmwareUpdate() (in module ics.ics), 21	attribute), 180
frame_len_12_5ns (ics.structures.ics_spy_message_flex_raw_ics_spy_message_flex_raw_ics_spy_message_flex_pluto	from_param(ics.structures.generic_api_status.generic_api_status
attribute), 102	attribute), 96
frame_reserved (ics.structures.ics_spy_message_flex_raw_ics_spy_message_flex_raw_ics_spy_message_flex_pluto	functionID(ics.structures.generic_api_selector.generic_api_selector
attribute), 103	attribute), 95
FrameMaster (ics.structures.spy_filter_long.spy_filter_long	
attribute), 156	
frameSkip (ics.structures.serdescam_settings.serdescam_settings	
attribute), 149	

G

- gateway (*ics.structures.ethernet10_g_settings.ethernet10_g_settings* attribute), 93
- gateway (*ics.structures.ethernet_settings2.ethernet_settings2* attribute), 94
- gatewayAddress (*ics.structures.start_dhcp_server_command.start_dhcp_server_command* attribute), 181
- General_Settings (*ics.structures.hw_eth_settings.hw_eth_settings* attribute), 99
- generalParams (*ics.structures.s_pluto_switch_settings.s_pluto_switch_settings* attribute), 141
- generic_api_data (class in *ics.structures.generic_api_data*), 95
- GENERIC_API_DATA_BUFFER_SIZE (in module *ics.ics*), 193
- generic_api_get_status () (in module *ics.ics*), 36
- generic_api_read_data () (in module *ics.ics*), 36
- generic_api_selector (class in *ics.structures.generic_api_selector*), 95
- generic_api_send_command () (in module *ics.ics*), 36
- generic_api_status (class in *ics.structures.generic_api_status*), 95
- GenericAPIGetStatus () (in module *ics.ics*), 21
- GenericAPIReadData () (in module *ics.ics*), 21
- GenericAPISendCommand () (in module *ics.ics*), 21
- get_active_vnet_channel () (in module *ics.ics*), 36
- get_all_chip_versions () (in module *ics.ics*), 37
- get_backup_power_enabled () (in module *ics.ics*), 37
- get_backup_power_ready () (in module *ics.ics*), 37
- get_bus_voltage () (in module *ics.ics*), 37
- get_component_versions (class in *ics.structures.get_component_versions*), 96
- get_component_versions_response (class in *ics.structures.get_component_versions_response*), 96
- get_device_settings () (in module *ics.ics*), 37
- get_device_status () (in module *ics.ics*), 38
- get_disk_details () (in module *ics.ics*), 38
- get_disk_format_progress () (in module *ics.ics*), 38
- get_dll_firmware_info () (in module *ics.ics*), 39
- get_dll_version () (in module *ics.ics*), 39
- get_error_messages () (in module *ics.ics*), 39
- get_gptp_status () (in module *ics.ics*), 39
- get_hw_firmware_info () (in module *ics.ics*), 39
- get_last_api_error () (in module *ics.ics*), 40
- get_library_path () (in module *ics.ics*), 40
- get_messages () (in module *ics.ics*), 40
- get_pcb_serial_number () (in module *ics.ics*), 40
- get_performance_parameters () (in module *ics.ics*), 41
- get_rtc () (in module *ics.ics*), 41
- get_script_status () (in module *ics.ics*), 41
- get_serial_number () (in module *ics.ics*), 41
- GET_SUPPORTED_FEATURES_COMMAND_VERSION (in module *ics.ics*), 193
- get_supported_features_response (class in *ics.structures.get_supported_features_response*), 96
- get_timestamp_for_msg () (in module *ics.ics*), 41
- GetActiveVNETChannel () (in module *ics.ics*), 21
- GetAllChipVersions () (in module *ics.ics*), 22
- GetBackupPowerEnabled () (in module *ics.ics*), 22
- GetBackupPowerReady () (in module *ics.ics*), 22
- GetBusVoltage () (in module *ics.ics*), 22
- GetDeviceSettings () (in module *ics.ics*), 22
- GetDeviceStatus () (in module *ics.ics*), 22
- GetDLLFirmwareInfo () (in module *ics.ics*), 22
- GetDLLVersion () (in module *ics.ics*), 22
- GetErrorMessages () (in module *ics.ics*), 23
- GetGPTPStatus () (in module *ics.ics*), 23
- GetHWFirmwareInfo () (in module *ics.ics*), 23
- GetLastAPIError () (in module *ics.ics*), 23
- GetMessages () (in module *ics.ics*), 23
- GetPCBSerialNumber () (in module *ics.ics*), 23
- GetPerformanceParameters () (in module *ics.ics*), 23
- GetRTC () (in module *ics.ics*), 23
- GetSerialNumber () (in module *ics.ics*), 23
- GetTimeStampForMsg () (in module *ics.ics*), 24
- global_settings (class in *ics.structures.global_settings*), 96
- GLOBAL_SETTINGS_SIZE (in module *ics.ics*), 193
- gm_priority (*ics.structures.gptp_status.gptp_status* attribute), 98
- gps_interval_ms (*ics.structures.rad_reporting_settings.rad_reporting_settings* attribute), 111
- gPTP (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 119
- gPTP (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 159
- gPTP (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 165
- gPTP (*ics.structures.srad_gptp_and_tap_settings.srad_gptp_and_tap_settings* attribute), 166
- gPTP (*ics.structures.srad_moon2_settings.srad_moon2_settings* attribute), 169
- gPTP (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 172
- gPTP (*ics.structures.srad_super_moon_settings.srad_super_moon_settings* attribute), 173
- gPTP (*ics.structures.srada2_b_settings.srada2_b_settings* attribute), 173

attribute), 174

gptp_status (class in ics.structures.gptp_status), 98

gptpEnabledPort (ics.structures.srad_gptp_settings.srad_gptp_settings (class in ics.structures.hw_eth_settings), 99

attribute), 167

gPTPportRole (ics.structures.s_jupiter_ptp_params.s.jupiter_ptp_params.SIZE (in module ics.ics), 193

attribute), 128

hwComLatencyTestEn

gPTPportRole (ics.structures.s_pluto_ptp_params.s.pluto_ptp_params.ics.structures.srad_galaxy_settings.srad_galaxy_settings

attribute), 140

attribute), 159

gPTPportRole (ics.structures.srad_gptp_settings.srad_gptp_settings.hwComLatencyTestEn

attribute), 167

(ics.structures.srad_moon2_settings.srad_moon2_settings

attribute), 169

GS_VERSION (in module ics.ics), 193

hwComLatencyTestEn

(ics.structures.srad_star2_settings.srad_star2_settings

attribute), 172

hwComLatencyTestEn

(ics.structures.srad_super_moon_settings.srad_super_moon_setti

attribute), 173

H

half_duplex (ics.structures.uart_settings.uart_settings

attribute), 189

Handle (ics.ics.NeoDevice attribute), 18

HARDWARE_TIMESTAMP_ID_AVT_716 (in module

ics.ics), 193

HARDWARE_TIMESTAMP_ID_AVT_717 (in module

ics.ics), 193

HARDWARE_TIMESTAMP_ID_DOUBLE_SEC (in mod-

ule ics.ics), 193

HARDWARE_TIMESTAMP_ID_NEORED_10NS (in

module ics.ics), 193

HARDWARE_TIMESTAMP_ID_NEORED_10US (in

module ics.ics), 193

HARDWARE_TIMESTAMP_ID_NEORED_25NS (in

module ics.ics), 193

HARDWARE_TIMESTAMP_ID_NEOVI (in module

ics.ics), 193

HARDWARE_TIMESTAMP_ID_NI_CAN (in module

ics.ics), 193

HARDWARE_TIMESTAMP_ID_NONE (in module

ics.ics), 193

HARDWARE_TIMESTAMP_ID_VSI (in module ics.ics),

193

hcrc_lsbs (ics.structures.ics_spy_message_flex_ray.ics_spy_message2_flex_ray.device_status (class in

ics.structures.ics_fire2_device_status), 99

attribute), 103

hcrc_msbs (ics.structures.ics_spy_message_flex_ray.ics_spy_message2_flex_ray.device_status (class in

ics.structures.ics_fire2_vnet_device_status),

100

Header (ics.ics.SpyMessageJ1850 attribute), 19

header (ics.structures.s_ext_sub_cmd_comm.s_ext_sub_cmd_comm.confire3_device_status (class in

ics.structures.ics_fire3_device_status), 100

attribute), 117

Header (ics.structures.spy_filter_long.spy_filter_long ics_flex_vnetz_device_status (class in

ics.structures.ics_flex_vnetz_device_status),

100

attribute), 156

HeaderLength (ics.structures.spy_filter_long.spy_filter_long

100

attribute), 156

HeaderMask (ics.structures.spy_filter_long.spy_filter_long

ics_obd2_pro_device_status (class in

ics.structures.ics_obd2_pro_device_status),

100

attribute), 156

high_speed_auto_switch

(ics.structures.swcan_settings.swcan_settings

ics_rad_bms_device_status (class in

ics.structures.ics_rad_bms_device_status),

attribute), 187

100

host_port (ics.structures.s_pluto_general_params.s.pluto_general_params.device_status (class in

ics.structures.ics_rad_epsilon_device_status),

attribute), 136

100
 ics_rad_jupiter_device_status (class in
 ics.structures.ics_rad_jupiter_device_status),
 101
 ics_rad_moon_duo_device_status (class in
 ics.structures.ics_rad_moon_duo_device_status),
 101
 ics_rad_pluto_device_status (class in
 ics.structures.ics_rad_pluto_device_status),
 101
 ics_spy_message_flex_ray (class in
 ics.structures.ics_spy_message_flex_ray),
 101
 ics_spy_message_long (class in
 ics.structures.ics_spy_message_long), 103
 ics_spy_message_vsb (class in
 ics.structures.ics_spy_message_vsb), 104
 ics_vcan4_device_status (class in
 ics.structures.ics_vcan4_device_status), 106
 ics_vcan4_industrial_device_status (class
 in ics.structures.ics_vcan4_industrial_device_status),
 106
 icsneoClosePort () (in module ics.ics), 42
 icsneoEnableBusVoltageMonitor () (in mod-
 ule ics.ics), 42
 icsneoEnableDOIPLine () (in module ics.ics), 42
 icsneoEnableNetworkCom () (in module ics.ics),
 42
 icsneoFindNeoDevices () (in module ics.ics), 42
 icsneoFirmwareUpdateRequired () (in module
 ics.ics), 42
 icsneoForceFirmwareUpdate () (in module
 ics.ics), 42
 icsneoGenericAPIGetStatus () (in module
 ics.ics), 42
 icsneoGenericAPIReadData () (in module
 ics.ics), 43
 icsneoGenericAPISendCommand () (in module
 ics.ics), 43
 icsneoGetActiveVNETChannel () (in module
 ics.ics), 43
 icsneoGetAllChipVersions () (in module
 ics.ics), 43
 icsneoGetBackupPowerEnabled () (in module
 ics.ics), 43
 icsneoGetBackupPowerReady () (in module
 ics.ics), 43
 icsneoGetBusVoltage () (in module ics.ics), 43
 icsneoGetDeviceSettings () (in module ics.ics),
 44
 icsneoGetDeviceStatus () (in module ics.ics), 44
 icsneoGetDLLFirmwareInfo () (in module
 ics.ics), 43
 icsneoGetDLLVersion () (in module ics.ics), 44
 icsneoGetErrorMessages () (in module ics.ics),
 44
 icsneoGetGPTPStatus () (in module ics.ics), 44
 icsneoGetHWFirmwareInfo () (in module ics.ics),
 44
 icsneoGetLastError () (in module ics.ics), 44
 icsneoGetMessages () (in module ics.ics), 44
 icsneoGetPCBSerialNumber () (in module
 ics.ics), 45
 icsneoGetPerformanceParameters () (in mod-
 ule ics.ics), 45
 icsneoGetRTC () (in module ics.ics), 45
 icsneoGetSerialNumber () (in module ics.ics), 45
 icsneoGetTimeStampForMsg () (in module
 ics.ics), 45
 icsneoIsDeviceFeatureSupported () (in mod-
 ule ics.ics), 46
 icsneoISO15765_DisableNetworks () (in mod-
 ule ics.ics), 45
 icsneoISO15765_EnableNetworks () (in mod-
 ule ics.ics), 45
 icsneoISO15765_ReceiveMessage () (in mod-
 ule ics.ics), 45
 icsneoISO15765_TransmitMessage () (in mod-
 ule ics.ics), 46
 icsneoLoadDefaultSettings () (in module
 ics.ics), 46
 icsneoOpenNeoDevice () (in module ics.ics), 46
 icsneoReadJupiterFirmware () (in module
 ics.ics), 46
 icsneoReadSDCard () (in module ics.ics), 46
 icsneoRequestDiskDetails () (in module
 ics.ics), 46
 icsneoRequestDiskFormat () (in module ics.ics),
 46
 icsneoRequestDiskFormatCancel () (in mod-
 ule ics.ics), 47
 icsneoRequestDiskFormatProgress () (in
 module ics.ics), 47
 icsneoRequestEnterSleepMode () (in module
 ics.ics), 47
 icsneoScriptClear () (in module ics.ics), 47
 icsneoScriptGetFBlockStatus () (in module
 ics.ics), 47
 icsneoScriptGetScriptStatus () (in module
 ics.ics), 47
 icsneoScriptGetScriptStatusEx () (in mod-
 ule ics.ics), 47
 icsneoScriptLoad () (in module ics.ics), 47
 icsneoScriptReadAppSignal () (in module
 ics.ics), 48
 icsneoScriptReadRxMessage () (in module
 ics.ics), 48
 icsneoScriptReadTxMessage () (in module

`ics.ics`), 48
`icsneoScriptStart()` (in module `ics.ics`), 48
`icsneoScriptStartFBlock()` (in module `ics.ics`), 48
`icsneoScriptStop()` (in module `ics.ics`), 48
`icsneoScriptStopFBlock()` (in module `ics.ics`), 48
`icsneoScriptWriteAppSignal()` (in module `ics.ics`), 48
`icsneoScriptWriteRxMessage()` (in module `ics.ics`), 49
`icsneoScriptWriteTxMessage()` (in module `ics.ics`), 49
`icsneoSetActiveVNETChannel()` (in module `ics.ics`), 49
`icsneoSetBackupPowerEnabled()` (in module `ics.ics`), 49
`icsneoSetBitRate()` (in module `ics.ics`), 49
`icsneoSetBitRateEx()` (in module `ics.ics`), 49
`icsneoSetContext()` (in module `ics.ics`), 49
`icsneoSetDeviceSettings()` (in module `ics.ics`), 49
`icsneoSetFDBitRate()` (in module `ics.ics`), 50
`icsneoSetLedProperty()` (in module `ics.ics`), 50
`icsneoSetReflashDisplayCallbacks()` (in module `ics.ics`), 50
`icsneoSetRTC()` (in module `ics.ics`), 50
`icsneoStartDHCPServer()` (in module `ics.ics`), 50
`icsneoStopDHCPServer()` (in module `ics.ics`), 50
`icsneoTxMessages()` (in module `ics.ics`), 50
`icsneoUartGetBaudrate()` (in module `ics.ics`), 50
`icsneoUartRead()` (in module `ics.ics`), 50
`icsneoUartSetBaudrate()` (in module `ics.ics`), 51
`icsneoUartWrite()` (in module `ics.ics`), 51
`icsneoValidateHObject()` (in module `ics.ics`), 51
`icsneowBMSManagerReset()` (in module `ics.ics`), 51
`icsneowBMSManagerWriteLock()` (in module `ics.ics`), 51
`icsneoWriteJupiterFirmware()` (in module `ics.ics`), 51
`icsneoWriteSDCard()` (in module `ics.ics`), 51
`id(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray_message attribute)`, 103
`id(ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute)`, 107
`id(ics.structures.scan_sleep_id.scan_sleep_id attribute)`, 146
`id(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute)`, 179
`id(ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute)`, 180
`id_mask(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_tx_message attribute)`, 179
`identifier(ics.structures.version_report.version_report attribute)`, 190
`idle_wakeup_network_enables_1(ics.structures.s_cyan_settings.s_cyan_settings attribute)`, 112
`idle_wakeup_network_enables_1(ics.structures.sievb_settings.sievb_settings attribute)`, 150
`idle_wakeup_network_enables_1(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute)`, 159
`idle_wakeup_network_enables_1(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute)`, 163
`idle_wakeup_network_enables_1(ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute)`, 165
`idle_wakeup_network_enables_1(ics.structures.srad_star2_settings.srad_star2_settings attribute)`, 172
`idle_wakeup_network_enables_1(ics.structures.svcanrf_settings.svcanrf_settings attribute)`, 185
`idle_wakeup_network_enables_2(ics.structures.s_cyan_settings.s_cyan_settings attribute)`, 112
`idle_wakeup_network_enables_2(ics.structures.sievb_settings.sievb_settings attribute)`, 150
`idle_wakeup_network_enables_2(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute)`, 160
`idle_wakeup_network_enables_2(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute)`, 163
`idle_wakeup_network_enables_2(ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute)`, 165
`idle_wakeup_network_enables_2(ics.structures.srad_star2_settings.srad_star2_settings attribute)`, 172
`idle_wakeup_network_enables_2(ics.structures.svcanrf_settings.svcanrf_settings attribute)`, 185
`idle_wakeup_network_enables_3(ics.structures.s_cyan_settings.s_cyan_settings attribute)`, 112
`idle_wakeup_network_enables_3(ics.structures.sievb_settings.sievb_settings attribute)`, 150
`idle_wakeup_network_enables_3(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute)`, 160
`idle_wakeup_network_enables_3(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute)`, 163
`idle_wakeup_network_enables_3(ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute)`, 165
`idle_wakeup_network_enables_3(ics.structures.srad_star2_settings.srad_star2_settings attribute)`, 172
`idle_wakeup_network_enables_3(ics.structures.svcanrf_settings.svcanrf_settings attribute)`, 185

(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 137
 attribute), 160 index (ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_add
 idle_wakeup_network_enables_3 attribute), 137
 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 163
 attribute), 139
 idle_wakeup_network_enables_3 ing_port (ics.structures.s_pluto_retagging_entry.s.s_pluto_retagging_en
 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 141
 attribute), 165 ingress (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config_s
 idle_wakeup_network_enables_3 attribute), 139
 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 172
 attribute), 108
 ievb (ics.structures.global_settings.global_settings at- init_steps (ics.structures.iso9141_keyword2000_settings.iso9141_keyw
 tribute), 97 attribute), 108
 ifg (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config attribute), 139
 attribute), 138 initLogPDelayReqInterval
 ignore2stf (ics.structures.s_pluto_general_params.s.s_pluto_general_params attribute), 137
 attribute), 138 initLogSyncInterval
 iMainFirmChkSum (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 176
 attribute), 128 (ics.structures.s_jupiter_ptp_params.s.s_jupiter_ptp_params_s
 iMainFirmDateDay (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 176
 attribute), 25us (ics.structures.can_settings.can_settings
 iMainFirmDateHour attribute), 88
 (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 177
 attribute), 95 (ics.structures.generic_api_selector.generic_api_selector
 iMainFirmDateMin (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 177
 attribute), 134 (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sy
 iMainFirmDateMonth inttosynth (ics.structures.s_pluto_clock_sync_params.s.s_pluto_cloc
 (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 134
 attribute), 177 inttotenth (ics.structures.s_pluto_clock_sync_params.s.s_pluto_cloc
 iMainFirmDateSecond attribute), 134
 (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 177
 attribute), 189 (ics.structures.uart_settings.uart_settings
 iMainFirmDateYear invert_tx (ics.structures.uart_settings.uart_settings
 (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 189
 attribute), 177 io_interval_ms (ics.structures.rad_reporting_settings.rad_reporting_s
 iMainVnetHWrevMajor attribute), 111
 (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 177
 attribute), 93 (ics.structures.ethernet10_g_settings.ethernet10_g_settings
 iMainVnetHWrevMinor ip_addr (ics.structures.ethernet_settings2.ethernet_settings2
 (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 94
 attribute), 177 ipAddress (ics.structures.rad_moon_duo_converter_settings.rad_moon_
 iMainVnetSRAMSize attribute), 110
 (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 177
 attribute), 134 (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_
 iManufactureDay (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 177
 attribute), 110 (ics.structures.rad_moon_duo_converter_settings.rad_moon_
 iManufactureMonth iPhySiliconRev (ics.structures.st_api_firmware_info.st_api_firmware_
 (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 177
 attribute), 177 ipMask (ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_
 iManufactureYear (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 177
 attribute), 110 (ics.structures.rad_moon_duo_converter_settings.rad_moon_
 attribute), 177 is_device_feature_supported() (in module
 incl_srcpt0 (ics.structures.s_pluto_general_params.s.s_pluto_general_params_s
 attribute), 137 is_sync (ics.structures.gptp_status.gptp_status at-
 incl_srcpt1 (ics.structures.s_pluto_general_params.s.s_pluto_general_params_s
 attribute), 137

is_synchronized(*ics.structures.gptp_status.gptp_status* *isol5765_separation_time_offset*
 attribute), 98 (ics.structures.s_ether_badge_settings.s_ether_badge_settings
 attribute), 116
 isBRSEnabled(*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message*
 attribute), 107 *isol5765_separation_time_offset*
 isBRSEnabled(*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message*
 attribute), 179 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 119
 isBRSEnabled(*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message*
 attribute), 180 (ics.structures.s_fire_settings.s_fire_settings
 attribute), 122
 iscanFD(*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message*
 attribute), 107 *isol5765_separation_time_offset*
 iscanFD(*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message*
 attribute), 179 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
 attribute), 125
 iscanFD(*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message*
 attribute), 181 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings
 attribute), 128
 IsDeviceFeatureSupported() (in module *ics.ics*), 24 *isol5765_separation_time_offset*
 iso15765_2015_tx_message (class in *ics.structures.iso15765_2015_tx_message*),
 106 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
 attribute), 129
 ISO15765_2_NETWORK_HSCAN (in module *ics.ics*),
 193 *isol5765_separation_time_offset*
 ISO15765_2_NETWORK_HSCAN2 (in module *ics.ics*),
 193 (ics.structures.s_pendant_settings.s_pendant_settings
 attribute), 131
 ISO15765_2_NETWORK_HSCAN3 (in module *ics.ics*),
 193 *isol5765_separation_time_offset*
 ISO15765_2_NETWORK_HSCAN4 (in module *ics.ics*),
 194 (ics.structures.s_vivid_can_settings.s_vivid_can_settings
 attribute), 145
 ISO15765_2_NETWORK_HSCAN5 (in module *ics.ics*),
 194 *isol5765_separation_time_offset*
 ISO15765_2_NETWORK_HSCAN6 (in module *ics.ics*),
 194 (ics.structures.scan_hub_settings.scan_hub_settings
 attribute), 146
 ISO15765_2_NETWORK_HSCAN7 (in module *ics.ics*),
 194 *isol5765_separation_time_offset*
 ISO15765_2_NETWORK_MSCAN (in module *ics.ics*),
 194 (ics.structures.secu_avb_settings.secu_avb_settings
 attribute), 147
 ISO15765_2_NETWORK_SWCAN (in module *ics.ics*),
 194 *isol5765_separation_time_offset*
 ISO15765_2_NETWORK_SWCAN2 (in module *ics.ics*),
 194 (ics.structures.secu_settings.secu_settings
 attribute), 147
 iso15765_disable_networks() (in module *ics.ics*), 52 *isol5765_separation_time_offset*
 ISO15765_DisableNetworks() (in module *ics.ics*), 24 (ics.structures.sobd2_lc_settings.sobd2_lc_settings
 attribute), 152
 iso15765_enable_networks() (in module *ics.ics*), 52 *isol5765_separation_time_offset*
 ISO15765_EnableNetworks() (in module *ics.ics*),
 24 (ics.structures.sobd2_pro_settings.sobd2_pro_settings
 attribute), 154
 iso15765_receive_message() (in module *ics.ics*), 52 *isol5765_separation_time_offset*
 ISO15765_ReceiveMessage() (in module *ics.ics*),
 24 (ics.structures.sobd2_sim_settings.sobd2_sim_settings
 attribute), 155
 iso15765_separation_time_offset (ics.structures.s_cyan_settings.s_cyan_settings
 attribute), 112 *isol5765_separation_time_offset*
 (ics.structures.srad_epsilon_settings.srad_epsilon_settings
 attribute), 157
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings
 attribute), 160

iso15765_separation_time_offset (ics.structures.s_fire_settings.s_fire_settings
 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 122
 attribute), 163 iso9141_kwp_enable_reserved
 iso15765_separation_time_offset (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
 (ics.structures.srad_gigastar_settings.srad_gigastar_setting attribute), 125
 attribute), 165 iso9141_kwp_enable_reserved
 iso15765_separation_time_offset (ics.structures.srad_epsilon_settings.srad_epsilon_settings
 (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 157
 attribute), 168 iso9141_kwp_enable_reserved
 iso15765_separation_time_offset (ics.structures.srad_jupiter_settings.srad_jupiter_settings
 (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 168
 attribute), 170 iso9141_kwp_enable_reserved
 iso15765_separation_time_offset (ics.structures.srad_pluto_settings.srad_pluto_settings
 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 171
 attribute), 172 iso9141_kwp_enable_reserved
 iso15765_separation_time_offset (ics.structures.svcanrf_settings.svcanrf_settings
 (ics.structures.srada2_b_settings.srada2_b_settings attribute), 185
 attribute), 174 iso9141_kwp_settings
 iso15765_separation_time_offset (ics.structures.s_ether_badge_settings.s_ether_badge_settings
 (ics.structures.sradbms_settings.sradbms_settings attribute), 116
 attribute), 175 iso9141_kwp_settings
 iso15765_separation_time_offset (ics.structures.s_fire_settings.s_fire_settings
 (ics.structures.svcan3_settings.svcan3_settings attribute), 122
 attribute), 182 iso9141_kwp_settings
 iso15765_separation_time_offset (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
 (ics.structures.svcan412_settings.svcan412_settings attribute), 125
 attribute), 182 iso9141_kwp_settings
 iso15765_separation_time_offset (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
 (ics.structures.svcan4_ind_settings.svcan4_ind_settings attribute), 129
 attribute), 183 iso9141_kwp_settings
 iso15765_separation_time_offset (ics.structures.s_pendant_settings.s_pendant_settings
 (ics.structures.svcan4_settings.svcan4_settings attribute), 131
 attribute), 184 iso9141_kwp_settings
 iso15765_separation_time_offset (ics.structures.secu_settings.secu_settings
 (ics.structures.svcanrf_settings.svcanrf_settings attribute), 147
 attribute), 185 iso9141_kwp_settings
 iso15765_transmit_message() (in module (ics.structures.sievb_settings.sievb_settings
 ics.ics), 52 attribute), 151
 ISO15765_TransmitMessage() (in module iso9141_kwp_settings
 ics.ics), 24 (ics.structures.srad_epsilon_settings.srad_epsilon_settings
 attribute), 157
 ISO9141_KEYWORD2000__INIT_STEP_SIZE (in iso9141_kwp_settings
 module ics.ics), 194 (ics.structures.srad_jupiter_settings.srad_jupiter_settings
 attribute), 168
 iso9141_keyword2000_init_step (class in iso9141_kwp_settings
 ics.structures.iso9141_keyword2000_init_step), 107 (ics.structures.srad_pluto_settings.srad_pluto_settings
 attribute), 171
 iso9141_keyword2000_settings (class in iso9141_kwp_settings
 ics.structures.iso9141_keyword2000_settings), 107 (ics.structures.svcan4_ind_settings.svcan4_ind_settings
 attribute), 183
 ISO9141_KEYWORD2000_SETTINGS_SIZE (in iso9141_kwp_settings
 module ics.ics), 194 (ics.structures.svcanrf_settings.svcanrf_settings
 attribute), 185
 iso9141_kwp_enable_reserved iso9141_kwp_settings
 (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 116
 iso9141_kwp_enable_reserved iso9141_kwp_settings_1

<i>(ics.structures.s_cyan_settings.s_cyan_settings attribute), 112</i>	<i>(ics.structures.svcanrf_settings.svcanrf_settings attribute), 185</i>
iso9141_kwp_settings_1 <i>(ics.structures.s_fire3_settings.s_fire3_settings attribute), 119</i>	iso9141_kwp_settings_3 <i>(ics.structures.s_cyan_settings.s_cyan_settings attribute), 113</i>
iso9141_kwp_settings_1 <i>(ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 153</i>	iso9141_kwp_settings_3 <i>(ics.structures.s_fire3_settings.s_fire3_settings attribute), 119</i>
iso9141_kwp_settings_1 <i>(ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 154</i>	iso9141_kwp_settings_3 <i>(ics.structures.s_fire_settings.s_fire_settings attribute), 122</i>
iso9141_kwp_settings_1 <i>(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160</i>	iso9141_kwp_settings_3 <i>(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 125</i>
iso9141_kwp_settings_1 <i>(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 163</i>	iso9141_kwp_settings_4 <i>(ics.structures.s_cyan_settings.s_cyan_settings attribute), 113</i>
iso9141_kwp_settings_1 <i>(ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 165</i>	iso9141_kwp_settings_4 <i>(ics.structures.s_fire3_settings.s_fire3_settings attribute), 119</i>
iso9141_kwp_settings_1 <i>(ics.structures.srad_star2_settings.srad_star2_settings attribute), 172</i>	iso9141_kwp_settings_4 <i>(ics.structures.s_fire_settings.s_fire_settings attribute), 123</i>
iso9141_kwp_settings_1 <i>(ics.structures.srada2_b_settings.srada2_b_settings attribute), 174</i>	iso9141_kwp_settings_4 <i>(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 125</i>
iso9141_kwp_settings_1 <i>(ics.structures.svcan4_settings.svcan4_settings attribute), 184</i>	iso9141_kwp_settings_5 <i>(ics.structures.s_fire3_settings.s_fire3_settings attribute), 119</i>
iso9141_kwp_settings_2 <i>(ics.structures.s_cyan_settings.s_cyan_settings attribute), 112</i>	iso9141_kwp_settings_6 <i>(ics.structures.s_fire3_settings.s_fire3_settings attribute), 119</i>
iso9141_kwp_settings_2 <i>(ics.structures.s_fire3_settings.s_fire3_settings attribute), 119</i>	iso_9141_kwp_enable_reserved <i>(ics.structures.s_cyan_settings.s_cyan_settings attribute), 113</i>
iso9141_kwp_settings_2 <i>(ics.structures.s_fire_settings.s_fire_settings attribute), 122</i>	iso_9141_kwp_enable_reserved <i>(ics.structures.s_neo_ecul2_settings.s_neo_ecul2_settings attribute), 129</i>
iso9141_kwp_settings_2 <i>(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 125</i>	iso_9141_kwp_enable_reserved <i>(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160</i>
iso9141_kwp_settings_2 <i>(ics.structures.s_pendant_settings.s_pendant_settings attribute), 131</i>	iso_9141_kwp_enable_reserved <i>(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 163</i>
iso9141_kwp_settings_2 <i>(ics.structures.secu_settings.secu_settings attribute), 147</i>	iso_9141_kwp_enable_reserved <i>(ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 165</i>
iso9141_kwp_settings_2 <i>(ics.structures.sievb_settings.sievb_settings attribute), 151</i>	iso_9141_kwp_enable_reserved <i>(ics.structures.srad_star2_settings.srad_star2_settings attribute), 172</i>
iso9141_kwp_settings_2 <i>(ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 154</i>	iso_9141_kwp_enable_reserved <i>(ics.structures.svcan4_settings.svcan4_settings attribute), 184</i>
iso9141_kwp_settings_2	iso_msg_termination

<i>(ics.structures.s_ether_badge_settings.s_ether_badge_settings</i> <i>attribute), 116</i>	<i>(ics.structures.srad_gigastar_settings.srad_gigastar_settings</i> <i>attribute), 165</i>
<i>iso_msg_termination</i> <i>(ics.structures.s_fire_settings.s_fire_settings</i> <i>attribute), 123</i>	<i>iso_msg_termination_1</i> <i>(ics.structures.srad_star2_settings.srad_star2_settings</i> <i>attribute), 172</i>
<i>iso_msg_termination</i> <i>(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> <i>attribute), 125</i>	<i>iso_msg_termination_1</i> <i>(ics.structures.srada2_b_settings.srada2_b_settings</i> <i>attribute), 174</i>
<i>iso_msg_termination</i> <i>(ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings</i> <i>attribute), 129</i>	<i>iso_msg_termination_1</i> <i>(ics.structures.svcan4_settings.svcan4_settings</i> <i>attribute), 184</i>
<i>iso_msg_termination</i> <i>(ics.structures.s_pendant_settings.s_pendant_settings</i> <i>attribute), 131</i>	<i>iso_msg_termination_2</i> <i>(ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute), 113</i>
<i>iso_msg_termination</i> <i>(ics.structures.secu_settings.secu_settings</i> <i>attribute), 147</i>	<i>iso_msg_termination_2</i> <i>(ics.structures.s_fire3_settings.s_fire3_settings</i> <i>attribute), 120</i>
<i>iso_msg_termination</i> <i>(ics.structures.sievb_settings.sievb_settings</i> <i>attribute), 151</i>	<i>iso_msg_termination_2</i> <i>(ics.structures.s_fire_settings.s_fire_settings</i> <i>attribute), 123</i>
<i>iso_msg_termination</i> <i>(ics.structures.srad_epsilon_settings.srad_epsilon_settings</i> <i>attribute), 157</i>	<i>iso_msg_termination_2</i> <i>(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> <i>attribute), 125</i>
<i>iso_msg_termination</i> <i>(ics.structures.srad_jupiter_settings.srad_jupiter_settings</i> <i>attribute), 168</i>	<i>iso_msg_termination_2</i> <i>(ics.structures.s_pendant_settings.s_pendant_settings</i> <i>attribute), 131</i>
<i>iso_msg_termination</i> <i>(ics.structures.srad_pluto_settings.srad_pluto_settings</i> <i>attribute), 171</i>	<i>iso_msg_termination_2</i> <i>(ics.structures.secu_settings.secu_settings</i> <i>attribute), 148</i>
<i>iso_msg_termination</i> <i>(ics.structures.svcan4_ind_settings.svcan4_ind_settings</i> <i>attribute), 183</i>	<i>iso_msg_termination_2</i> <i>(ics.structures.sievb_settings.sievb_settings</i> <i>attribute), 151</i>
<i>iso_msg_termination</i> <i>(ics.structures.svcanrf_settings.svcanrf_settings</i> <i>attribute), 185</i>	<i>iso_msg_termination_2</i> <i>(ics.structures.sobd2_pro_settings.sobd2_pro_settings</i> <i>attribute), 154</i>
<i>iso_msg_termination_1</i> <i>(ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute), 113</i>	<i>iso_msg_termination_2</i> <i>(ics.structures.svcanrf_settings.svcanrf_settings</i> <i>attribute), 186</i>
<i>iso_msg_termination_1</i> <i>(ics.structures.s_fire3_settings.s_fire3_settings</i> <i>attribute), 120</i>	<i>iso_msg_termination_3</i> <i>(ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute), 113</i>
<i>iso_msg_termination_1</i> <i>(ics.structures.sobd2_lc_settings.sobd2_lc_settings</i> <i>attribute), 153</i>	<i>iso_msg_termination_3</i> <i>(ics.structures.s_fire3_settings.s_fire3_settings</i> <i>attribute), 120</i>
<i>iso_msg_termination_1</i> <i>(ics.structures.sobd2_pro_settings.sobd2_pro_settings</i> <i>attribute), 154</i>	<i>iso_msg_termination_3</i> <i>(ics.structures.s_fire_settings.s_fire_settings</i> <i>attribute), 123</i>
<i>iso_msg_termination_1</i> <i>(ics.structures.srad_galaxy_settings.srad_galaxy_settings</i> <i>attribute), 160</i>	<i>iso_msg_termination_3</i> <i>(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> <i>attribute), 125</i>
<i>iso_msg_termination_1</i> <i>(ics.structures.srad_gigalog_settings.srad_gigalog_settings</i> <i>attribute), 163</i>	<i>iso_msg_termination_4</i> <i>(ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute), 113</i>
<i>iso_msg_termination_1</i>	<i>iso_msg_termination_4</i>

<code>(ics.structures.s_fire3_settings.s_fire3_settings</code>	<code>iso_parity_1 (ics.structures.srada2_b_settings.srada2_b_settings</code>
<code>attribute), 120</code>	<code>attribute), 174</code>
<code>iso_msg_termination_4</code>	<code>iso_parity_1 (ics.structures.svcan4_settings.svcan4_settings</code>
<code>(ics.structures.s_fire_settings.s_fire_settings</code>	<code>attribute), 184</code>
<code>attribute), 123</code>	<code>iso_parity_2 (ics.structures.s_cyan_settings.s_cyan_settings</code>
<code>iso_msg_termination_4</code>	<code>attribute), 113</code>
<code>(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</code>	<code>iso_parity_2 (ics.structures.s_fire3_settings.s_fire3_settings</code>
<code>attribute), 125</code>	<code>attribute), 120</code>
<code>iso_msg_termination_5</code>	<code>iso_parity_2 (ics.structures.s_fire_settings.s_fire_settings</code>
<code>(ics.structures.s_fire3_settings.s_fire3_settings</code>	<code>attribute), 123</code>
<code>attribute), 120</code>	<code>iso_parity_2 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</code>
<code>iso_msg_termination_6</code>	<code>attribute), 125</code>
<code>(ics.structures.s_fire3_settings.s_fire3_settings</code>	<code>iso_parity_2 (ics.structures.s_pendant_settings.s_pendant_settings</code>
<code>attribute), 120</code>	<code>attribute), 131</code>
<code>iso_parity (ics.structures.s_ether_badge_settings.s_ether_badge_settings</code>	<code>iso_parity (ics.structures.secu_settings.secu_settings</code>
<code>attribute), 116</code>	<code>attribute), 148</code>
<code>iso_parity (ics.structures.s_fire_settings.s_fire_settings</code>	<code>iso_parity_2 (ics.structures.sievb_settings.sievb_settings</code>
<code>attribute), 123</code>	<code>attribute), 151</code>
<code>iso_parity (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</code>	<code>iso_parity_2 (ics.structures.sobd2_pro_settings.sobd2_pro_settings</code>
<code>attribute), 125</code>	<code>attribute), 154</code>
<code>iso_parity (ics.structures.s_neo_ecul2_settings.s_neo_ecul2_settings</code>	<code>iso_parity_2 (ics.structures.svcanrf_settings.svcanrf_settings</code>
<code>attribute), 129</code>	<code>attribute), 186</code>
<code>iso_parity (ics.structures.s_pendant_settings.s_pendant_settings</code>	<code>iso_parity_3 (ics.structures.s_cyan_settings.s_cyan_settings</code>
<code>attribute), 131</code>	<code>attribute), 113</code>
<code>iso_parity (ics.structures.secu_settings.secu_settings</code>	<code>iso_parity_3 (ics.structures.s_fire3_settings.s_fire3_settings</code>
<code>attribute), 148</code>	<code>attribute), 120</code>
<code>iso_parity (ics.structures.sievb_settings.sievb_settings</code>	<code>iso_parity_3 (ics.structures.s_fire_settings.s_fire_settings</code>
<code>attribute), 151</code>	<code>attribute), 123</code>
<code>iso_parity (ics.structures.srad_epsilon_settings.srad_epsilon_settings</code>	<code>iso_parity_3 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</code>
<code>attribute), 157</code>	<code>attribute), 125</code>
<code>iso_parity (ics.structures.srad_jupiter_settings.srad_jupiter_settings</code>	<code>iso_parity_4 (ics.structures.s_cyan_settings.s_cyan_settings</code>
<code>attribute), 168</code>	<code>attribute), 113</code>
<code>iso_parity (ics.structures.srad_pluto_settings.srad_pluto_settings</code>	<code>iso_parity_4 (ics.structures.s_fire3_settings.s_fire3_settings</code>
<code>attribute), 171</code>	<code>attribute), 120</code>
<code>iso_parity (ics.structures.svcan4_ind_settings.svcan4_ind_settings</code>	<code>iso_parity_4 (ics.structures.s_fire_settings.s_fire_settings</code>
<code>attribute), 183</code>	<code>attribute), 123</code>
<code>iso_parity (ics.structures.svcanrf_settings.svcanrf_settings</code>	<code>iso_parity_4 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</code>
<code>attribute), 186</code>	<code>attribute), 125</code>
<code>iso_parity_1 (ics.structures.s_cyan_settings.s_cyan_settings</code>	<code>iso_parity_5 (ics.structures.s_fire3_settings.s_fire3_settings</code>
<code>attribute), 113</code>	<code>attribute), 120</code>
<code>iso_parity_1 (ics.structures.s_fire3_settings.s_fire3_settings</code>	<code>iso_parity_6 (ics.structures.s_fire3_settings.s_fire3_settings</code>
<code>attribute), 120</code>	<code>attribute), 120</code>
<code>iso_parity_1 (ics.structures.sobd2_lc_settings.sobd2_lc_settings</code>	<code>iso_tester_pullup_enable</code>
<code>attribute), 153</code>	<code>(ics.structures.s_ether_badge_settings.s_ether_badge_settings</code>
<code>iso_parity_1 (ics.structures.sobd2_pro_settings.sobd2_pro_settings</code>	<code>attribute), 116</code>
<code>attribute), 154</code>	<code>iso_tester_pullup_enable</code>
<code>iso_parity_1 (ics.structures.srad_galaxy_settings.srad_galaxy_settings</code>	<code>iso_tester_pullup_enable</code>
<code>attribute), 160</code>	<code>(ics.structures.s_fire_settings.s_fire_settings</code>
<code>iso_parity_1 (ics.structures.srad_gigalog_settings.srad_gigalog_settings</code>	<code>attribute), 123</code>
<code>attribute), 163</code>	<code>iso_tester_pullup_enable</code>
<code>iso_parity_1 (ics.structures.srad_gigastar_settings.srad_gigastar_settings</code>	<code>(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</code>
<code>attribute), 165</code>	<code>attribute), 125</code>
<code>iso_parity_1 (ics.structures.srad_star2_settings.srad_star2_settings</code>	<code>iso_tester_pullup_enable</code>
<code>attribute), 172</code>	<code>(ics.structures.sievb_settings.sievb_settings</code>
	<code>attribute), 151</code>

iso_tester_pullup_enable (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 141

iso_tester_pullup_enable (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 168

iso_tester_pullup_enable (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 171

iso_tester_pullup_enable (ics.structures.svcanrf_settings.svcanrf_settings attribute), 186

IsOpen (ics.ics.NeoDevice attribute), 18

iType (ics.structures.st_api_firmware_info.st_api_firmware_info attribute), 177

J

j1708_settings (class in ics.structures.j1708_settings), 108

J1708_SETTINGS_SIZE (in module ics.ics), 194

jitter (ics.structures.s_pluto_vl_policing_entry.s.s_pluto_vl_policing_entry attribute), 142

jupiter (ics.structures.global_settings.global_settings attribute), 97

JUPITER_PTP_ROLE_DISABLED (in module ics.ics), 194

JUPITER_PTP_ROLE_MASTER (in module ics.ics), 194

JUPITER_PTP_ROLE_SLAVE (in module ics.ics), 194

jupiter_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 177

jupiterStatus (ics.structures.ics_device_status.ics_device_status attribute), 99

l2_policing (ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute), 141

learnedEntry (ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry attribute), 138

startTime (ics.structures.start_dhcp_server_command.start_dhcp_server_command attribute), 181

led_mode (ics.structures.ethernet_settings.ethernet_settings attribute), 93

legacy (ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings attribute), 158

len (ics.structures.global_settings.global_settings attribute), 97

len (ics.structures.s_extended_data_flash_header.s_extended_data_flash_header attribute), 117

len (ics.structures.uart_port_data.uart_port_data attribute), 188

len (ics.structures.uart_port_port_bytes.uart_port_port_bytes attribute), 189

length (ics.structures.generic_api_data.generic_api_data attribute), 95

length (ics.structures.s_ext_sub_cmd_hdr.s_ext_sub_cmd_hdr attribute), 117

lin1 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 113

lin1 (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 116

lin1 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 120

lin1 (ics.structures.s_fire_settings.s_fire_settings attribute), 123

lin1 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 126

lin1 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 129

lin1 (ics.structures.s_pendant_settings.s_pendant_settings attribute), 131

k (ics.structures.iso9141_keyword2000_init_step.iso9141_keyword2000_init_step attribute), 107

L

l (ics.structures.iso9141_keyword2000_init_step.iso9141_keyword2000_init_step attribute), 107

l2_addressLookupEntries (ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute), 141

l2_addressLookupParams (ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute), 141

l2_ForwardingEntries (ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute), 141

l2_forwardingParams (ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute), 141

lin1 (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 153

lin1 (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 154

lin1 (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 157

lin1 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160

lin1 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 163

lin1 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 165

- lin1 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings* attribute), 168
- lin1 (*ics.structures.srad_pluto_settings.srad_pluto_settings* attribute), 171
- lin1 (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 172
- lin1 (*ics.structures.srada2_b_settings.srada2_b_settings* attribute), 175
- lin1 (*ics.structures.svcan4_ind_settings.svcan4_ind_settings* attribute), 183
- lin1 (*ics.structures.svcan4_settings.svcan4_settings* attribute), 184
- lin1 (*ics.structures.svcanrf_settings.svcanrf_settings* attribute), 186
- lin2 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 113
- lin2 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 120
- lin2 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 123
- lin2 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 126
- lin2 (*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 131
- lin2 (*ics.structures.s_red_settings.s_red_settings* attribute), 143
- lin2 (*ics.structures.secu_settings.secu_settings* attribute), 148
- lin2 (*ics.structures.sievb_settings.sievb_settings* attribute), 151
- lin2 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 154
- lin2 (*ics.structures.svcanrf_settings.svcanrf_settings* attribute), 186
- lin3 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 113
- lin3 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 120
- lin3 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 123
- lin3 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 126
- lin4 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 113
- lin4 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 120
- lin4 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 123
- lin4 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 126
- lin5 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 113
- lin5 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 120
- lin5 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 126
- lin6 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 113
- lin6 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 120
- lin7 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 120
- lin8 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 120
- lin_settings (class in *ics.structures.lin_settings*), 108
- LIN_SETTINGS_SIZE (in module *ics.ics*), 194
- link_delay_ns (*ics.structures.gptp_status.gptp_status* attribute), 99
- link_spd (*ics.structures.op_eth_settings.op_eth_settings* attribute), 109
- link_speed (*ics.structures.ethernet10_g_settings.ethernet10_g_settings* attribute), 93
- link_speed (*ics.structures.ethernet_settings.ethernet_settings* attribute), 93
- link_speed (*ics.structures.ethernet_settings2.ethernet_settings2* attribute), 94
- link_status (*ics.structures.gptp_status.gptp_status* attribute), 99
- linkFullDuplex (*ics.structures.ethernet_network_status_t.ethernet_network_status_t* attribute), 93
- linkMode (*ics.structures.ethernet_network_status_t.ethernet_network_status_t* attribute), 93
- linkMode0 (*ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_converter_settings* attribute), 110
- linkModel1 (*ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_converter_settings* attribute), 110
- linkSpeed (*ics.structures.ethernet_network_status_t.ethernet_network_status_t* attribute), 93
- linkStatus (*ics.structures.ethernet_network_status_t.ethernet_network_status_t* attribute), 93
- LINUX_BOOT_ALLOWED (in module *ics.ics*), 194
- LINUX_CONFIG_PORT_ETH_01 (in module *ics.ics*), 194
- LINUX_CONFIG_PORT_ETH_02 (in module *ics.ics*), 194
- LINUX_CONFIG_PORT_NONE (in module *ics.ics*), 194
- LISTEN_ALL (in module *ics.ics*), 194
- LISTEN_ONLY (in module *ics.ics*), 194
- listentmout (*ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params* attribute), 134
- load_default_settings () (in module *ics.ics*), 52
- loadDefaultSettings () (in module *ics.ics*), 24
- logAnnounceInterval (*ics.structures.s_pluto_ptp_params.s_pluto_ptp_params* attribute), 140
- logAnnounceInterval (*ics.structures.srad_gptp_settings.srad_gptp_settings* attribute), 140

attribute), 167
 logger (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 109
 attribute), 160
 logger (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 137
 attribute), 163
 logger (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 137
 attribute), 165
 logger (ics.structures.srada2_b_settings.srada2_b_settings attribute), 137
 attribute), 175
 logger_settings (class in attribute), 137
 ics.structures.logger_settings), 108
 LOGGER_SETTINGS_SIZE (in module ics.ics), 194
 logPDelayReqInterval
 (ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params_ics.structures.op_eth_settings.op_eth_settings
 attribute), 140
 logPDelayReqInterval
 (ics.structures.srad_gptp_settings.srad_gptp_settings_s attribute), 138
 attribute), 167
 logSyncInterval (ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params attribute), 140
 attribute), 140
 logSyncInterval (ics.structures.srad_gptp_settings.srad_gptp_settings_ics.structures.w_bms_manager_reset.w_bms_manager_
 attribute), 167
 attribute), 190
 LOOPBACK (in module ics.ics), 194
 lsftcan (ics.structures.s_fire_settings.s_fire_settings attribute), 123
 lsftcan (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 188
 attribute), 126
 lsftcan (ics.structures.s_pendant_settings.s_pendant_settings attribute), 188
 attribute), 131
 lsftcan (ics.structures.secu_settings.secu_settings attribute), 148
 lsftcan1 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 113
 lsftcan1 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 120
 lsftcan1 (ics.structures.s_neo_ecul2_settings.s_neo_ecul2_settings attribute), 129
 attribute), 129
 lsftcan1 (ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute), 145
 attribute), 145
 lsftcan2 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 113
 attribute), 113
 lsftcan2 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 121
 attribute), 121
 lsftcan2 (ics.structures.s_neo_ecul2_settings.s_neo_ecul2_settings attribute), 129
 attribute), 129
 lsftcan2 (ics.structures.s_pendant_settings.s_pendant_settings attribute), 131
 attribute), 131
 lsftcan2 (ics.structures.secu_settings.secu_settings attribute), 148
 attribute), 148
 mac_addr1 (ics.structures.op_eth_settings.op_eth_settings attribute), 109
 mac_addr2 (ics.structures.op_eth_settings.op_eth_settings
 attribute), 109
 mac_flt0 (ics.structures.s_pluto_general_params.s.s_pluto_general_params
 attribute), 137
 mac_flt1 (ics.structures.s_pluto_general_params.s.s_pluto_general_params
 attribute), 137
 mac_fltres0 (ics.structures.s_pluto_general_params.s.s_pluto_general_params
 attribute), 137
 mac_fltres1 (ics.structures.s_pluto_general_params.s.s_pluto_general_params
 attribute), 137
 mac_spoofing_en (ics.structures.op_eth_settings.op_eth_settings
 attribute), 109
 mac_spoofing_isDstOrSrc
 (ics.structures.op_eth_settings.op_eth_settings
 attribute), 109
 macaddr (ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry
 attribute), 138
 macConfig (ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings
 attribute), 141
 MAIN_VNET (in module ics.ics), 194
 managerIndex (ics.structures.w_bms_manager_reset.w_bms_manager_reset
 attribute), 190
 MasterEnable (ics.structures.timesync_icshardware_settings.timesync_icshardware_settings
 attribute), 188
 MasterNetwork (ics.structures.timesync_icshardware_settings.timesync_icshardware_settings
 attribute), 188
 MasterResistor (ics.structures.lin_settings.lin_settings
 attribute), 108
 max_dynp (ics.structures.s_pluto_l2_forwarding_params.s.s_pluto_l2_forwarding_params
 attribute), 139
 MAX_NUMBYTES_PHYSETTINGS (in module ics.ics),
 194
 MAX_PHY_REG_PKT_ENTRIES (in module ics.ics),
 194
 MAX_PHY_SETTINGS_STRUCT (in module ics.ics),
 194
 MAX_REPORTED_VERSIONS (in module ics.ics), 194
 MAX_VL_FORWARDING_ENTRIES (in module ics.ics),
 194
 MAX_VL_POLICING_ENTRIES (in module ics.ics),
 194
 max_age (ics.structures.s_pluto_l2_address_lookup_params.s.s_pluto_l2_address_lookup_params
 attribute), 138
 max_age (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config_s
 attribute), 140
 MaxAllowedClients (ics.ics.NeoDevice attribute),
 18
 maxintegcy (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params
 attribute), 134
 maxlen (ics.structures.s_pluto_l2_policing.s.s_pluto_l2_policing_s
 attribute), 139
 maxlen (ics.structures.s_pluto_vl_policing_entry.s.s_pluto_vl_policing_entry
 attribute), 139

M

attribute), 142
 maxtranspclock (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params_s
 attribute), 134
 MessagePieceID (ics.ics.SpyMessage attribute), 18
 MessagePieceID (ics.ics.SpyMessageJ1850 attribute), 19
 MessagePieceID (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray
 attribute), 101
 MessagePieceID (ics.structures.ics_spy_message_long.ics_spy_message_long
 attribute), 103
 MessagePieceID (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
 attribute), 105
 mirr_port (ics.structures.s_pluto_general_params.s_pluto_general_params_s
 attribute), 137
 mirr_ptacu (ics.structures.s_pluto_general_params.s_pluto_general_params_s
 attribute), 137
 misc_io_analog_enable (ics.structures.s_cyan_settings.s_cyan_settings
 attribute), 113
 misc_io_analog_enable (ics.structures.s_ether_badge_settings.s_ether_badge_settings
 attribute), 116
 misc_io_analog_enable (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 121
 misc_io_analog_enable (ics.structures.s_fire_settings.s_fire_settings
 attribute), 123
 misc_io_analog_enable (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
 attribute), 126
 misc_io_analog_enable (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
 attribute), 129
 misc_io_analog_enable (ics.structures.s_pendant_settings.s_pendant_settings
 attribute), 131
 misc_io_analog_enable (ics.structures.secu_settings.secu_settings
 attribute), 148
 misc_io_analog_enable (ics.structures.sievb_settings.sievb_settings
 attribute), 151
 misc_io_analog_enable (ics.structures.sobd2_pro_settings.sobd2_pro_settings
 attribute), 154
 misc_io_analog_enable (ics.structures.sobd2_sim_settings.sobd2_sim_settings
 attribute), 155
 misc_io_analog_enable (ics.structures.srad_epsilon_settings.srad_epsilon_settings
 attribute), 157
 misc_io_analog_enable (ics.structures.srad_galaxy_settings.srad_galaxy_settings
 attribute), 160
 misc_io_analog_enable (ics.structures.srad_jupiter_settings.srad_jupiter_settings
 attribute), 168
 misc_io_analog_enable (ics.structures.srad_pluto_settings.srad_pluto_settings
 attribute), 172
 misc_io_analog_enable (ics.structures.srad_star2_settings.srad_star2_settings
 attribute), 172
 misc_io_analog_enable (ics.structures.svcnrf_settings.svcnrf_settings
 attribute), 186
 misc_io_analog_enable_2 (ics.structures.sievb_settings.sievb_settings
 attribute), 151
 misc_io_initial_ddr (ics.structures.s_cyan_settings.s_cyan_settings
 attribute), 113
 misc_io_initial_ddr (ics.structures.s_ether_badge_settings.s_ether_badge_settings
 attribute), 116
 misc_io_initial_ddr (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 121
 misc_io_initial_ddr (ics.structures.s_fire_settings.s_fire_settings
 attribute), 123
 misc_io_initial_ddr (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
 attribute), 126
 misc_io_initial_ddr (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
 attribute), 129
 misc_io_initial_ddr (ics.structures.s_pendant_settings.s_pendant_settings
 attribute), 131
 misc_io_initial_ddr (ics.structures.secu_settings.secu_settings
 attribute), 148
 misc_io_initial_ddr (ics.structures.sievb_settings.sievb_settings
 attribute), 151
 misc_io_initial_ddr (ics.structures.sobd2_sim_settings.sobd2_sim_settings
 attribute), 155
 misc_io_initial_ddr (ics.structures.srad_galaxy_settings.srad_galaxy_settings
 attribute), 160
 misc_io_initial_ddr (ics.structures.srad_star2_settings.srad_star2_settings
 attribute), 172
 misc_io_initial_ddr (ics.structures.svcn3_settings.svcn3_settings
 attribute), 186

attribute), 182	attribute), 121
misc_io_initial_ddr (ics.structures.svcanrf_settings.svcanrf_settings attribute), 186	misc_io_on_report_events (ics.structures.s_fire_settings.s_fire_settings attribute), 123
misc_io_initial_latch (ics.structures.s_cyan_settings.s_cyan_settings attribute), 114	misc_io_on_report_events (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 126
misc_io_initial_latch (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 116	misc_io_on_report_events (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 128
misc_io_initial_latch (ics.structures.s_fire3_settings.s_fire3_settings attribute), 121	misc_io_on_report_events (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 130
misc_io_initial_latch (ics.structures.s_fire_settings.s_fire_settings attribute), 123	misc_io_on_report_events (ics.structures.s_pendant_settings.s_pendant_settings attribute), 131
misc_io_initial_latch (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 126	misc_io_on_report_events (ics.structures.secu_settings.secu_settings attribute), 148
misc_io_initial_latch (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 130	misc_io_on_report_events (ics.structures.sievb_settings.sievb_settings attribute), 151
misc_io_initial_latch (ics.structures.s_pendant_settings.s_pendant_settings attribute), 131	misc_io_on_report_events (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 153
misc_io_initial_latch (ics.structures.secu_settings.secu_settings attribute), 148	misc_io_on_report_events (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 155
misc_io_initial_latch (ics.structures.sievb_settings.sievb_settings attribute), 151	misc_io_on_report_events (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160
misc_io_initial_latch (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 155	misc_io_on_report_events (ics.structures.srad_star2_settings.srad_star2_settings attribute), 172
misc_io_initial_latch (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160	misc_io_on_report_events (ics.structures.svcan3_settings.svcan3_settings attribute), 182
misc_io_initial_latch (ics.structures.srad_star2_settings.srad_star2_settings attribute), 172	misc_io_on_report_events (ics.structures.svcanrf_settings.svcanrf_settings attribute), 186
misc_io_initial_latch (ics.structures.svcan3_settings.svcan3_settings attribute), 182	misc_io_report_period (ics.structures.s_cyan_settings.s_cyan_settings attribute), 114
misc_io_initial_latch (ics.structures.svcanrf_settings.svcanrf_settings attribute), 186	misc_io_report_period (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 116
misc_io_on_report_events (ics.structures.s_cyan_settings.s_cyan_settings attribute), 114	misc_io_report_period (ics.structures.s_fire3_settings.s_fire3_settings attribute), 121
misc_io_on_report_events (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 116	misc_io_report_period (ics.structures.s_fire_settings.s_fire_settings attribute), 123
misc_io_on_report_events (ics.structures.s_fire3_settings.s_fire3_settings attribute), 121	misc_io_report_period (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 126

[attribute\), 126](#)
[misc_io_report_period \(ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute\), 130](#)
[misc_io_report_period \(ics.structures.s_pendant_settings.s_pendant_settings attribute\), 131](#)
[misc_io_report_period \(ics.structures.secu_settings.secu_settings attribute\), 148](#)
[misc_io_report_period \(ics.structures.sievb_settings.sievb_settings attribute\), 151](#)
[misc_io_report_period \(ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute\), 155](#)
[misc_io_report_period \(ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute\), 160](#)
[misc_io_report_period \(ics.structures.srad_star2_settings.srad_star2_settings attribute\), 172](#)
[misc_io_report_period \(ics.structures.svcan3_settings.svcan3_settings attribute\), 182](#)
[misc_io_report_period \(ics.structures.svcanrf_settings.svcanrf_settings attribute\), 186](#)
[MiscData \(ics.ics.SpyMessage attribute\), 18](#)
[MiscData \(ics.ics.SpyMessageJ1850 attribute\), 19](#)
[MiscData \(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute\), 101](#)
[MiscData \(ics.structures.ics_spy_message_long.ics_spy_message_long attribute\), 103](#)
[MiscData \(ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute\), 105](#)
[MiscData \(ics.structures.spy_filter_long.spy_filter_long attribute\), 156](#)
[MiscDataMask \(ics.structures.spy_filter_long.spy_filter_long attribute\), 156](#)
[mod_id \(ics.structures.serdesgen_settings.serdesgen_settings attribute\), 150](#)
[Mode \(ics.structures.can_settings.can_settings attribute\), 88](#)
[Mode \(ics.structures.lin_settings.lin_settings attribute\), 108](#)
[mode \(ics.structures.s_pluto_custom_params_s.s_pluto_custom_params_s attribute\), 136](#)
[mode \(ics.structures.serdescam_settings.serdescam_settings attribute\), 149](#)
[mode \(ics.structures.serdespoc_settings.serdespoc_settings attribute\), 150](#)
[Mode \(ics.structures.swcan_settings.swcan_settings attribute\), 187](#)
[ms_offset_ns \(ics.structures.gptp_status.gptp_status attribute\), 99](#)
N
[Name \(ics.ics.NeoDevice attribute\), 18](#)
[Nameless11656 \(ics.structures.s_pluto_vl_lookup_entry.s.s_pluto_vl_lookup_entry attribute\), 142](#)
[Nameless14996 \(ics.structures.op_eth_settings.op_eth_settings attribute\), 109](#)
[Nameless18511 \(ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute\), 132](#)
[Nameless19471 \(ics.structures.op_eth_general_settings.op_eth_general_settings attribute\), 109](#)
[Nameless21903 \(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute\), 101](#)
[Nameless2284 \(ics.structures.uart_settings.uart_settings attribute\), 189](#)
[Nameless32656 \(ics.structures.global_settings.global_settings attribute\), 96](#)
[Nameless40028 \(ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute\), 132](#)
[Nameless43713 \(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute\), 179](#)
[Nameless45381 \(ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute\), 105](#)
[Nameless59426 \(ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute\), 180](#)
[Nameless65087 \(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute\), 101](#)
[Nameless9252 \(ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute\), 106](#)
[Nameless9872 \(ics.structures.ics_spy_message_long.ics_spy_message_long attribute\), 104](#)
[nanoseconds \(ics.structures.timestamp.timestamp attribute\), 188](#)
[neighborPropDelay \(ics.structures.s_jupiter_ptp_params_s.s_jupiter_ptp_params_s attribute\), 128](#)
[neighborPropDelayThresh \(ics.structures.s_pluto_ptp_params_s.s_pluto_ptp_params_s attribute\), 140](#)
[neighborPropDelayThresh \(ics.structures.srad_gptp_settings.srad_gptp_settings attribute\), 167](#)
[NEO_CFG_MPIC_HS_CAN_CNF1 \(in module ics.ics\), 197](#)
[NEO_CFG_MPIC_HS_CAN_CNF2 \(in module ics.ics\), 197](#)
[NEO_CFG_MPIC_HS_CAN_CNF3 \(in module ics.ics\), 197](#)
[NEO_CFG_MPIC_HS_CAN_MODE \(in module ics.ics\), 197](#)
[NEO_CFG_MPIC_LSFT_CAN_CNF1 \(in module ics.ics\), 197](#)

- NEO_CFG_MPIC_LSFT_CAN_CNF2 (in module *ics.ics*), 197
- NEO_CFG_MPIC_LSFT_CAN_CNF3 (in module *ics.ics*), 197
- NEO_CFG_MPIC_MS_CAN_CNF1 (in module *ics.ics*), 197
- NEO_CFG_MPIC_MS_CAN_CNF2 (in module *ics.ics*), 197
- NEO_CFG_MPIC_MS_CAN_CNF3 (in module *ics.ics*), 197
- NEO_CFG_MPIC_SW_CAN_CNF1 (in module *ics.ics*), 197
- NEO_CFG_MPIC_SW_CAN_CNF2 (in module *ics.ics*), 197
- NEO_CFG_MPIC_SW_CAN_CNF3 (in module *ics.ics*), 197
- NeoDevice (class in *ics.ics*), 18
- NEODEVICE_ANY_ION (in module *ics.ics*), 194
- NEODEVICE_ANY_PLASMA (in module *ics.ics*), 194
- NEODEVICE_BLUE (in module *ics.ics*), 194
- NEODEVICE_CMPROBE (in module *ics.ics*), 194
- NEODEVICE_CT_OBD (in module *ics.ics*), 194
- NEODEVICE_DONT_REUSE0 (in module *ics.ics*), 194
- NEODEVICE_DONT_REUSE1 (in module *ics.ics*), 194
- NEODEVICE_DONT_REUSE2 (in module *ics.ics*), 195
- NEODEVICE_DONT_REUSE3 (in module *ics.ics*), 195
- NEODEVICE_DW_VCAN (in module *ics.ics*), 195
- NEODEVICE_ECU (in module *ics.ics*), 195
- NEODEVICE_ECU22 (in module *ics.ics*), 195
- NEODEVICE_ECU_AVB (in module *ics.ics*), 195
- NEODEVICE_ECUCHIP_UART (in module *ics.ics*), 195
- NEODEVICE_EEVB (in module *ics.ics*), 195
- NEODEVICE_ETHER_BADGE (in module *ics.ics*), 195
- NEODEVICE_FIRE (in module *ics.ics*), 195
- NEODEVICE_FIRE2 (in module *ics.ics*), 195
- NEODEVICE_FIRE2_REDLINE (in module *ics.ics*), 195
- NEODEVICE_FIRE3 (in module *ics.ics*), 195
- NEODEVICE_FLEX (in module *ics.ics*), 195
- NEODEVICE_GIGASTAR (in module *ics.ics*), 195
- NEODEVICE_IEVB (in module *ics.ics*), 195
- NEODEVICE_ION (in module *ics.ics*), 195
- NEODEVICE_NEOANALOG (in module *ics.ics*), 195
- NEODEVICE_NEOECU12 (in module *ics.ics*), 195
- NEODEVICE_NEOECUCHIP (in module *ics.ics*), 195
- NEODEVICE_NEW_DEVICE_58 (in module *ics.ics*), 195
- NEODEVICE_NEW_DEVICE_59 (in module *ics.ics*), 195
- NEODEVICE_NEW_DEVICE_FF (in module *ics.ics*), 195
- NEODEVICE_OBD2_DEV (in module *ics.ics*), 195
- NEODEVICE_OBD2_LC (in module *ics.ics*), 195
- NEODEVICE_OBD2_PRO (in module *ics.ics*), 195
- NEODEVICE_OBD2_SIM (in module *ics.ics*), 195
- NEODEVICE_OBD2_SIM_DOIP (in module *ics.ics*), 195
- NEODEVICE_PENDANT (in module *ics.ics*), 195
- NEODEVICE_PLASMA (in module *ics.ics*), 195
- NEODEVICE_RAD_A2B (in module *ics.ics*), 196
- NEODEVICE_RAD_BMS (in module *ics.ics*), 196
- NEODEVICE_RAD_MOON_DUO (in module *ics.ics*), 196
- NEODEVICE_RADCOMET (in module *ics.ics*), 195
- NEODEVICE_RADEPSILON (in module *ics.ics*), 195
- NEODEVICE_RADEPSILON_EXPRESS (in module *ics.ics*), 195
- NEODEVICE_RADEPSILON_T (in module *ics.ics*), 195
- NEODEVICE_RADGALAXY (in module *ics.ics*), 195
- NEODEVICE_RADGIGALOG (in module *ics.ics*), 195
- NEODEVICE_RADIO_CANHUB (in module *ics.ics*), 196
- NEODEVICE_RADJUPITER (in module *ics.ics*), 196
- NEODEVICE_RADMOON2 (in module *ics.ics*), 196
- NEODEVICE_RADMOON3 (in module *ics.ics*), 196
- NEODEVICE_RADPLUTO (in module *ics.ics*), 196
- NEODEVICE_RADPROXIMA (in module *ics.ics*), 196
- NEODEVICE_RADSTAR (in module *ics.ics*), 196
- NEODEVICE_RADSTAR2 (in module *ics.ics*), 196
- NEODEVICE_RADSUPERMOON (in module *ics.ics*), 196
- NEODEVICE_RED (in module *ics.ics*), 196
- NEODEVICE_RED2 (in module *ics.ics*), 196
- NEODEVICE_UNKNOWN (in module *ics.ics*), 196
- NEODEVICE_VCAN3 (in module *ics.ics*), 196
- NEODEVICE_VCAN41 (in module *ics.ics*), 196
- NEODEVICE_VCAN42 (in module *ics.ics*), 196
- NEODEVICE_VCAN42_EL (in module *ics.ics*), 196
- NEODEVICE_VCAN44 (in module *ics.ics*), 196
- NEODEVICE_VCAN4_IND (in module *ics.ics*), 196
- NEODEVICE_VCANRF (in module *ics.ics*), 196
- NEODEVICE_VIVIDCAN (in module *ics.ics*), 196
- neoecu12 (*ics.structures.global_settings.global_settings* attribute), 97
- neoecu_avb (*ics.structures.global_settings.global_settings* attribute), 97
- neoecu_avb_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 178
- neoMostGateway (*ics.structures.s_fire_settings.s_fire_settings* attribute), 123
- neoMostGateway (*ics.structures.s_fire_vnet_settings.s_fire_vnet_setting* attribute), 126
- neoobd2_sim (*ics.structures.global_settings.global_settings* attribute), 97
- NEOVI6_VCAN_TIMESTAMP_1 (in module *ics.ics*), 196
- NEOVI6_VCAN_TIMESTAMP_2 (in module *ics.ics*), 196
- NEOVI_3G_MAX_SETTINGS_SIZE (in module *ics.ics*), 196

- NEOVI_COMMTYPE_FIRE_USB (in module *ics.ics*), 196
- NEOVI_COMMTYPE_RS232 (in module *ics.ics*), 196
- NEOVI_COMMTYPE_TCPIP (in module *ics.ics*), 196
- NEOVI_COMMTYPE_USB_BULK (in module *ics.ics*), 196
- NEOVI_RED_TIMESTAMP_1_10NS (in module *ics.ics*), 196
- NEOVI_RED_TIMESTAMP_1_25NS (in module *ics.ics*), 196
- NEOVI_RED_TIMESTAMP_2_10NS (in module *ics.ics*), 196
- NEOVI_RED_TIMESTAMP_2_25NS (in module *ics.ics*), 196
- NEOVI_TIMESTAMP_1 (in module *ics.ics*), 197
- NEOVI_TIMESTAMP_2 (in module *ics.ics*), 197
- NEOVIPRO_VCAN_TIMESTAMP_1 (in module *ics.ics*), 196
- NEOVIPRO_VCAN_TIMESTAMP_2 (in module *ics.ics*), 196
- netId (*ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway_settings* attribute), 130
- NETID_3G_APP_SIGNAL_STATUS (in module *ics.ics*), 197
- NETID_3G_FB_STATUS (in module *ics.ics*), 197
- NETID_3G_LOGGING_OVERFLOW (in module *ics.ics*), 197
- NETID_3G_READ_DATA LINK_CM_RX_MSG (in module *ics.ics*), 197
- NETID_3G_READ_DATA LINK_CM_TX_MSG (in module *ics.ics*), 197
- NETID_3G_READ_SETTINGS_EX (in module *ics.ics*), 197
- NETID_3G_RESET_STATUS (in module *ics.ics*), 197
- NETID_A2B_01 (in module *ics.ics*), 197
- NETID_A2B_02 (in module *ics.ics*), 197
- NETID_AUTOSAR (in module *ics.ics*), 197
- NETID_AUX (in module *ics.ics*), 197
- NETID_CAN_SWITCH (in module *ics.ics*), 197
- NETID_CGI (in module *ics.ics*), 197
- NETID_DATA_TO_HOST (in module *ics.ics*), 197
- NETID_DEVICE (in module *ics.ics*), 197
- NETID_DEVICE_STATUS (in module *ics.ics*), 197
- NETID_ETHERNET (in module *ics.ics*), 197
- NETID_ETHERNET2 (in module *ics.ics*), 197
- NETID_ETHERNET3 (in module *ics.ics*), 197
- NETID_ETHERNET_DAQ (in module *ics.ics*), 197
- NETID_ETHERNET_TX_WRAP (in module *ics.ics*), 197
- NETID_FLEXRAY (in module *ics.ics*), 198
- NETID_FLEXRAY1A (in module *ics.ics*), 198
- NETID_FLEXRAY1B (in module *ics.ics*), 198
- NETID_FLEXRAY2 (in module *ics.ics*), 198
- NETID_FLEXRAY2A (in module *ics.ics*), 198
- NETID_FLEXRAY2B (in module *ics.ics*), 198
- NETID_FORDSCP (in module *ics.ics*), 198
- NETID_FORWARDED_MESSAGE (in module *ics.ics*), 198
- NETID_GMFSA (in module *ics.ics*), 198
- NETID_HSCAN (in module *ics.ics*), 198
- NETID_HSCAN2 (in module *ics.ics*), 198
- NETID_HSCAN3 (in module *ics.ics*), 198
- NETID_HSCAN4 (in module *ics.ics*), 198
- NETID_HSCAN5 (in module *ics.ics*), 198
- NETID_HSCAN6 (in module *ics.ics*), 198
- NETID_HSCAN7 (in module *ics.ics*), 198
- NETID_HW_COM_LATENCY_TEST (in module *ics.ics*), 198
- NETID_I2C1 (in module *ics.ics*), 198
- NETID_I2C2 (in module *ics.ics*), 198
- NETID_I2C3 (in module *ics.ics*), 198
- NETID_I2C4 (in module *ics.ics*), 198
- NETID_INVALID (in module *ics.ics*), 198
- NETID_ISM_LOGGER (in module *ics.ics*), 198
- NETID_ISO (in module *ics.ics*), 198
- NETID_ISO1 (in module *ics.ics*), 198
- NETID_ISO2 (in module *ics.ics*), 198
- NETID_ISO3 (in module *ics.ics*), 198
- NETID_ISO4 (in module *ics.ics*), 198
- NETID_ISOPIC (in module *ics.ics*), 198
- NETID_J1708 (in module *ics.ics*), 198
- NETID_JVPW (in module *ics.ics*), 198
- NETID_LIN (in module *ics.ics*), 198
- NETID_LIN2 (in module *ics.ics*), 198
- NETID_LIN3 (in module *ics.ics*), 198
- NETID_LIN4 (in module *ics.ics*), 198
- NETID_LIN5 (in module *ics.ics*), 198
- NETID_LIN6 (in module *ics.ics*), 199
- NETID_LSFTCAN (in module *ics.ics*), 199
- NETID_LSFTCAN2 (in module *ics.ics*), 199
- NETID_MAIN51 (in module *ics.ics*), 199
- NETID_MAX (in module *ics.ics*), 199
- NETID_MOST (in module *ics.ics*), 199
- NETID_MOST150 (in module *ics.ics*), 199
- NETID_MOST25 (in module *ics.ics*), 199
- NETID_MOST50 (in module *ics.ics*), 199
- NETID_MSCAN (in module *ics.ics*), 199
- NETID_OP_ETHERNET1 (in module *ics.ics*), 199
- NETID_OP_ETHERNET10 (in module *ics.ics*), 199
- NETID_OP_ETHERNET11 (in module *ics.ics*), 199
- NETID_OP_ETHERNET12 (in module *ics.ics*), 199
- NETID_OP_ETHERNET2 (in module *ics.ics*), 199
- NETID_OP_ETHERNET3 (in module *ics.ics*), 199
- NETID_OP_ETHERNET4 (in module *ics.ics*), 199
- NETID_OP_ETHERNET5 (in module *ics.ics*), 199
- NETID_OP_ETHERNET6 (in module *ics.ics*), 199
- NETID_OP_ETHERNET7 (in module *ics.ics*), 199
- NETID_OP_ETHERNET8 (in module *ics.ics*), 199
- NETID_OP_ETHERNET9 (in module *ics.ics*), 199

NETID_RED (in module ics.ics), 199
 NETID_RED_APP_ERROR (in module ics.ics), 199
 NETID_RED_VBAT (in module ics.ics), 199
 NETID_RS232 (in module ics.ics), 199
 NETID_SCI (in module ics.ics), 199
 NETID_SPI1 (in module ics.ics), 199
 NETID_SWCAN (in module ics.ics), 199
 NETID_SWCAN2 (in module ics.ics), 199
 NETID_TCP (in module ics.ics), 199
 NETID_TEXTAPI_TO_HOST (in module ics.ics), 199
 NETID_UART (in module ics.ics), 199
 NETID_UART2 (in module ics.ics), 199
 NETID_UART3 (in module ics.ics), 199
 NETID_UART4 (in module ics.ics), 199
 NETID_UDP (in module ics.ics), 200
 NETID_WBMS (in module ics.ics), 200
 netmask (ics.structures.ethernet10_g_settings.ethernet10_g_settings attribute), 93
 netmask (ics.structures.ethernet_settings2.ethernet_settings2 attribute), 94
 network_data_capture_config (ics.structures.s_wil_connection_settings.s_wil_connection_settings attribute), 145
 network_enabled_on_boot (ics.structures.s_cm_probe_settings.s_cm_probe_settings attribute), 111
 network_enabled_on_boot (ics.structures.s_cyan_settings.s_cyan_settings attribute), 114
 network_enabled_on_boot (ics.structures.s_ether_badge_settings.s_ether_badge_settings attribute), 116
 network_enabled_on_boot (ics.structures.s_fire3_settings.s_fire3_settings attribute), 121
 network_enabled_on_boot (ics.structures.s_fire_settings.s_fire_settings attribute), 124
 network_enabled_on_boot (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 126
 network_enabled_on_boot (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 128
 network_enabled_on_boot (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 130
 network_enabled_on_boot (ics.structures.s_pendant_settings.s_pendant_settings attribute), 131
 network_enabled_on_boot (ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings attribute), 143
 network_enabled_on_boot (ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute), 145
 network_enabled_on_boot (ics.structures.scan_hub_settings.scan_hub_settings attribute), 146
 network_enabled_on_boot (ics.structures.secu_avb_settings.secu_avb_settings attribute), 147
 network_enabled_on_boot (ics.structures.secu_settings.secu_settings attribute), 148
 network_enabled_on_boot (ics.structures.seevb_settings.seevb_settings attribute), 149
 network_enabled_on_boot (ics.structures.sievb_settings.sievb_settings attribute), 151
 network_enabled_on_boot (ics.structures.sobd2_lc_settings.sobd2_lc_settings attribute), 153
 network_enabled_on_boot (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 154
 network_enabled_on_boot (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 155
 network_enabled_on_boot (ics.structures.srad_epsilon_settings.srad_epsilon_settings attribute), 157
 network_enabled_on_boot (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160
 network_enabled_on_boot (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 163
 network_enabled_on_boot (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 165
 network_enabled_on_boot (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 168
 network_enabled_on_boot (ics.structures.srad_moon2_settings.srad_moon2_settings attribute), 169
 network_enabled_on_boot (ics.structures.srad_moon3_settings.srad_moon3_settings attribute), 170
 network_enabled_on_boot (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 171
 network_enabled_on_boot (ics.structures.srad_star2_settings.srad_star2_settings attribute), 172
 network_enabled_on_boot (ics.structures.srad_star3_settings.srad_star3_settings attribute), 173

(ics.structures.srad_super_moon_settings.srad_super_moon_settings), 149
 attribute), 173
 network_enabled_on_boot
 (ics.structures.srada2_b_settings.srada2_b_settings), 175
 network_enabled_on_boot
 (ics.structures.sradbms_settings.sradbms_settings), 175
 network_enabled_on_boot
 (ics.structures.svcan3_settings.svcan3_settings), 182
 network_enabled_on_boot
 (ics.structures.svcan412_settings.svcan412_settings), 182
 network_enabled_on_boot
 (ics.structures.svcan4_ind_settings.svcan4_ind_settings), 183
 network_enabled_on_boot
 (ics.structures.svcan4_settings.svcan4_settings), 184
 network_enabled_on_boot
 (ics.structures.svcanrf_settings.svcanrf_settings), 186
 network_enables (ics.structures.s_cm_probe_settings.s_cm_probe_settings), 111
 network_enables (ics.structures.s_cyan_settings.s_cyan_settings), 114
 network_enables (ics.structures.s_ether_badge_settings.s_ether_badge_settings), 116
 network_enables (ics.structures.s_fire3_settings.s_fire3_settings), 121
 network_enables (ics.structures.s_fire_settings.s_fire_settings), 124
 network_enables (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings), 126
 network_enables (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings), 128
 network_enables (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings), 130
 network_enables (ics.structures.s_pendant_settings.s_pendant_settings), 131
 network_enables (ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings), 143
 network_enables (ics.structures.s_text_api_settings.s_text_api_settings), 144
 network_enables (ics.structures.s_vivid_can_settings.s_vivid_can_settings), 145
 network_enables (ics.structures.scan_hub_settings.scan_hub_settings), 146
 network_enables (ics.structures.secu_avb_settings.secu_avb_settings), 147
 network_enables (ics.structures.secu_settings.secu_settings), 148
 network_enables (ics.structures.seevb_settings.seevb_settings), 149
 network_enables (ics.structures.sievb_settings.sievb_settings), 151
 network_enables (ics.structures.sobd2_lc_settings.sobd2_lc_settings), 153
 network_enables (ics.structures.sobd2_pro_settings.sobd2_pro_settings), 154
 network_enables (ics.structures.sobd2_sim_settings.sobd2_sim_settings), 155
 network_enables (ics.structures.srad_epsilon_settings.srad_epsilon_settings), 157
 network_enables (ics.structures.srad_galaxy_settings.srad_galaxy_settings), 160
 network_enables (ics.structures.srad_gigalog_settings.srad_gigalog_settings), 163
 network_enables (ics.structures.srad_gigastar_settings.srad_gigastar_settings), 165
 network_enables (ics.structures.srad_jupiter_settings.srad_jupiter_settings), 168
 network_enables (ics.structures.srad_moon2_settings.srad_moon2_settings), 169
 network_enables (ics.structures.srad_moon3_settings.srad_moon3_settings), 170
 network_enables (ics.structures.srad_pluto_settings.srad_pluto_settings), 171
 network_enables (ics.structures.srad_star2_settings.srad_star2_settings), 173
 network_enables (ics.structures.srad_super_moon_settings.srad_super_moon_settings), 173
 network_enables (ics.structures.srada2_b_settings.srada2_b_settings), 175
 network_enables (ics.structures.sradbms_settings.sradbms_settings), 175
 network_enables (ics.structures.svcan3_settings.svcan3_settings), 182
 network_enables (ics.structures.svcan412_settings.svcan412_settings), 182
 network_enables (ics.structures.svcan4_ind_settings.svcan4_ind_settings), 183
 network_enables (ics.structures.svcan4_settings.svcan4_settings), 185
 network_enables (ics.structures.svcanrf_settings.svcanrf_settings), 186
 network_enables_2
 (ics.structures.s_cyan_settings.s_cyan_settings), 114
 network_enables_2
 (ics.structures.s_ether_badge_settings.s_ether_badge_settings), 116
 network_enables_2
 (ics.structures.s_fire3_settings.s_fire3_settings), 121
 network_enables_2
 (ics.structures.s_fire_settings.s_fire_settings), 124

<i>attribute</i>), 124	<i>attribute</i>), 114
network_enables_2 (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> <i>attribute</i>), 126	network_enables_3 (<i>ics.structures.s_ether_badge_settings.s_ether_badge_settings</i> <i>attribute</i>), 116
network_enables_2 (<i>ics.structures.s_pendant_settings.s_pendant_settings</i> <i>attribute</i>), 131	network_enables_3 (<i>ics.structures.srad_epsilon_settings.srad_epsilon_settings</i> <i>attribute</i>), 158
network_enables_2 (<i>ics.structures.secu_settings.secu_settings</i> <i>attribute</i>), 148	network_enables_3 (<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings</i> <i>attribute</i>), 160
network_enables_2 (<i>ics.structures.sievb_settings.sievb_settings</i> <i>attribute</i>), 151	network_enables_3 (<i>ics.structures.srad_gigalog_settings.srad_gigalog_settings</i> <i>attribute</i>), 163
network_enables_2 (<i>ics.structures.srad_epsilon_settings.srad_epsilon_settings</i> <i>attribute</i>), 158	network_enables_3 (<i>ics.structures.srad_gigastar_settings.srad_gigastar_settings</i> <i>attribute</i>), 165
network_enables_2 (<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings</i> <i>attribute</i>), 160	network_enables_3 (<i>ics.structures.srad_jupiter_settings.srad_jupiter_settings</i> <i>attribute</i>), 168
network_enables_2 (<i>ics.structures.srad_gigalog_settings.srad_gigalog_settings</i> <i>attribute</i>), 163	network_enables_3 (<i>ics.structures.srad_moon2_settings.srad_moon2_settings</i> <i>attribute</i>), 169
network_enables_2 (<i>ics.structures.srad_gigastar_settings.srad_gigastar_settings</i> <i>attribute</i>), 165	network_enables_3 (<i>ics.structures.srad_moon3_settings.srad_moon3_settings</i> <i>attribute</i>), 170
network_enables_2 (<i>ics.structures.srad_jupiter_settings.srad_jupiter_settings</i> <i>attribute</i>), 168	network_enables_3 (<i>ics.structures.srad_pluto_settings.srad_pluto_settings</i> <i>attribute</i>), 171
network_enables_2 (<i>ics.structures.srad_moon2_settings.srad_moon2_settings</i> <i>attribute</i>), 169	network_enables_3 (<i>ics.structures.srad_star2_settings.srad_star2_settings</i> <i>attribute</i>), 173
network_enables_2 (<i>ics.structures.srad_moon3_settings.srad_moon3_settings</i> <i>attribute</i>), 170	network_enables_3 (<i>ics.structures.srad_super_moon_settings.srad_super_moon_settings</i> <i>attribute</i>), 173
network_enables_2 (<i>ics.structures.srad_pluto_settings.srad_pluto_settings</i> <i>attribute</i>), 171	network_enables_3 (<i>ics.structures.sradbms_settings.sradbms_settings</i> <i>attribute</i>), 176
network_enables_2 (<i>ics.structures.srad_star2_settings.srad_star2_settings</i> <i>attribute</i>), 173	network_enables_3 (<i>ics.structures.svcan4_settings.svcan4_settings</i> <i>attribute</i>), 185
network_enables_2 (<i>ics.structures.srad_super_moon_settings.srad_super_moon_settings</i> <i>attribute</i>), 173	network_enables_4 (<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings</i> <i>attribute</i>), 160
network_enables_2 (<i>ics.structures.sradbms_settings.sradbms_settings</i> <i>attribute</i>), 176	network_enables_4 (<i>ics.structures.srad_gigalog_settings.srad_gigalog_settings</i> <i>attribute</i>), 163
network_enables_2 (<i>ics.structures.svcan4_settings.svcan4_settings</i> <i>attribute</i>), 185	network_enables_4 (<i>ics.structures.srad_gigastar_settings.srad_gigastar_settings</i> <i>attribute</i>), 166
network_enables_2 (<i>ics.structures.svcanrf_settings.svcanrf_settings</i> <i>attribute</i>), 186	networkDWCAN01 (<i>ics.structures.device_feature.device_feature</i> <i>attribute</i>), 89
network_enables_3 (<i>ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute</i>), 186	networkDWCAN02 (<i>ics.structures.device_feature.device_feature</i> <i>attribute</i>), 89
	networkDWCAN03 (<i>ics.structures.device_feature.device_feature</i> <i>attribute</i>), 89

attribute), 89
 networkDWCAN04 (ics.structures.device_feature.device_feature attribute), 89
 networkDWCAN05 (ics.structures.device_feature.device_feature attribute), 89
 networkDWCAN06 (ics.structures.device_feature.device_feature attribute), 89
 networkDWCAN07 (ics.structures.device_feature.device_feature attribute), 89
 networkDWCAN08 (ics.structures.device_feature.device_feature attribute), 89
 NetworkID (ics.ics.SpyMessage attribute), 18
 NetworkID (ics.ics.SpyMessageJ1850 attribute), 19
 networkId (ics.structures.ethernet_network_status_t.ethernet_network_status_t attribute), 93
 NetworkID (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 101
 NetworkID (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 104
 NetworkID (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 105
 NetworkID (ics.structures.spy_filter_long.spy_filter_long attribute), 156
 networkId (ics.structures.start_dhcp_server_command.start_dhcp_server_command attribute), 181
 networkId (ics.structures.stop_dhcp_server_command.stop_dhcp_server_command attribute), 181
 NetworkID2 (ics.ics.SpyMessage attribute), 18
 NetworkID2 (ics.ics.SpyMessageJ1850 attribute), 19
 NetworkID2 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 101
 NetworkID2 (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 104
 NetworkID2 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 105
 networkTerminationDWCAN01 (ics.structures.device_feature.device_feature attribute), 89
 networkTerminationDWCAN02 (ics.structures.device_feature.device_feature attribute), 89
 networkTerminationDWCAN03 (ics.structures.device_feature.device_feature attribute), 89
 networkTerminationDWCAN04 (ics.structures.device_feature.device_feature attribute), 89
 networkTerminationDWCAN05 (ics.structures.device_feature.device_feature attribute), 90
 networkTerminationDWCAN06 (ics.structures.device_feature.device_feature attribute), 90
 networkTerminationDWCAN07 (ics.structures.device_feature.device_feature attribute), 90
 networkTerminationDWCAN08 (ics.structures.device_feature.device_feature attribute), 90
 NOCANFD (in module ics.ics), 200
 no_enf_hostprt (ics.structures.s_pluto_l2_address_lookup_params.s_pluto_l2_address_lookup_params attribute), 138
 no_mgmt_learn (ics.structures.s_pluto_l2_address_lookup_params.s_pluto_l2_address_lookup_params attribute), 138
 NodeID (ics.ics.SpyMessage attribute), 18
 NodeID (ics.ics.SpyMessageJ1850 attribute), 19
 NodeID (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 101
 NodeID (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 104
 NodeID (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 105
 NodeID (ics.structures.spy_filter_long.spy_filter_long attribute), 156
 nodeType (ics.structures.a2_b_monitor_settings.a2_b_monitor_settings attribute), 87
 noExtraDataPtrCleanup (ics.ics.SpyMessage attribute), 20
 noExtraDataPtrCleanup (ics.ics.SpyMessageJ1850 attribute), 20
 NORMAL (in module ics.ics), 200
 NORMAL_MODE (in module ics.ics), 200
 null_frame (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 103
 num_bytes (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 107
 num_bytes (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 181
 NUM_DEVICE_FEATURE_BITFIELDS (in module ics.ics), 200
 NUM_VALID_DEVICE_FEATURES (ics.structures.device_feature.device_feature attribute), 89
 NUM_VALID_DEVICE_FEATURES (in module ics.ics), 200
 NumberBytesData (ics.ics.SpyMessage attribute), 18
 NumberBytesData (ics.ics.SpyMessageJ1850 attribute), 20
 NumberBytesData (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute), 101
 NumberBytesData (ics.structures.ics_spy_message_long.ics_spy_message_long attribute), 104
 NumberBytesData (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute), 105
 NumberBytesHeader (ics.ics.SpyMessage attribute), 18
 NumberBytesHeader (ics.ics.SpyMessageJ1850 attribute), 20

NumberBytesHeader (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_structures.op_eth_link_mode), 109
 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_structures.op_eth_link_mode), 102
 NumberBytesHeader (ics.structures.ics_spy_message_long.ics_spy_message_long_structures.op_eth_settings), 109
 (ics.structures.ics_spy_message_long.ics_spy_message_long_structures.op_eth_settings), 104
 NumberBytesHeader (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb_structures.op_eth_settings), 109
 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb_structures.op_eth_settings), 105
 NumberOfClients (ics.ics.NeoDevice attribute), 18
 numBitsDelay (ics.structures.lin_settings.lin_settings attribute), 108
 numEntries (ics.structures.s_phy_reg_pkt_hdr.s_phy_reg_pkt_hdr attribute), 129
 (ics.structures.s_phy_reg_pkt_hdr.s_phy_reg_pkt_hdr attribute), 133
 numstbcy (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 140
 (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 134
 numunstbcy (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 140
 (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 134
 numValidBits (ics.structures.get_supported_features_response.get_supported_features_response attribute), 96
 numVersions (ics.structures.get_component_versions_response.get_component_versions_response attribute), 96
 (ics.structures.get_component_versions_response.get_component_versions_response attribute), 96
O
 obd2dev_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 178
 (ics.structures.st_chip_versions.st_chip_versions attribute), 178
 obd2lc (ics.structures.global_settings.global_settings attribute), 97
 (ics.structures.global_settings.global_settings attribute), 97
 obd2lc_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 178
 (ics.structures.st_chip_versions.st_chip_versions attribute), 178
 obd2pro (ics.structures.global_settings.global_settings attribute), 97
 (ics.structures.global_settings.global_settings attribute), 97
 obd2pro_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 178
 (ics.structures.st_chip_versions.st_chip_versions attribute), 178
 obd2proStatus (ics.structures.ics_device_status.ics_device_status attribute), 99
 (ics.structures.ics_device_status.ics_device_status attribute), 99
 obvwinsz (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 134
 (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 134
 offset (ics.structures.software_update_command.software_update_command attribute), 156
 (ics.structures.software_update_command.software_update_command attribute), 156
 offset_scaled_log_variance (ics.structures.clock_quality.clock_quality attribute), 89
 (ics.structures.clock_quality.clock_quality attribute), 89
 offset_scaled_log_variance (ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params attribute), 140
 (ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params attribute), 140
 offset_scaled_log_variance (ics.structures.srad_gptp_settings.s.srad_gptp_settings attribute), 167
 (ics.structures.srad_gptp_settings.s.srad_gptp_settings attribute), 167
 op_eth_general_settings (class in ics.structures.op_eth_general_settings), 108
 OP_ETH_GENERAL_SETTINGS_SIZE (in module ics.ics), 200
 op_eth_link_mode (class in ics.structures.op_eth_link_mode), 109
 op_eth_settings (class in ics.structures.op_eth_settings), 109
 OP_ETH_SETTINGS_SIZE (in module ics.ics), 200
 open_device() (in module ics.ics), 53
 OpenNeoDevice() (in module ics.ics), 25
 operationLogPDelayReqInterval (ics.structures.s_jupiter_ptp_params.s.s_jupiter_ptp_params attribute), 128
 operationLogSyncInterval (ics.structures.s_jupiter_ptp_params.s.s_jupiter_ptp_params attribute), 128
 opEth1 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160
 opEth1 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
 opEth1 (ics.structures.srad_moon2_settings.srad_moon2_settings attribute), 173
 (ics.structures.srad_moon2_settings.srad_moon2_settings attribute), 173
 opEth1 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 173
 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 173
 opEth1 (ics.structures.srad_super_moon_settings.srad_super_moon_settings attribute), 174
 (ics.structures.srad_super_moon_settings.srad_super_moon_settings attribute), 174
 opEth10 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 160
 opEth11 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEth12 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEth2 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEth2 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
 opEth2 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 173
 (ics.structures.srad_star2_settings.srad_star2_settings attribute), 173
 opEth3 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEth4 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEth5 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEth6 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEth7 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEth8 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEth9 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 OPETH_FUNC_MEDIACONVERTER (in module ics.ics), 200
 OPETH_FUNC_RAW_MEDIA_CONVERTER (in module ics.ics), 200
 OPETH_FUNC_RAW_MEDIA_CONVERTER2 (in module ics.ics), 200

rule ics.ics), 200
 OPETH_FUNC_RAW_MEDIA_CONVERTER2_LOW_LATENCY (in module ics.ics), 200
 OPETH_FUNC_TAP (in module ics.ics), 200
 OPETH_FUNC_TAP_LOW_LATENCY (in module ics.ics), 200
 OPETH_LINK_AUTO (ics.structures.op_eth_link_mode.op_eth_link_mode attribute), 109
 OPETH_LINK_AUTO (in module ics.ics), 200
 OPETH_LINK_MASTER (ics.structures.op_eth_link_mode.op_eth_link_mode attribute), 109
 OPETH_LINK_MASTER (in module ics.ics), 200
 OPETH_LINK_SLAVE (ics.structures.op_eth_link_mode.op_eth_link_mode attribute), 109
 OPETH_LINK_SLAVE (in module ics.ics), 200
 OPETH_MAC_SPOOF_DST_ADDR (in module ics.ics), 200
 OPETH_MAC_SPOOF_SRC_ADDR (in module ics.ics), 200
 opEthGen (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161
 opEthGen (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
 opEthGen (ics.structures.srad_moon2_settings.srad_moon2_settings attribute), 169
 opEthGen (ics.structures.srad_star2_settings.srad_star2_settings attribute), 173
 opEthGen (ics.structures.srad_super_moon_settings.srad_super_moon_settings attribute), 174
 options (ics.structures.s_disk_structure.s_disk_structure attribute), 115
 os_settings (ics.structures.s_fire3_settings.s_fire3_settings attribute), 121
 override_library_name() (in module ics.ics), 53
 overrideBlockSize (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 107
 overrideBlockSize (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 181
 overrideSTmin (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 107
 overrideSTmin (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 181
 overwrite (ics.structures.start_dhcp_server_command.start_dhcp_server_command attribute), 181

P
 p2_500us (ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings attribute), 108
 p3_500us (ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings attribute), 108
 p4_500us (ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings attribute), 108
 pad (ics.structures.s_pluto_custom_params.s.s_pluto_custom_params attribute), 136
 pad (ics.structures.s_pluto_l2_address_lookup_params.s.s_pluto_l2_address_lookup_params attribute), 138
 pad (ics.structures.s_pluto_l2_forwarding_entry.s.s_pluto_l2_forwarding_entry attribute), 138
 pad (ics.structures.s_pluto_l2_forwarding_params.s.s_pluto_l2_forwarding_params attribute), 139
 pad (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config attribute), 140
 pad (ics.structures.s_pluto_retagging_entry.s.s_pluto_retagging_entry attribute), 141
 pad (ics.structures.s_pluto_vl_forwarding_params.s.s_pluto_vl_forwarding_params attribute), 142
 pad (ics.structures.s_pluto_vlan_lookup.s.s_pluto_vlan_lookup attribute), 143
 pad (ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings attribute), 158
 pad (ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings attribute), 169
 pad (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 135
 pad (ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry attribute), 138
 pad (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 135
 pad (ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry attribute), 138
 padding (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 107
 padding (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 179
 padding (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 181
 paddingEnable (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 107
 paddingEnable (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 180
 paddingEnable (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 181
 parity (ics.structures.uart_settings.uart_settings attribute), 133

PHYREG_RESERVED1 (in module ics.ics), 200	plutoStatus (ics.structures.ics_device_status.ics_device_status attribute), 133
PHYREG_RESERVED2 (ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_status attribute), 133	poly (ics.structures.s_pluto_l2_address_lookup_params.s.s_pluto_l2_address_lookup_params attribute), 138
PHYREG_RESERVED2 (in module ics.ics), 200	port (ics.structures.uart_port_config.uart_port_config attribute), 188
PHYREG_RESERVED3 (ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_status attribute), 134	port (ics.structures.uart_port_data.uart_port_data attribute), 188
PHYREG_RESERVED3 (in module ics.ics), 200	port (ics.structures.uart_port_port_bytes.uart_port_port_bytes attribute), 189
PHYREG_SUCCESS (ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_status attribute), 134	port7Select (ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings attribute), 169
PHYREG_SUCCESS (in module ics.ics), 200	port8Legacy (ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings attribute), 169
PHYREG_UNSUPPORTED_MDIO_CLAUSE (ics.structures.s_phy_reg_pkt_status.s_phy_reg_pkt_status attribute), 134	port8Select (ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings attribute), 169
PHYREG_UNSUPPORTED_MDIO_CLAUSE (in module ics.ics), 200	port8Select (ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings attribute), 169
PHYREG_WRITE (ics.structures.s_phy_reg_pkt_rw.s_phy_reg_pkt_rw attribute), 133	port_a (ics.structures.s_spi_port_settings.s_spi_port_settings attribute), 144
PHYREG_WRITE (in module ics.ics), 200	port_b (ics.structures.s_spi_port_settings.s_spi_port_settings attribute), 144
plasma_fire_vnet (ics.structures.st_chip_versions.st_chip_versions attribute), 178	port_identity (class in ics.structures.port_identity), 110
PLASMA_SLAVE1_OFFSET (in module ics.ics), 200	port_number (ics.structures.port_identity.port_identity attribute), 110
PLASMA_SLAVE1_OFFSET_RANGE2 (in module ics.ics), 200	port_number (ics.structures.priority_vector.priority_vector attribute), 110
PLASMA_SLAVE2_OFFSET (in module ics.ics), 200	portid (ics.structures.priority_vector.priority_vector attribute), 110
PLASMA_SLAVE2_OFFSET_RANGE2 (in module ics.ics), 200	preemption_en (ics.structures.op_eth_settings.op_eth_settings attribute), 110
PLASMA_SLAVE3_OFFSET_RANGE2 (in module ics.ics), 201	priority1 (ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params attribute), 140
PLASMA_SLAVE_NUM (in module ics.ics), 201	priority1 (ics.structures.srad_gptp_settings.srad_gptp_settings_s attribute), 167
PlasmaIonVnetChannelA (ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet_channel_t attribute), 92	priority2 (ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params attribute), 140
PlasmaIonVnetChannelB (ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet_channel_t attribute), 92	priority2 (ics.structures.srad_gptp_settings.srad_gptp_settings_s attribute), 167
PlasmaIonVnetChannelMain (ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet_channel_t attribute), 92	priority_1 (ics.structures.system_identity.system_identity attribute), 187
pluto (ics.structures.global_settings.global_settings attribute), 97	priority_2 (ics.structures.system_identity.system_identity attribute), 187
PLUTO_MAX_FORWARDING_ENTRIES (in module ics.ics), 201	priority_vector (class in ics.structures.priority_vector), 110
PLUTO_MAX_L2_ADDRESS_LOOKUP (in module ics.ics), 201	priority_vector (class in ics.structures.priority_vector), 110
PLUTO_MAX_L2_POLICING (in module ics.ics), 201	pluto_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 178
PLUTO_MAX_MAC_CONFIG_ENTRIES (in module ics.ics), 201	pluto_versions (ics.structures.s_pluto_ptp_params.s.s_pluto_ptp_params attribute), 141
PLUTO_MAX_RETAGGING_ENTRIES (in module ics.ics), 201	
PLUTO_MAX_VLAN_LOOKUP (in module ics.ics), 201	
PLUTO_NUM_PORTS (in module ics.ics), 201	
PLUTO_NUM_PRIORITY (in module ics.ics), 201	
pluto_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 178	

pwr_man_timeout (*ics.structures.srad_gigalog_settings.rad_reporting_settings*
 attribute), 163 (in module *ics.ics*), 201
 pwr_man_timeout (*ics.structures.srad_gigastar_settings.rad_reporting_settings*
 attribute), 166 (in module *ics.ics*), 201
 pwr_man_timeout (*ics.structures.srad_jupiter_settings.rad_reporting_settings*
 attribute), 168 (in module *ics.ics*), 201
 pwr_man_timeout (*ics.structures.srad_pluto_settings.rad_reporting_settings*
 attribute), 171 (in module *ics.ics*), 201
 pwr_man_timeout (*ics.structures.srad_star2_settings.rad_reporting_settings*
 attribute), 173 (in module *ics.ics*), 201
 pwr_man_timeout (*ics.structures.srada2_b_settings.srada2_b_reporting_settings*
 attribute), 175 (in module *ics.ics*), 201
 pwr_man_timeout (*ics.structures.sradbms_settings.sradbms_reporting_settings*
 attribute), 176 (in module *ics.ics*), 201
 pwr_man_timeout (*ics.structures.svcan412_settings.svcan412_reporting_settings*
 attribute), 183 (in module *ics.ics*), 201
 pwr_man_timeout (*ics.structures.svcan4_ind_settings.svcan4_ind_reporting_settings*
 attribute), 184 (in module *ics.structures.ics_device_status.ics_device_status*
 attribute), 99
 pwr_man_timeout (*ics.structures.svcan4_settings.svcan4_reporting_settings*
 attribute), 185 (in module *ics.ics*), 201
 pwr_man_timeout (*ics.structures.svcanrf_settings.svcanrf_reporting_settings*
 attribute), 186 (in module *ics.ics*), 201
 radgalaxy (*ics.structures.global_settings.global_settings*
 attribute), 97
 radgalaxy_versions
 (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
Q
 q2112_phy_mode (*ics.structures.op_eth_settings.op_eth_settings*
 attribute), 110 (in module *ics.structures.global_settings.global_settings*
 attribute), 97
R
 rad_a2b (*ics.structures.global_settings.global_settings*
 attribute), 97 (in module *ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 rad_a2b_versions (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178 (in module *ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 rad_bms (*ics.structures.global_settings.global_settings*
 attribute), 97 (in module *ics.structures.global_settings.global_settings*
 attribute), 97
 RAD_GPTP_AND_TAP_SETTINGS_SIZE (in module *ics.ics*), 201 (in module *ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 RAD_GPTP_SETTINGS_SIZE (in module *ics.ics*), 201 (in module *ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 rad_moon_duo_converter_settings (class in *ics.structures.rad_moon_duo_converter_settings*),
 110 (in module *ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 rad_moon_duo_versions
 (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 rad_reporting_settings (class in *ics.structures.rad_reporting_settings*), 110
 RAD_REPORTING_SETTINGS_FLAG_AIN1 (in mod-
 ule *ics.ics*), 201 (in module *ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 RAD_REPORTING_SETTINGS_FLAG_FAN_SPEED_ENABLE
 (in module *ics.ics*), 201 (in module *ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 RAD_REPORTING_SETTINGS_FLAG_INT_GPS_ENABLE
 (in module *ics.ics*), 201 (in module *ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE
 (in module *ics.ics*), 201 (in module *ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 radmoon2 (*ics.structures.global_settings.global_settings*
 attribute), 98
 radmoon2_versions
 (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 radmoon2_z7010_versions
 (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 radmoon3 (*ics.structures.global_settings.global_settings*
 attribute), 98
 radmoon3_versions
 (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 178
 RADJUPITER_NUM_PORTS (in module *ics.ics*), 201

radmoonduo (*ics.structures.global_settings.global_settings* reporting (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*
attribute), 98 *attribute*), 161
 RADMOONDUO_CONVERTER_SETTINGS_SIZE (in reporting (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*
module ics.ics), 201 *attribute*), 163
 radMoonDuoStatus (*ics.structures.ics_device_status.ics_device_status* (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*
attribute), 99 *attribute*), 166
 radstar2 (*ics.structures.global_settings.global_settings* reporting (*ics.structures.srad_star2_settings.srad_star2_settings*
attribute), 98 *attribute*), 173
 radstar2_versions reporting (*ics.structures.srada2_b_settings.srada2_b_settings*
(ics.structures.st_chip_versions.st_chip_versions *attribute*), 175
attribute), 178 request_enter_sleep_mode () (in module
 radsupermoon (*ics.structures.global_settings.global_settings ics.ics*), 54
attribute), 98 RequestDiskDetails () (in module *ics.ics*), 25
 radsupermoon_versions RequestDiskFormat () (in module *ics.ics*), 25
(ics.structures.st_chip_versions.st_chip_versions RequestDiskFormatCancel () (in module *ics.ics*),
attribute), 178 25
 rate (*ics.structures.s_pluto_l2_policing.s.s_pluto_l2_policing* RequestDiskFormatProgress () (in module
attribute), 139 *ics.ics*), 25
 reach_port (*ics.structures.s_pluto_l2_forwarding_entry.s.pluto_l2_forwarding_entry* (*ics.ics*), 25
attribute), 138 res1 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray*
 read_jupiter_firmware () (in module *ics.ics*), 53 *attribute*), 103
 read_sdcard () (in module *ics.ics*), 54 res2 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray*
 ReadJupiterFirmware () (in module *ics.ics*), 25 *attribute*), 103
 ReadSDCard () (in module *ics.ics*), 25 reserve (*ics.structures.uart_port_config.uart_port_config*
 red (*ics.structures.global_settings.global_settings* *attribute*), 188
attribute), 98 reserved (*ics.structures.a2_b_monitor_settings.a2_b_monitor_settings*
 red2 (*ics.structures.global_settings.global_settings* *attribute*), 87
attribute), 98 reserved (*ics.structures.canfd_settings.canfd_settings*
 red2_versions (*ics.structures.st_chip_versions.st_chip_versions* *attribute*), 89
attribute), 178 reserved (*ics.structures.canterm_settings.canterm_settings*
 regAddr (*ics.structures.s_phy_reg_pkt_clause22_mess.s.s_phy_reg_pkt_clause22_mess* *attribute*), 229
attribute), 133 reserved (*ics.structures.fire3_linux_settings.fire3_linux_settings*
 regAddr (*ics.structures.s_phy_reg_pkt_clause45_mess.s.s_phy_reg_pkt_clause45_mess* *attribute*), 495
attribute), 133 reserved (*ics.structures.get_component_versions.get_component_versions*
 REGISTER_BY_SERIAL (in module *ics.ics*), 201 *attribute*), 96
 regVal (*ics.structures.s_phy_reg_pkt_clause22_mess.s.s_phy_reg_pkt_clause22_mess* *attribute*), 99
attribute), 133 reserved (*ics.structures.gtp_status.gtp_status* *attribute*), 99
 regVal (*ics.structures.s_phy_reg_pkt_clause45_mess.s.s_phy_reg_pkt_clause45_mess* *attribute*), 102
attribute), 133 reserved (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex*
 REPORT_ON_GPS (in module *ics.ics*), 201 *attribute*), 102
 REPORT_ON_KLINE (in module *ics.ics*), 201 Reserved (*ics.structures.ics_spy_message_long.ics_spy_message_long*
 REPORT_ON_LED1 (in module *ics.ics*), 201 *attribute*), 104
 REPORT_ON_LED2 (in module *ics.ics*), 201 Reserved (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb*
 REPORT_ON_MISC1 (in module *ics.ics*), 201 *attribute*), 105
 REPORT_ON_MISC2 (in module *ics.ics*), 201 reserved (*ics.structures.op_eth_settings.op_eth_settings*
 REPORT_ON_MISC3 (in module *ics.ics*), 201 *attribute*), 110
 REPORT_ON_MISC3_AIN (in module *ics.ics*), 201 reserved (*ics.structures.s_fire3_settings.s_fire3_settings*
 REPORT_ON_MISC4 (in module *ics.ics*), 202 *attribute*), 121
 REPORT_ON_MISC4_AIN (in module *ics.ics*), 202 reserved (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt*
 REPORT_ON_MISC5 (in module *ics.ics*), 202 *attribute*), 132
 REPORT_ON_MISC5_AIN (in module *ics.ics*), 202 reserved (*ics.structures.s_text_api_settings.s_text_api_settings*
 REPORT_ON_MISC6 (in module *ics.ics*), 202 *attribute*), 144
 REPORT_ON_MISC6_AIN (in module *ics.ics*), 202 reserved (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652*
 REPORT_ON_PERIODIC (in module *ics.ics*), 202 *attribute*), 180
 RESERVED (*ics.structures.swcan_settings.swcan_settings*

[attribute\), 187](#)
[Reserved \(ics.structures.tag_options_find_neo_ex.tag_options_find_neo_ex.attribute\), 187](#)
[Reserved \(ics.structures.tag_options_open_neo_ex.tag_options_open_neo_ex.attribute\), 187](#)
[reserved \(ics.structures.version_report.version_report_attribute\), 190](#)
[reserved0 \(ics.structures.op_eth_general_settings.op_eth_general_settings.attribute\), 109](#)
[reserved0 \(ics.structures.op_eth_settings.op_eth_settings_attribute\), 110](#)
[reserved_1 \(ics.structures.sievb_settings.sievb_settings_attribute\), 152](#)
[reserved_1 \(ics.structures.uart_settings.uart_settings_attribute\), 189](#)
[reserved_2 \(ics.structures.sievb_settings.sievb_settings_attribute\), 152](#)
[reserved_bits \(ics.structures.uart_settings.uart_settings_attribute\), 189](#)
[reserved_bits2 \(ics.structures.uart_settings.uart_settings_attribute\), 189](#)
[reserved_field \(ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings_attribute\), 130](#)
[reservedZero \(ics.structures.svcanrf_settings.svcanrf_settings_attribute\), 186](#)
[resHeight \(ics.structures.serdescam_settings.serdescam_settings_attribute\), 149](#)
[RESISTOR_OFF \(in module ics.ics\), 202](#)
[RESISTOR_ON \(in module ics.ics\), 202](#)
[resWidth \(ics.structures.serdescam_settings.serdescam_settings_attribute\), 149](#)
[retag \(ics.structures.s_pluto_mac_config.s_pluto_mac_config_attribute\), 140](#)
[retagging \(ics.structures.s_pluto_switch_settings.s_pluto_switch_settings_attribute\), 141](#)
[returnCode \(ics.structures.extended_response_generic.extended_response_generic_attribute\), 95](#)
[rsvd \(ics.structures.disk_settings.disk_settings_attribute\), 90](#)
[rsvd \(ics.structures.ethernet_settings.ethernet_settings_attribute\), 93](#)
[rsvd \(ics.structures.ethernet_settings2.ethernet_settings2_attribute\), 94](#)
[rsvd \(ics.structures.logger_settings.logger_settings_attribute\), 108](#)
[rsvd \(ics.structures.rad_reporting_settings.rad_reporting_settings_attribute\), 111](#)
[rsvd \(ics.structures.seevb_settings.seevb_settings_attribute\), 149](#)
[rsvd \(ics.structures.serdespoc_settings.serdespoc_settings_attribute\), 150](#)
[rsvd \(ics.structures.srad_gptp_settings.srad_gptp_settings_attribute\), 167](#)
[rsvd1 \(ics.structures.serdescam_settings.serdescam_settings_attribute\), 149](#)
[rsvd2 \(ics.structures.serdesgen_settings.serdesgen_settings_attribute\), 150](#)
[rsvd2 \(ics.structures.srad_gigalog_settings.srad_gigalog_settings_attribute\), 163](#)
[rsvd2 \(ics.structures.ethernet10_g_settings.ethernet10_g_settings_attribute\), 93](#)
[rsvd2 \(ics.structures.serdescam_settings.serdescam_settings_attribute\), 149](#)
[rsvd2 \(ics.structures.serdesgen_settings.serdesgen_settings_attribute\), 150](#)
[rsvd2 \(ics.structures.srad_gigalog_settings.srad_gigalog_settings_attribute\), 163](#)
[RuntimeError, 18](#)
[rx_speed \(ics.structures.serdesgen_settings.serdesgen_settings_attribute\), 150](#)
[S](#)
[s_cm_probe_settings \(class in ics.structures.s_cm_probe_settings\), 111](#)
[s_cyan_settings \(class in ics.structures.s_cyan_settings\), 111](#)
[s_device_settings \(class in ics.structures.s_device_settings\), 114](#)
[s_disk_details \(class in ics.structures.s_disk_details\), 114](#)
[s_disk_format_progress \(class in ics.structures.s_disk_format_progress\), 115](#)
[s_disk_status \(class in ics.structures.s_disk_status\), 115](#)
[s_disk_structure \(class in ics.structures.s_disk_structure\), 115](#)
[s_ether_badge_settings \(class in ics.structures.s_ether_badge_settings\), 115](#)
[s_ext_sub_cmd_comm \(class in ics.structures.s_ext_sub_cmd_comm\), 117](#)
[s_ext_sub_cmd_hdr \(class in ics.structures.s_ext_sub_cmd_hdr\), 117](#)
[s_extended_data_flash_header \(class in ics.structures.s_extended_data_flash_header\), 117](#)
[s_fire3_settings \(class in ics.structures.s_fire3_settings\), 117](#)
[s_fire_settings \(class in ics.structures.s_fire_settings\), 122](#)
[s_fire_vnet_settings \(class in ics.structures.s_fire_vnet_settings\), 124](#)
[s_flex_vnetz_settings \(class in ics.structures.s_flex_vnetz_settings\), 127](#)
[s_jupiter_ptp_params_s \(class in ics.structures.s_jupiter_ptp_params_s\), 128](#)
[s_neo_ecu12_settings \(class in ics.structures.s_neo_ecu12_settings\), 129](#)

<code>s_neo_most_gateway_settings</code> (class in <code>ics.structures.s_neo_most_gateway_settings</code>), 130	<code>s_pluto_vl_forwarding_entry_s</code> (class in <code>ics.structures.s_pluto_vl_forwarding_entry_s</code>), 142
<code>s_pendant_settings</code> (class in <code>ics.structures.s_pendant_settings</code>), 130	<code>s_pluto_vl_forwarding_params_s</code> (class in <code>ics.structures.s_pluto_vl_forwarding_params_s</code>), 142
<code>s_phy_reg_pkt</code> (class in <code>ics.structures.s_phy_reg_pkt</code>), 132	<code>s_pluto_vl_lookup_entry_s</code> (class in <code>ics.structures.s_pluto_vl_lookup_entry_s</code>), 142
<code>s_phy_reg_pkt_clause22_mess</code> (class in <code>ics.structures.s_phy_reg_pkt_clause22_mess</code>), 133	<code>s_pluto_vl_policing_entry_s</code> (class in <code>ics.structures.s_pluto_vl_policing_entry_s</code>), 142
<code>s_phy_reg_pkt_clause45_mess</code> (class in <code>ics.structures.s_phy_reg_pkt_clause45_mess</code>), 133	<code>s_pluto_vlan_lookup_s</code> (class in <code>ics.structures.s_pluto_vlan_lookup_s</code>), 142
<code>s_phy_reg_pkt_hdr</code> (class in <code>ics.structures.s_phy_reg_pkt_hdr</code>), 133	<code>s_rad_moon_duo_settings</code> (class in <code>ics.structures.s_rad_moon_duo_settings</code>), 143
<code>s_phy_reg_pkt_rw</code> (class in <code>ics.structures.s_phy_reg_pkt_rw</code>), 133	<code>s_red_settings</code> (class in <code>ics.structures.s_red_settings</code>), 143
<code>s_phy_reg_pkt_status</code> (class in <code>ics.structures.s_phy_reg_pkt_status</code>), 133	<code>s_spi_port_settings</code> (class in <code>ics.structures.s_spi_port_settings</code>), 143
<code>s_pluto_avb_params_s</code> (class in <code>ics.structures.s_pluto_avb_params_s</code>), 134	<code>s_text_api_settings</code> (class in <code>ics.structures.s_text_api_settings</code>), 144
<code>s_pluto_clock_sync_params_s</code> (class in <code>ics.structures.s_pluto_clock_sync_params_s</code>), 134	<code>s_vivid_can_settings</code> (class in <code>ics.structures.s_vivid_can_settings</code>), 144
<code>s_pluto_custom_params_s</code> (class in <code>ics.structures.s_pluto_custom_params_s</code>), 136	<code>s_wil_bridge_config</code> (class in <code>ics.structures.s_wil_bridge_config</code>), 145
<code>s_pluto_general_params_s</code> (class in <code>ics.structures.s_pluto_general_params_s</code>), 136	<code>s_wil_connection_settings</code> (class in <code>ics.structures.s_wil_connection_settings</code>), 145
<code>s_pluto_l2_address_lookup_entry_s</code> (class in <code>ics.structures.s_pluto_l2_address_lookup_entry_s</code>), 137	<code>s_wil_fault_servicing_settings</code> (class in <code>ics.structures.s_wil_fault_servicing_settings</code>), 145
<code>s_pluto_l2_address_lookup_params_s</code> (class in <code>ics.structures.s_pluto_l2_address_lookup_params_s</code>), 138	<code>s_wil_network_data_capture_settings</code> (class in <code>ics.structures.s_wil_network_data_capture_settings</code>), 146
<code>s_pluto_l2_forwarding_entry_s</code> (class in <code>ics.structures.s_pluto_l2_forwarding_entry_s</code>), 138	<code>scan_hub_settings</code> (class in <code>ics.structures.scan_hub_settings</code>), 146
<code>s_pluto_l2_forwarding_params_s</code> (class in <code>ics.structures.s_pluto_l2_forwarding_params_s</code>), 138	<code>scan_sleep_id</code> (class in <code>ics.structures.scan_sleep_id</code>), 146
<code>s_pluto_l2_policing_s</code> (class in <code>ics.structures.s_pluto_l2_policing_s</code>), 139	<code>SCRIPT_LOCATION_EMMC</code> (in module <code>ics.ics</code>), 202
<code>s_pluto_mac_config_s</code> (class in <code>ics.structures.s_pluto_mac_config_s</code>), 139	<code>SCRIPT_LOCATION_FLASH_MEM</code> (in module <code>ics.ics</code>), 202
<code>s_pluto_ptp_params_s</code> (class in <code>ics.structures.s_pluto_ptp_params_s</code>), 140	<code>SCRIPT_LOCATION_INTERNAL_FLASH</code> (in module <code>ics.ics</code>), 202
<code>s_pluto_retagging_entry_s</code> (class in <code>ics.structures.s_pluto_retagging_entry_s</code>), 141	<code>SCRIPT_LOCATION_SDCARD</code> (in module <code>ics.ics</code>), 202
<code>s_pluto_switch_settings_s</code> (class in <code>ics.structures.s_pluto_switch_settings_s</code>), 141	<code>SCRIPT_LOCATION_VCAN3_MEM</code> (in module <code>ics.ics</code>), 202
	<code>SCRIPT_STATUS_RUNNING</code> (in module <code>ics.ics</code>), 202
	<code>SCRIPT_STATUS_STOPPED</code> (in module <code>ics.ics</code>), 202
	<code>ScriptClear()</code> (in module <code>ics.ics</code>), 25
	<code>ScriptGetFBlockStatus()</code> (in module <code>ics.ics</code>), 26
	<code>ScriptGetScriptStatus()</code> (in module <code>ics.ics</code>), 26
	<code>ScriptGetScriptStatusEx()</code> (in module <code>ics.ics</code>),

- 26
- ScriptLoad() (in module ics.ics), 26
- ScriptReadAppSignal() (in module ics.ics), 26
- ScriptReadRxMessage() (in module ics.ics), 26
- ScriptReadTxMessage() (in module ics.ics), 26
- ScriptStart() (in module ics.ics), 26
- ScriptStartFBlock() (in module ics.ics), 27
- ScriptStop() (in module ics.ics), 27
- ScriptStopFBlock() (in module ics.ics), 27
- ScriptWriteAppSignal() (in module ics.ics), 27
- ScriptWriteRxMessage() (in module ics.ics), 27
- ScriptWriteTxMessage() (in module ics.ics), 27
- seconds_lsb (ics.structures.timestamp_.timestamp_ attribute), 188
- seconds_msb (ics.structures.timestamp_.timestamp_ attribute), 188
- sectors (ics.structures.s_disk_status.s_disk_status attribute), 115
- sectorsRemaining (ics.structures.s_disk_format_progress_.s_disk_format_progress attribute), 115
- secu_avb_settings (class in ics.structures.secu_avb_settings), 146
- secu_settings (class in ics.structures.secu_settings), 147
- seevb_settings (class in ics.structures.seevb_settings), 149
- selectable_network_1 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 121
- selectable_network_2 (ics.structures.s_fire3_settings.s_fire3_settings attribute), 121
- selected_network (ics.structures.s_pendant_settings.s_pendant_settings attribute), 132
- selected_network (ics.structures.secu_settings.secu_settings attribute), 148
- selected_network (ics.structures.sievb_settings.sievb_settings attribute), 152
- selected_role (ics.structures.gptp_status.gptp_status attribute), 99
- send_meta0 (ics.structures.s_pluto_general_params.s_pluto_general_params attribute), 137
- send_meta1 (ics.structures.s_pluto_general_params.s_pluto_general_params attribute), 137
- sensor_buffer_size (ics.structures.s_wil_connection_settings.s_wil_connection_settings attribute), 145
- serdes_interval_ms (ics.structures.rad_reporting_settings.rad_reporting_settings attribute), 111
- serdescam1 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 164
- serdescam1 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
- serdescam2 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 164
- serdescam2 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
- serdescam3 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 164
- serdescam3 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
- serdescam4 (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 164
- serdescam4 (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
- SERDESCAM_MODE_COUNT (in module ics.ics), 202
- SERDESCAM_MODE_CUSTOM (in module ics.ics), 202
- SERDESCAM_MODE_LOG_ONLY (in module ics.ics), 202
- SERDESCAM_MODE_SPLITTER (in module ics.ics), 202
- SERDESCAM_MODE_REPEAT (in module ics.ics), 202
- SERDESCAM_PIXEL_BIT_POS_0 (in module ics.ics), 202
- SERDESCAM_PIXEL_BIT_POS_1 (in module ics.ics), 202
- SERDESCAM_PIXEL_BIT_POS_2 (in module ics.ics), 202
- SERDESCAM_PIXEL_BIT_POS_3 (in module ics.ics), 202
- serdescam_settings (class in ics.structures.serdescam_settings), 149
- SERDESCAM_SETTINGS_FLAG_AUTO_DET_RES_ENABLE (in module ics.ics), 202
- SERDESCAM_SETTINGS_FLAG_CONFIG_ENABLE (in module ics.ics), 202
- SERDESCAM_SETTINGS_FLAG_ENABLE (in module ics.ics), 202
- SERDESCAM_SETTINGS_FLAG_LOGGING_ENABLE (in module ics.ics), 202
- SERDESCAM_SETTINGS_FLAG_RTSP_ENABLE (in module ics.ics), 202
- SERDESCAM_SETTINGS_FLAG_TX0_ENABLE (in module ics.ics), 202
- SERDESCAM_SETTINGS_FLAG_TX1_ENABLE (in module ics.ics), 202
- SERDESCAM_SETTINGS_FLAG_TX2_ENABLE (in module ics.ics), 202
- SERDESCAM_SETTINGS_FLAG_TX3_ENABLE (in module ics.ics), 202
- SERDESCAM_SETTINGS_SIZE (in module ics.ics), 202
- VIDEO_FORMAT_BAYER_BGGR_10LE_PACKED (in module ics.ics), 202
- VIDEO_FORMAT_BAYER_BGGR_12LE_PACKED (in module ics.ics), 203

SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16BE (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GRBG_8 (in module ics.ics), 203
SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16LE (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_RGGB_10LE_PACKED (in module ics.ics), 203
SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_8 (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_RGGB_12LE_PACKED (in module ics.ics), 203
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_10LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_RGGB_8 (in module ics.ics), 203
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_12LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_10 (in module ics.ics), 203
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_16BE (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_12 (in module ics.ics), 203
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_16LE (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_14 (in module ics.ics), 203
SERDESCAM_VIDEO_FORMAT_BAYER_GBRG_8 (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_16 (in module ics.ics), 203
SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_10LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_20 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_12LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_24 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_16BE (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_30 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_16LE (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_32 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_BAYER_GRBG_8 (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_36 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_10LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RAW_8 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_12LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RGB565 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_16BE (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RGB666 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_16LE (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_RGB888 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_BAYER_RGGB_8 (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_10LE_PACKED (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_COUNT (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_12LE_PACKED (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_10LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_8 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_12LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_10LE_PACKED (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_8 (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_12LE_PACKED (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GBRG_10LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_8 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GBRG_12LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_10LE_PACKED (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GBRG_8 (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_12LE_PACKED (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GRBG_10LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_8 (in module ics.ics), 204
SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_GRBG_12LE_PACKED (in module ics.ics), 203	SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_10LE_PACKED (in module ics.ics), 204

SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_12LE_PACKED (in module ics.ics), 204	SERDESCAM_VIDEO_FORMAT_YUYV_422_8 (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_8 (in module ics.ics), 204	SERDESCAM_VIDEO_FORMAT_YVYU_422_10LE_PACKED (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_JPEG (in module ics.ics), 204	SERDESCAM_VIDEO_FORMAT_YVYU_422_12LE_PACKED (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_NONE (in module ics.ics), 204	SERDESCAM_VIDEO_FORMAT_YVYU_422_8 (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_RAW_10 (in module ics.ics), 204	serdesgen (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 164
SERDESCAM_VIDEO_FORMAT_RAW_12 (in module ics.ics), 204	serdesgen (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
SERDESCAM_VIDEO_FORMAT_RAW_14 (in module ics.ics), 204	SERDESGEN_MOD_ID_NONE (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_RAW_16 (in module ics.ics), 204	SERDESGEN_MOD_ID_UNKNOWN (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_RAW_20 (in module ics.ics), 204	serdesgen_settings (class in ics.structures.serdesgen_settings), 150
SERDESCAM_VIDEO_FORMAT_RAW_24 (in module ics.ics), 204	SERDESGEN_SETTINGS_FLAG_TX_PATGEN_ENABLE (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_RAW_30 (in module ics.ics), 204	SERDESGEN_SETTINGS_SIZE (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_RAW_32 (in module ics.ics), 204	serdespoc (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 164
SERDESCAM_VIDEO_FORMAT_RAW_36 (in module ics.ics), 204	serdespoc (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166
SERDESCAM_VIDEO_FORMAT_RAW_8 (in module ics.ics), 204	serdespoc_settings (class in ics.structures.serdespoc_settings), 150
SERDESCAM_VIDEO_FORMAT_RGB565 (in module ics.ics), 204	SERDESPOC_SETTINGS_MODE_DISABLED (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_RGB666 (in module ics.ics), 204	SERDESPOC_SETTINGS_MODE_SERIALIZER (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_RGB888 (in module ics.ics), 204	SERDESPOC_SETTINGS_MODE_SUPPLY (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_UYVY_422_10LE_PACKED (in module ics.ics), 205	SERDESPOC_SETTINGS_SIZE (in module ics.ics), 205
SERDESCAM_VIDEO_FORMAT_UYVY_422_12LE_PACKED (in module ics.ics), 205	SerialNumber (ics.ics.NeoDevice attribute), 18
SERDESCAM_VIDEO_FORMAT_UYVY_422_8 (in module ics.ics), 205	SetDeviceIpAddress (ics.structures.start_dhcp_server_command.start_dhcp_server_command attribute), 181
SERDESCAM_VIDEO_FORMAT_VYUY_422_10LE_PACKED (in module ics.ics), 205	set_active_vnet_channel() (in module ics.ics), 54
SERDESCAM_VIDEO_FORMAT_VYUY_422_12LE_PACKED (in module ics.ics), 205	set_backup_power_enabled() (in module ics.ics), 54
SERDESCAM_VIDEO_FORMAT_VYUY_422_8 (in module ics.ics), 205	set_bit_rate() (in module ics.ics), 54
SERDESCAM_VIDEO_FORMAT_YUV422_10LE_PLANAR (in module ics.ics), 205	set_bit_rate_ex() (in module ics.ics), 55
SERDESCAM_VIDEO_FORMAT_YUV422_16LE_PLANAR (in module ics.ics), 205	set_context() (in module ics.ics), 55
SERDESCAM_VIDEO_FORMAT_YUYV_422_10LE_PACKED (in module ics.ics), 205	set_device_settings() (in module ics.ics), 55
SERDESCAM_VIDEO_FORMAT_YUYV_422_12LE_PACKED (in module ics.ics), 205	set_fd_bit_rate() (in module ics.ics), 55
SERDESCAM_VIDEO_FORMAT_YUYV_422_8 (in module ics.ics), 205	set_led_property() (in module ics.ics), 56
	set_reflash_callback() (in module ics.ics), 56
	set_rtc() (in module ics.ics), 56
	SetActiveVNETChannel() (in module ics.ics), 27
	SetBackupPowerEnabled() (in module ics.ics), 27
	SetBaudrate (ics.structures.can_settings.can_settings attribute), 88

SetBaudrate (*ics.structures.swcan_settings.swcan_settings*
 attribute), 187

SetBitRate () (*in module ics.ics*), 28

SetBitRateEx () (*in module ics.ics*), 28

SetContext () (*in module ics.ics*), 28

SetDeviceSettings () (*in module ics.ics*), 28

SetFDBitRate () (*in module ics.ics*), 28

SetLedProperty () (*in module ics.ics*), 28

setLock (*ics.structures.w_bms_manager_set_lock.w_bms_manager_set_lock*
 attribute), 190

SetReflashDisplayCallback () (*in module ics.ics*), 28

SetRTC () (*in module ics.ics*), 28

Settings (*ics.structures.s_device_settings.s_device_settings*
 attribute), 114

settings (*ics.structures.s_disk_structure.s_disk_structure*
 attribute), 115

shared_learn (*ics.structures.s_pluto_l2_address_lookup.s_pluto_l2_address_lookup*
 attribute), 138

sharindx (*ics.structures.s_pluto_l2_policing_s.s_pluto_l2_policing_s*
 attribute), 139

sharindx (*ics.structures.s_pluto_vl_policing_entry_s.s_pluto_vl_policing_entry_s*
 attribute), 142

sievb_settings (class *in ics.structures.sievb_settings*), 150

SLAVE_VNET_A (*in module ics.ics*), 205

SLAVE_VNET_B (*in module ics.ics*), 205

SlaveEnable (*ics.structures.timesync_icshardware_settings.timesync_icshardware_settings*
 attribute), 188

SlaveNetwork (*ics.structures.timesync_icshardware_settings.timesync_icshardware_settings*
 attribute), 188

slaveVnetA (*ics.structures.s_cyan_settings.s_cyan_settings*
 attribute), 114

slaveVnetA (*ics.structures.s_fire3_settings.s_fire3_settings*
 attribute), 121

slaveVnetA (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*
 attribute), 128

slaveVnetB (*ics.structures.s_cyan_settings.s_cyan_settings*
 attribute), 114

slaveVnetB (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*
 attribute), 128

sleep_id (*ics.structures.scan_hub_settings.scan_hub_settings*
 attribute), 146

SLEEP_MODE (*in module ics.ics*), 205

SLOW_MODE (*in module ics.ics*), 205

smax (*ics.structures.s_pluto_l2_policing_s.s_pluto_l2_policing_s*
 attribute), 139

sobd2_lc_settings (class *in ics.structures.sobd2_lc_settings*), 152

sobd2_pro_settings (class *in ics.structures.sobd2_pro_settings*), 153

sobd2_sim_settings (class *in ics.structures.sobd2_sim_settings*), 155

software_update_command (class *in ics.structures.software_update_command*), 155

spbrg (*ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings*
 attribute), 108

spbrg (*ics.structures.lin_settings.lin_settings* *attribute*), 108

spbrg (*ics.structures.uart_settings.uart_settings* *attribute*), 189

spbrg (*ics.structures.s_pluto_custom_params_s.s_pluto_custom_params_s*
 attribute), 136

speed (*ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s*
 attribute), 140

speed (*ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings*
 attribute), 158

spi_config (*ics.structures.sradbms_settings.sradbms_settings*
 attribute), 176

SPI_PORT_EXTERNAL (*in module ics.ics*), 205

SPI_PORT_SONBOARD (*in module ics.ics*), 205

spoofedMac (*ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings*
 attribute), 158

spoofedMac (*ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings*
 attribute), 169

spoofMacFlag (*ics.structures.srad_epsilon_switch_settings.srad_epsilon_switch_settings*
 attribute), 158

spoofMacFlag (*ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings*
 attribute), 169

spy_filter_long (class *in ics.structures.spy_filter_long*), 156

SPY_PROTOCOL_A2B (*in module ics.ics*), 205

SPY_PROTOCOL_BEAN (*in module ics.ics*), 205

SPY_PROTOCOL_CAN (*in module ics.ics*), 205

SPY_PROTOCOL_CANFD (*in module ics.ics*), 205

SPY_PROTOCOL_CGI (*in module ics.ics*), 205

SPY_PROTOCOL_CHRYSLER_CCD (*in module ics.ics*), 205

SPY_PROTOCOL_CHRYSLER_JVPW (*in module ics.ics*), 205

SPY_PROTOCOL_CHRYSLER_SCI (*in module ics.ics*), 206

SPY_PROTOCOL_CUSTOM (*in module ics.ics*), 206

SPY_PROTOCOL_DALLAS_1WIRE (*in module ics.ics*), 206

SPY_PROTOCOL_ETHERNET (*in module ics.ics*), 206

SPY_PROTOCOL_FLEXRAY (*in module ics.ics*), 206

SPY_PROTOCOL_FORD_UBP (*in module ics.ics*), 206

SPY_PROTOCOL_GENERIC_MANCHSESTER (*in module ics.ics*), 206

SPY_PROTOCOL_GENERIC_UART (*in module ics.ics*), 206

SPY_PROTOCOL_GM_ALDL_UART (*in module ics.ics*), 206

SPY_PROTOCOL_GME_CIM_SCL_KLINE (*in module ics.ics*), 206

SPY_PROTOCOL_GMFSA (in module ics.ics), 206
 SPY_PROTOCOL_GMLAN (in module ics.ics), 206
 SPY_PROTOCOL_I2C (in module ics.ics), 206
 SPY_PROTOCOL_ISO9141 (in module ics.ics), 206
 SPY_PROTOCOL_J1708 (in module ics.ics), 206
 SPY_PROTOCOL_J1850PWM (in module ics.ics), 206
 SPY_PROTOCOL_J1850VPW (in module ics.ics), 206
 SPY_PROTOCOL_J1939 (in module ics.ics), 206
 SPY_PROTOCOL_JTAG (in module ics.ics), 206
 SPY_PROTOCOL_LIN (in module ics.ics), 206
 SPY_PROTOCOL_MOST (in module ics.ics), 206
 SPY_PROTOCOL_SENT_PROTOCOL (in module ics.ics), 206
 SPY_PROTOCOL_SPI (in module ics.ics), 206
 SPY_PROTOCOL_TCP (in module ics.ics), 206
 SPY_PROTOCOL_UART (in module ics.ics), 206
 SPY_PROTOCOL_UDP (in module ics.ics), 206
 SPY_PROTOCOL_UNIO (in module ics.ics), 206
 SPY_PROTOCOL_WBMS (in module ics.ics), 206
 SPY_STATUS2_CAN_HAVE_LINK_DATA (in module ics.ics), 206
 SPY_STATUS2_CAN_ISO15765_LOGICAL_FRAME (in module ics.ics), 206
 SPY_STATUS2_END_OF_LONG_MESSAGE (in module ics.ics), 206
 SPY_STATUS2_ERROR_FRAME (in module ics.ics), 206
 SPY_STATUS2_ETHERNET_CRC_ERROR (in module ics.ics), 206
 SPY_STATUS2_ETHERNET_FCS_VERIFIED (in module ics.ics), 206
 SPY_STATUS2_ETHERNET_FRAME_TOO_SHORT (in module ics.ics), 206
 SPY_STATUS2_ETHERNET_MANUALFCS_ENABLED (in module ics.ics), 206
 SPY_STATUS2_ETHERNET_NO_PADDING (in module ics.ics), 207
 SPY_STATUS2_ETHERNET_PREEMPTION_ENABLED (in module ics.ics), 207
 SPY_STATUS2_ETHERNET_UPDATE_CHECKSUMS (in module ics.ics), 207
 SPY_STATUS2_FLEXRAY_NO_CRC (in module ics.ics), 207
 SPY_STATUS2_FLEXRAY_NO_HEADERCRC (in module ics.ics), 207
 SPY_STATUS2_FLEXRAY_TX_AB (in module ics.ics), 207
 SPY_STATUS2_FLEXRAY_TX_AB_NO_A (in module ics.ics), 207
 SPY_STATUS2_FLEXRAY_TX_AB_NO_B (in module ics.ics), 207
 SPY_STATUS2_FLEXRAY_TX_AB_NO_MATCH (in module ics.ics), 207
 SPY_STATUS2_GLOBAL_CHANGE (in module ics.ics), 207
 SPY_STATUS2_HAS_VALUE (in module ics.ics), 207
 SPY_STATUS2_HIGH_VOLTAGE (in module ics.ics), 207
 SPY_STATUS2_I2C_DIR_READ (in module ics.ics), 207
 SPY_STATUS2_I2C_ERR_NACK (in module ics.ics), 207
 SPY_STATUS2_I2C_ERR_TIMEOUT (in module ics.ics), 207
 SPY_STATUS2_I2C_NODE_FAULT (in module ics.ics), 207
 SPY_STATUS2_ISO_FRAME_ERROR (in module ics.ics), 207
 SPY_STATUS2_ISO_OVERFLOW_ERROR (in module ics.ics), 207
 SPY_STATUS2_ISO_PARITY_ERROR (in module ics.ics), 207
 SPY_STATUS2_LIN_ERR_MSG_ID_PARITY (in module ics.ics), 207
 SPY_STATUS2_LIN_ERR_RX_BREAK_NOT_0 (in module ics.ics), 207
 SPY_STATUS2_LIN_ERR_RX_BREAK_TOO_SHORT (in module ics.ics), 207
 SPY_STATUS2_LIN_ERR_RX_DATA_GREATER_8 (in module ics.ics), 207
 SPY_STATUS2_LIN_ERR_RX_SYNC_NOT_55 (in module ics.ics), 207
 SPY_STATUS2_LIN_ERR_TX_RX_MISMATCH (in module ics.ics), 207
 SPY_STATUS2_LIN_ID_FRAME_ERROR (in module ics.ics), 207
 SPY_STATUS2_LIN_NO_SLAVE_DATA (in module ics.ics), 207
 SPY_STATUS2_LIN_SLAVE_BYTE_ERROR (in module ics.ics), 207
 SPY_STATUS2_LIN_SYNC_FRAME_ERROR (in module ics.ics), 207
 SPY_STATUS2_LONG_MESSAGE (in module ics.ics), 207
 SPY_STATUS2_MOST_CHANGED_PAR (in module ics.ics), 207
 SPY_STATUS2_MOST_CONTROL_DATA (in module ics.ics), 207
 SPY_STATUS2_MOST_I2S_DUMP (in module ics.ics), 207
 SPY_STATUS2_MOST_LOW_LEVEL (in module ics.ics), 207
 SPY_STATUS2_MOST_MHP_CONTROL_DATA (in module ics.ics), 207
 SPY_STATUS2_MOST_MHP_USER_DATA (in module ics.ics), 207
 SPY_STATUS2_MOST_MOST150 (in module ics.ics), 208

SPY_STATUS2_MOST_MOST50 (in module *ics.ics*), 208
 SPY_STATUS2_MOST_PACKET_DATA (in module *ics.ics*), 208
 SPY_STATUS2_MOST_STATUS (in module *ics.ics*), 208
 SPY_STATUS2_MOST_TOO_SHORT (in module *ics.ics*), 208
 SPY_STATUS2_RX_TIMEOUT_ERROR (in module *ics.ics*), 208
 SPY_STATUS2_VALUE_IS_BOOLEAN (in module *ics.ics*), 208
 SPY_STATUS2_WBMS_NODE_DISCONNECTED (in module *ics.ics*), 208
 SPY_STATUS3_CANFD_BRS (in module *ics.ics*), 208
 SPY_STATUS3_CANFD_ESI (in module *ics.ics*), 208
 SPY_STATUS3_CANFD_FDF (in module *ics.ics*), 208
 SPY_STATUS3_CANFD_IDE (in module *ics.ics*), 208
 SPY_STATUS3_CANFD_RTR (in module *ics.ics*), 208
 SPY_STATUS3_LIN_JUST_BREAK_SYNC (in module *ics.ics*), 208
 SPY_STATUS3_LIN_ONLY_UPDATE_SLAVE_TABLE_ONCE (in module *ics.ics*), 208
 SPY_STATUS3_LIN_SLAVE_DATA_TOO_SHORT (in module *ics.ics*), 208
 SPY_STATUS_A2B_CONTROL (in module *ics.ics*), 208
 SPY_STATUS_A2B_MONITOR (in module *ics.ics*), 208
 SPY_STATUS_A2B_SCF_VALID_WAITING (in module *ics.ics*), 208
 SPY_STATUS_A2B_UPSTREAM (in module *ics.ics*), 208
 SPY_STATUS_ANALOG_DIGITAL_INPUT (in module *ics.ics*), 208
 SPY_STATUS_AUDIO_COMMENT (in module *ics.ics*), 208
 SPY_STATUS_AVSI_REC_OVERFLOW (in module *ics.ics*), 208
 SPY_STATUS_BAD_MESSAGE_BIT_TIME_ERROR (in module *ics.ics*), 208
 SPY_STATUS_BREAK (in module *ics.ics*), 208
 SPY_STATUS_BUS_RECOVERED (in module *ics.ics*), 208
 SPY_STATUS_BUS_SHORTED_GND (in module *ics.ics*), 208
 SPY_STATUS_BUS_SHORTED_PLUS (in module *ics.ics*), 208
 SPY_STATUS_CAN_BUS_OFF (in module *ics.ics*), 208
 SPY_STATUS_CAN_ERROR_PASSIVE (in module *ics.ics*), 208
 SPY_STATUS_CANFD (in module *ics.ics*), 208
 SPY_STATUS_CHECKSUM_ERROR (in module *ics.ics*), 208
 SPY_STATUS_COMM_IN_OVERFLOW (in module *ics.ics*), 208
 SPY_STATUS_CRC_ERROR (in module *ics.ics*), 208
 SPY_STATUS_EXPECTED_LEN_MISMATCH (in module *ics.ics*), 208
 SPY_STATUS_EXTENDED (in module *ics.ics*), 208
 SPY_STATUS_FLEXRAY_PDU (in module *ics.ics*), 209
 SPY_STATUS_FLEXRAY_PDU_NO_UPDATE_BIT (in module *ics.ics*), 209
 SPY_STATUS_FLEXRAY_PDU_UPDATE_BIT_SET (in module *ics.ics*), 209
 SPY_STATUS_GLOBAL_ERR (in module *ics.ics*), 209
 SPY_STATUS_GPS_DATA (in module *ics.ics*), 209
 SPY_STATUS_HEADERCRC_ERROR (in module *ics.ics*), 209
 SPY_STATUS_HIGH_SPEED (in module *ics.ics*), 209
 SPY_STATUS_INCOMPLETE_FRAME (in module *ics.ics*), 209
 SPY_STATUS_INIT_MESSAGE (in module *ics.ics*), 209
 SPY_STATUS_LIN_MASTER (in module *ics.ics*), 209
 SPY_STATUS_LOST_ARBITRATION (in module *ics.ics*), 209
 SPY_STATUS_MSG_NO_MATCH (in module *ics.ics*), 209
 SPY_STATUS_NETWORK_MESSAGE_TYPE (in module *ics.ics*), 209
 SPY_STATUS_PDU (in module *ics.ics*), 209
 SPY_STATUS_REMOTE_FRAME (in module *ics.ics*), 209
 SPY_STATUS_TEST_TRIGGER (in module *ics.ics*), 209
 SPY_STATUS_TEXT_COMMENT (in module *ics.ics*), 209
 SPY_STATUS_TX_MSG (in module *ics.ics*), 209
 SPY_STATUS_TX_NOMATCH (in module *ics.ics*), 209
 SPY_STATUS_UNDEFINED_ERROR (in module *ics.ics*), 209
 SPY_STATUS_VSI_IFR_CRC_BIT (in module *ics.ics*), 209
 SPY_STATUS_VSI_TX_UNDERRUN (in module *ics.ics*), 209
 SPY_STATUS_XTD_FRAME (in module *ics.ics*), 209
 SpyMessage (class in *ics.ics*), 18
 SpyMessageJ1850 (class in *ics.ics*), 19
 srاد_epsilon_settings (class in *ics.structures.srad_epsilon_settings*), 157
 srاد_epsilon_switch_settings (class in *ics.structures.srad_epsilon_switch_settings*), 158
 srاد_galaxy_settings (class in *ics.structures.srad_galaxy_settings*), 158
 srاد_gigalog_settings (class in *ics.structures.srad_gigalog_settings*), 161
 srاد_gigastar_settings (class in *ics.structures.srad_gigastar_settings*), 164

srاد_gptp_and_tap_settings_s (class in *ics.structures.srad_gptp_and_tap_settings_s*), 166
 srاد_gptp_settings_s (class in *ics.structures.srad_gptp_settings_s*), 166
 srاد_jupiter_settings (class in *ics.structures.srad_jupiter_settings*), 167
 srاد_jupiter_switch_settings (class in *ics.structures.srad_jupiter_switch_settings*), 168
 srاد_moon2_settings (class in *ics.structures.srad_moon2_settings*), 169
 srاد_moon3_settings (class in *ics.structures.srad_moon3_settings*), 170
 srاد_pluto_settings (class in *ics.structures.srad_pluto_settings*), 170
 srاد_star2_settings (class in *ics.structures.srad_star2_settings*), 171
 srاد_super_moon_settings (class in *ics.structures.srad_super_moon_settings*), 173
 srاد2_b_settings (class in *ics.structures.srad2_b_settings*), 174
 sradbms_settings (class in *ics.structures.sradbms_settings*), 175
 srcmeta (*ics.structures.s_pluto_avb_params.s.s_pluto_avb_params* attribute), 134
 srcport (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params* attribute), 135
 st_api_firmware_info (class in *ics.structures.st_api_firmware_info*), 176
 st_chip_versions (class in *ics.structures.st_chip_versions*), 177
 st_cm_iso157652_rx_message (class in *ics.structures.st_cm_iso157652_rx_message*), 179
 st_cm_iso157652_tx_message (class in *ics.structures.st_cm_iso157652_tx_message*), 180
 stabasyen (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params* attribute), 135
 start_dhcp_server () (in module *ics.ics*), 56
 start_dhcp_server_command (class in *ics.structures.start_dhcp_server_command*), 181
 startAddress (*ics.structures.start_dhcp_server_command.start_dhcp_server_command* attribute), 181
 StartDHCPServer () (in module *ics.ics*), 29
 startup (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray* attribute), 103
 state (*ics.structures.s_disk_format_progress.s_disk_format_progress* attribute), 115
 status (*ics.structures.s_disk_details.s_disk_details* attribute), 115
 status (*ics.structures.s_disk_status.s_disk_status* attribute), 115
 status (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt* attribute), 132
 Status2Mask (*ics.structures.spy_filter_long.spy_filter_long* attribute), 156
 Status2Value (*ics.structures.spy_filter_long.spy_filter_long* attribute), 156
 StatusBitField (*ics.ics.SpyMessage* attribute), 19
 StatusBitField (*ics.ics.SpyMessageJ1850* attribute), 20
 StatusBitField (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray* attribute), 102
 StatusBitField (*ics.structures.ics_spy_message_long.ics_spy_message_long* attribute), 104
 StatusBitField (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb* attribute), 105
 StatusBitField2 (*ics.ics.SpyMessage* attribute), 19
 StatusBitField2 (*ics.ics.SpyMessageJ1850* attribute), 20
 StatusBitField2 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray* attribute), 102
 StatusBitField2 (*ics.structures.ics_spy_message_long.ics_spy_message_long* attribute), 104
 StatusBitField2 (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb* attribute), 105
 StatusBitField3 (*ics.ics.SpyMessage* attribute), 19
 StatusBitField3 (*ics.ics.SpyMessageJ1850* attribute), 20
 StatusBitField3 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray* attribute), 102
 StatusBitField3 (*ics.structures.ics_spy_message_long.ics_spy_message_long* attribute), 104
 StatusBitField3 (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb* attribute), 105
 StatusBitField4 (*ics.ics.SpyMessage* attribute), 19
 StatusBitField4 (*ics.ics.SpyMessageJ1850* attribute), 20
 StatusBitField4 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray* attribute), 102
 StatusBitField4 (*ics.structures.ics_spy_message_long.ics_spy_message_long* attribute), 104
 StatusBitField4 (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb* attribute), 105
 StatusMask (*ics.structures.spy_filter_long.spy_filter_long* attribute), 156
 StatusValue (*ics.structures.spy_filter_long.spy_filter_long* attribute), 157
 stMax (*ics.structures.priority_vector.priority_vector* attribute), 110
 stMin (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message* attribute), 107
 stMin (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message* attribute), 180

`stMin` (`ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message` attribute), 181
`stop_bits` (`ics.structures.uart_settings.uart_settings` attribute), 189
`stop_dhcp_server()` (in module `ics.ics`), 57
`stop_dhcp_server_command` (class in `ics.structures.stop_dhcp_server_command`), 181
`StopDHCPServer()` (in module `ics.ics`), 29
`structure` (`ics.structures.s_disk_details.s_disk_details` attribute), 115
`stth` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 135
`sttointh` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 135
`subnetMask` (`ics.structures.start_dhcp_server_command.start_dhcp_server_command` attribute), 181
`supportedFeatureMax` (`ics.structures.device_feature.device_feature` attribute), 90
`svcan3_settings` (class in `ics.structures.svcan3_settings`), 182
`svcan412_settings` (class in `ics.structures.svcan412_settings`), 182
`svcan4_ind_settings` (class in `ics.structures.svcan4_ind_settings`), 183
`svcan4_settings` (class in `ics.structures.svcan4_settings`), 184
`svcanrf_settings` (class in `ics.structures.svcanrf_settings`), 185
`swcan` (`ics.structures.s_fire_settings.s_fire_settings` attribute), 124
`swcan` (`ics.structures.s_fire_vnet_settings.s_fire_vnet_settings` attribute), 126
`swcan` (`ics.structures.s_pendant_settings.s_pendant_settings` attribute), 132
`swcan` (`ics.structures.secu_settings.secu_settings` attribute), 148
`swcan1` (`ics.structures.s_cyan_settings.s_cyan_settings` attribute), 114
`swcan1` (`ics.structures.s_fire3_settings.s_fire3_settings` attribute), 121
`swcan1` (`ics.structures.s_neo_ecul2_settings.s_neo_ecul2_settings` attribute), 130
`swcan1` (`ics.structures.s_vivid_can_settings.s_vivid_can_settings` attribute), 145
`swcan1` (`ics.structures.sobd2_lc_settings.sobd2_lc_settings` attribute), 153
`swcan1` (`ics.structures.sobd2_pro_settings.sobd2_pro_settings` attribute), 154
`swcan1` (`ics.structures.srad_galaxy_settings.srad_galaxy_settings` attribute), 161
`swcan2` (`ics.structures.s_cyan_settings.s_cyan_settings` attribute), 114
`swcan2` (`ics.structures.s_fire_vnet_settings.s_fire_vnet_settings` attribute), 126
`swcan2` (`ics.structures.s_neo_ecul2_settings.s_neo_ecul2_settings` attribute), 130
`swcan2` (`ics.structures.s_pendant_settings.s_pendant_settings` attribute), 132
`swcan2` (`ics.structures.secu_settings.secu_settings` attribute), 148
`swcan2` (`ics.structures.srad_galaxy_settings.srad_galaxy_settings` attribute), 161
`SWCAN_AUTOSWITCH_DISABLED` (in module `ics.ics`), 209
`SWCAN_AUTOSWITCH_DISABLED_RESISTOR_ENABLED` (in module `ics.ics`), 209
`SWCAN_AUTOSWITCH_NO_RESISTOR` (in module `ics.ics`), 209
`SWCAN_AUTOSWITCH_WITH_RESISTOR` (in module `ics.ics`), 209
`swcan_settings` (class in `ics.structures.swcan_settings`), 186
`SWCAN_SETTINGS_SIZE` (in module `ics.ics`), 209
`switchid` (`ics.structures.s_pluto_general_params.s.s_pluto_general_params` attribute), 137
`switchSettings` (`ics.structures.srad_epsilon_settings.srad_epsilon_settings` attribute), 158
`switchSettings` (`ics.structures.srad_jupiter_settings.srad_jupiter_settings` attribute), 168
`swmaster` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 135
`syasyen` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 135
`sydomain` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 135
`sync` (`ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray` attribute), 103
`sypriority` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 135
`syrelen` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 135
`sys_phc_sync_interval` (`ics.structures.srad_gptp_settings.srad_gptp_settings` attribute), 167
`sysid` (`ics.structures.priority_vector.priority_vector` attribute), 110
`system_identity` (class in `ics.structures.system_identity`), 187
`sysyen` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 135
`syth` (`ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params` attribute), 135

attribute), 135
 systostben (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s
 attribute), 135
 systousyth (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s
 attribute), 135
T
 tag_options_find_neo_ex (class in termination_enables
 ics.structures.tag_options_find_neo_ex),
 187
 tag_options_open_neo_ex (class in termination_enables
 ics.structures.tag_options_open_neo_ex),
 187
 tag_port (ics.structures.s_pluto_vlan_lookup.s.s_pluto_vlan_lookup
 attribute), 143
 tagicsneo_vi_command (class in termination_enables
 ics.structures.tagicsneo_vi_command), 188
 tap (ics.structures.srad_gtp_and_tap_settings.srad_gtp_and_tap_settings
 attribute), 166
 tapPair0 (ics.structures.op_eth_general_settings.op_eth_general_settings
 attribute), 109
 tapPair1 (ics.structures.op_eth_general_settings.op_eth_general_settings
 attribute), 109
 tapPair2 (ics.structures.op_eth_general_settings.op_eth_general_settings
 attribute), 109
 tapPair3 (ics.structures.op_eth_general_settings.op_eth_general_settings
 attribute), 109
 tapPair4 (ics.structures.op_eth_general_settings.op_eth_general_settings
 attribute), 109
 tapPair5 (ics.structures.op_eth_general_settings.op_eth_general_settings
 attribute), 109
 tdmMode (ics.structures.a2_b_monitor_settings.a2_b_monitor_settings
 attribute), 87
 tdmModeTDM12 (ics.structures.a2_btdm_mode.a2_btdm_mode
 attribute), 87
 tdmModeTDM16 (ics.structures.a2_btdm_mode.a2_btdm_mode
 attribute), 87
 tdmModeTDM2 (ics.structures.a2_btdm_mode.a2_btdm_mode
 attribute), 87
 tdmModeTDM20 (ics.structures.a2_btdm_mode.a2_btdm_mode
 attribute), 88
 tdmModeTDM24 (ics.structures.a2_btdm_mode.a2_btdm_mode
 attribute), 88
 tdmModeTDM32 (ics.structures.a2_btdm_mode.a2_btdm_mode
 attribute), 88
 tdmModeTDM4 (ics.structures.a2_btdm_mode.a2_btdm_mode
 attribute), 88
 tdmModeTDM8 (ics.structures.a2_btdm_mode.a2_btdm_mode
 attribute), 88
 temp_interval_ms (ics.structures.rad_reporting_settings.rad_reporting_settings
 attribute), 111
 tentsyrelen (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s
 attribute), 135
 term_enabled (ics.structures.canterm_settings.canterm_settings
 attribute), 80
 term_network (ics.structures.canterm_settings.canterm_settings
 attribute), 80
 termination_enables
 (ics.structures.s_cyan_settings.s_cyan_settings
 attribute), 114
 (ics.structures.s_ether_badge_settings.s_ether_badge_settings
 attribute), 116
 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings
 attribute), 128
 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
 attribute), 130
 (ics.structures.s_vivid_can_settings.s_vivid_can_settings
 attribute), 145
 (ics.structures.scan_hub_settings.scan_hub_settings
 attribute), 146
 (ics.structures.secu_avb_settings.secu_avb_settings
 attribute), 147
 (ics.structures.srad_epsilon_settings.srad_epsilon_settings
 attribute), 158
 (ics.structures.srad_gigalog_settings.srad_gigalog_settings
 attribute), 164
 (ics.structures.srad_gigastar_settings.srad_gigastar_settings
 attribute), 166
 (ics.structures.srad_jupiter_settings.srad_jupiter_settings
 attribute), 168
 (ics.structures.srad_pluto_settings.srad_pluto_settings
 attribute), 171
 (ics.structures.srada2_b_settings.srada2_b_settings
 attribute), 175
 (ics.structures.sradbms_settings.sradbms_settings
 attribute), 176
 (ics.structures.svcan412_settings.svcan412_settings
 attribute), 183
 (ics.structures.svcan4_ind_settings.svcan4_ind_settings
 attribute), 184
 (ics.structures.svcan4_settings.svcan4_settings
 attribute), 184

attribute), 185
 termination_enables_1
 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 121
 termination_enables_2
 (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 121
 text_api (ics.structures.s_cyan_settings.s_cyan_settings
 attribute), 114
 text_api (ics.structures.s_ether_badge_settings.s_ether_badge_settings
 attribute), 117
 text_api (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 122
 text_api (ics.structures.s_fire_settings.s_fire_settings
 attribute), 124
 text_api (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
 attribute), 126
 text_api (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings
 attribute), 128
 text_api (ics.structures.s_neo_ecul2_settings.s_neo_ecul2_settings
 attribute), 130
 text_api (ics.structures.s_pendant_settings.s_pendant_settings
 attribute), 132
 text_api (ics.structures.secu_avb_settings.secu_avb_settings
 attribute), 147
 text_api (ics.structures.secu_settings.secu_settings
 attribute), 148
 text_api (ics.structures.sievb_settings.sievb_settings
 attribute), 152
 text_api (ics.structures.sobd2_lc_settings.sobd2_lc_settings
 attribute), 153
 text_api (ics.structures.sobd2_pro_settings.sobd2_pro_settings
 attribute), 154
 text_api (ics.structures.sobd2_sim_settings.sobd2_sim_settings
 attribute), 155
 text_api (ics.structures.srad_epsilon_settings.srad_epsilon_settings
 attribute), 158
 text_api (ics.structures.srad_galaxy_settings.srad_galaxy_settings
 attribute), 161
 text_api (ics.structures.srad_gigalog_settings.srad_gigalog_settings
 attribute), 164
 text_api (ics.structures.srad_gigastar_settings.srad_gigastar_settings
 attribute), 166
 text_api (ics.structures.srad_jupiter_settings.srad_jupiter_settings
 attribute), 168
 text_api (ics.structures.srad_moon2_settings.srad_moon2_settings
 attribute), 170
 text_api (ics.structures.srad_pluto_settings.srad_pluto_settings
 attribute), 171
 text_api (ics.structures.srad_star2_settings.srad_star2_settings
 attribute), 173
 text_api (ics.structures.srad_super_moon_settings.srad_super_moon_settings
 attribute), 174
 text_api (ics.structures.svcan412_settings.svcan412_settings
 attribute), 183
 text_api (ics.structures.svcan4_settings.svcan4_settings
 attribute), 185
 time_500us (ics.structures.iso9141_keyword2000_init_step.iso9141_key
 attribute), 107
 TimeHardware (ics.ics.SpyMessage attribute), 19
 TimeHardware (ics.ics.SpyMessageJ1850 attribute),
 20
 TimeHardware (ics.structures.ics_spy_message_flex_ray.ics_spy_messag
 attribute), 102
 TimeHardware (ics.structures.ics_spy_message_long.ics_spy_message_l
 attribute), 104
 TimeHardware (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
 attribute), 105
 TimeHardware2 (ics.ics.SpyMessage attribute), 19
 TimeHardware2 (ics.ics.SpyMessageJ1850 attribute),
 20
 TimeHardware2 (ics.structures.ics_spy_message_flex_ray.ics_spy_messag
 attribute), 102
 TimeHardware2 (ics.structures.ics_spy_message_long.ics_spy_message_l
 attribute), 104
 TimeHardware2 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
 attribute), 105
 timestamp_ (class in ics.structures.timestamp_), 188
 TimestampHardwareID (ics.ics.SpyMessage attribute), 19
 TimestampHardwareID (ics.ics.SpyMessageJ1850
 attribute), 20
 TimestampHardwareID
 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_r
 attribute), 102
 TimestampHardwareID
 (ics.structures.ics_spy_message_long.ics_spy_message_long
 attribute), 104
 TimestampHardwareID
 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
 attribute), 105
 TimestampSystemID (ics.ics.SpyMessage attribute),
 19
 TimestampSystemID (ics.ics.SpyMessageJ1850 attribute), 20
 TimestampSystemID
 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_r
 attribute), 102
 TimestampSystemID
 (ics.structures.ics_spy_message_long.ics_spy_message_long
 attribute), 104
 TimestampSystemID
 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
 attribute), 106
 timeSync (ics.structures.s_cyan_settings.s_cyan_settings
 attribute), 114
 timeSync (ics.structures.s_fire3_settings.s_fire3_settings
 attribute), 122

timeSync (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 187

timesync_icshardware_settings (class in ics.structures.timesync_icshardware_settings), 188

TIMESYNC_ICSHARDWARE_SETTINGS_SIZE (in module ics.ics), 209

timeSyncSettings (ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute), 161

timeSyncSettings (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 164

timeSyncSettings (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 166

timeSyncSettings (ics.structures.srad_moon2_settings.srad_moon2_settings attribute), 170

timeSyncSettings (ics.structures.srad_star2_settings.srad_star2_settings attribute), 173

timeSyncSettings (ics.structures.srad_super_moon_settings.srad_super_moon_settings attribute), 174

timeSyncSettings (ics.structures.srada2_b_settings.srada2_b_settings attribute), 175

TimeSystem (ics.ics.SpyMessage attribute), 19

TimeSystem (ics.ics.SpyMessageJ1850 attribute), 20

TimeSystem (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex attribute), 102

TimeSystem (ics.structures.ics_spy_message_long.ics_spy_message attribute), 104

TimeSystem (ics.structures.ics_spy_message_vsb.ics_spy_message attribute), 106

TimeSystem2 (ics.ics.SpyMessage attribute), 19

TimeSystem2 (ics.ics.SpyMessageJ1850 attribute), 20

TimeSystem2 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex attribute), 102

TimeSystem2 (ics.structures.ics_spy_message_long.ics_spy_message attribute), 104

TimeSystem2 (ics.structures.ics_spy_message_vsb.ics_spy_message attribute), 106

top (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute), 140

tp_delin (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute), 140

tp_delout (ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute), 140

tpid (ics.structures.s_pluto_general_params_s.s_pluto_general_params_s attribute), 137

tpid2 (ics.structures.s_pluto_general_params_s.s_pluto_general_params_s attribute), 137

TqProp (ics.structures.can_settings.can_settings attribute), 88

TqProp (ics.structures.swcan_settings.swcan_settings attribute), 187

TqSeg1 (ics.structures.can_settings.can_settings attribute), 88

TqSeg1 (ics.structures.swcan_settings.swcan_settings attribute), 187

TqSeg2 (ics.structures.can_settings.can_settings attribute), 88

TqSeg2 (ics.structures.swcan_settings.swcan_settings attribute), 187

TqSync (ics.structures.can_settings.can_settings attribute), 88

tx_dl (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 181

tx_dl (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 181

tx_index (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 181

tx_index (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 181

tx_speed (ics.structures.serdesgen_settings.serdesgen_settings attribute), 151

TxMessages () (in module ics.ics), 29

u (ics.structures.s_pluto_vl_forwarding_entry_s.s_pluto_vl_forwarding_entry_s attribute), 142

uart (ics.structures.sievb_settings.sievb_settings attribute), 152

uart2 (ics.structures.s_fire_settings.s_fire_settings attribute), 124

uart2 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 127

vividcan_versions (ics.structures.st_chip_versions.st_chip_versions attribute), 179

vividcan_versions (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652 attribute), 180

vividcan_versions (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652 attribute), 181

vlan_bc (ics.structures.s_pluto_vlan_lookup.s.s_pluto_vlan_lookup attribute), 143

vlan_egr (ics.structures.s_pluto_retagging_entry.s.s_pluto_retagging_entry_s attribute), 141

vlan_ing (ics.structures.s_pluto_retagging_entry.s.s_pluto_retagging_entry_s attribute), 141

vlan_LookupEntries (ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute), 142

vlan_pmap (ics.structures.s_pluto_l2_forwarding_entry.s.s_pluto_l2_forwarding_entry attribute), 138

vlanID (ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_l2_address_lookup_entry attribute), 138

vlanid (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config_wil_1 (ics.structures.sradbms_settings.sradbms_settings attribute), 140

vlanid (ics.structures.s_pluto_vlan_lookup.s.s_pluto_vlan_lookup_wil_2 (ics.structures.sradbms_settings.sradbms_settings attribute), 143

vlanprio (ics.structures.s_pluto_mac_config.s.s_pluto_mac_config_wil_fault_servicing (ics.structures.s_wil_fault_servicing_settings.s_wil_fault_servicing attribute), 140

vldimnmin (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 136

vldinmax (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 136

vldout (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 136

vldselect (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 136

vllupformat (ics.structures.s_pluto_general_params.s.s_pluto_general_params attribute), 137

vllupformat0 (ics.structures.s_pluto_vl_lookup_entry.s.s_pluto_vl_lookup_entry attribute), 142

vllupformat1 (ics.structures.s_pluto_vl_lookup_entry.s.s_pluto_vl_lookup_entry attribute), 142

vlmarker (ics.structures.s_pluto_general_params.s.s_pluto_general_params attribute), 137

vlmask (ics.structures.s_pluto_general_params.s.s_pluto_general_params attribute), 137

vmemb_port (ics.structures.s_pluto_vlan_lookup.s.s_pluto_vlan_lookup attribute), 143

vnetBits (ics.structures.s_fire_settings.s_fire_settings attribute), 124

vnetBits (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 127

VNETBITS_FEATURE_ANDROID_MSGS (in module ics.ics), 209

VNETBITS_FEATURE_DISABLE_USB_CHECK (in module ics.ics), 209

voltage (ics.structures.serdespoc_settings.serdespoc_settings attribute), 150

vs_netid (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 107

vs_netid (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652 attribute), 180

vs_netid (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652 attribute), 181

W

w_bms_manager_reset (class in ics.structures.w_bms_manager_reset), 190

w_bms_manager_set_lock (class in ics.structures.w_bms_manager_set_lock), 190

waitthsync (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 136

wbms_manager_reset () (in module ics.ics), 59

w_bms_manager_set_lock () (in module ics.ics), 59

wil_1 (ics.structures.sradbms_settings.sradbms_settings attribute), 176

wil_2 (ics.structures.sradbms_settings.sradbms_settings attribute), 176

wil_fault_servicing (ics.structures.s_wil_fault_servicing_settings.s_wil_fault_servicing attribute), 146

wBMSManagerReset () (in module ics.ics), 59

wBMSManagerWriteLock () (in module ics.ics), 59

wil_nwk_metadata_buff_count (ics.structures.sradbms_settings.sradbms_settings attribute), 176

wil_nwk_metadata_buff_count (ics.structures.sradbms_settings.sradbms_settings attribute), 176

wil_config (ics.structures.sradbms_settings.sradbms_settings attribute), 176

word (ics.structures.scan_sleep_id.scan_sleep_id attribute), 146

write_jupiter_firmware () (in module ics.ics), 29

write_sdcard () (in module ics.ics), 60

WriteEnable (ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute), 132

WriteJupiterFirmware () (in module ics.ics), 29

WriteSDCard () (in module ics.ics), 30

Z

zero0 (ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway_settings attribute), 130