
python_ics Documentation

Release 904.18

David Rebbe

Jul 19, 2021

Contents

1	Whats New?	3
1.1	ISO 15765-2	3
1.2	Settings	4
1.3	PyInstaller	5
1.4	Other Fixes and Changes	6
2	Versioning Information	7
2.1	v903	7
2.2	Older Versions:	7
3	Installation on Windows	9
3.1	Building from source	9
3.2	Intrepid icsneo40 Library	9
4	Installation on Linux	11
4.1	Fedora Dependencies (FC28)	11
4.2	Debian/Ubuntu Dependencies	11
4.3	Others (Required dependencies)	11
4.4	Installation	11
4.5	Intrepid libicsneoapi.so Library	12
5	Getting Started	13
6	Examples	15
6.1	Opening a device	15
6.2	Transmitting and Receiving a CAN message	15
6.3	ISO 15765-2 Example	15
6.4	Missing an example?	16
7	Module Documentation	17
8	Module Functions	53
9	Module Structures	73
10	Module Variables	161
	Python Module Index	177

Intrepid Control Systems, Inc. open source Python module for interfacing to Intrepid hardware. Basic knowledge of using and installing Python modules is assumed. Please see <https://docs.python.org/3/installing/index.html> for documentation on how to install Python modules.

This module is essentially just a wrapper around icsneo40.dll. For more documentation please visit neoVI DLL Documentation under <https://intrepides.com/support/support-resources/>

CHAPTER 1

Whats New?

v903 is a new release that implements features that break existing API in some areas.

1.1 ISO 15765-2

old naming conventions have been updated to reflect closer to the actual codebase.

```
# Old:  
tx_msg = ics.CmISO157652TxMessage()  
rx_msg = ics.CmISO157652RxMessage()  
  
# New:  
tx_msg = ics.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message()  
rx_msg = ics.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message()
```

ics.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message() data structure is now a ctypes.c_ubyte array instead of a python list.

```
# Old:  
msg.data = [x for x in range(number_of_bytes)]  
  
# New:  
my_data = [x for x in range(number_of_bytes)]  
msg.data = (ctypes.c_ubyte*len(msg.data))(*my_data)  
  
>>> msg.data  
<ics.structures.st_cm_iso157652_tx_message.c_ubyte_Array_4096 object at  
0x0000023E534BE940>
```

1.2 Settings

v903 and up have converted over to a new auto generation of `icsnVC40.h`. This enables faster support for newer Intrepid devices and less error prone. With this switch we have moved to using `ics.s_device_settings`.

```
# Old behavior:  
device = ics.open_device()  
settings = ics.get_device_settings(device)  
# settings is a Vcan3Settings type  
settings.can1.Baudrate = 1  
ics.set_device_settings(device, settings)  
  
# New behavior  
device = ics.open_device()  
settings = ics.get_device_settings(device)  
# settings is a s_device_settings type  
settings.vcan3.can1.Baudrate = 1  
ics.set_device_settings(device, settings)
```

Setting support for the following devices:

- red: `s_red_settings`
- fire: `s_fire_settings`
- firevnet: `s_fire_vnet_settings`
- cyan: `s_cyan_settings` (FIRE2)
- vcan3: `svcn3_settings`
- vcan4: `svcn4_settings`
- ecu: `secu_settings`
- ievb: `sievb_settings`
- pendant: `s_pendant_settings`
- radgalaxy: `srad_galaxy_settings`
- radstar2: `srad_star2_settings`
- neoobd2_sim: `sobd2_sim_settings`
- cmprobe: `s_cm_probe_settings`
- obd2pro: `sobd2_pro_settings`
- vcan412: `svcn412_settings`
- vcan4_12: `svcn412_settings`
- neoezu_avb: `secu_avb_settings`
- radsupermoon: `srad_super_moon_settings`
- radmoon2: `srad_moon2_settings`
- pluto: `srad_pluto_settings`
- plutoswitch: `s_pluto_switch_settings_s`
- radgigalog: `srad_gigalog_settings`
- canhub: `scan_hub_settings`

- neoeclu12: s_neo_ecu12_settings
- vcanrf: svcanrf_settings
- eevb: seevb_settings
- flexvnetz: s_flex_vnetz_settings
- vividcan: s_vivid_can_settings
- vcan4_ind: svcan4_ind_settings
- radgigastar: srad_gigastar_settings
- jupiter: srad_jupiter_settings
- fire3: s_fire3_settings
- radmoon_duo: s_rad_moon_duo_settings

1.3 PyInstaller

Due to the added complexity underneath when building PyInstaller `hidden_imports.py` should be used now in your spec script:

```
# -*- mode: python ; coding: utf-8 -*-

import ics

block_cipher = None

a = Analysis(['test.py'],
             pathex=['.'],
             binaries=[],
             datas=[],
             hiddenimports=ics.hiddenimports.hidden_imports,
             hookspath=[],
             runtime_hooks=[],
             excludes=[],
             win_no_prefer_redirects=False,
             win_private_assemblies=False,
             cipher=block_cipher,
             noarchive=False)
pyz = PYZ(a.pure, a.zipped_data,
          cipher=block_cipher)
exe = EXE(pyz,
          a.scripts,
          [],
          exclude_binaries=True,
          name='test',
          debug=False,
          bootloader_ignore_signals=False,
          strip=False,
          upx=True,
          console=True )
coll = COLLECT(exe,
               a.binaries,
               a.zipfiles,
```

(continues on next page)

(continued from previous page)

```
a.datas,  
strip=False,  
upx=True,  
upx_exclude=[ ],  
name='test')
```

1.4 Other Fixes and Changes

- Expanded documentation.
- Adding support for Python 3.8 and Python 3.9.
- Updated iso15765 example to utilize new flags.
- Updated documentation to mention libicsneolegacy.so
- Fixed an issue when get_messages() timeout was 0 no messages were returned.
- Updated documentation and added use_server option for opening devices.
- Added read_jupiter_firmware and write_jupiter_firmware methods.
- Fixed a memory leak in find_devices()
- Add methods for Gigalog/Gigastar disk formatting
- Fixed a documentation issue per issue #90
- Fixed month being offset by 1 in ics.get_rtc().
- Fixed transmit_messages() to handle extended network ids.
- Fixed code related to meth_get_backup_power_ready() internally.

CHAPTER 2

Versioning Information

Minor differences can occur between different icsnVC40.h versions. These differences are usually just structures and constant differences. Below is a list of how the python_ics version correlates to the icsnVC40.h version:

2.1 v903

Starting with 903, python_ics module will now match official upstream version releases.

```
pip install 'python_ics>=5.0,<904.0' --force-reinstall
```

Note: Refer to platform specific installation if not on Windows

2.2 Older Versions:

- **v802** pip install 'python_ics>=2.0,<3.0' --force-reinstall

Note: Refer to platform specific installation if not on Windows

- **v803** pip install 'python_ics>=3.0,<4.0' --force-reinstall

Note: Refer to platform specific installation if not on Windows

- **v900** pip install 'python_ics>=4.0,<5.0' --force-reinstall

Note: Refer to platform specific installation if not on Windows

CHAPTER 3

Installation on Windows

PyPi provides binary packages for Windows. You can simply install the `python_ics` module by running the following command:

```
pip install python_ics
```

Note: `pip.exe` is usually located under the `Scripts` directory under the Python installation directory.

3.1 Building from source

Building from source on windows is not usually need so it won't really be covered here in detail. As a starting point you'll need to match the compiler version used to build the official Python binaries (MSVC). If the build environment is setup correctly, you should be able to run `python setup.py build` like usual.

3.2 Intrepid icsneo40 Library

`python_ics` module looks for `icsneo40.dll` in the normal windows DLL search paths. The module will throw an exception if its not found.

CHAPTER 4

Installation on Linux

python_ics does not provide binaries for linux distributions so we will have to compile from source. This can be easily achieved by utilizing Python's PIP. First we need to make sure we have some base packages installed.

libicsneo is a newer library and has wider support for Intrepid Products under linux (<https://github.com/intrepidcs/libicsneo>). libicsneo has a legacy library (libicsneolegacy.so) that can be loaded by utilizing ics.override_library_name("libicsneolegacy.so").

4.1 Fedora Dependencies (FC28)

```
sudo dnf install redhat-rpm-config gcc g++ python3-devel
```

4.2 Debian/Ubuntu Dependencies

```
sudo apt install build-essential python-dev
```

4.3 Others (Required dependencies)

- GCC
- G++
- Python Development packages (We Need to link to Python.h)

4.4 Installation

After dependencies are installed we can run the following pip command:

```
pip install python_ics
```

Note: A lot of distributions have Python 2 and 3 installed side by side. As of this writing without a version suffix the commands still default to version 2 of the Python binaries. In order to utilize the Python 3 binaries you must append a 3 after the binary names (python3 and pip3 instead of just python and pip).

4.5 Intrepid libicsneoapi.so Library

Please see <https://github.com/intrepidcs/icsneoapi> for more details.

CHAPTER 5

Getting Started

Please see https://github.com/intrepidcs/python_ics/tree/master/examples for simple examples on how to use this module. Most function documentation has a simple example on how its intended to be used. Every function was designed to be as close as possible to it's C counterpart unless it was deemed to make the function more pythonic in nature.

For those experienced with the C API `ics.open_device (icsneoOpenNeoDevice())` behavior has been changed the most (no parameters makes it auto utilize `ics.find_devices (icsneoFindNeoDevices())` and open the first device). Also since python is a object oriented language the module utilizes this and auto cleans up device handles when going out of scope so there is usually no need to call `ics.close_device()`.

CHAPTER 6

Examples

Examples can be found at https://github.com/intrepidcs/python_ics/tree/master/examples

For extra information on data structures and underlying functionality, please visit neoVI DLL Documentation under <https://intrepidcs.com/support/support-resources/>

6.1 Opening a device

The `open_device_example.py` example shows how to successfully open and close an Intrepid device.

6.2 Transmitting and Receiving a CAN message

The following examples show how to interact with CAN messages on an Intrepid device.

- `transmit_can_example.py`: Basic example showing how to transmit and receive standard CAN frame
- `transmit_can_xtd_example.py`: Builds off of the CAN example and adds extended Arbitration ID attributes
- `canfd_transmit_example.py`: Bare minimum example on how to transmit over CANFD.

6.3 ISO 15765-2 Example

The `iso15765_example.py` example shows how to setup basic ISO 15765-2 receive filters and transmitting an ISO 15765-2 message.

After opening an Intrepid device `ics.iso15765_enable_networks` should be called to enable ISO 15765-2.

Receive filtering can be established by passing a custom `ics.CmISO157652RxMessage()` to `ics.iso15765_receive_message()`.

Similarly transmitting an ISO 15765-2 frame can be accomplished by passing a custom `ics.CmISO157652TxMessage()` to `ics.iso15765_transmit_message()`.

6.4 Missing an example?

Need an example on something that isn't covered here? Please submit an issue on [github](#) or feel free to send over a Pull Request of your own.

CHAPTER 7

Module Documentation

Python C Code module for interfacing to the icsneo40 dynamic library. Code tries to respect PEP 8 (<http://python.org/dev/peps/pep-0008>). Function naming convention does not follow the tradition c style icsneo40 naming convention as pyics module name acts as the namespace (icsneo portion of the function) and function names are suppose to be lowercase with underscores instead of mixedCase like icsneo API.

C API can be mimiced almost identically by doing the following:

```
>>> import ics as icsneo
>>> devices = icsneo.FindNeoDevices()
>>> for device in devices:
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

Recommended Python way by doing the following:

```
>>> import ics
>>> devices = ics.find_devices()
>>> for device in devices:
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

It should be noted that `ics.ics.NeoDevice` is used a little bit differently than the C API. `ics.ics.NeoDevice` contains two extra members:

`ics.ics.NeoDevice.AutoHandleClose` and `ics.ics.NeoDevice._Handle`

The handle normally returned from `icsneoOpenNeoDevice()` is stored inside `_Handle` and setting `AutoHandleClose` to True (Default) will automatically close the handle when the `ics.ics.NeoDevice` goes out of scope.

Installation:

`pip install python_ics`

<https://pypi.python.org/pypi/python-ics>

```
exception ics.ics.ArgumentError
    Bases: Exception

exception ics.ics.RuntimeError
    Bases: Exception

class ics.ics.NeoDevice
    Bases: object

    NeoDevice object

    AutoHandleClose
        When NeoDevice is freed the handle will automatically be closed, if true.

    DeviceType

    Handle

    IsOpen
        This contains the handle returned from icsneoOpenDevice() API. If uncertain, don't use this.

    MaxAllowedClients

    Name
        String describing DeviceType, extension to Python api only.

    NumberOfClients

    SerialNumber

class ics.ics.SpyMessage
    Bases: object

    SpyMessage object

    AckBytes

    ArbIDOrHeader

    Data

    DescriptionID
        Not Used

    ExtraDataPtr

    ExtraDataPtrEnabled

    MessagePieceID
        Not Used

    MiscData

    NetworkID
        This value is used to identify which network this message was received on.

    NetworkID2
        This value is used to identify which network this message was received on.

    NodeID
        Not Used

    NumberBytesData
        Holds the number of bytes in the Data(1 to 8) array or the number of bytes in a CAN remote frame (The DLC).
```

NumberBytesHeader

Used for J1850/ISO messages. It indicates how many bytes are stored in the Header(1 to 4) array.

Protocol

Valid values are SPY_PROTOCOL_CAN, SPY_PROTOCOL_J1850VPW, and SPY_PROTOCOL_ISO9141.

StatusBitField

StatusBitField2

StatusBitField3

StatusBitField4

TimeHardware

Hardware time stamp. The TimeStamp is reset on device open

TimeHardware2

Hardware time stamp. The TimeStamp is reset on device open

TimeStampHardwareID

This is an identifier of what type of hardware timestamp is used. Since neoVI's timestamp is always the same, this doesn't change.

TimeStampSystemID

This is an identifier of what type of system timestamp is used. Since WIN32 neoVI's timestamp is always the same, from the timeGetTime API, this doesn't change.

TimeSystem

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

TimeSystem2

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

noExtraDataPtrCleanup

Tells Python to not clean up ExtraDataPtrMemory, If this is enabled. Ignore, if unsure.

class ics.ics.SpyMessageJ1850

Bases: object

SpyMessageJ1850 object

AckBytes

Data

DescriptionID

Not Used

ExtraDataPtr

ExtraDataPtrEnabled

Header

MessagePieceID

Not Used

MiscData

NetworkID

This value is used to identify which network this message was received on.

NetworkID2

This value is used to identify which network this message was received on.

NodeID

Not Used

NumberBytesData

Holds the number of bytes in the Data(1 to 8) array or the number of bytes in a CAN remote frame (The DLC).

NumberBytesHeader

Used for J1850/ISO messages. It indicates how many bytes are stored in the Header(1 to 4) array.

Protocol

Valid values are SPY_PROTOCOL_CAN, SPY_PROTOCOL_J1850VPW, and SPY_PROTOCOL_ISO9141.

StatusBitField

StatusBitField2

StatusBitField3

StatusBitField4

TimeHardware

Hardware time stamp. The TimeStamp is reset on device open

TimeHardware2

Hardware time stamp. The TimeStamp is reset on device open

TimeStampHardwareID

This is an identifier of what type of hardware timestamp is used. Since neoVI's timestamp is always the same, this doesn't change.

TimeStampSystemID

This is an identifier of what type of system timestamp is used. Since WIN32 neoVI's timestamp is always the same, from the timeGetTime API, this doesn't change.

TimeSystem

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

TimeSystem2

TimeSystem is loaded with the value received from the timeGetTime call in the WIN32 multimedia API.

noExtraDataPtrCleanup

Tells Python to not clean up ExtraDataPtrMemory, If this is enabled. Ignore, if unsure.

`ics.ics.ClosePort()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.close_device()` method.

`ics.ics.EnableBusVoltageMonitor()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_bus_voltage_monitor()` method.

`ics.ics.EnableNetworkCom()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_network_com()` method.

`ics.ics.FindNeoDevices()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.find_devices()` method.

`ics.ics.FirmwareUpdateRequired()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.firmware_update_required()` method.

`ics.ics.ForceFirmwareUpdate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.force_firmware_update()` method.

`ics.ics.GetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_active_vnet_channel()` method.

`ics.ics.GetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_enabled()` method.

`ics.ics.GetBackupPowerReady()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_ready()` method.

`ics.ics.GetBusVoltage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_bus_voltage()` method.

`ics.ics.GetDLLFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_firmware_info()` method.

`ics.ics.GetDLLVersion()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_dll_version()` method.

`ics.ics.GetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_settings()` method.

`ics.ics.GetDeviceStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_device_status()` method.

`ics.ics.GetErrorMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_error_messages()` method.

`ics.ics.GetHWFirmwareInfo()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_hw_firmware_info()` method.

`ics.ics.GetLastAPIError()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_last_api_error()` method.

`ics.ics.GetMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_messages()` method.

`ics.ics.GetPerformanceParameters()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_performance_parameters()` method.

`ics.ics.GetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_rtc()` method.

`ics.ics.GetSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_serial_number()` method.

`ics.ics.GetTimeStampForMsg()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_timestamp_for_msg()` method.

`ics.ics.ISO15765_DisableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_disable_networks()` method.

`ics.ics.ISO15765_EnableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_enable_networks()` method.

`ics.ics.ISO15765_ReceiveMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.ics.ISO15765_TransmitMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.ics.LoadDefaultSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.load_default_settings()` method.

`ics.ics.OpenNeoDevice()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.open_device()` method.

`ics.ics.ReadJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_jupiter_firmware()` method.

`ics.ics.ReadSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_sdcard()` method.

`ics.ics.RequestDiskDetails()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_details()` method.

`ics.ics.RequestDiskFormat()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format()` method.

`ics.ics.RequestDiskFormatCancel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format_cancel()` method.

`ics.ics.RequestDiskFormatProgress()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_format_progress()` method.

`ics.ics.RequestEnterSleepMode()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.request_enter_sleep_mode()`

method.

`ics.ics.ScriptClear()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_clear()` method.

`ics.ics.ScriptGetFBlockStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_fblock_status()` method.

`ics.ics.ScriptGetScriptStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_status()` method.

`ics.ics.ScriptGetScriptStatusEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_script_status()` method.

`ics.ics.ScriptLoad()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_load()` method.

`ics.ics.ScriptReadAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_app_signal()` method.

`ics.ics.ScriptReadRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_rx_message()` method.

`ics.ics.ScriptReadTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_tx_message()`

method.

`ics.ics.ScriptStart()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start()` method.

`ics.ics.ScriptStartFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start_fblock()` method.

`ics.ics.ScriptStop()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop()` method.

`ics.ics.ScriptStopFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop_fblock()` method.

`ics.ics.ScriptWriteAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_app_signal()` method.

`ics.ics.ScriptWriteRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_rx_message()` method.

`ics.ics.ScriptWriteTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_tx_message()` method.

`ics.ics.SetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_active_vnet_channel()` method.

`ics.ics.SetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_backup_power_enabled()` method.

`ics.ics.SetBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate()` method.

`ics.ics.SetBitRateEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate_ex()` method.

`ics.ics.SetContext()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_context()` method.

`ics.ics.SetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_device_settings()` method.

`ics.ics.SetFDBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_fd_bit_rate()` method.

`ics.ics.SetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_rtc()` method.

`ics.ics.SetReflashDisplayCallback()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_reflash_callback()`

method.

`ics.ics.TxMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.transmit_messages()` method.

`ics.ics.ValidateHObject()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.validate_hobject()` method.

`ics.ics.WriteJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_jupiter_firmware()` method.

`ics.ics.WriteSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_sdcard()` method.

`ics.ics.base36enc(serial)`

Converts a decimal serial number to base36.

Args: serial (int): serial number.

Raises: `ics.ics.RuntimeError`

Returns: Str: Serial Number

```
>>> ics.base36enc(device.SerialNumber)
CY0024
```

`ics.ics.close_device(device)`

Closes the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Error Count (int)

```
>>> for device in ics.find_devices():
...     ics.open_device(device)
...     # Do something with the device...
...     ics.close_device(device)
... 
```

Note: `ics.ics.NeoDevice` will automatically close the device when it goes out of scope.

ics.ics.coremini_clear(device, location)

Clears the CoreMini into the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

location (int): Accepts *ics.ics.SCRIPT_LOCATION_FLASH_MEM*, *ics.ics.SCRIPT_LOCATION_SDCARD*, or *ics.ics.SCRIPT_LOCATION_VCAN3_MEM*

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_clear(device, ics.SCRIPT_LOCATION_SDCARD)
```

ics.ics.coremini_get_fblock_status(device, index)

Gets the status of a Coremini Function Block at *index* on *device*.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

index (int): Index of the function block.

Raises: *ics.ics.RuntimeError*

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_get_fblock_status(device, 1)
True
```

ics.ics.coremini_get_status(device)

Gets the status of the CoreMini in the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: True if running, otherwise False.

```
>>> device = ics.open_device()
>>> ics.coremini_get_status(device)
>>>
```

ics.ics.coremini_load(device, coremini, location)

Loads the CoreMini into the device.

Args: device (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

coremini (str/tuple): Use string to load from file, Use Tuple if file data.

location (int): Accepts *ics.ics.SCRIPT_LOCATION_FLASH_MEM*, *ics.ics.SCRIPT_LOCATION_SDCARD*, or *ics.ics.SCRIPT_LOCATION_VCAN3_MEM*

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_load(device, 'cmvspy.vs3cmb', ics.SCRIPT_LOCATION_SDCARD)
```

ics.ics.coremini_read_app_signal(device, index)

Gets the value of a Coremini application signal at *index* on *device*.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
index (int): Index of the application signal.

Raises: `ics.ics.RuntimeError`

Returns: float on Success.

```
>>> device = ics.open_device()  
>>> ics.coremini_read_app_signal(device, 1)  
52
```

`ics.ics.coremini_read_rx_message` (device, index, j1850=False)
Gets the value of a Coremini Message at `index` on `device`.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
index (int): Index of the application signal.
j1850 (bool): Use `ics.ics.SpyMessageJ1850` instead.

Raises: `ics.ics.RuntimeError`

Returns: `ics.ics.SpyMessage` Success.

```
>>> device = ics.open_device()  
>>> msg = ics.coremini_read_tx_message(device, 0)
```

`ics.ics.coremini_read_tx_message` (device, index, j1850=False)
Gets the value of a Coremini Message at `index` on `device`.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
index (int): Index of the application signal.
j1850 (bool): Use `ics.ics.SpyMessageJ1850` instead.

Raises: `ics.ics.RuntimeError`

Returns: `ics.ics.SpyMessage` Success.

```
>>> device = ics.open_device()  
>>> msg = ics.coremini_read_tx_message(device, 0)
```

`ics.ics.coremini_start` (device, location)
Starts the CoreMini into the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
location (int): Accepts `ics.ics.SCRIPT_LOCATION_FLASH_MEM`, `ics.ics.SCRIPT_LOCATION_SDCARD`, or `ics.ics.SCRIPT_LOCATION_VCAN3_MEM`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()  
>>> ics.coremini_start(device, ics.SCRIPT_LOCATION_SDCARD)
```

`ics.ics.coremini_start_fblock` (device, index)
Starts a Coremini Function Block at `index` on `device`.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
index (int): Index of the function block.

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_start_fblock(device, 1)
```

`ics.ics.coremini_stop(device)`

Stops the CoreMini into the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.coremini_stop(device)
```

`ics.ics.coremini_stop_fblock(device, index)`

Stops a Coremini Function Block at `index` on `device`.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`index (int): Index of the function block.`

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_stop_fblock(device, 1)
```

`ics.ics.coremini_write_app_signal(device, index, value)`

Sets the value of a Coremini application signal at `index` on `device`.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`index (int): Index of the application signal.`

`value (float): New value of the application signal.`

Raises: `ics.ics.RuntimeError`

Returns: None on Success.

```
>>> device = ics.open_device()
>>> ics.coremini_write_app_signal(device, 1, 52)
>>>
```

`ics.ics.coremini_write_rx_message(device, index, TODO)`

TODO

`ics.ics.coremini_write_tx_message(device, index, msg)`

TODO

`ics.ics.create_neovi_radio_message(Relay1, Relay2, Relay3, Relay4, Relay5, LED6, LED5, MSB_report_rate, LSB_report_rate, analog_change_report_rate, relay_timeout)`

Python API only. Generates data bytes for use with neoVI RADI/O CAN Messages

Kwargs: `Relay1 (boolean): Enable/Disable Relay1`

`Relay2 (boolean): Enable/Disable Relay2`

Relay3 (boolean): Enable/Disable Relay3
Relay4 (boolean): Enable/Disable Relay4
Relay5 (boolean): Enable/Disable Relay5
LED5 (boolean): Enable/Disable LED5
LED6 (boolean): Enable/Disable LED6
MSB_report_rate (int): MSB Report Rate in ms (0-255)
LSB_report_rate (int): LSB Report Rate in ms (0-255)
analog_change_report_rate (int): Analog change report rate
relay_timeout (int): Relay Timeout (0-255)*255ms

Returns:

Tuple of data bytes for use with `ics.ics.SpyMessage`

Raises: `ics.ics.RuntimeError`

```
>>> msg = ics.SpyMessage()  
>>> msg.Data = ics.create_neovi_radio_message(Relay1=True, Relay4=False,  
    ↪ LED6=True, MSB_report_rate=10)  
>>> msg.Data  
(65, 10, 0, 0, 0)
```

`ics.ics.disk_format(device)`

Starts disk formatting on the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics  
>>> d = ics.open_device()  
>>> details = ics.get_disk_details(d)  
>>> details. = ics.get_disk_details(d)  
>>> ics.disk_format(d, details)  
>>>
```

`ics.ics.disk_format_cancel(device)`

Cancel in progress disk formatting on the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics  
>>> d = ics.open_device()  
>>> ics.disk_format(d, details)  
>>> ics.disk_format_cancel(d)  
>>>
```

`ics.ics.enable_bus_voltage_monitor(device, enable, reserved)`

Enable or disable bus voltage monitoring.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`
 enable (bool): int
 reserved (int): int: Optional. Should be set to zero. Don't set, if unsure.

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_bus_voltage_monitor(d, 1)
>>>
```

`ics.ics.enable_network_com`(device, enable, net_id)
 Enable or disable network communication.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

enable (bool): bool
 net_id (int): int: Optional. If left blank, disables/enables all networks.

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_network_com(d, True)
>>>
```

`ics.ics.find_devices`(device_type=`ics.ics.NEODEVICE_ALL`)

Finds all connected devices and returns a tuple of `ics.ics.NeoDevice` for use in `ics.ics.open_device()`

Args: device_type (int): Accepts `ics.ics.NEODEVICE_*` Macros

New in 3.0 (803):

device_types (List/Tuple): Accepts a Container of `ics.ics.NEODEVICE_*` Macros

network_id (int): OptionsFindNeoEx.CANOptions.iNetworkID. Usually `ics.NETID_CAN`, if needed

Raises: `ics.ics.RuntimeError`

Returns: Tuple of `ics.ics.NeoDevice` for use in `ics.ics.open_device()`

```
>>> for device in ics.find_devices():
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

New in 3.0 (803):

```
>>> for device in ics.find_devices([ics.NEODEVICE_FIRE, ics.NEODEVICE_VCAN3]):
...     print(device.Name, device.SerialNumber)
...
neoVI FIRE 59886
```

`ics.ics.firmware_update_required`(device)

Determines if the device firmware needs flashing.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

```
>>> ics.force_firmware_update(device)
True
```

`ics.ics.force_firmware_update(device)`

Forces the device to flash firmware.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

```
>>> ics.force_firmware_update(device)
True
```

`ics.ics.get_active_vnet_channel(device)`

Gets active vnet channel for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Int: Returns active vnet channel.

`ics.ics.get_backup_power_enabled(device)`

Returns the device backup power enabled for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.get_backup_power_ready(device)`

Returns the device backup power is ready for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.get_bus_voltage(device, reserved)`

Reads bus voltage. (`ics.ics.enable_bus_voltage_monitor`) needs to be called first.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

reserved (int): int: Optional. Should be set to zero. Don't set, if unsure.

Raises: `ics.ics.RuntimeError`

Returns: Int: value returned is in mV.

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.enable_bus_voltage_monitor(d, 1)
>>> ics.get_bus_voltage(d)
12000
>>>
```

`ics.ics.get_device_settings(device, device_type, vnet_slot)`

Gets the settings in the device. vnet_slot defaults to ics.ics.PlasmaIonVnetChannelMain

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`device_type (EDeviceSettingsType): Optional: Overrides default device settings type. Defaults to '-1'`

`vnet_slot (PlasmaIonVnetChannelMain): Optional: Defaults to PlasmaIonVnetChannelMain, Used only for PLASMA/ION Devices.`

Raises: `ics.ics.RuntimeError`

Returns: `ics.ics.device_settings`

```
>>> d = ics.open_device()
>>> d.Name
'neoVI ION'
>>> d.SerialNumber
404444
>>> s = ics.get_device_settings(d)
>>> s.DeviceSettingType
2
>>> s.cyan
<ics.CyanSettings object at 0x01E61B40>
>>> s.cyan.canfd1.FDMode
4
>>> s2.cyan
<ics.CyanSettings object at 0x02B113C8>
>>> s2 = ics.get_device_settings(d, -1, ics.PlasmaIonVnetChannelA)
>>> s2.DeviceSettingType
2
>>> s2.cyan.canfd1.FDMode
4
```

`ics.ics.get_device_status(device)`

Returns the device status.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: `(ics.ics.ics_device_status).`

```
>>> import ics
>>> d = ics.open_device()
>>> status = ics.get_device_status(d)
>>> status.fire2Status.ethernetActivationLineEnabled
0
```

`ics.ics.get_disk_details(device)`

Returns the device disk details.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: `(ics.ics.srad_gigalog_disk_details).`

```
>>> import ics
>>> d = ics.open_device()
>>> details = ics.get_disk_details(d)
```

(continues on next page)

(continued from previous page)

```
>>> details.structure.options  
>>>
```

`ics.ics.get_disk_format_progress(device)`

Returns the device disk formatting progress.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: (`ics.ics.srad_gigalog_disk_format_progress`).

```
>>> import ics  
>>> d = ics.open_device()  
>>> d = ics.disk_format(d, details)  
>>> progress = ics.get_disk_format_progress(d)  
>>> progress.sectorsRemaining  
>>>
```

`ics.ics.get_dll_firmware_info(device)`

Returns the DLL firmware info for the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: (`ics.ics.st_api_firmware_info`)

```
>>> device = ics.open_device()  
>>> info = ics.get_dll_firmware_info(device)  
>>> info.iAppMajor  
7  
>>> info.iAppMinor  
55  
>>>
```

`ics.ics.get_dll_version(device)`

Gets the DLL version.

Args: None

Raises: `ics.ics.RuntimeError`

Returns: Int: DLL Version

```
>>> ics.get_dll_version()  
700
```

`ics.ics.get_error_messages(device[,j1850,timeout])`

Gets the error message(s) on the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: list of tuple's. :class:`tuple` contents: (error_number, description_short, description_long, severity, restart_needed)

```
>>> device = ics.open_device()  
>>> errors = ics.get_error_messages(device)
```

`ics.ics.get_hw_firmware_info(device)`

Returns the device firmware info for the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: `(ics.ics.st_api_firmware_info)`

```
>>> device = ics.open_device()
>>> info = ics.get_hw_firmware_info(device)
>>> info.iAppMajor
7
>>> info.iAppMinor
55
>>>
```

`ics.ics.get_last_api_error(device)`

Gets the error message from the last API call.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Tuple: (error, description short, description long, severity, restart needed)

```
>>> device = ics.open_device()
>>> try:
...     msg = ics.coremini_read_tx_message(device, 0)
... except ics.RuntimeError as ex:
...     print(ex)
...     print(ics.get_last_api_error(device))
...
Error: coremini_read_tx_message(): icsneoScriptReadTxMessage() Failed
(224, 'Invalid Message Index for script.', 'Invalid Message Index for script.
', 16, 0)
```

`ics.ics.get_library_path()`

`ics.ics.get_messages(device[, j1850, timeout])`

Gets the message(s) on the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`j1850 (bool): Return ics.ics.SpyMessageJ1850 instead.`

`timeout (float): Optional timeout to wait for messages in seconds (0.1 = 100ms).`

Raises: `ics.ics.RuntimeError`

Returns: tuple of two items. First item is a tuple of `ics.ics.SpyMessage` and second is the error count.

```
>>> device = ics.open_device()
>>> messages, errors = ics.get_messages(device)
>>> len(messages)
14
>>> hex(messages[0].ArbIDOrHeader)
'0x160'
>>> messages[0].Data
(36, 11, 11, 177, 37, 3, 11, 199)
```

(continues on next page)

(continued from previous page)

```
>>> errors  
0
```

`ics.ics.get_performance_parameters(device)`

Gets the Performance Parameters on *device*.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Tuple on Success: (buffer count, buffer max, overflow count, reserved, reserved, reserved, reserved, reserved)

```
>>> device = ics.open_device()  
>>> ics.get_performance_parameters(device)  
(0, 24576, 0, 0, 0, 0, 0, 0)
```

`ics.ics.get_rtc(device)`

Gets the Real-Time Clock of the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Tuple: (datetime.datetime object, offset in seconds)

```
>>> device = ics.open_device()  
>>> ics.get_rtc(device)  
(datetime.datetime(2014, 9, 10, 17, 45, 45), 3)
```

`ics.ics.get_script_status()`

Accepts a `ics.ics.NeoDevice`, exception on error. Returns a list of values of what ulParameters would hold

`ics.ics.get_serial_number(device)`

Gets the serial number out of the device.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Int: Serial Number Version

```
>>> ics.get_serial_number(device)  
53123
```

`ics.ics.get_timestamp_for_msg(device, msg)`

Calculates the timestamp for a message.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`msg (ics.ics.SpyMessage): ics.ics.SpyMessage`

Raises: `ics.ics.RuntimeError`

Returns: Float: Timestamp for the message.

```
>>> import ics  
>>> d = ics.open_device()  
>>> msgs, error_count = ics.get_messages(d)  
>>> ics.get_timestamp_for_msg(d, msgs[0])  
354577568.9145524
```

`ics.ics.icsneoClosePort()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.close_device()` method.

`ics.ics.icsneoEnableBusVoltageMonitor()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_bus_voltage_monitor()` method.

`ics.ics.icsneoEnableNetworkCom()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.enable_network_com()` method.

`ics.ics.icsneoFindNeoDevices()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.find_devices()` method.

`ics.ics.icsneoFirmwareUpdateRequired()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.firmware_update_required()` method.

`ics.ics.icsneoForceFirmwareUpdate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.force_firmware_update()` method.

`ics.ics.icsneoGetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_active_vnet_channel()` method.

`ics.ics.icsneoGetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_backup_power_enabled()` method.

ics.ics.icsneoGetBackupPowerReady()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_backup_power_ready()* method.

ics.ics.icsneoGetBusVoltage()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_bus_voltage()* method.

ics.ics.icsneoGetDLLFirmwareInfo()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_dll_firmware_info()* method.

ics.ics.icsneoGetDLLVersion()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_dll_version()* method.

ics.ics.icsneoGetDeviceSettings()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_device_settings()* method.

ics.ics.icsneoGetDeviceStatus()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_device_status()* method.

ics.ics.icsneoGetErrorMessages()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_error_messages()* method.

ics.ics.icsneoGetHWFirmwareInfo()

Note: Compatibility Function: Identical to PEP8 compliant *ics.ics.get_hw_firmware_info()* method.

ics.ics.icsneoGetLastAPIError()

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_last_api_error()` method.

`ics.ics.icsneoGetMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_messages()` method.

`ics.ics.icsneoGetPerformanceParameters()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_performance_parameters()` method.

`ics.ics.icsneoGetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_rtc()` method.

`ics.ics.icsneoGetSerialNumber()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_serial_number()` method.

`ics.ics.icsneoGetTimeStampForMsg()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_timestamp_for_msg()` method.

`ics.ics.icsneoISO15765_DisableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_disable_networks()` method.

`ics.ics.icsneoISO15765_EnableNetworks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_enable_networks()` method.

`ics.ics.icsneoISO15765_ReceiveMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.ics.icsneoISO15765_TransmitMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.ics.icsneoLoadDefaultSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.load_default_settings()` method.

`ics.ics.icsneoOpenNeoDevice()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.open_device()` method.

`ics.ics.icsneoReadJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_jupiter_firmware()` method.

`ics.ics.icsneoReadSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.read_sdcard()` method.

`ics.ics.icsneoRequestDiskDetails()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_details()` method.

`ics.ics.icsneoRequestDiskFormat()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format()` method.

`ics.ics.icsneoRequestDiskFormatCancel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.disk_format_cancel()` method.

`ics.ics.icsneoRequestDiskFormatProgress()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_disk_format_progress()` method.

`ics.ics.icsneoRequestEnterSleepMode()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.request_enter_sleep_mode()` method.

`ics.ics.icsneoScriptClear()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_clear()` method.

`ics.ics.icsneoScriptGetFBlockStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_fblock_status()` method.

`ics.ics.icsneoScriptGetScriptStatus()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_get_status()` method.

`ics.ics.icsneoScriptGetScriptStatusEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.get_script_status()` method.

`ics.ics.icsneoScriptLoad()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_load()` method.

`ics.ics.icsneoScriptReadAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_app_signal()` method.

`ics.ics.icsneoScriptReadRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_rx_message()` method.

`ics.ics.icsneoScriptReadTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_read_tx_message()` method.

`ics.ics.icsneoScriptStart()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start()` method.

`ics.ics.icsneoScriptStartFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_start_fblock()` method.

`ics.ics.icsneoScriptStop()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop()` method.

`ics.ics.icsneoScriptStopFBlock()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_stop_fblock()` method.

`ics.ics.icsneoScriptWriteAppSignal()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_app_signal()` method.

`ics.ics.icsneoScriptWriteRxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_rx_message()` method.

`ics.ics.icsneoScriptWriteTxMessage()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.coremini_write_tx_message()` method.

`ics.ics.icsneoSetActiveVNETChannel()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_active_vnet_channel()` method.

`ics.ics.icsneoSetBackupPowerEnabled()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_backup_power_enabled()` method.

`ics.ics.icsneoSetBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate()` method.

`ics.ics.icsneoSetBitRateEx()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_bit_rate_ex()` method.

`ics.ics.icsneoSetContext()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_context()` method.

`ics.ics.icsneoSetDeviceSettings()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_device_settings()` method.

`ics.ics.icsneoSetFDBitRate()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_fd_bit_rate()` method.

`ics.ics.icsneoSetRTC()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_rtc()` method.

`ics.ics.icsneoSetReflashDisplayCallbacks()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_reflash_callback()` method.

`ics.ics.icsneoTxMessages()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.transmit_messages()` method.

`ics.ics.icsneoValidateHObject()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.validate_hobject()` method.

`ics.ics.icsneoWriteJupiterFirmware()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_jupiter_firmware()` method.

`ics.ics.icsneoWriteSDCard()`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_sdcard()` method.

`ics.ics.iso15765_disable_networks(device)`

Disables ISO15765 networks.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None

`ics.ics.iso15765_enable_networks(device, networks)`

Enables ISO15765 networks.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None

`ics.ics.iso15765_receive_message(device, netid, rx_msg)`
Setup rx ISO15765 Message.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

prx_msg (ics.ics.st_cm_iso157652_rx_message):
`st_cm_iso157652_rx_message` ics.ics.

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.iso15765_transmit_message(device, ulNetworkID, pMsg, ulBlockingTimeout)`
Transmits an ISO15765 Message.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

pMsg (ics.ics.st_cm_iso157652_tx_message):
`st_cm_iso157652_tx_message` ics.ics.

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.load_default_settings(device)`
Load the default settings in the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> ics.load_default_settings(device)
>>>
```

`ics.ics.open_device(device)`

Opens the device. `device` can be omitted to return a `ics.ics.NeoDevice` of the first free available device, a `ics.ics.NeoDevice`, or a serial number of the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

device (int): Serial Number of the device

network_ids (List/Tuple): This is an array of number IDs which specify the NetworkID parameter of each network. This allows you to assign a custom network ID to each network. Normally, you will assign consecutive IDs to each of the networks. See NetworkIDList for a list of current network ID's. You may also set this parameter to NULL (zero) and the default network ID's will be used.

bconfig_read (int): Specifies whether the DLL should read the neoVI's device configuration before enabling the device. It is recommended that this value be set to 1.

options (int): DEVICE_OPTION_* defines

network_id (int): OptionsFindNeoEx.CANOptions.iNetworkID. Usually ics.NETID_CAN, if needed

use_server (int): Defaults to False, Setting to True allows opening the same device more than once.

Raises: `ics.ics.RuntimeError`

Returns: If `ics.ics.NeoDevice` is passed as a parameter, None. If serial number is passed as a parameter, a `ics.ics.NeoDevice` will be returned. If `device` parameter is omitted, a `ics.ics.NeoDevice` will be returned with the first available free device.

```
>>> for device in ics.find_devices():
...     ics.open_device(device)
...
...
```

Note: `ics.ics.NeoDevice` will automatically close the device when it goes out of scope.

`ics.ics.override_library_name(new_name)`
Overrides the default search for loading the icsneo40 library

Args: name: Absolute path or relative path including filename.

Raises: `ics.ics.RuntimeError`

Returns: None

```
>>> import ics
>>> ics.find_devices()
Traceback (most recent call last):
  File "<stdin>", line 1, in <module>
ics.RuntimeError: Error: find_devices(): Failed to open library: 'icsneo40.dll'
 ↵' with error code: #126
>>> ics.override_library_name(r"C:\Windows\SysWOW64\icsneo40-different.dll")
>>> ics.find_devices()
(<ics.NeoDevice object at 0x00284C50>, <ics.NeoDevice object at 0x007C9A10>)
```

`ics.ics.read_jupiter_firmware(device, size[, vnetChannel])`
Reads firmware binary from a RAD-Jupiter. If not sure, don't use this method

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

size (int): int: size of the bytes to read of the firmware binary.

vnetChannel (int): int: Optional. Don't set, if unsure.

Raises: `ics.ics.RuntimeError`

Returns: None

`ics.ics.read_sdcard()`
icsneoReadSDCard(), Accepts a ics.ics.NeoDevice and sector index. Returns a bytearray of 512 bytes max. Exception on error.

`ics.ics.request_enter_sleep_mode(device, timeout_ms, mode, reserved_zero)`

Signal neoVI to immediate go to sleep. Currently only supported by FIREVNET/PLASMA. If using over USB this will likely return true but never cause PLASMA to sleep since USB insertion keeps it alive. This API allows Android/Linux applications to invoke power management.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

timeout_ms (int): 16bit word for how long to wait on idle bus before going to sleep. If caller does not want to change it pass in 65535 (0xFFFF) and it will stay whatever it was set to in explorer/coremini.

mode (int): 16bit word for power mode to enter. If caller does not want to change it pass in 65535 (0xFFFF) and it will stay whatever it was set to in explorer/coremini. If it is zero then neoVI will do 'normal sleep'. 0 - power mode off but calling this function will do 'normal sleep'. 1 - normal sleep. 2 - instant sleep. 3 - comatose sleep.

reserved_zero (int): Reserved, Keep as zero.

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

```
>>> ics.request_enter_sleep_mode(device, 1, 0)
True
```

`ics.ics.set_active_vnet_channel(device, channel)`

Sets active vnet channel for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.set_backup_power_enabled(device, enable)`

Sets the device backup power enabled for the device.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

`ics.ics.set_bit_rate(device, BitRate, NetworkID)`

Specifies bit rate setting. Valid values depend on the network specified.

For the networks NETID_HSCAN, NETID_MSCAN, NETID_SWCAN, NETID_FIRE_HSCAN2, NETID_HSCAN3, NETID_LSFTCAN, valid bit rates are 2000, 33333, 50000, 62500, 83333, 100000, 125000, 250000, 500000, 800000, 1000000

For the networks NETID_LIN, NETID_ISO2, NETID_FIRE_LIN2, NETID_FIRE_LIN3, NETID_FIRE_LIN4, valid bit rates are

For the network NETID_FIRE_CGI valid bit rates are 625000 and 115200

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Int: None.

`ics.ics.set_bit_rate_ex(device, BitRate, NetworkID, iOptions)`

Sets the bitrate for a given Network ID on the device with extended options.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Int: None.

`ics.ics.set_context(device)`

Sets the “context” of how icsneoFindNeoDevices(Ex) and icsneoOpenNeoDevice(Ex) function. If the context is 0 (null) than icsneoFindNeoDevices(Ex) will be system wide, searching USB and other supported computer interfaces. icsneoFindNeoDevices can then be used to connect to devices found in this manner. If the context is a handle to connected CAN tool than icsneoFindNeoDevices(Ex) will search a specific CAN bus for supported IntrepidCS CAN Nodes. Again icsneoOpenNeoDevice(Ex) would be used create logical connections to found CAN Nodes.

Args: device (`ics.ics.NeoDevice`): `ics.ics.NeoDevice`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True on success, False on failure.

```
>>> ics.set_context(device)
True
```

ics.ics.set_device_settings(*device*, *settings*, *save_to_eeprom*, *vnet_slot*)
Sets the settings in the device. *vnet_slot* defaults to *ics.ics.PlasmaIonVnetChannelMain*

Args: *device* (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

settings (*ics.ics.device_settings*): *ics.ics.device_settings*

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> d = ics.open_device()
>>> d.Name
'neoVI ION'
>>> d.SerialNumber
404444
>>> s = ics.get_device_settings(d, ics.PlasmaIonVnetChannelA) # Get Slave
    ↵settings, channel selection not needed if not a Plasma/Ion
>>> s.DeviceSettingType
2
>>> s.cyan.can_switch_mode
1
>>> s.cyan.can_switch_mode = 2
>>> ics.set_device_settings(d, s, True, ics.PlasmaIonVnetChannelA)
>>>
```

ics.ics.set_fd_bit_rate(*device*, *BitRate*, *NetworkID*)
Sets the FD bitrate for a given Network ID on the device..

Args: *device* (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

Raises: *ics.ics.RuntimeError*

Returns: Int: None.

ics.ics.set_reflash_callback(*callback*)
Sets the reflash display callback.

Args: *callback* (function): Must be a callable Python function (*def callback(msg, progress)*)

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> def callback(msg, progress):
...     print(msg, progress)
...
>>> ics.set_reflash_callback(callback)
>>>
```

ics.ics.set_rtc(*device*[, *time*])
Sets the Real-Time Clock of the device.

Args: *device* (*ics.ics.NeoDevice*): *ics.ics.NeoDevice*

time (*datetime.datetime*): Optional. Sets to current time, if omitted.

Raises: *ics.ics.RuntimeError*

Returns: None.

```
>>> device = ics.open_device()
>>> ics.set_rtc(device)
```

`ics.ics.transmit_messages(device, messages)`

Transmits message(s) on the device. `messages` can be a tuple of `ics.ics.SpyMessage`

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`messages (ics.ics.SpyMessage): ics.ics.SpyMessage`

Raises: `ics.ics.RuntimeError`

Returns: None.

```
>>> device = ics.open_device()
>>> msg = ics.SpyMessage()
>>> msg.ArbIDOrHeader = 0xFF
>>> msg.NetworkID = ics.NETID_HSCAN
>>> msg.Data = (0,1,2,3,4,5,6,7)
>>> ics.transmit_messages(device, msg)
>>>
```

`ics.ics.validate_hobject(device)`

Validates the handle is valid for a `device`. Handles are only valid when the device is open.

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

or:

`device (int): c style integer handle to the device.`

Raises: `ics.ics.RuntimeError`

Returns: Boolean: True if valid, false otherwise.

```
>>> device = ics.open_device()
>>> ics.validate_hobject(device)
1
>>> ics.validate_hobject(device._Handle)
1
```

`ics.ics.write_jupiter_firmware(device, bytes[, vnetChannel])`

Writes firmware binary to a RAD-Jupiter. If not sure, don't use this method

Args: `device (ics.ics.NeoDevice): ics.ics.NeoDevice`

`bytes (bytes): bytes: bytes of the firmware binary.`

`vnetChannel (int): int: Optional. Don't set, if unsure.`

Raises: `ics.ics.RuntimeError`

Returns: None

`ics.ics.write_sdcard()`

`icsneoReadSDCard()`, Accepts a `ics.ics.NeoDevice`, sector index, and a bytearray of 512 bytes. Exception on error.

CHAPTER 8

Module Functions

`ics.ISO15765_DisableNetworks`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_disable_networks()` method.

`ics.ISO15765_EnableNetworks`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_enable_networks()` method.

`ics.ISO15765_ReceiveMessage`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_receive_message()` method.

`ics.ISO15765_TransmitMessage`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.iso15765_transmit_message()` method.

`ics.close_device(device)`

Closes the device.

`ics.coremini_clear(device, location)`

Clears the CoreMini into the device.

Continued on next page

Table 1 – continued from previous page

<code>ics.coremini_get_fblock_status(device, index)</code>	Gets the status of a Coremini Function Block at <i>index</i> on <i>device</i> .
<code>ics.coremini_get_status(device)</code>	Gets the status of the CoreMini in the device.
<code>ics.coremini_load(device, coremini, location)</code>	Loads the CoreMini into the device.
<code>ics.coremini_read_app_signal(device, index)</code>	Gets the value of a Coremini application signal at <i>index</i> on <i>device</i> .
<code>ics.coremini_read_rx_message(device, index)</code>	Gets the value of a Coremini Message at <i>index</i> on <i>device</i> .
<code>ics.coremini_read_tx_message(device, index)</code>	Gets the value of a Coremini Message at <i>index</i> on <i>device</i> .
<code>ics.coremini_start(device, location)</code>	Starts the CoreMini into the device.
<code>ics.coremini_start_fblock(device, index)</code>	Starts a Coremini Function Block at <i>index</i> on <i>device</i> .
<code>ics.coremini_stop(device)</code>	Stops the CoreMini into the device.
<code>ics.coremini_stop_fblock(device, index)</code>	Stops a Coremini Function Block at <i>index</i> on <i>device</i> .
<code>ics.coremini_write_app_signal(device, index, ...)</code>	Sets the value of a Coremini application signal at <i>index</i> on <i>device</i> .
<code>ics.coremini_write_rx_message(device, index, ...)</code>	TODO
<code>ics.coremini_write_tx_message(device, index, msg)</code>	TODO
<code>ics.create_neovi_radio_message(Relay1, ...)</code>	Python API only.
<code>ics.disk_format(device)</code>	Starts disk formatting on the device.
<code>ics.disk_format_cancel(device)</code>	Cancel in progress disk formatting on the device.
<code>ics.enable_bus_voltage_monitor(device, ...)</code>	Enable or disable bus voltage monitoring.
<code>ics.enable_network_com(device, net_id)</code>	Enable or disable network communication.
<code>ics.find_devices([device_type])</code>	Finds all connected devices and returns a tuple of <code>ics.ics.NeoDevice</code> for use in <code>ics.ics.open_device()</code>
<code>ics.firmware_update_required(device)</code>	Determines if the device firmware needs flashing.
<code>ics.force_firmware_update(device)</code>	Forces the device to flash firmware.
<code>ics.get_active_vnet_channel(device)</code>	Gets active vnet channel for the device.
<code>ics.get_backup_power_enabled(device)</code>	Returns the device backup power enabled for the device.
<code>ics.get_backup_power_ready(device)</code>	Returns the device backup power is ready for the device.
<code>ics.get_bus_voltage(device, reserved)</code>	Reads bus voltage.
<code>ics.get_device_settings(device, device_type, ...)</code>	Gets the settings in the device.
<code>ics.get_device_status(device)</code>	Returns the device status.
<code>ics.get_disk_details(device)</code>	Returns the device disk details.
<code>ics.get_disk_format_progress(device)</code>	Returns the device disk formatting progress.
<code>ics.get_dll_firmware_info(device)</code>	Returns the DLL firmware info for the device.
<code>ics.get_dll_version(device)</code>	Gets the DLL version.
<code>ics.get_error_messages(device[, j1850, timeout])</code>	Gets the error message(s) on the device.
<code>ics.get_hw_firmware_info(device)</code>	Returns the device firmware info for the device.
<code>ics.get_last_api_error(device)</code>	Gets the error message from the last API call.
<code>ics.get_library_path</code>	
<code>ics.get_messages(device[, j1850, timeout])</code>	Gets the message(s) on the device.
<code>ics.get_performance_parameters(device)</code>	Gets the Performance Parameters on <i>device</i> .

Continued on next page

Table 1 – continued from previous page

<code>ics.get_rtc(device)</code>	Gets the Real-Time Clock of the device.
<code>ics.get_script_status</code>	Accepts a <code>ics.ics.NeoDevice</code> , exception on error.
<code>ics.get_serial_number(device)</code>	Gets the serial number out of the device.
<code>ics.get_timestamp_for_msg(device, msg)</code>	Calculates the timestamp for a message.
<code>ics.iso15765_disable_networks(device)</code>	Disables ISO15765 networks.
<code>ics.iso15765_enable_networks(device, networks)</code>	Enables ISO15765 networks.
<code>ics.iso15765_receive_message(device, netid, ...)</code>	Setup rx ISO15765 Message.
<code>ics.iso15765_transmit_message(device, ...)</code>	Transmits an ISO15765 Message.
<code>ics.load_default_settings(device)</code>	Load the default settings in the device.
<code>ics.open_device(device)</code>	Opens the device.
<code>ics.override_library_name(new_name)</code>	Overrides the default search for loading the <code>icsneo40</code> library
<code>ics.read_jupiter_firmware(device, size, ...)</code>	Reads firmware binary from a RAD-Jupiter.
<code>ics.read_sdcard</code>	<code>icsneoReadSDCard()</code> , Accepts a <code>ics.ics.NeoDevice</code> and sector index.
<code>ics.request_enter_sleep_mode(device, ...)</code>	Signal neoVI to immediate go to sleep.
<code>ics.set_active_vnet_channel(device, channel)</code>	Sets active vnet channel for the device.
<code>ics.set_backup_power_enabled(device, enable)</code>	Sets the device backup power enabled for the device.
<code>ics.set_bit_rate(device, BitRate, NetworkID)</code>	Specifies bit rate setting.
<code>ics.set_bit_rate_ex(device, BitRate, ...)</code>	Sets the bitrate for a given Network ID on the device with extended options.
<code>ics.set_context(device)</code>	Sets the “context” of how <code>icsneoFindNeoDevices(Ex)</code> and <code>icsneoOpenNeoDevice(Ex)</code> function.
<code>ics.set_device_settings(device, settings, ...)</code>	Sets the settings in the device.
<code>ics.set_fd_bit_rate(device, BitRate, NetworkID)</code>	Sets the FD bitrate for a given Network ID on the device..
<code>ics.set_reflash_callback(callback)</code>	Sets the reflash display callback.
<code>ics.set_rtc(device[, time])</code>	Sets the Real-Time Clock of the device.
<code>ics.transmit_messages(device, messages)</code>	Transmits message(s) on the device.
<code>ics.validate_hobject(device)</code>	Validates the handle is valid for a <code>device</code> .
<code>ics.write_jupiter_firmware(device, bytes, ...)</code>	Writes firmware binary to a RAD-Jupiter.
<code>ics.write_sdcard</code>	<code>icsneoReadSDCard()</code> , Accepts a <code>ics.ics.NeoDevice</code> , sector index, and a bytearray of 512 bytes.
<code>ics.ClosePort</code>	

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.close_device()` method.

Continued on next page

Table 1 – continued from previous page

<code>ics.EnableBusVoltageMonitor</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_bus_voltage_monitor()</code> method.
<code>ics.EnableNetworkCom</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_network_com()</code> method.
<code>ics.FindNeoDevices</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.find_devices()</code> method.
<code>ics.FirmwareUpdateRequired</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.firmware_update_required()</code> method.
<code>ics.ForceFirmwareUpdate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.force_firmware_update()</code> method.
<code>ics.GetActiveVNETChannel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_active_vnet_channel()</code> method.
<code>ics.GetBackupPowerEnabled</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_enabled()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.GetBackupPowerReady</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_ready()</code> method.
<code>ics.GetBusVoltage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_bus_voltage()</code> method.
<code>ics.GetDLLFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_firmware_info()</code> method.
<code>ics.GetDLLVersion</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_version()</code> method.
<code>ics.GetDeviceSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_settings()</code> method.
<code>ics.GetDeviceStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_status()</code> method.
<code>ics.GetErrorMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_error_messages()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.GetHWFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_hw_firmware_info()</code> method.
<code>ics.GetLastAPIError</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_last_api_error()</code> method.
<code>ics.GetMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_messages()</code> method.
<code>ics.GetPerformanceParameters</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_performance_parameters()</code> method.
<code>ics.GetRTC</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_rtc()</code> method.
<code>ics.GetSerialNumber</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_serial_number()</code> method.
<code>ics.GetTimeStampForMsg</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_timestamp_for_msg()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.LoadDefaultSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.load_default_settings()</code> method.
<code>ics.OpenNeoDevice</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.open_device()</code> method.
<code>ics.ReadJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_jupiter_firmware()</code> method.
<code>ics.ReadSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_sdcard()</code> method.
<code>ics.RequestDiskDetails</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_details()</code> method.
<code>ics.RequestDiskFormat</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format()</code> method.
<code>ics.RequestDiskFormatCancel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format_cancel()</code> method.
<code>ics.RequestDiskFormatProgress</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_format_progress()</code> method.

Continued on next page

Table 1 – continued from previous page

ics.RequestEnterSleepMode	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.request_enter_sleep_mode()</i> method.
ics.ScriptClear	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.coremini_clear()</i> method.
ics.ScriptGetFBlockStatus	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.coremini_get_fblock_status()</i> method.
ics.ScriptGetScriptStatus	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.coremini_get_status()</i> method.
ics.ScriptGetScriptStatusEx	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.get_script_status()</i> method.
ics.ScriptLoad	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.coremini_load()</i> method.
ics.ScriptReadAppSignal	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.coremini_read_app_signal()</i> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.ScriptReadRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_rx_message()</code> method.
<code>ics.ScriptReadTxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_tx_message()</code> method.
<code>ics.ScriptStart</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start()</code> method.
<code>ics.ScriptStartFBBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start_fblock()</code> method.
<code>ics.ScriptStop</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop()</code> method.
<code>ics.ScriptStopFBBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop_fblock()</code> method.
<code>ics.ScriptWriteAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_app_signal()</code> method.

Continued on next page

Table 1 – continued from previous page

ics.ScriptWriteRxMessage	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.coremini_write_rx_message()</i> method.
ics.ScriptWriteTxMessage	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.coremini_write_tx_message()</i> method.
ics.SetActiveVNETChannel	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_active_vnet_channel()</i> method.
ics.SetBackupPowerEnabled	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_backup_power_enabled()</i> method.
ics.SetBitRate	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_bit_rate()</i> method.
ics.SetBitRateEx	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_bit_rate_ex()</i> method.
ics.SetContext	Note: Compatibility Function: Identical to PEP8 compliant <i>ics.ics.set_context()</i> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.SetDeviceSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_device_settings()</code> method.
<code>ics.SetFDBitRate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_fd_bit_rate()</code> method.
<code>ics.SetRTC</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_rtc()</code> method.
<code>ics.SetReflashDisplayCallback</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_reflash_callback()</code> method.
<code>ics.TxMessages</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.transmit_messages()</code> method.
<code>ics.ValidateHObject</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.validate_hobject()</code> method.
<code>ics.WriteJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.write_jupiter_firmware()</code> method.
<code>ics.WriteSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.write_sdcard()</code> method.
<code>ics.base36enc(serial)</code>	Converts a decimal serial number to base36.

Continued on next page

Table 1 – continued from previous page

ics.icsneoClosePort	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.close_device()</code> method.</p>
ics.icsneoEnableBusVoltageMonitor	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_bus_voltage_monitor()</code> method.</p>
ics.icsneoEnableNetworkCom	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.enable_network_com()</code> method.</p>
ics.icsneoFindNeoDevices	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.find_devices()</code> method.</p>
ics.icsneoFirmwareUpdateRequired	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.firmware_update_required()</code> method.</p>
ics.icsneoForceFirmwareUpdate	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.force_firmware_update()</code> method.</p>
ics.icsneoGetActiveVNETChannel	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_active_vnet_channel()</code> method.</p>

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoGetBackupPowerEnabled</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_enabled()</code> method.
<code>ics.icsneoGetBackupPowerReady</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_backup_power_ready()</code> method.
<code>ics.icsneoGetBusVoltage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_bus_voltage()</code> method.
<code>ics.icsneoGetDLLFirmwareInfo</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_firmware_info()</code> method.
<code>ics.icsneoGetDLLVersion</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_dll_version()</code> method.
<code>ics.icsneoGetDeviceSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_settings()</code> method.
<code>ics.icsneoGetDeviceStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_device_status()</code> method.

Continued on next page

Table 1 – continued from previous page

ics.icsneoGetErrorMessages	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_error_messages()</code> method.</p>
ics.icsneoGetHWFirmwareInfo	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_hw_firmware_info()</code> method.</p>
ics.icsneoGetLastAPIError	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_last_api_error()</code> method.</p>
ics.icsneoGetMessages	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_messages()</code> method.</p>
ics.icsneoGetPerformanceParameters	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_performance_parameters()</code> method.</p>
ics.icsneoGetRTC	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_rtc()</code> method.</p>
ics.icsneoGetSerialNumber	<p>Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_serial_number()</code> method.</p>

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoGetTimeStampForMsg</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_timestamp_for_msg()</code> method.
<code>ics.icsneoISO15765_DisableNetworks</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.iso15765_disable_networks()</code> method.
<code>ics.icsneoISO15765_EnableNetworks</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.iso15765_enable_networks()</code> method.
<code>ics.icsneoISO15765_ReceiveMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.iso15765_receive_message()</code> method.
<code>ics.icsneoISO15765_TransmitMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.iso15765_transmit_message()</code> method.
<code>ics.icsneoLoadDefaultSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.load_default_settings()</code> method.
<code>ics.icsneoOpenNeoDevice</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.open_device()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoReadJupiterFirmware</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_jupiter_firmware()</code> method.
<code>ics.icsneoReadSDCard</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.read_sdcard()</code> method.
<code>ics.icsneoRequestDiskDetails</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_details()</code> method.
<code>ics.icsneoRequestDiskFormat</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format()</code> method.
<code>ics.icsneoRequestDiskFormatCancel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.disk_format_cancel()</code> method.
<code>ics.icsneoRequestDiskFormatProgress</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_disk_format_progress()</code> method.
<code>ics.icsneoRequestEnterSleepMode</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.request_enter_sleep_mode()</code> method.
<code>ics.icsneoScriptClear</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_clear()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoScriptGetFBlockStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_fblock_status()</code> method.
<code>ics.icsneoScriptGetScriptStatus</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_get_status()</code> method.
<code>ics.icsneoScriptGetScriptStatusEx</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.get_script_status()</code> method.
<code>ics.icsneoScriptLoad</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_load()</code> method.
<code>ics.icsneoScriptReadAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_app_signal()</code> method.
<code>ics.icsneoScriptReadRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_rx_message()</code> method.
<code>ics.icsneoScriptReadTxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_read_tx_message()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoScriptStart</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start()</code> method.
<code>ics.icsneoScriptStartFBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_start_fblock()</code> method.
<code>ics.icsneoScriptStop</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop()</code> method.
<code>ics.icsneoScriptStopFBlock</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_stop_fblock()</code> method.
<code>ics.icsneoScriptWriteAppSignal</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_app_signal()</code> method.
<code>ics.icsneoScriptWriteRxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_rx_message()</code> method.
<code>ics.icsneoScriptWriteTxMessage</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.coremini_write_tx_message()</code> method.

Continued on next page

Table 1 – continued from previous page

<code>ics.icsneoSetActiveVNETChannel</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_active_vnet_channel()</code> method.
<code>ics.icsneoSetBackupPowerEnabled</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_backup_power_enabled()</code> method.
<code>ics.icsneoSetBitRate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_bit_rate()</code> method.
<code>ics.icsneoSetBitRateEx</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_bit_rate_ex()</code> method.
<code>ics.icsneoSetContext</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_context()</code> method.
<code>ics.icsneoSetDeviceSettings</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_device_settings()</code> method.
<code>ics.icsneoSetFDBitRate</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_fd_bit_rate()</code> method.
<code>ics.icsneoSetRTC</code>	Note: Compatibility Function: Identical to PEP8 compliant <code>ics.ics.set_rtc()</code> method.

Continued on next page

Table 1 – continued from previous page

`ics.icsneoSetReflashDisplayCallbacks`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.set_reflash_callback()` method.

`ics.icsneoTxMessages`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.transmit_messages()` method.

`ics.icsneoValidateHObject`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.validate_hobject()` method.

`ics.icsneoWriteJupiterFirmware`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_jupiter_firmware()` method.

`ics.icsneoWriteSDCard`

Note: Compatibility Function: Identical to PEP8 compliant `ics.ics.write_sdcard()` method.

CHAPTER 9

Module Structures

```
class ics.structures.can_settings.can_settings

    BRP
        Structure/Union member

    Baudrate
        Structure/Union member

    Mode
        Structure/Union member

    SetBaudrate
        Structure/Union member

    TqProp
        Structure/Union member

    TqSeg1
        Structure/Union member

    TqSeg2
        Structure/Union member

    TqSync
        Structure/Union member

    auto_baud
        Structure/Union member

    innerFrameDelay25us
        Structure/Union member

    transceiver_mode
        Structure/Union member

class ics.structures.canfd_settings.canfd_settings
```

```
FDBRP
    Structure/Union member

FDBaudrate
    Structure/Union member

FDMode
    Structure/Union member

FDTDC
    Structure/Union member

FDTqProp
    Structure/Union member

FDTqSeg1
    Structure/Union member

FDTqSeg2
    Structure/Union member

FDTqSync
    Structure/Union member

reserved
    Structure/Union member

class ics.structures.canterm_settings.canterm_settings

reserved
    Structure/Union member

term_enabled
    Structure/Union member

term_network
    Structure/Union member

class ics.structures.disk_settings.disk_settings

disk_enables
    Structure/Union member

disk_format
    Structure/Union member

disk_layout
    Structure/Union member

rsvd
    Structure/Union member

class ics.structures.e_device_settings_type.e_device_settings_type
A ctypes-compatible IntEnum superclass.

DeviceCANHUBSettingsType = 19
DeviceCMProbeSettingsType = 22
DeviceECU_AVBSettingsType = 9
DeviceEEVBSettingsType = 15
```

```
DeviceEtherBadgeSettingsType = 30
DeviceFire2SettingsType = 2
DeviceFire3SettingsType = 28
DeviceFireSettingsType = 0
DeviceFireVnetSettingsType = 1
DeviceFlexVnetzSettingsType = 18
DeviceIEVBSettingsType = 20
DeviceNeoECU12SettingsType = 17
DeviceOBD2ProSettingsType = 23
DeviceOBD2SimSettingsType = 21
DeviceRADGalaxySettingsType = 4
DeviceRADGigalogSettingsType = 13
DeviceRADGigastarSettingsType = 26
DeviceRADJupiterSettingsType = 27
DeviceRADMoon2SettingsType = 11
DeviceRADPlutoSettingsType = 12
DeviceRADPlutoSwitchSettingsType = 25
DeviceRADStar2SettingsType = 5
DeviceRADSuperMoonSettingsType = 10
DeviceRadMoonDuoSettingsType = 29
DeviceRedSettingsType = 24
DeviceSettingsNone = 4294967295
DeviceSettingsTypeMax = 31
DeviceVCAN3SettingsType = 3
DeviceVCAN412SettingsType = 7
DeviceVCAN4IndSettingsType = 16
DeviceVCAN4SettingsType = 6
DeviceVCANRFSettingsType = 14
DeviceVividCANSettingsType = 8
from_param = <bound method e_device_settings_type.from_param of <enum 'e_device_set

class ics.structures.e_disk_format.e_disk_format
A ctypes-compatible IntEnum superclass.

DiskFormatFAT32 = 1
DiskFormatUnknown = 0
DiskFormatexFAT = 2
from_param = <bound method e_disk_format.from_param of <enum 'e_disk_format'>>
```

```
class ics.structures.e_disk_layout.e_disk_layout
    A ctypes-compatible IntEnum superclass.

        DiskLayoutIndividual = 4
        DiskLayoutRAID0 = 1
        DiskLayoutRAID1 = 2
        DiskLayoutRAID5 = 3
        DiskLayoutSpanned = 0
        from_param = <bound method e_disk_layout.from_param of <enum 'e_disk_layout'>>

class ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet_channel_t
    A ctypes-compatible IntEnum superclass.

        PlasmaIonVnetChannelA = 1
        PlasmaIonVnetChannelB = 2
        PlasmaIonVnetChannelMain = 0
        eFpgaStatusResp = 4
        eSoftCore = 3
        from_param = <bound method e_plasma_ion_vnet_channel_t.from_param of <enum 'e_plasma_ion_vnet_channel_t'>>

class ics.structures.ethernet10_g_settings.ethernet10_g_settings

    flags
        Structure/Union member

    gateway
        Structure/Union member

    ip_addr
        Structure/Union member

    link_speed
        Structure/Union member

    netmask
        Structure/Union member

    rsvd2
        Structure/Union member

class ics.structures.ethernet_network_status_t.ethernet_network_status_t

    linkFullDuplex
        Structure/Union member

    linkMode
        Structure/Union member

    linkSpeed
        Structure/Union member

    linkStatus
        Structure/Union member
```

```

networkId
    Structure/Union member

class ics.structures.ethernet_settings.ethernet_settings

auto_neg
    Structure/Union member

duplex
    Structure/Union member

led_mode
    Structure/Union member

link_speed
    Structure/Union member

rsvd
    Structure/Union member

class ics.structures.ethernet_settings2.ethernet_settings2

flags
    Structure/Union member

gateway
    Structure/Union member

ip_addr
    Structure/Union member

link_speed
    Structure/Union member

netmask
    Structure/Union member

rsvd
    Structure/Union member

class ics.structures.flex_vnet_mode.flex_vnet_mode
A ctypes-compatible IntEnum superclass.

flexVnetModeColdStart = 4
flexVnetModeDisabled = 0
flexVnetModeOneDual = 2
flexVnetModeOneSingle = 1
flexVnetModeTwoSingle = 3
from_param = <bound method flex_vnet_mode.from_param of <enum 'flex_vnet_mode'>>

class ics.structures.global_settings.global_settings

canhub
    Structure/Union member

chksum
    Structure/Union member

```

cmprobe
Structure/Union member

cyan
Structure/Union member

ecu
Structure/Union member

eevb
Structure/Union member

etherBadge
Structure/Union member

fire
Structure/Union member

fire3
Structure/Union member

firevnet
Structure/Union member

flexvnetz
Structure/Union member

ievb
Structure/Union member

jupiter
Structure/Union member

len
Structure/Union member

neoecu12
Structure/Union member

neoecu_avb
Structure/Union member

neoobd2_sim
Structure/Union member

obd2pro
Structure/Union member

pendant
Structure/Union member

pluto
Structure/Union member

radgalaxy
Structure/Union member

radgigalog
Structure/Union member

radgigastar
Structure/Union member

```
radmoon2
    Structure/Union member

radmoonduo
    Structure/Union member

radstar2
    Structure/Union member

radsupermoon
    Structure/Union member

red
    Structure/Union member

vcan3
    Structure/Union member

vcan4
    Structure/Union member

vcan412
    Structure/Union member

vcan4_12
    Structure/Union member

vcan4_ind
    Structure/Union member

vcanrf
    Structure/Union member

version
    Structure/Union member

vividcan
    Structure/Union member

class ics.structures.ics_device_status.ics_device_status

    fire2Status
        Structure/Union member

    fire3Status
        Structure/Union member

    flexVnetzStatus
        Structure/Union member

    jupiterStatus
        Structure/Union member

    obd2proStatus
        Structure/Union member

    plutoStatus
        Structure/Union member

    radMoonDuoStatus
        Structure/Union member
```

```
    vcan4Status
        Structure/Union member

    vcan4indStatus
        Structure/Union member

class ics.structures.ics_fire2_device_status.ics_fire2_device_status

        backupPowerEnabled
            Structure/Union member

        backupPowerGood
            Structure/Union member

        ethernetActivationLineEnabled
            Structure/Union member

        ethernetStatus
            Structure/Union member

        usbHostPowerEnabled
            Structure/Union member

class ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device_status

        ethernetActivationLineEnabled
            Structure/Union member

        ethernetStatus
            Structure/Union member

        unused
            Structure/Union member

class ics.structures.ics_fire3_device_status.ics_fire3_device_status

        ethernetActivationLineEnabled
            Structure/Union member

        ethernetStatus
            Structure/Union member

        unused
            Structure/Union member

class ics.structures.ics_flex_vnetz_device_status.ics_flex_vnetz_device_status

        ethernetActivationLineEnabled
            Structure/Union member

        ethernetStatus
            Structure/Union member

        unused
            Structure/Union member

class ics.structures.ics_obd2_pro_device_status.ics_obd2_pro_device_status
```

```
    ethernetStatus
        Structure/Union member

class ics.structures.ics_rad_jupiter_device_status.ics_rad_jupiter_device_status

    ethernetStatus
        Structure/Union member

class ics.structures.ics_rad_moon_duo_device_status.ics_rad_moon_duo_device_status

    ethernetStatus
        Structure/Union member

class ics.structures.ics_rad_pluto_device_status.ics_rad_pluto_device_status

    ethernetStatus
        Structure/Union member

class ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray

    AckBytes
        Structure/Union member

    ArbIDOrHeader
        Structure/Union member

    Data
        Structure/Union member

    DescriptionID
        Structure/Union member

    ExtraDataPtr
        Structure/Union member

    ExtraDataPtrEnabled
        Structure/Union member

    MessagePieceID
        Structure/Union member

    MiscData
        Structure/Union member

    NetworkID
        Structure/Union member

    NetworkID2
        Structure/Union member

    NodeID
        Structure/Union member

    NumberBytesData
        Structure/Union member

    NumberBytesHeader
        Structure/Union member
```

Protocol
Structure/Union member

Reserved
Structure/Union member

StatusBitField
Structure/Union member

StatusBitField2
Structure/Union member

StatusBitField3
Structure/Union member

StatusBitField4
Structure/Union member

TimeHardware
Structure/Union member

TimeHardware2
Structure/Union member

TimeStampHardwareID
Structure/Union member

TimeStampSystemID
Structure/Union member

TimeSystem
Structure/Union member

TimeSystem2
Structure/Union member

chA
Structure/Union member

chB
Structure/Union member

cycle
Structure/Union member

dynamic
Structure/Union member

fcrc0
Structure/Union member

fcrc1
Structure/Union member

fcrc2
Structure/Union member

frame_len_12_5ns
Structure/Union member

frame_reserved
Structure/Union member

```
    hcrc_lsbs
        Structure/Union member

    hcrc_msbs
        Structure/Union member

    id
        Structure/Union member

    null_frame
        Structure/Union member

    payload_preamble
        Structure/Union member

    res1
        Structure/Union member

    res2
        Structure/Union member

    startup
        Structure/Union member

    sync
        Structure/Union member

    tss_len_12_5ns
        Structure/Union member

class ics.structures.ics_spy_message_long.ics_spy_message_long

    AckBytes
        Structure/Union member

    ArbIDOrHeader
        Structure/Union member

    DataLsb
        Structure/Union member

    DataMsb
        Structure/Union member

    DescriptionID
        Structure/Union member

    ExtraDataPtr
        Structure/Union member

    ExtraDataPtrEnabled
        Structure/Union member

    MessagePieceID
        Structure/Union member

    MiscData
        Structure/Union member

    NetworkID
        Structure/Union member
```

```
NetworkID2
Structure/Union member

NodeID
Structure/Union member

NumberBytesData
Structure/Union member

NumberBytesHeader
Structure/Union member

Protocol
Structure/Union member

Reserved
Structure/Union member

StatusBitField
Structure/Union member

StatusBitField2
Structure/Union member

StatusBitField3
Structure/Union member

StatusBitField4
Structure/Union member

TimeHardware
Structure/Union member

TimeHardware2
Structure/Union member

TimeStampHardwareID
Structure/Union member

TimeStampSystemID
Structure/Union member

TimeSystem
Structure/Union member

TimeSystem2
Structure/Union member

class ics.structures.ics_spy_message_vsb.ics_spy_message_vsb

AckBytes
Structure/Union member

ArbIDOrHeader
Structure/Union member

Data
Structure/Union member

DescriptionID
Structure/Union member
```

ExtraDataPtr
Structure/Union member

ExtraDataPtrEnabled
Structure/Union member

MessagePieceID
Structure/Union member

MiscData
Structure/Union member

NetworkID
Structure/Union member

NetworkID2
Structure/Union member

NodeID
Structure/Union member

NumberBytesData
Structure/Union member

NumberBytesHeader
Structure/Union member

Protocol
Structure/Union member

Reserved
Structure/Union member

StatusBitField
Structure/Union member

StatusBitField2
Structure/Union member

StatusBitField3
Structure/Union member

StatusBitField4
Structure/Union member

TimeHardware
Structure/Union member

TimeHardware2
Structure/Union member

TimeStampHardwareID
Structure/Union member

TimeStampSystemID
Structure/Union member

TimeSystem
Structure/Union member

TimeSystem2
Structure/Union member

```
class ics.structures.ics_vcan4_device_status.ics_vcan4_device_status

    ethernetActivationLineEnabled
        Structure/Union member

    ethernetStatus
        Structure/Union member

    unused
        Structure/Union member

class ics.structures.ics_vcan4_industrial_device_status.ics_vcan4_industrial_device_status

    ethernetStatus
        Structure/Union member

class ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message

    blockSize
        Structure/Union member

    data
        Structure/Union member

    ext_address_enable
        Structure/Union member

    extendedAddress
        Structure/Union member

    fc_ext_address_enable
        Structure/Union member

    fc_id
        Structure/Union member

    fc_id_29_bit_enable
        Structure/Union member

    fc_id_mask
        Structure/Union member

    flags
        Structure/Union member

    flowControlExtendedAddress
        Structure/Union member

    fs_timeout
        Structure/Union member

    fs_wait
        Structure/Union member

    id
        Structure/Union member

    id_29_bit_enable
        Structure/Union member
```

```
    isBRSEnabled
        Structure/Union member

    iscanFD
        Structure/Union member

    num_bytes
        Structure/Union member

    overrideBlockSize
        Structure/Union member

    overrideSTmin
        Structure/Union member

    padding
        Structure/Union member

    paddingEnable
        Structure/Union member

    stMin
        Structure/Union member

    tx_dl
        Structure/Union member

    tx_index
        Structure/Union member

    vs_netid
        Structure/Union member

class ics.structures.iso9141_keyword2000_init_step.iso9141_keyword2000_init_step

    k
        Structure/Union member

    l
        Structure/Union member

    time_500us
        Structure/Union member

class ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings

    Baudrate
        Structure/Union member

    brgh
        Structure/Union member

    chksum_enabled
        Structure/Union member

    init_step_count
        Structure/Union member

    init_steps
        Structure/Union member
```

```
p2_500us
Structure/Union member

p3_500us
Structure/Union member

p4_500us
Structure/Union member

spbrg
Structure/Union member

class ics.structures.j1708_settings.j1708_settings

enable_convert_mode
Structure/Union member

class ics.structures.j2534_adapter_information.j2534_adapter_information

Status
Structure/Union member

bIPV4_Address
Structure/Union member

bIPV6_Address
Structure/Union member

bMAC_Address
Structure/Union member

szDeviceName
Structure/Union member

szName
Structure/Union member

class ics.structures.lin_settings.lin_settings

Baudrate
Structure/Union member

MasterResistor
Structure/Union member

Mode
Structure/Union member

brgh
Structure/Union member

numBitsDelay
Structure/Union member

spbrg
Structure/Union member

class ics.structures.logger_settings.logger_settings
```

```
extraction_timeout
    Structure/Union member

rsvd
    Structure/Union member

class ics.structures.op_eth_general_settings.op_eth_general_settings

    flags
        Structure/Union member

    reserved0
        Structure/Union member

    tapPair0
        Structure/Union member

    tapPair1
        Structure/Union member

    tapPair2
        Structure/Union member

    tapPair3
        Structure/Union member

    tapPair4
        Structure/Union member

    tapPair5
        Structure/Union member

    uFlags
        Structure/Union member

    ucInterfaceType
        Structure/Union member

class ics.structures.op_eth_link_mode.op_eth_link_mode
A ctypes-compatible IntEnum superclass.

    OPETH_LINK_AUTO = 0
    OPETH_LINK_MASTER = 1
    OPETH_LINK_SLAVE = 2

    from_param = <bound method op_eth_link_mode.from_param of <enum 'op_eth_link_mode'>

class ics.structures.op_eth_settings.op_eth_settings

    link_spd
        Structure/Union member

    mac_addr1
        Structure/Union member

    mac_addr2
        Structure/Union member

    mac_spoofing_en
        Structure/Union member
```

```
mac_spoofing_isDstOrSrc
    Structure/Union member

preemption_en
    Structure/Union member

q2112_phy_mode
    Structure/Union member

reserved
    Structure/Union member

reserved0
    Structure/Union member

ucConfigMode
    Structure/Union member

class ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_converter_settings

    converter1Mode
        Structure/Union member

    ipAddress
        Structure/Union member

    ipGateway
        Structure/Union member

    ipMask
        Structure/Union member

    linkMode0
        Structure/Union member

    linkMode1
        Structure/Union member

class ics.structures.rad_reporting_settings.rad_reporting_settings

    flags
        Structure/Union member

    gps_interval_ms
        Structure/Union member

    io_interval_ms
        Structure/Union member

    rsvd
        Structure/Union member

    serdes_interval_ms
        Structure/Union member

    temp_interval_ms
        Structure/Union member

class ics.structures.s_cm_probe_settings.s_cm_probe_settings
```

```
network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

class ics.structures.s_cyan_settings.s_cyan_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    busMessagesToAndroid
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    can3
        Structure/Union member

    can4
        Structure/Union member

    can5
        Structure/Union member

    can6
        Structure/Union member

    can7
        Structure/Union member

    can8
        Structure/Union member

    can_switch_mode
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    canfd3
        Structure/Union member

    canfd4
        Structure/Union member

    canfd5
        Structure/Union member

    canfd6
        Structure/Union member
```

```
canfd7
    Structure/Union member

canfd8
    Structure/Union member

digitalIoThresholdEnable
    Structure/Union member

digitalIoThresholdTicks
    Structure/Union member

disableUsbCheckOnBoot
    Structure/Union member

disk
    Structure/Union member

enableDefaultLogger
    Structure/Union member

enableDefaultUpload
    Structure/Union member

enableLatencyTest
    Structure/Union member

enablePcEthernetComm
    Structure/Union member

ethernet
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

idle_wakeup_network_enables_1
    Structure/Union member

idle_wakeup_network_enables_2
    Structure/Union member

idle_wakeup_network_enables_3
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso9141_kwp_settings_2
    Structure/Union member

iso9141_kwp_settings_3
    Structure/Union member

iso9141_kwp_settings_4
    Structure/Union member
```

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_msg_termination_3
Structure/Union member

iso_msg_termination_4
Structure/Union member

iso_parity_1
Structure/Union member

iso_parity_2
Structure/Union member

iso_parity_3
Structure/Union member

iso_parity_4
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

lin3
Structure/Union member

lin4
Structure/Union member

lin5
Structure/Union member

lin6
Structure/Union member

lsftcan1
Structure/Union member

lsftcan2
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

```
misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

slaveVnetA
    Structure/Union member

slaveVnetB
    Structure/Union member

swcan1
    Structure/Union member

swcan2
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

timeSync
    Structure/Union member

class ics.structures.s_device_settings.s_device_settings

    DeviceSettingType
        Structure/Union member

    Settings
        Structure/Union member

    canhub
        Structure/Union member

    cmprobe
        Structure/Union member
```

cyan
Structure/Union member

ecu
Structure/Union member

eevb
Structure/Union member

etherBadge
Structure/Union member

fire
Structure/Union member

fire3
Structure/Union member

firevnet
Structure/Union member

flexvnetz
Structure/Union member

ievb
Structure/Union member

jupiter
Structure/Union member

neoecu12
Structure/Union member

neoecu_avb
Structure/Union member

neoobd2_sim
Structure/Union member

obd2pro
Structure/Union member

pendant
Structure/Union member

pluto
Structure/Union member

plutoswitch
Structure/Union member

radgalaxy
Structure/Union member

radgigalog
Structure/Union member

radgigastar
Structure/Union member

radmoon2
Structure/Union member

```
radmoon_duo
    Structure/Union member

radstar2
    Structure/Union member

radsupermoon
    Structure/Union member

red
    Structure/Union member

vcan3
    Structure/Union member

vcan4
    Structure/Union member

vcan412
    Structure/Union member

vcan4_12
    Structure/Union member

vcan4_ind
    Structure/Union member

vcanrf
    Structure/Union member

vividcan
    Structure/Union member

class ics.structures.s_disk_details.s_disk_details

    status
        Structure/Union member

    structure
        Structure/Union member

class ics.structures.s_disk_format_progress.s_disk_format_progress

    sectorsRemaining
        Structure/Union member

    state
        Structure/Union member

class ics.structures.s_disk_status.s_disk_status

    bytesPerSector
        Structure/Union member

    sectors
        Structure/Union member

    status
        Structure/Union member
```

```
class ics.structures.s_disk_structure.s_disk_structure

    options
        Structure/Union member

    settings
        Structure/Union member

class ics.structures.s_ext_sub_cmd_comm.s_ext_sub_cmd_comm

    details
        Structure/Union member

    hdr
        Structure/Union member

    progress
        Structure/Union member

    structure
        Structure/Union member

class ics.structures.s_ext_sub_cmd_hdr.s_ext_sub_cmd_hdr

    cmd
        Structure/Union member

    length
        Structure/Union member

class ics.structures.s_extended_data_flash_header.s_extended_data_flash_header

    chksum
        Structure/Union member

    len
        Structure/Union member

    version
        Structure/Union member

class ics.structures.s_fire3_settings.s_fire3_settings

    ain_threshold
        Structure/Union member

    busMessagesToAndroid
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    can3
        Structure/Union member
```

can4
Structure/Union member

can5
Structure/Union member

can6
Structure/Union member

can7
Structure/Union member

can8
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

canfd5
Structure/Union member

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

digitalIoThresholdEnable
Structure/Union member

digitalIoThresholdTicks
Structure/Union member

disableUsbCheckOnBoot
Structure/Union member

disk
Structure/Union member

enableDefaultLogger
Structure/Union member

enableDefaultUpload
Structure/Union member

enableLatencyTest
Structure/Union member

enablePcEthernetComm
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_parity_1
Structure/Union member

iso_parity_2
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

```
perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

slaveVnetA
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

timeSync
    Structure/Union member

word
    Structure/Union member

class ics.structures.s_fire_settings.s_fire_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    can3
        Structure/Union member

    can4
        Structure/Union member

    cgi_baud
        Structure/Union member

    cgi_chksum_enable
        Structure/Union member

    cgi_enable_reserved
        Structure/Union member

    cgi_rx_ifs_bit_times
        Structure/Union member

    cgi_tx_ifs_bit_times
        Structure/Union member
```

```
fast_init_network_enables_1
    Structure/Union member

fast_init_network_enables_2
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_enable_reserved
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso9141_kwp_settings_2
    Structure/Union member

iso9141_kwp_settings_3
    Structure/Union member

iso9141_kwp_settings_4
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_msg_termination_2
    Structure/Union member

iso_msg_termination_3
    Structure/Union member

iso_msg_termination_4
    Structure/Union member

iso_parity
    Structure/Union member

iso_parity_2
    Structure/Union member

iso_parity_3
    Structure/Union member

iso_parity_4
    Structure/Union member

iso_tester_pullup_enable
    Structure/Union member

lin1
    Structure/Union member

lin2
    Structure/Union member

lin3
    Structure/Union member

lin4
    Structure/Union member
```

```
    lsftcan
        Structure/Union member

    misc_io_analog_enable
        Structure/Union member

    misc_io_initial_ddr
        Structure/Union member

    misc_io_initial_latch
        Structure/Union member

    misc_io_on_report_events
        Structure/Union member

    misc_io_report_period
        Structure/Union member

    neoMostGateway
        Structure/Union member

    network_enabled_on_boot
        Structure/Union member

    network_enables
        Structure/Union member

    network_enables_2
        Structure/Union member

    perf_en
        Structure/Union member

    pwm_man_timeout
        Structure/Union member

    pwr_man_enable
        Structure/Union member

    swcan
        Structure/Union member

    text_api
        Structure/Union member

    uart
        Structure/Union member

    uart2
        Structure/Union member

    vnetBits
        Structure/Union member

class ics.structures.s_fire_vnet_settings.s_fire_vnet_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member
```

can1
Structure/Union member

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

can5
Structure/Union member

can6
Structure/Union member

cgi_baud
Structure/Union member

cgi_chksum_enable
Structure/Union member

cgi_enable_reserved
Structure/Union member

cgi_rx_ifs_bit_times
Structure/Union member

cgi_tx_ifs_bit_times
Structure/Union member

fast_init_network_enables_1
Structure/Union member

fast_init_network_enables_2
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_enable_reserved
Structure/Union member

iso9141_kwp_settings
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso9141_kwp_settings_3
Structure/Union member

iso9141_kwp_settings_4
Structure/Union member

iso_msg_termination
Structure/Union member

iso_msg_termination_2
Structure/Union member

```
iso_msg_termination_3
    Structure/Union member

iso_msg_termination_4
    Structure/Union member

iso_parity
    Structure/Union member

iso_parity_2
    Structure/Union member

iso_parity_3
    Structure/Union member

iso_parity_4
    Structure/Union member

iso_tester_pullup_enable
    Structure/Union member

lin1
    Structure/Union member

lin2
    Structure/Union member

lin3
    Structure/Union member

lin4
    Structure/Union member

lin5
    Structure/Union member

lsftcan
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

neoMostGateway
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member
```

```
network_enables_2
    Structure/Union member

perf_en
    Structure/Union member

pwm_man_timeout
    Structure/Union member

pwr_man_enable
    Structure/Union member

swcan
    Structure/Union member

swcan2
    Structure/Union member

text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

vnetBits
    Structure/Union member

class ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings

busMessagesToAndroid
    Structure/Union member

can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can5
    Structure/Union member

can6
    Structure/Union member

can7
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member
```

```
canfd3
    Structure/Union member

canfd4
    Structure/Union member

canfd5
    Structure/Union member

canfd6
    Structure/Union member

canfd7
    Structure/Union member

disableUsbCheckOnBoot
    Structure/Union member

disk
    Structure/Union member

enableDefaultLogger
    Structure/Union member

enableDefaultUpload
    Structure/Union member

enableLatencyTest
    Structure/Union member

enablePcEthernetComm
    Structure/Union member

ethernet
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

flex_mode
    Structure/Union member

flex_termination
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member
```

```
network_enables_3
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

slaveVnetA
    Structure/Union member

slaveVnetB
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

timeSync
    Structure/Union member

word
    Structure/Union member

class ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    can_switch_mode
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    disableUsbCheckOnBoot
        Structure/Union member

    ecu_id
        Structure/Union member
```

```
enableLatencyTest
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso_9141_kwp_enable_reserved
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_parity
    Structure/Union member

lin1
    Structure/Union member

lsftcan1
    Structure/Union member

lsftcan2
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member
```

```
    swcan1
        Structure/Union member

    swcan2
        Structure/Union member

    termination_enables
        Structure/Union member

    text_api
        Structure/Union member

class ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway_settings

    Config
        Structure/Union member

    netId
        Structure/Union member

    zero0
        Structure/Union member

class ics.structures.s_pendant_settings.s_pendant_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    ecu_id
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    iso9141_kwp_settings
        Structure/Union member

    iso9141_kwp_settings_2
        Structure/Union member

    iso_msg_termination
        Structure/Union member

    iso_msg_termination_2
        Structure/Union member

    iso_parity
        Structure/Union member

    iso_parity_2
        Structure/Union member
```

```
lin1
    Structure/Union member

lin2
    Structure/Union member

lsftcan
    Structure/Union member

lsftcan2
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

selected_network
    Structure/Union member

swcan
    Structure/Union member

swcan2
    Structure/Union member

text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

class ics.structures.s_phy_reg_pkt.s_phy_reg_pkt
```

```
Clause45Enable
    Structure/Union member

Enabled
    Structure/Union member

WriteEnable
    Structure/Union member

clause22
    Structure/Union member

clause45
    Structure/Union member

flags
    Structure/Union member

reserved
    Structure/Union member

version
    Structure/Union member

class ics.structures.s_phy_reg_pkt_clause22_mess.s_phy_reg_pkt_clause22_mess

page
    Structure/Union member

phyAddr
    Structure/Union member

regAddr
    Structure/Union member

regVal
    Structure/Union member

class ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt_clause45_mess

device
    Structure/Union member

port
    Structure/Union member

regAddr
    Structure/Union member

regVal
    Structure/Union member

class ics.structures.s_phy_reg_pkt_hdr.s_phy_reg_pkt_hdr

entryBytes
    Structure/Union member

numEntries
    Structure/Union member
```

```
version
    Structure/Union member

class ics.structures.s_pluto_avb_params_s.s_pluto_avb_params_s

destmeta
    Structure/Union member

srcmeta
    Structure/Union member

class ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_sync_params_s

accdevwin
    Structure/Union member

asytensyen
    Structure/Union member

caentmout
    Structure/Union member

etssrcpcf
    Structure/Union member

fullcbg
    Structure/Union member

intcydur
    Structure/Union member

inttosyncth
    Structure/Union member

inttotentth
    Structure/Union member

ipcframesy
    Structure/Union member

listentmout
    Structure/Union member

maxintegcy
    Structure/Union member

maxtranspclk
    Structure/Union member

numstbcy
    Structure/Union member

numunstbcy
    Structure/Union member

obvwinsz
    Structure/Union member

pad1
    Structure/Union member
```

pad2
Structure/Union member

pad3
Structure/Union member

pcfpriority
Structure/Union member

pcfsze
Structure/Union member

srcport
Structure/Union member

stabasyen
Structure/Union member

stth
Structure/Union member

sttointth
Structure/Union member

swmaster
Structure/Union member

syasyen
Structure/Union member

sydomain
Structure/Union member

sypriority
Structure/Union member

syrelen
Structure/Union member

sysyen
Structure/Union member

syth
Structure/Union member

sytostben
Structure/Union member

sytousyth
Structure/Union member

tentsyrelen
Structure/Union member

tsyth
Structure/Union member

tsytosyth
Structure/Union member

tsytousyth
Structure/Union member

```
unsytoсыт
Structure/Union member

unsytотсыт
Structure/Union member

vlidимнmin
Structure/Union member

vlidинmax
Structure/Union member

vlidout
Structure/Union member

vlidselect
Structure/Union member

waitthsync
Structure/Union member

wfintmout
Structure/Union member

class ics.structures.s_pluto_custom_params_s.s_pluto_custom_params_s

ae1Select
Structure/Union member

enablePhy
Structure/Union member

mode
Structure/Union member

pad
Structure/Union member

ptpParams
Structure/Union member

speed
Structure/Union member

usbSelect
Structure/Union member

class ics.structures.s_pluto_general_params_s.s_pluto_general_params_s

casc_port
Structure/Union member

host_port
Structure/Union member

hostprio
Structure/Union member

ignore2stf
Structure/Union member
```

```
    incl_srcpt0
        Structure/Union member

    incl_srcpt1
        Structure/Union member

    mac_flt0
        Structure/Union member

    mac_flt1
        Structure/Union member

    mac_fltres0
        Structure/Union member

    mac_fltres1
        Structure/Union member

    mirr_port
        Structure/Union member

    mirr_ptacu
        Structure/Union member

    send_meta0
        Structure/Union member

    send_meta1
        Structure/Union member

    switchid
        Structure/Union member

    tpid
        Structure/Union member

    tpid2
        Structure/Union member

    vllupformat
        Structure/Union member

    vlmarker
        Structure/Union member

    vlmask
        Structure/Union member

class ics.structures.s_pluto_12_address_lookup_entry_s.s_pluto_12_address_lookup_entry

    destports
        Structure/Union member

    enfport
        Structure/Union member

    index
        Structure/Union member

    learnedEntry
        Structure/Union member
```

```
macaddr
    Structure/Union member

pad1
    Structure/Union member

pad2
    Structure/Union member

pad3
    Structure/Union member

vlanID
    Structure/Union member

class ics.structures.s_pluto_12_address_lookup_params_s.s_pluto_12_address_lookup_params_s

dyn_tbsz
    Structure/Union member

maxage
    Structure/Union member

no_enf_hostprt
    Structure/Union member

no_mgmt_learn
    Structure/Union member

pad
    Structure/Union member

poly
    Structure/Union member

shared_learn
    Structure/Union member

class ics.structures.s_pluto_12_forwarding_entry_s.s_pluto_12_forwarding_entry_s

bc_domain
    Structure/Union member

f1_domain
    Structure/Union member

pad
    Structure/Union member

reach_port
    Structure/Union member

vlan_pmap
    Structure/Union member

class ics.structures.s_pluto_12_forwarding_params_s.s_pluto_12_forwarding_params_s

max_dynp
    Structure/Union member
```

```
pad
    Structure/Union member

part_spc
    Structure/Union member

class ics.structures.s_pluto_12_policing_s.s_pluto_12_policing_s

maxlen
    Structure/Union member

partition
    Structure/Union member

rate
    Structure/Union member

sharindx
    Structure/Union member

smax
    Structure/Union member

class ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s

base
    Structure/Union member

drpdtag
    Structure/Union member

drpnona64
    Structure/Union member

drpuntag
    Structure/Union member

dyn_learn
    Structure/Union member

egr_mirr
    Structure/Union member

egress
    Structure/Union member

enabled
    Structure/Union member

ifg
    Structure/Union member

ing_mirr
    Structure/Union member

ingress
    Structure/Union member

maxage
    Structure/Union member
```

```
pad
    Structure/Union member

retag
    Structure/Union member

speed
    Structure/Union member

top
    Structure/Union member

tp_delin
    Structure/Union member

tp_delout
    Structure/Union member

vlanid
    Structure/Union member

vlanprio
    Structure/Union member

class ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s

destports
    Structure/Union member

do_not_learn
    Structure/Union member

egr_port
    Structure/Union member

ing_port
    Structure/Union member

pad
    Structure/Union member

use_dest_ports
    Structure/Union member

vlan_egress
    Structure/Union member

vlan_ingress
    Structure/Union member

class ics.structures.s_pluto_switch_settings_s.s_pluto_switch_settings_s

flashHeader
    Structure/Union member

generalParams
    Structure/Union member

l2ForwardingEntries
    Structure/Union member
```

```
12_addressLookupEntries
    Structure/Union member

12_addressLookupParams
    Structure/Union member

12_forwardingParams
    Structure/Union member

12_policing
    Structure/Union member

macConfig
    Structure/Union member

retagging
    Structure/Union member

vlan_LookupEntries
    Structure/Union member

class ics.structures.s_pluto_vl_forwarding_entry_s.s_pluto_vl_forwarding_entry_s

destports
    Structure/Union member

partition
    Structure/Union member

priority
    Structure/Union member

type
    Structure/Union member

class ics.structures.s_pluto_vl_forwarding_params_s.s_pluto_vl_forwarding_params_s

debugen
    Structure/Union member

pad
    Structure/Union member

partspc
    Structure/Union member

class ics.structures.s_pluto_vl_lookup_entry_s.s_pluto_vl_lookup_entry_s

vllupformat0
    Structure/Union member

vllupformat1
    Structure/Union member

class ics.structures.s_pluto_vl_policing_entry_s.s_pluto_vl_policing_entry_s

bag
    Structure/Union member
```

```
jitter
    Structure/Union member

maxlen
    Structure/Union member

sharindx
    Structure/Union member

type
    Structure/Union member

class ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_s

pad
    Structure/Union member

tag_port
    Structure/Union member

vegr_mirr
    Structure/Union member

ving_mirr
    Structure/Union member

vlan_bc
    Structure/Union member

vlanid
    Structure/Union member

vmemb_port
    Structure/Union member

class ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings

converter
    Structure/Union member

disableUsbCheckOnBoot
    Structure/Union member

enableLatencyTest
    Structure/Union member

flags
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member
```

```
pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

class ics.structures.s_red_settings.s_red_settings

    can1
        Structure/Union member

    can2
        Structure/Union member

    lin1
        Structure/Union member

    lin2
        Structure/Union member

class ics.structures.s_text_api_settings.s_text_api_settings

    DWord
        Structure/Union member

    bExtended
        Structure/Union member

    can1_options
        Structure/Union member

    can1_rx_id
        Structure/Union member

    can1_tx_id
        Structure/Union member

    can2_options
        Structure/Union member

    can2_rx_id
        Structure/Union member

    can2_tx_id
        Structure/Union member

    can3_options
        Structure/Union member

    can3_rx_id
        Structure/Union member

    can3_tx_id
        Structure/Union member

    can4_options
        Structure/Union member

    can4_rx_id
        Structure/Union member
```

```
can4_tx_id
Structure/Union member

network_enables
Structure/Union member

reserved
Structure/Union member

class ics.structures.s_vivid_can_settings.s_vivid_can_settings

can1
Structure/Union member

can_switch_mode
Structure/Union member

disableUsbCheckOnBoot
Structure/Union member

ecu_id
Structure/Union member

enableLatencyTest
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

lsftcan1
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reserved
Structure/Union member

swcan1
Structure/Union member

termination_enables
Structure/Union member

class ics.structures.scan_hub_settings.scan_hub_settings
```

```
can1
    Structure/Union member

canfd1
    Structure/Union member

ecu_id
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

termination_enables
    Structure/Union member

class ics.structures.secu_avb_settings.secu_avb_settings

can1
    Structure/Union member

can2
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

disableUsbCheckOnBoot
    Structure/Union member

enableLatencyTest
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member
```

```
pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.secu_settings.secu_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    ecu_id
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    iso9141_kwp_settings
        Structure/Union member

    iso9141_kwp_settings_2
        Structure/Union member

    iso_msg_termination
        Structure/Union member

    iso_msg_termination_2
        Structure/Union member

    iso_parity
        Structure/Union member

    iso_parity_2
        Structure/Union member

    lin1
        Structure/Union member

    lin2
        Structure/Union member

    lsftcan
        Structure/Union member
```

```
lsftcan2
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

selected_network
    Structure/Union member

swcan
    Structure/Union member

swcan2
    Structure/Union member

text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

class ics.structures.seevb_settings.seevb_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member
```

```
    ecu_id
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    network_enabled_on_boot
        Structure/Union member

    network_enables
        Structure/Union member

    perf_en
        Structure/Union member

    rsvd
        Structure/Union member

class ics.structures.serdescam_settings.serdescam_settings

    bitPos
        Structure/Union member

    flags
        Structure/Union member

    frameSkip
        Structure/Union member

    mode
        Structure/Union member

    resHeight
        Structure/Union member

    resWidth
        Structure/Union member

    rsvd1
        Structure/Union member

    rsvd2
        Structure/Union member

    videoFormat
        Structure/Union member

class ics.structures.serdespoc_settings.serdespoc_settings

    chksum
        Structure/Union member

    mode
        Structure/Union member

    rsvd
        Structure/Union member

    voltage
        Structure/Union member
```

```
class ics.structures.sievb_settings.sievb_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    ecu_id
        Structure/Union member

    idle_wakeup_network_enables_1
        Structure/Union member

    idle_wakeup_network_enables_2
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    iso9141_kwp_settings
        Structure/Union member

    iso9141_kwp_settings_2
        Structure/Union member

    iso_msg_termination
        Structure/Union member

    iso_msg_termination_2
        Structure/Union member

    iso_parity
        Structure/Union member

    iso_parity_2
        Structure/Union member

    iso_tester_pullup_enable
        Structure/Union member

    lin1
        Structure/Union member

    lin2
        Structure/Union member

    misc_io_analog_enable
        Structure/Union member

    misc_io_analog_enable_2
        Structure/Union member

    misc_io_initial_ddr
        Structure/Union member
```

```
misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved_1
    Structure/Union member

reserved_2
    Structure/Union member

selected_network
    Structure/Union member

text_api
    Structure/Union member

uart
    Structure/Union member

uart2
    Structure/Union member

class ics.structures.sobd2_pro_settings.sobd2_pro_settings

can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can_switch_mode
    Structure/Union member

canfd1
    Structure/Union member
```

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

disableUsbCheckOnBoot
Structure/Union member

enableLatencyTest
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso9141_kwp_settings_2
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_msg_termination_2
Structure/Union member

iso_parity_1
Structure/Union member

iso_parity_2
Structure/Union member

lin1
Structure/Union member

lin2
Structure/Union member

misc_io_analog_enable
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

perf_en
Structure/Union member

```
pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

swcan1
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.sobd2_sim_settings.sobd2_sim_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    enableLatencyTest
        Structure/Union member

    flags
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    misc_io_analog_enable
        Structure/Union member

    misc_io_initial_ddr
        Structure/Union member

    misc_io_initial_latch
        Structure/Union member

    misc_io_on_report_events
        Structure/Union member

    misc_io_report_period
        Structure/Union member

    network_enabled_on_boot
        Structure/Union member
```

```
network_enables
    Structure/Union member

perf_en
    Structure/Union member

reserved
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.spy_filter_long.spy_filter_long

    ByteDataLSB
        Structure/Union member

    ByteDataLength
        Structure/Union member

    ByteDataMSB
        Structure/Union member

    ByteDataMaskLSB
        Structure/Union member

    ByteDataMaskMSB
        Structure/Union member

    ExpectedLength
        Structure/Union member

    FrameMaster
        Structure/Union member

    Header
        Structure/Union member

    HeaderLength
        Structure/Union member

    HeaderMask
        Structure/Union member

    MiscData
        Structure/Union member

    MiscDataMask
        Structure/Union member

    NetworkID
        Structure/Union member

    NodeID
        Structure/Union member

    Status2Mask
        Structure/Union member

    Status2Value
        Structure/Union member
```

```
statusMask
    Structure/Union member

statusValue
    Structure/Union member

bStuff2
    Structure/Union member

bUseArbIdRangeFilter
    Structure/Union member

class ics.structures.srad_galaxy_settings.srad_galaxy_settings

    ain_sample_period
        Structure/Union member

    ain_threshold
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    can3
        Structure/Union member

    can4
        Structure/Union member

    can5
        Structure/Union member

    can6
        Structure/Union member

    can7
        Structure/Union member

    can8
        Structure/Union member

    can_switch_mode
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    canfd3
        Structure/Union member

    canfd4
        Structure/Union member

    canfd5
        Structure/Union member
```

canfd6
Structure/Union member

canfd7
Structure/Union member

canfd8
Structure/Union member

disk
Structure/Union member

ethernet1
Structure/Union member

ethernet2
Structure/Union member

hwComLatencyTestEn
Structure/Union member

idle_wakeup_network_enables_1
Structure/Union member

idle_wakeup_network_enables_2
Structure/Union member

idle_wakeup_network_enables_3
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

logger
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

```
misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

network_enables_4
    Structure/Union member

opEth1
    Structure/Union member

opEth10
    Structure/Union member

opEth11
    Structure/Union member

opEth12
    Structure/Union member

opEth2
    Structure/Union member

opEth3
    Structure/Union member

opEth4
    Structure/Union member

opEth5
    Structure/Union member

opEth6
    Structure/Union member

opEth7
    Structure/Union member

opEth8
    Structure/Union member

opEth9
    Structure/Union member

opEthGen
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member
```

```
pwr_man_timeout
    Structure/Union member

reporting
    Structure/Union member

swcan1
    Structure/Union member

swcan2
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.srad_gigalog_settings.srad_gigalog_settings

can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can5
    Structure/Union member

can6
    Structure/Union member

can7
    Structure/Union member

can8
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

canfd3
    Structure/Union member

canfd4
    Structure/Union member

canfd5
    Structure/Union member

canfd6
    Structure/Union member
```

```
canfd7
    Structure/Union member

canfd8
    Structure/Union member

disableUsbCheckOnBoot
    Structure/Union member

disk
    Structure/Union member

ecu_id
    Structure/Union member

ethernet
    Structure/Union member

ethernet10g
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

hwComLatencyTestEn
    Structure/Union member

idle_wakeup_network_enables_1
    Structure/Union member

idle_wakeup_network_enables_2
    Structure/Union member

idle_wakeup_network_enables_3
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso_9141_kwp_enable_reserved
    Structure/Union member

iso_msg_termination_1
    Structure/Union member

iso_parity_1
    Structure/Union member

lin1
    Structure/Union member

logger
    Structure/Union member

network_enabled_on_boot
    Structure/Union member
```

```
network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

network_enables_4
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reporting
    Structure/Union member

reserved
    Structure/Union member

rsvd1
    Structure/Union member

rsvd2
    Structure/Union member

serdescam1
    Structure/Union member

serdescam2
    Structure/Union member

serdescam3
    Structure/Union member

serdescam4
    Structure/Union member

serdespoc
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.srad_gigastar_settings.srad_gigastar_settings

can1
    Structure/Union member
```

```
can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

can5
    Structure/Union member

can6
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

canfd3
    Structure/Union member

canfd4
    Structure/Union member

canfd5
    Structure/Union member

canfd6
    Structure/Union member

disk
    Structure/Union member

ecu_id
    Structure/Union member

ethernet1
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

hwComLatencyTestEn
    Structure/Union member

idle_wakeup_network_enables_1
    Structure/Union member

idle_wakeup_network_enables_2
    Structure/Union member

idle_wakeup_network_enables_3
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member
```

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

logger
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

network_enables_4
Structure/Union member

opEth1
Structure/Union member

opEth2
Structure/Union member

opEthGen
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reporting
Structure/Union member

reserved
Structure/Union member

serdescam1
Structure/Union member

serdescam2
Structure/Union member

```
    serdescam3
        Structure/Union member

    serdescam4
        Structure/Union member

    serdespoc
        Structure/Union member

    termination_enables
        Structure/Union member

    text_api
        Structure/Union member

    timeSyncSettings
        Structure/Union member

class ics.structures.srad_jupiter_settings.srad_jupiter_settings

    can1
        Structure/Union member

    can2
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    disableUsbCheckOnBoot
        Structure/Union member

    enableLatencyTest
        Structure/Union member

    enablePcEthernetComm
        Structure/Union member

    ethernet
        Structure/Union member

    ethernet2
        Structure/Union member

    flags
        Structure/Union member

    iso15765_separation_time_offset
        Structure/Union member

    iso9141_kwp_enable_reserved
        Structure/Union member

    iso9141_kwp_settings
        Structure/Union member

    iso_msg_termination
        Structure/Union member
```

```
    iso_parity
        Structure/Union member

    iso_tester_pullup_enable
        Structure/Union member

    lin1
        Structure/Union member

    misc_io_analog_enable
        Structure/Union member

    network_enabled_on_boot
        Structure/Union member

    network_enables
        Structure/Union member

    network_enables_2
        Structure/Union member

    network_enables_3
        Structure/Union member

    perf_en
        Structure/Union member

    pwr_man_enable
        Structure/Union member

    pwr_man_timeout
        Structure/Union member

    reserved
        Structure/Union member

    switchSettings
        Structure/Union member

    termination_enables
        Structure/Union member

    text_api
        Structure/Union member

class ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings

    enablePhy
        Structure/Union member

    pad
        Structure/Union member

    phyMode
        Structure/Union member

    port7Select
        Structure/Union member

    port8Legacy
        Structure/Union member
```

```
port8Select
    Structure/Union member

port8Speed
    Structure/Union member

spoofMacFlag
    Structure/Union member

spoofedMac
    Structure/Union member

class ics.structures.srad_moon2_settings.srad_moon2_settings

hwComLatencyTestEn
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

opEth1
    Structure/Union member

opEthGen
    Structure/Union member

pc_com_mode
    Structure/Union member

perf_en
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.srad_pluto_settings.srad_pluto_settings

can1
    Structure/Union member

can2
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member
```

```
custom
    Structure/Union member

disableUsbCheckOnBoot
    Structure/Union member

enableLatencyTest
    Structure/Union member

enablePcEthernetComm
    Structure/Union member

ethernet
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_enable_reserved
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_parity
    Structure/Union member

iso_tester_pullup_enable
    Structure/Union member

lin1
    Structure/Union member

misc_io_analog_enable
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member
```

```
pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.srad_star2_settings.srad_star2_settings

ain_sample_period
    Structure/Union member

ain_threshold
    Structure/Union member

can1
    Structure/Union member

can2
    Structure/Union member

can_switch_mode
    Structure/Union member

canfd1
    Structure/Union member

canfd2
    Structure/Union member

ethernet
    Structure/Union member

hwComLatencyTestEn
    Structure/Union member

idle_wakeup_network_enables_1
    Structure/Union member

idle_wakeup_network_enables_2
    Structure/Union member

idle_wakeup_network_enables_3
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings_1
    Structure/Union member

iso_9141_kwp_enable_reserved
    Structure/Union member

iso_msg_termination_1
    Structure/Union member
```

iso_parity_1
Structure/Union member

lin1
Structure/Union member

misc_io_analog_enable
Structure/Union member

misc_io_initial_ddr
Structure/Union member

misc_io_initial_latch
Structure/Union member

misc_io_on_report_events
Structure/Union member

misc_io_report_period
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

network_enables_3
Structure/Union member

opEth1
Structure/Union member

opEth2
Structure/Union member

opEthGen
Structure/Union member

pc_com_mode
Structure/Union member

perf_en
Structure/Union member

pwr_man_enable
Structure/Union member

pwr_man_timeout
Structure/Union member

reporting
Structure/Union member

text_api
Structure/Union member

timeSyncSettings
Structure/Union member

```
class ics.structures.srad_super_moon_settings.srad_super_moon_settings

Eth2
    Structure/Union member

hwComLatencyTestEn
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

opEth1
    Structure/Union member

opEthGen
    Structure/Union member

pc_com_mode
    Structure/Union member

perf_en
    Structure/Union member

text_api
    Structure/Union member

timeSyncSettings
    Structure/Union member

class ics.structures.st_api_firmware_info.st_api_firmware_info

iAppMajor
    Structure/Union member

iAppMinor
    Structure/Union member

iBoardRevMajor
    Structure/Union member

iBoardRevMinor
    Structure/Union member

iBootLoaderVersionMajor
    Structure/Union member

iBootLoaderVersionMinor
    Structure/Union member

iMainFirmChkSum
    Structure/Union member
```

```
iMainFirmDateDay
    Structure/Union member

iMainFirmDateHour
    Structure/Union member

iMainFirmDateMin
    Structure/Union member

iMainFirmDateMonth
    Structure/Union member

iMainFirmDateSecond
    Structure/Union member

iMainFirmDateYear
    Structure/Union member

iMainVnetHWrevMajor
    Structure/Union member

iMainVnetHWrevMinor
    Structure/Union member

iMainVnetSRAMSize
    Structure/Union member

iManufactureDay
    Structure/Union member

iManufactureMonth
    Structure/Union member

iManufactureYear
    Structure/Union member

iPhySiliconRev
    Structure/Union member

iType
    Structure/Union member

class ics.structures.st_chip_versions.st_chip_versions

    cmprobe_versions
        Structure/Union member

    core_maj
        Structure/Union member

    core_major
        Structure/Union member

    core_min
        Structure/Union member

    core_minor
        Structure/Union member

    ether_badge_versions
        Structure/Union member
```

ext_flash_maj
Structure/Union member

ext_flash_min
Structure/Union member

fire3_versions
Structure/Union member

fire_versions
Structure/Union member

hid_maj
Structure/Union member

hid_min
Structure/Union member

jpic_maj
Structure/Union member

jpic_min
Structure/Union member

jupiter_versions
Structure/Union member

lpic_maj
Structure/Union member

lpic_min
Structure/Union member

mchip_major
Structure/Union member

mchip_minor
Structure/Union member

mpic_maj
Structure/Union member

mpic_min
Structure/Union member

neoecu_avb_versions
Structure/Union member

nrf52_maj
Structure/Union member

nrf52_min
Structure/Union member

obd2pro_versions
Structure/Union member

plasma_fire_vnet
Structure/Union member

pluto_versions
Structure/Union member

rad_moon_duo_versions
Structure/Union member

radgalaxy_versions
Structure/Union member

radgigalog3_versions
Structure/Union member

radgigalog_versions
Structure/Union member

radgigastar_usbz_versions
Structure/Union member

radgigastar_versions
Structure/Union member

radmoon2_versions
Structure/Union member

radstar2_versions
Structure/Union member

radsupermoon_versions
Structure/Union member

schip_major
Structure/Union member

schip_minor
Structure/Union member

upic_maj
Structure/Union member

upic_min
Structure/Union member

vcan3_versions
Structure/Union member

vcan41_versions
Structure/Union member

vcan42_versions
Structure/Union member

vcanrf_versions
Structure/Union member

vividcan_versions
Structure/Union member

zchip_major
Structure/Union member

zchip_minor
Structure/Union member

zyng_core_major
Structure/Union member

```
    zyng_core_minor
        Structure/Union member

class ics.structures.st_cm_isol57652_rx_message.st_cm_isol57652_rx_message

    blockSize
        Structure/Union member

    cf_timeout
        Structure/Union member

    enableFlowControlTransmission
        Structure/Union member

    ext_address_enable
        Structure/Union member

    extendedAddress
        Structure/Union member

    fc_ext_address_enable
        Structure/Union member

    fc_id
        Structure/Union member

    fc_id_29_bit_enable
        Structure/Union member

    flags
        Structure/Union member

    flowControlExtendedAddress
        Structure/Union member

    id
        Structure/Union member

    id_29_bit_enable
        Structure/Union member

    id_mask
        Structure/Union member

    isBRSEnabled
        Structure/Union member

    iscanFD
        Structure/Union member

    padding
        Structure/Union member

    paddingEnable
        Structure/Union member

    reserved
        Structure/Union member

    stMin
        Structure/Union member
```

```
vs_netid
    Structure/Union member

class ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message

    blockSize
        Structure/Union member

    data
        Structure/Union member

    ext_address_enable
        Structure/Union member

    extendedAddress
        Structure/Union member

    fc_ext_address_enable
        Structure/Union member

    fc_id
        Structure/Union member

    fc_id_29_bit_enable
        Structure/Union member

    fc_id_mask
        Structure/Union member

    flags
        Structure/Union member

    flowControlExtendedAddress
        Structure/Union member

    fs_timeout
        Structure/Union member

    fs_wait
        Structure/Union member

    id
        Structure/Union member

    id_29_bit_enable
        Structure/Union member

    isBRSEnabled
        Structure/Union member

    iscanFD
        Structure/Union member

    num_bytes
        Structure/Union member

    overrideBlockSize
        Structure/Union member

    overrideSTmin
        Structure/Union member
```

```
padding
    Structure/Union member

paddingEnable
    Structure/Union member

stMin
    Structure/Union member

tx_dl
    Structure/Union member

tx_index
    Structure/Union member

vs_netid
    Structure/Union member

class ics.structures.svcanc3_settings.svcanc3_settings

can1
    Structure/Union member

can2
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

misc_io_initial_ddr
    Structure/Union member

misc_io_initial_latch
    Structure/Union member

misc_io_on_report_events
    Structure/Union member

misc_io_report_period
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

class ics.structures.svcanc412_settings.svcanc412_settings

can1
    Structure/Union member

can2
    Structure/Union member

canfd1
    Structure/Union member
```

```
canfd2
    Structure/Union member

disableUsbCheckOnBoot
    Structure/Union member

enableLatencyTest
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.svcn4_ind_settings.svcn4_ind_settings

    busMessagesToAndroid
        Structure/Union member

    can1
        Structure/Union member

    can2
        Structure/Union member

    canfd1
        Structure/Union member

    canfd2
        Structure/Union member

    disableUsbCheckOnBoot
        Structure/Union member

    enableLatencyTest
        Structure/Union member
```

```
enablePcEthernetComm
    Structure/Union member

ethernet
    Structure/Union member

ethernet2
    Structure/Union member

flags
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_parity
    Structure/Union member

lin1
    Structure/Union member

network_enabled_on_boot
    Structure/Union member

network_enables
    Structure/Union member

network_enables_2
    Structure/Union member

network_enables_3
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

termination_enables
    Structure/Union member

word
    Structure/Union member

class ics.structures.svcanc4_settings.svcan4_settings

can1
    Structure/Union member
```

can2
Structure/Union member

can3
Structure/Union member

can4
Structure/Union member

canfd1
Structure/Union member

canfd2
Structure/Union member

canfd3
Structure/Union member

canfd4
Structure/Union member

enableLatencyTest
Structure/Union member

enablePcEthernetComm
Structure/Union member

ethernet
Structure/Union member

ethernet2
Structure/Union member

flags
Structure/Union member

iso15765_separation_time_offset
Structure/Union member

iso9141_kwp_settings_1
Structure/Union member

iso_9141_kwp_enable_reserved
Structure/Union member

iso_msg_termination_1
Structure/Union member

iso_parity_1
Structure/Union member

lin1
Structure/Union member

network_enabled_on_boot
Structure/Union member

network_enables
Structure/Union member

network_enables_2
Structure/Union member

```
network_enables_3
    Structure/Union member

perf_en
    Structure/Union member

pwr_man_enable
    Structure/Union member

pwr_man_timeout
    Structure/Union member

reserved
    Structure/Union member

termination_enables
    Structure/Union member

text_api
    Structure/Union member

class ics.structures.svcancrf_settings.svcancrf_settings

can1
    Structure/Union member

can2
    Structure/Union member

can3
    Structure/Union member

can4
    Structure/Union member

disableFwLEDs
    Structure/Union member

idle_wakeup_network_enables_1
    Structure/Union member

idle_wakeup_network_enables_2
    Structure/Union member

iso15765_separation_time_offset
    Structure/Union member

iso9141_kwp_enable_reserved
    Structure/Union member

iso9141_kwp_settings
    Structure/Union member

iso9141_kwp_settings_2
    Structure/Union member

iso_msg_termination
    Structure/Union member

iso_msg_termination_2
    Structure/Union member
```

```
    iso_parity
        Structure/Union member

    iso_parity_2
        Structure/Union member

    iso_tester_pullup_enable
        Structure/Union member

    lin1
        Structure/Union member

    lin2
        Structure/Union member

    misc_io_analog_enable
        Structure/Union member

    misc_io_initial_ddr
        Structure/Union member

    misc_io_initial_latch
        Structure/Union member

    misc_io_on_report_events
        Structure/Union member

    misc_io_report_period
        Structure/Union member

    network_enabled_on_boot
        Structure/Union member

    network_enables
        Structure/Union member

    network_enables_2
        Structure/Union member

    perf_en
        Structure/Union member

    pwr_man_enable
        Structure/Union member

    pwr_man_timeout
        Structure/Union member

    reservedZero
        Structure/Union member

class ics.structures.swcan_settings.swcan_settings

    BRP
        Structure/Union member

    Baudrate
        Structure/Union member

    Mode
        Structure/Union member
```

```
RESERVED
    Structure/Union member

SetBaudrate
    Structure/Union member

TqProp
    Structure/Union member

TqSeg1
    Structure/Union member

TqSeg2
    Structure/Union member

TqSync
    Structure/Union member

auto_baud
    Structure/Union member

high_speed_auto_switch
    Structure/Union member

transceiver_mode
    Structure/Union member

class ics.structures.tag_options_find_neo_ex.tag_options_find_neo_ex

CANOptions
    Structure/Union member

Reserved
    Structure/Union member

iNetworkID
    Structure/Union member

class ics.structures.tag_options_open_neo_ex.tag_options_open_neo_ex

CANOptions
    Structure/Union member

Reserved
    Structure/Union member

iNetworkID
    Structure/Union member

class ics.structures.tagicsneo_vi_command.tagicsneo_vi_command

CommandByteLength
    Structure/Union member

CommandType
    Structure/Union member

Data
    Structure/Union member
```

```
class ics.structures.timesync_icshardware_settings.timesync_icshardware_settings

MasterEnable
    Structure/Union member

MasterNetwork
    Structure/Union member

SlaveEnable
    Structure/Union member

SlaveNetwork
    Structure/Union member

class ics.structures.uart_settings.uart_settings

Baudrate
    Structure/Union member

bOptions
    Structure/Union member

brgh
    Structure/Union member

flow_control
    Structure/Union member

half_duplex
    Structure/Union member

invert_rx
    Structure/Union member

invert_tx
    Structure/Union member

parity
    Structure/Union member

reserved_1
    Structure/Union member

reserved_bits
    Structure/Union member

reserved_bits2
    Structure/Union member

spbrg
    Structure/Union member

stop_bits
    Structure/Union member
```


CHAPTER 10

Module Variables

```
ics.ics.AUTO = 0
ics.ics.BPS100 = 5
ics.ics.BPS1000 = 10
ics.ics.BPS100000 = 7
ics.ics.BPS10400 = 1
ics.ics.BPS117647 = 8
ics.ics.BPS125 = 6
ics.ics.BPS20 = 0
ics.ics.BPS2000 = 12
ics.ics.BPS250 = 7
ics.ics.BPS33 = 1
ics.ics.BPS3333 = 2
ics.ics.BPS4000 = 13
ics.ics.BPS50 = 2
ics.ics.BPS500 = 8
ics.ics.BPS5000 = 0
ics.ics.BPS50000 = 3
ics.ics.BPS62 = 3
ics.ics.BPS62500 = 4
ics.ics.BPS666 = 11
ics.ics.BPS71429 = 5
ics.ics.BPS800 = 9
```

```
  ics.ics.BPS83 = 4
  ics.ics.BPS83333 = 6
  ics.ics.BUILD_DATETIME = Apr 5 2021 10:56:06
  ics.ics.CANFD_BRS_ENABLED = 2
  ics.ics.CANFD_BRS_ENABLED_ISO = 4
  ics.ics.CANFD_ENABLED = 1
  ics.ics.CANFD_ENABLED_ISO = 3
  ics.ics.CANFD_SETTINGS_SIZE = 10
  ics.ics.CANNODE_STATUS_COREMINI_IS_RUNNING = 1
  ics.ics.CANNODE_STATUS_IN_BOOTLOADER = 2
  ics.ics.CANTERM_SETTINGS_SIZE = 6
  ics.ics.CAN_BPS10000 = 17
  ics.ics.CAN_BPS5000 = 14
  ics.ics.CAN_BPS6667 = 15
  ics.ics.CAN_BPS8000 = 16
  ics.ics.CAN_SETTINGS_SIZE = 12
  ics.ics.DISABLE = 1
  ics.ics.DISK_SETTINGS_SIZE = 14
  ics.ics.DISK_STATUS_FLAG_INITIALIZED = 2
  ics.ics.DISK_STATUS_FLAG_PRESENT = 1
  ics.ics.DISK_STRUCTURE_FLAG_FULL_FORMAT = 1
  ics.ics.ETHERNET10G_SETTINGS_SIZE = 24
  ics.ics.ETHERNET_SETTINGS10G_FLAG_AUTO_NEG = 2
  ics.ics.ETHERNET_SETTINGS10G_FLAG_COMM_IN_USE = -2147483648
  ics.ics.ETHERNET_SETTINGS10G_FLAG_DEVICE_HOSTING_ENABLE = 16
  ics.ics.ETHERNET_SETTINGS10G_FLAG_FULL_DUPLEX = 1
  ics.ics.ETHERNET_SETTINGS10G_FLAG_RTSP_ENABLE = 8
  ics.ics.ETHERNET_SETTINGS10G_FLAG_TCPIP_ENABLE = 4
  ics.ics.ETHERNET_SETTINGS2_FLAG_AUTO_NEG = 2
  ics.ics.ETHERNET_SETTINGS2_FLAG_COMM_IN_USE = 128
  ics.ics.ETHERNET_SETTINGS2_FLAG_DEVICE_HOSTING_ENABLE = 16
  ics.ics.ETHERNET_SETTINGS2_FLAG_FULL_DUPLEX = 1
  ics.ics.ETHERNET_SETTINGS2_FLAG_RTSP_ENABLE = 8
  ics.ics.ETHERNET_SETTINGS2_FLAG_TCPIP_ENABLE = 4
  ics.ics.ETHERNET_SETTINGS2_SIZE = 16
  ics.ics.ETHERNET_SETTINGS_SIZE = 8
```

```
 ics.ics.FAST_MODE = 3
 ics.ics.GLOBAL_SETTINGS_SIZE = 926
 ics.ics.GS_VERSION = 5
 ics.ics.HARDWARE_TIMESTAMP_ID_AVT_716 = 2
 ics.ics.HARDWARE_TIMESTAMP_ID_AVT_717 = 5
 ics.ics.HARDWARE_TIMESTAMP_ID_DOUBLE_SEC = 7
 ics.ics.HARDWARE_TIMESTAMP_ID_NEORED_10NS = 10
 ics.ics.HARDWARE_TIMESTAMP_ID_NEORED_10US = 8
 ics.ics.HARDWARE_TIMESTAMP_ID_NEORED_25NS = 9
 ics.ics.HARDWARE_TIMESTAMP_ID_NEOVI = 4
 ics.ics.HARDWARE_TIMESTAMP_ID_NI_CAN = 3
 ics.ics.HARDWARE_TIMESTAMP_ID_NONE = 0
 ics.ics.HARDWARE_TIMESTAMP_ID_VSI = 1
 ics.ics.ISO15765_2_NETWORK_HSCAN = 1
 ics.ics.ISO15765_2_NETWORK_HSCAN2 = 4
 ics.ics.ISO15765_2_NETWORK_HSCAN3 = 8
 ics.ics.ISO15765_2_NETWORK_HSCAN4 = 20
 ics.ics.ISO15765_2_NETWORK_HSCAN5 = 24
 ics.ics.ISO15765_2_NETWORK_HSCAN6 = 28
 ics.ics.ISO15765_2_NETWORK_HSCAN7 = 32
 ics.ics.ISO15765_2_NETWORK_MSCAN = 2
 ics.ics.ISO15765_2_NETWORK_SWCAN = 16
 ics.ics.ISO15765_2_NETWORK_SWCAN2 = 36
 ics.ics.ISO9141_KEYWORD2000_SETTINGS_SIZE = 114
 ics.ics.ISO9141_KEYWORD2000_INIT_STEP_SIZE = 6
 ics.ics.J1708_SETTINGS_SIZE = 2
 ics.ics.LIN_SETTINGS_SIZE = 10
 ics.ics.LISTEN_ALL = 7
 ics.ics.LISTEN_ONLY = 3
 ics.ics.LOGGER_SETTINGS_SIZE = 4
 ics.ics.LOOPBACK = 2
 ics.ics.MAIN_VNET = 1
 ics.ics.MAX_NUMBYTES_PHYSETTINGS = 512
 ics.ics.MAX_PHY_REG_PKT_ENTRIES = 128
 ics.ics.MAX_PHY_SETTINGS_STRUCT = 128
 ics.ics.MAX_VL_FORWARDING_ENTRIES = 1024
```

```
  ics.ics.MAX_VL_POLICING_ENTRIES = 1024
  ics.ics.NEODEVICE_ANY_ION = 262144
  ics.ics.NEODEVICE_ANY_PLASMA = 4096
  ics.ics.NEODEVICE_BLUE = 1
  ics.ics.NEODEVICE_CMPROBE = 8388608
  ics.ics.NEODEVICE_CT_OBD = 32768
  ics.ics.NEODEVICE_DONT_REUSE0 = 8192
  ics.ics.NEODEVICE_DONT_REUSE1 = 65536
  ics.ics.NEODEVICE_DONT_REUSE2 = 131072
  ics.ics.NEODEVICE_DONT_REUSE3 = 1048576
  ics.ics.NEODEVICE_DW_VCAN = 4
  ics.ics.NEODEVICE_ECU = 128
  ics.ics.NEODEVICE_ECU22 = 21
  ics.ics.NEODEVICE_ECUCHIP_UART = 2048
  ics.ics.NEODEVICE_ECU_AVB = 2
  ics.ics.NEODEVICE_EEVB = 16777216
  ics.ics.NEODEVICE_FIRE = 8
  ics.ics.NEODEVICE_FIRE2 = 67108864
  ics.ics.NEODEVICE_FIRE3 = 15
  ics.ics.NEODEVICE_FLEX = 134217728
  ics.ics.NEODEVICE_GIGASTAR = 19
  ics.ics.NEODEVICE_IENV = 256
  ics.ics.NEODEVICE_ION = 262144
  ics.ics.NEODEVICE_NEOANALOG = 16384
  ics.ics.NEODEVICE_NEOECU12 = 12
  ics.ics.NEODEVICE_NEOECUCHIP = 256
  ics.ics.NEODEVICE_OBD2_LCBADGE = 13
  ics.ics.NEODEVICE_OBD2_PRO = 1024
  ics.ics.NEODEVICE_OBD2_SIM = -2147483648
  ics.ics.NEODEVICE_PENDANT = 512
  ics.ics.NEODEVICE_PLASMA = 4096
  ics.ics.NEODEVICE_RADGALAXY = 268435456
  ics.ics.NEODEVICE_RADGIGALOG = 6
  ics.ics.NEODEVICE_RADIO_CANHUB = 11
  ics.ics.NEODEVICE_RADJUPITER = 17
  ics.ics.NEODEVICE_RADMOON2 = 5
```

```
  ics.ics.NEODEVICE_RADPLUTO = 9
  ics.ics.NEODEVICE_RADSTAR = 524288
  ics.ics.NEODEVICE_RADSTAR2 = 536870912
  ics.ics.NEODEVICE_RADSUPERMOON = 3
  ics.ics.NEODEVICE_RAD_MOON_DUO = 14
  ics.ics.NEODEVICE_RED = 64
  ics.ics.NEODEVICE_RED2 = 20
  ics.ics.NEODEVICE_UNKNOWN = 0
  ics.ics.NEODEVICE_VCAN3 = 16
  ics.ics.NEODEVICE_VCAN41 = 7
  ics.ics.NEODEVICE_VCAN42 = 4194304
  ics.ics.NEODEVICE_VCAN42_EL = 10
  ics.ics.NEODEVICE_VCAN44 = 2097152
  ics.ics.NEODEVICE_VCAN4_IND = 18
  ics.ics.NEODEVICE_VCANRF = 33554432
  ics.ics.NEODEVICE_VIVIDCAN = 1073741824
  ics.ics.NEOVI6_VCAN_TIMESTAMP_1 = 1e-06
  ics.ics.NEOVI6_VCAN_TIMESTAMP_2 = 0.065536
  ics.ics.NEOVIPRO_VCAN_TIMESTAMP_1 = 1e-06
  ics.ics.NEOVIPRO_VCAN_TIMESTAMP_2 = 0.065536
  ics.ics.NEOVI_3G_MAX_SETTINGS_SIZE = 926
  ics.ics.NEOVI_COMMTYPE_FIRE_USB = 5
  ics.ics.NEOVI_COMMTYPE_RS232 = 0
  ics.ics.NEOVI_COMMTYPE_TCPIP = 3
  ics.ics.NEOVI_COMMTYPE_USB_BULK = 1
  ics.ics.NEOVI_RED_TIMESTAMP_1_10NS = 1e-08
  ics.ics.NEOVI_RED_TIMESTAMP_1_25NS = 2.5e-08
  ics.ics.NEOVI_RED_TIMESTAMP_2_10NS = 429.4967296
  ics.ics.NEOVI_RED_TIMESTAMP_2_25NS = 107.3741824
  ics.ics.NEOVI_TIMESTAMP_1 = 1.6e-06
  ics.ics.NEOVI_TIMESTAMP_2 = 0.1048576
  ics.ics.NEO_CFG_MPIC_HS_CAN_CNF1 = 522
  ics.ics.NEO_CFG_MPIC_HS_CAN_CNF2 = 521
  ics.ics.NEO_CFG_MPIC_HS_CAN_CNF3 = 520
  ics.ics.NEO_CFG_MPIC_HS_CAN_MODE = 566
  ics.ics.NEO_CFG_MPIC_LSFT_CAN_CNF1 = 558
```

```
    ics.ics.NEO_CFG_MPIC_LSFT_CAN_CNF2 = 557
    ics.ics.NEO_CFG_MPIC_LSFT_CAN_CNF3 = 556
    ics.ics.NEO_CFG_MPIC_MS_CAN_CNF1 = 534
    ics.ics.NEO_CFG_MPIC_MS_CAN_CNF2 = 533
    ics.ics.NEO_CFG_MPIC_MS_CAN_CNF3 = 532
    ics.ics.NEO_CFG_MPIC_SW_CAN_CNF1 = 546
    ics.ics.NEO_CFG_MPIC_SW_CAN_CNF2 = 545
    ics.ics.NEO_CFG_MPIC_SW_CAN_CNF3 = 544
    ics.ics.NETID_3G_APP_SIGNAL_STATUS = 56
    ics.ics.NETID_3G_FB_STATUS = 55
    ics.ics.NETID_3G_LOGGING_OVERFLOW = 59
    ics.ics.NETID_3G_READ_DATALINK_CM_RX_MSG = 58
    ics.ics.NETID_3G_READ_DATALINK_CM_TX_MSG = 57
    ics.ics.NETID_3G_READ_SETTINGS_EX = 60
    ics.ics.NETID_3G_RESET_STATUS = 54
    ics.ics.NETID_AUTOSAR = 515
    ics.ics.NETID_AUX = 7
    ics.ics.NETID_CGI = 53
    ics.ics.NETID_DATA_TO_HOST = 70
    ics.ics.NETID_DEVICE = 0
    ics.ics.NETID_DEVICE_STATUS = 513
    ics.ics.NETID_ETHERNET = 93
    ics.ics.NETID_ETHERNET2 = 520
    ics.ics.NETID_ETHERNET_DAQ = 69
    ics.ics.NETID_FLEXRAY = 85
    ics.ics.NETID_FLEXRAY1A = 80
    ics.ics.NETID_FLEXRAY1B = 81
    ics.ics.NETID_FLEXRAY2 = 86
    ics.ics.NETID_FLEXRAY2A = 82
    ics.ics.NETID_FLEXRAY2B = 83
    ics.ics.NETID_FORDSCP = 5
    ics.ics.NETID_FORWARDED_MESSAGE = 516
    ics.ics.NETID_GMFSA = 94
    ics.ics.NETID_HSCAN = 1
    ics.ics.NETID_HSCAN2 = 42
    ics.ics.NETID_HSCAN3 = 44
```

```
    ics.ics.NETID_HSCAN4 = 61
    ics.ics.NETID_HSCAN5 = 62
    ics.ics.NETID_HSCAN6 = 96
    ics.ics.NETID_HSCAN7 = 97
    ics.ics.NETID_HW_COM_LATENCY_TEST = 512
    ics.ics.NETID_I2C1 = 88
    ics.ics.NETID_I2C2 = 517
    ics.ics.NETID_I2C3 = 518
    ics.ics.NETID_I2C4 = 519
    ics.ics.NETID_INVALID = 65535
    ics.ics.NETID_ISO = 9
    ics.ics.NETID_ISO14230 = 15
    ics.ics.NETID_ISO2 = 14
    ics.ics.NETID_ISO3 = 41
    ics.ics.NETID_ISO4 = 47
    ics.ics.NETID_ISOPIC = 10
    ics.ics.NETID_J1708 = 6
    ics.ics.NETID_JVPW = 8
    ics.ics.NETID_LIN = 16
    ics.ics.NETID_LIN2 = 48
    ics.ics.NETID_LIN3 = 49
    ics.ics.NETID_LIN4 = 50
    ics.ics.NETID_LIN5 = 84
    ics.ics.NETID_LIN6 = 98
    ics.ics.NETID_LSFTCAN = 4
    ics.ics.NETID_LSFTCAN2 = 99
    ics.ics.NETID_MAIN51 = 11
    ics.ics.NETID_MAX = 100
    ics.ics.NETID_MOST = 51
    ics.ics.NETID_MOST150 = 92
    ics.ics.NETID_MOST25 = 90
    ics.ics.NETID_MOST50 = 91
    ics.ics.NETID_MSCAN = 2
    ics.ics.NETID_OP_ETHERNET1 = 17
    ics.ics.NETID_OP_ETHERNET10 = 78
    ics.ics.NETID_OP_ETHERNET11 = 79
```

```
    ics.ics.NETID_OP_ETHERNET12 = 87
    ics.ics.NETID_OP_ETHERNET2 = 18
    ics.ics.NETID_OP_ETHERNET3 = 19
    ics.ics.NETID_OP_ETHERNET4 = 45
    ics.ics.NETID_OP_ETHERNET5 = 46
    ics.ics.NETID_OP_ETHERNET6 = 73
    ics.ics.NETID_OP_ETHERNET7 = 75
    ics.ics.NETID_OP_ETHERNET8 = 76
    ics.ics.NETID_OP_ETHERNET9 = 77
    ics.ics.NETID_RED = 12
    ics.ics.NETID_RED_APP_ERROR = 52
    ics.ics.NETID_RED_VBAT = 74
    ics.ics.NETID_RS232 = 63
    ics.ics.NETID_SCI = 13
    ics.ics.NETID_SPI1 = 72
    ics.ics.NETID_SWCAN = 3
    ics.ics.NETID_SWCAN2 = 68
    ics.ics.NETID_TCP = 95
    ics.ics.NETID_TEXTAPI_TO_HOST = 71
    ics.ics.NETID_UART = 64
    ics.ics.NETID_UART2 = 65
    ics.ics.NETID_UART3 = 66
    ics.ics.NETID_UART4 = 67
    ics.ics.NETID_UDP = 514
    ics.ics.NORMAL = 0
    ics.ics.NORMAL_MODE = 2
    ics.ics.NO_CANFD = 0
    ics.ics.OPETH_FUNC_MEDIACONVERTER = 1
    ics.ics.OPETH_FUNC_RAW_MEDIA_CONVERTER = 3
    ics.ics.OPETH_FUNC_TAP = 0
    ics.ics.OPETH_FUNC_TAP_LOW_LATENCY = 2
    ics.ics.OPETH_LINK_AUTO = 0
    ics.ics.OPETH_LINK_MASTER = 1
    ics.ics.OPETH_LINK_SLAVE = 2
    ics.ics.OPETH_MAC_SPOOF_DST_ADDR = 0
    ics.ics.OPETH_MAC_SPOOF_SRC_ADDR = 1
```

```
  ics.ics.OP_ETH_GENERAL_SETTINGS_SIZE = 20
  ics.ics.OP_ETH_SETTINGS_SIZE = 16
  ics.ics.PHY_REG_PKT_VERSION = 1
  ics.ics.PLASMA_SLAVE1_OFFSET = 100
  ics.ics.PLASMA_SLAVE1_OFFSET_RANGE2 = 4608
  ics.ics.PLASMA_SLAVE2_OFFSET = 200
  ics.ics.PLASMA_SLAVE2_OFFSET_RANGE2 = 8704
  ics.ics.PLASMA_SLAVE3_OFFSET_RANGE2 = 12800
  ics.ics.PLASMA_SLAVE_NUM = 51
  ics.ics.PLUTO_MAX_FORWARDING_ENTRIES = 13
  ics.ics.PLUTO_MAX_L2_ADDRESS_LOOKUP = 1024
  ics.ics.PLUTO_MAX_L2_POLICING = 45
  ics.ics.PLUTO_MAX_MAC_CONFIG_ENTRIES = 5
  ics.ics.PLUTO_MAX RETAGGING_ENTRIES = 32
  ics.ics.PLUTO_MAX_VLAN_LOOKUP = 4096
  ics.ics.PLUTO_NUM_PRIORITY = 8
  ics.ics.RADJUPITER_NUM_PORTS = 8
  ics.ics.RADMOONDUO_CONVERTER_SETTINGS_SIZE = 16
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_AIN1 = 256
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_AIN2 = 512
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_INT_GPS_ENABLE = 4
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE = 2
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE2 = 8
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC1_DIN = 16
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC1_PWMIN = 64
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC2_DIN = 32
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_MISC2_PWMIN = 128
  ics.ics.RAD_REPORTING_SETTINGS_FLAG_TEMP_ENABLE = 1
  ics.ics.RAD_REPORTING_SETTINGS_SIZE = 16
  ics.ics.REPORT_ON_GPS = 15
  ics.ics.REPORT_ON_KLINE = 9
  ics.ics.REPORT_ON_LED1 = 7
  ics.ics.REPORT_ON_LED2 = 8
  ics.ics.REPORT_ON_MISC1 = 1
  ics.ics.REPORT_ON_MISC2 = 2
  ics.ics.REPORT_ON_MISC3 = 3
```

```
    ics.ics.REPORT_ON_MISC3_AIN = 10
    ics.ics.REPORT_ON_MISC4 = 4
    ics.ics.REPORT_ON_MISC4_AIN = 11
    ics.ics.REPORT_ON_MISC5 = 5
    ics.ics.REPORT_ON_MISC5_AIN = 12
    ics.ics.REPORT_ON_MISC6 = 6
    ics.ics.REPORT_ON_MISC6_AIN = 13
    ics.ics.REPORT_ON_PERIODIC = 0
    ics.ics.RESISTOR_OFF = 1
    ics.ics.RESISTOR_ON = 0
    ics.ics.SCRIPT_LOCATION_FLASH_MEM = 0
    ics.ics.SCRIPT_LOCATION_INTERNAL_FLASH = 2
    ics.ics.SCRIPT_LOCATION_SDCARD = 1
    ics.ics.SCRIPT_LOCATION_VCAN3_MEM = 4
    ics.ics.SCRIPT_STATUS_RUNNING = 1
    ics.ics.SCRIPT_STATUS_STOPPED = 0
    ics.ics.SERDESCAM_CONFIG_MODE_EXTERNAL_OVER_TAP = 0
    ics.ics.SERDESCAM_CONFIG_MODE_LOCAL_SCRIPT = 1
    ics.ics.SERDESCAM_MODE_PASSTHROUGH = 0
    ics.ics.SERDESCAM_MODE_PLAYBACK = 2
    ics.ics.SERDESCAM_MODE_TAP = 1
    ics.ics.SERDESCAM_PIXEL_BIT_POS_0 = 0
    ics.ics.SERDESCAM_PIXEL_BIT_POS_1 = 1
    ics.ics.SERDESCAM_PIXEL_BIT_POS_2 = 2
    ics.ics.SERDESCAM_PIXEL_BIT_POS_3 = 3
    ics.ics.SERDESCAM_SETTINGS_AUTO_DETECT_ENABLE = 4
    ics.ics.SERDESCAM_SETTINGS_CONFIG_ENABLE = 8
    ics.ics.SERDESCAM_SETTINGS_FLAG_ENABLE = 1
    ics.ics.SERDESCAM_SETTINGS_RTSP_ENABLE = 2
    ics.ics.SERDESCAM_SETTINGS_SIZE = 32
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_10LE_PACKED = 19
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_12LE_PACKED = 20
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16BE = 22
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16LE = 21
    ics.ics.SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_8 = 4
    ics.ics.SERDESCAM_VIDEO_FORMAT_COUNT = 65
```

```
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_10LE_PACKED = 51
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_12LE_PACKED = 52
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_BAYER_BGGR_8 = 50
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_10 = 54
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_12 = 56
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_14 = 58
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_16 = 59
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_20 = 60
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_24 = 61
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_30 = 62
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_32 = 63
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_36 = 64
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RAW_8 = 53
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RGB565 = 47
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RGB666 = 48
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_RGB888 = 49
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_10LE_PACKED = 39
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_12LE_PACKED = 43
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_UYVY_422_8 = 35
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_10LE_PACKED = 42
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_12LE_PACKED = 46
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_VYUY_422_8 = 38
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_10LE_PACKED = 40
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_12LE_PACKED = 44
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_8 = 36
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_10LE_PACKED = 41
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_12LE_PACKED = 45
    ics.ics.SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_8 = 37
    ics.ics.SERDESCAM_VIDEO_FORMAT_JPEG = 23
    ics.ics.SERDESCAM_VIDEO_FORMAT_NONE = -1
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_10 = 6
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_12 = 7
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_14 = 34
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_16 = 8
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_20 = 9
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_24 = 10
```

```
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_30 = 11
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_32 = 12
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_36 = 13
    ics.ics.SERDESCAM_VIDEO_FORMAT_RAW_8 = 5
    ics.ics.SERDESCAM_VIDEO_FORMAT_RGB565 = 30
    ics.ics.SERDESCAM_VIDEO_FORMAT_RGB666 = 31
    ics.ics.SERDESCAM_VIDEO_FORMAT_RGB888 = 14
    ics.ics.SERDESCAM_VIDEO_FORMAT_UYVY_422_10LE_PACKED = 15
    ics.ics.SERDESCAM_VIDEO_FORMAT_UYVY_422_12LE_PACKED = 24
    ics.ics.SERDESCAM_VIDEO_FORMAT_UYVY_422_8 = 0
    ics.ics.SERDESCAM_VIDEO_FORMAT_VYUY_422_10LE_PACKED = 18
    ics.ics.SERDESCAM_VIDEO_FORMAT_VYUY_422_12LE_PACKED = 27
    ics.ics.SERDESCAM_VIDEO_FORMAT_VYUY_422_8 = 3
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUV422_10LE_PLANAR = 28
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUV422_16LE_PLANAR = 29
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUYV_422_10LE_PACKED = 16
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUYV_422_12LE_PACKED = 25
    ics.ics.SERDESCAM_VIDEO_FORMAT_YUYV_422_8 = 1
    ics.ics.SERDESCAM_VIDEO_FORMAT_YVYU_422_10LE_PACKED = 17
    ics.ics.SERDESCAM_VIDEO_FORMAT_YVYU_422_12LE_PACKED = 26
    ics.ics.SERDESCAM_VIDEO_FORMAT_YVYU_422_8 = 2
    ics.ics.SERDESPOC_SETTINGS_MODE_DISABLED = 0
    ics.ics.SERDESPOC_SETTINGS_MODE_SERIALIZER = 2
    ics.ics.SERDESPOC_SETTINGS_MODE_SUPPLY = 1
    ics.ics.SERDESPOC_SETTINGS_SIZE = 10
    ics.ics.SLAVE_VNET_A = 2
    ics.ics.SLAVE_VNET_B = 4
    ics.ics.SLEEP_MODE = 0
    ics.ics.SLOW_MODE = 1
    ics.ics.SPY_PROTOCOL_AUTOSAR = 34
    ics.ics.SPY_PROTOCOL_BEAN = 11
    ics.ics.SPY_PROTOCOL_CAN = 1
    ics.ics.SPY_PROTOCOL_CANFD = 30
    ics.ics.SPY_PROTOCOL_CGI = 18
    ics.ics.SPY_PROTOCOL_CHRYSLER_CCD = 8
    ics.ics.SPY_PROTOCOL_CHRYSLER_JVPW = 14
```

```
  ics.ics.SPY_PROTOCOL_CHRYSLER_SCI = 9
  ics.ics.SPY_PROTOCOL_CUSTOM = 0
  ics.ics.SPY_PROTOCOL_DALLAS_1WIRE = 25
  ics.ics.SPY_PROTOCOL_ETHERNET = 29
  ics.ics.SPY_PROTOCOL_FLEXRAY = 16
  ics.ics.SPY_PROTOCOL_FORD_UPP = 10
  ics.ics.SPY_PROTOCOL_GENERIC_MANCHSESTER = 26
  ics.ics.SPY_PROTOCOL_GENERIC_UART = 22
  ics.ics.SPY_PROTOCOL_GME_CIM_SCL_KLINE = 19
  ics.ics.SPY_PROTOCOL_GMFSA = 31
  ics.ics.SPY_PROTOCOL_GMLAN = 2
  ics.ics.SPY_PROTOCOL_GM_ALDL_UART = 7
  ics.ics.SPY_PROTOCOL_I2C = 21
  ics.ics.SPY_PROTOCOL_ISO9141 = 5
  ics.ics.SPY_PROTOCOL_J1708 = 13
  ics.ics.SPY_PROTOCOL_J1850PWM = 4
  ics.ics.SPY_PROTOCOL_J1850VPW = 3
  ics.ics.SPY_PROTOCOL_J1939 = 15
  ics.ics.SPY_PROTOCOL_JTAG = 23
  ics.ics.SPY_PROTOCOL_LIN = 12
  ics.ics.SPY_PROTOCOL_MOST = 17
  ics.ics.SPY_PROTOCOL_SENT_PROTOCOL = 27
  ics.ics.SPY_PROTOCOL_SPI = 20
  ics.ics.SPY_PROTOCOL_TCP = 32
  ics.ics.SPY_PROTOCOL_UART = 28
  ics.ics.SPY_PROTOCOL_UDP = 33
  ics.ics.SPY_PROTOCOL_UNIO = 24
  ics.ics.SPY_STATUS2_CAN_HAVE_LINK_DATA = 4194304
  ics.ics.SPY_STATUS2_CAN_ISO15765_LOGICAL_FRAME = 2097152
  ics.ics.SPY_STATUS2_END_OF_LONG_MESSAGE = 1048576
  ics.ics.SPY_STATUS2_ERROR_FRAME = 131072
  ics.ics.SPY_STATUS2_ETHERNET_CRC_ERROR = 2097152
  ics.ics.SPY_STATUS2_ETHERNET_FCS_AVAILABLE = 8388608
  ics.ics.SPY_STATUS2_ETHERNET_FRAME_TOO_SHORT = 4194304
  ics.ics.SPY_STATUS2_ETHERNET_NO_PADDING = 16777216
  ics.ics.SPY_STATUS2_ETHERNET_PREEMPTION_ENABLED = 33554432
```

```
ics.ics.SPY_STATUS2_FLEXRAY_NO_CRC = 33554432
ics.ics.SPY_STATUS2_FLEXRAY_NO_HEADERCRC = 67108864
ics.ics.SPY_STATUS2_FLEXRAY_TX_AB = 2097152
ics.ics.SPY_STATUS2_FLEXRAY_TX_AB_NO_A = 4194304
ics.ics.SPY_STATUS2_FLEXRAY_TX_AB_NO_B = 8388608
ics.ics.SPY_STATUS2_FLEXRAY_TX_AB_NO_MATCH = 16777216
ics.ics.SPY_STATUS2_GLOBAL_CHANGE = 65536
ics.ics.SPY_STATUS2_HAS_VALUE = 1
ics.ics.SPY_STATUS2_HIGH_VOLTAGE = 4
ics.ics.SPY_STATUS2_I2C_DIR_READ = 8388608
ics.ics.SPY_STATUS2_I2C_ERR_NACK = 4194304
ics.ics.SPY_STATUS2_I2C_ERR_TIMEOUT = 2097152
ics.ics.SPY_STATUS2_ISO_FRAME_ERROR = 134217728
ics.ics.SPY_STATUS2_ISO_OVERFLOW_ERROR = 268435456
ics.ics.SPY_STATUS2_ISO_PARITY_ERROR = 536870912
ics.ics.SPY_STATUS2_LIN_ERR_MSG_ID_PARITY = 67108864
ics.ics.SPY_STATUS2_LIN_ERR_RX_BREAK_NOT_0 = 2097152
ics.ics.SPY_STATUS2_LIN_ERR_RX_BREAK_TOO_SHORT = 4194304
ics.ics.SPY_STATUS2_LIN_ERR_RX_DATA_GREATER_8 = 16777216
ics.ics.SPY_STATUS2_LIN_ERR_RX_SYNC_NOT_55 = 8388608
ics.ics.SPY_STATUS2_LIN_ERR_TX_RX_MISMATCH = 33554432
ics.ics.SPY_STATUS2_LIN_ID_FRAME_ERROR = 268435456
ics.ics.SPY_STATUS2_LIN_NO_SLAVE_DATA = -2147483648
ics.ics.SPY_STATUS2_LIN_SLAVE_BYTE_ERROR = 536870912
ics.ics.SPY_STATUS2_LIN_SYNC_FRAME_ERROR = 134217728
ics.ics.SPY_STATUS2_LONG_MESSAGE = 8
ics.ics.SPY_STATUS2_MOST_CHANGED_PAR = -2147483648
ics.ics.SPY_STATUS2_MOST_CONTROL_DATA = 16777216
ics.ics.SPY_STATUS2_MOST_I2S_DUMP = 134217728
ics.ics.SPY_STATUS2_MOST_LOW_LEVEL = 8388608
ics.ics.SPY_STATUS2_MOST_MHP_CONTROL_DATA = 67108864
ics.ics.SPY_STATUS2_MOST_MHP_USER_DATA = 33554432
ics.ics.SPY_STATUS2_MOST_MOST150 = 1073741824
ics.ics.SPY_STATUS2_MOST_MOST50 = 536870912
ics.ics.SPY_STATUS2_MOST_PACKET_DATA = 2097152
ics.ics.SPY_STATUS2_MOST_STATUS = 4194304
```

```
ics.ics.SPY_STATUS2_MOST_TOO_SHORT = 268435456
ics.ics.SPY_STATUS2_RX_TIMEOUT_ERROR = 1073741824
ics.ics.SPY_STATUS2_VALUE_IS_BOOLEAN = 2
ics.ics.SPY_STATUS3_CANFD_BRS = 16
ics.ics.SPY_STATUS3_CANFD_ESI = 1
ics.ics.SPY_STATUS3_CANFD_FDF = 8
ics.ics.SPY_STATUS3_CANFD_IDE = 2
ics.ics.SPY_STATUS3_CANFD_RTR = 4
ics.ics.SPY_STATUS3_LIN_JUST_BREAK_SYNC = 1
ics.ics.SPY_STATUS3_LIN_ONLY_UPDATE_SLAVE_TABLE_ONCE = 4
ics.ics.SPY_STATUS3_LIN_SLAVE_DATA_TOO_SHORT = 2
ics.ics.SPY_STATUS_ANALOG_DIGITAL_INPUT = 16777216
ics.ics.SPY_STATUS_AUDIO_COMMENT = 4194304
ics.ics.SPY_STATUS_AVSI_REC_OVERFLOW = 1048576
ics.ics.SPY_STATUS_BAD_MESSAGE_BIT_TIME_ERROR = 16384
ics.ics.SPY_STATUS_BREAK = 524288
ics.ics.SPY_STATUS_BUS_RECOVERED = 1024
ics.ics.SPY_STATUS_BUS_SHORTED_GND = 4096
ics.ics.SPY_STATUS_BUS_SHORTED_PLUS = 2048
ics.ics.SPY_STATUS_CANFD = 536870912
ics.ics.SPY_STATUS_CAN_BUS_OFF = 512
ics.ics.SPY_STATUS_CAN_ERROR_PASSIVE = 32
ics.ics.SPY_STATUS_CHECKSUM_ERROR = 8192
ics.ics.SPY_STATUS_COMM_IN_OVERFLOW = 65536
ics.ics.SPY_STATUS_CRC_ERROR = 16
ics.ics.SPY_STATUS_EXPECTED_LEN_MISMATCH = 131072
ics.ics.SPY_STATUS_EXTENDED = -2147483648
ics.ics.SPY_STATUS_FLEXRAY_PDU = 268435456
ics.ics.SPY_STATUS_FLEXRAY_PDU_NO_UPDATE_BIT = 8
ics.ics.SPY_STATUS_FLEXRAY_PDU_UPDATE_BIT_SET = 1073741824
ics.ics.SPY_STATUS_GLOBAL_ERR = 1
ics.ics.SPY_STATUS_GPS_DATA = 8388608
ics.ics.SPY_STATUS_HEADERCRC_ERROR = 32
ics.ics.SPY_STATUS_HIGH_SPEED = 1073741824
ics.ics.SPY_STATUS_INCOMPLETE_FRAME = 64
ics.ics.SPY_STATUS_INIT_MESSAGE = 536870912
```

```
ics.ics.SPY_STATUS_LIN_MASTER = 536870912
ics.ics.SPY_STATUS_LOST_ARBITRATION = 128
ics.ics.SPY_STATUS_MSG_NO_MATCH = 262144
ics.ics.SPY_STATUS_NETWORK_MESSAGE_TYPE = 67108864
ics.ics.SPY_STATUS_PDU = 268435456
ics.ics.SPY_STATUS_REMOTE_FRAME = 8
ics.ics.SPY_STATUS_TEST_TRIGGER = 2097152
ics.ics.SPY_STATUS_TEXT_COMMENT = 33554432
ics.ics.SPY_STATUS_TX_MSG = 2
ics.ics.SPY_STATUS_TX_NOMATCH = 32768
ics.ics.SPY_STATUS_UNDEFINED_ERROR = 256
ics.ics.SPY_STATUS_VSI_IFR_CRC_BIT = 268435456
ics.ics.SPY_STATUS_VSI_TX_UNDERRUN = 134217728
ics.ics.SPY_STATUS_XTD_FRAME = 4
ics.ics.SWCAN_AUTOSWITCH_DISABLED = 0
ics.ics.SWCAN_AUTOSWITCH_DISABLED_RESISTOR_ENABLED = 3
ics.ics.SWCAN_AUTOSWITCH_NO_RESISTOR = 1
ics.ics.SWCAN_AUTOSWITCH_WITH_RESISTOR = 2
ics.ics.SWCAN_SETTINGS_SIZE = 14
ics.ics.TIMESYNC_ICSHARDWARE_SETTINGS_SIZE = 4
ics.ics.UART_SETTINGS_SIZE = 16
ics.ics.USE_TQ = 1
ics.ics.VNETBITS_FEATURE_ANDROID_MSGS = 1
ics.ics.VNETBITS_FEATURE_DISABLE_USB_CHECK = 2
ics.ics.WIFI_CONNECTION = 8
```

Python Module Index

i

ics.ics, [17](#)

A

accdevwin (*ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_sync_params_s.attribute*), 112
AckBytes (*ics.ics.SpyMessage attribute*), 18
AckBytes (*ics.ics.SpyMessageJ1850 attribute*), 19
AckBytes (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray.attribute*), 81
AckBytes (*ics.structures.ics_spy_message_long.ics_spy_message_long.attribute*), 83
AckBytes (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb.attribute*), 84
ae1Select (*ics.structures.s_pluto_custom_params_s.s_pluto_custom_params_s.attribute*), 114
ain_sample_period
 (*ics.structures.s_cyan_settings.s_cyan_settings.attribute*), 91
ain_sample_period
 (*ics.structures.s_fire_settings.s_fire_settings.attribute*), 100
ain_sample_period
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings.attribute*), 102
ain_sample_period
 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings.attribute*), 107
ain_sample_period
 (*ics.structures.s_pendant_settings.s_pendant_settings.attribute*), 109
ain_sample_period
 (*ics.structures.secu_settings.secu_settings.attribute*), 124
ain_sample_period
 (*ics.structures.seevb_settings.seevb_settings.attribute*), 125
ain_sample_period
 (*ics.structures.sievb_settings.sievb_settings.attribute*), 127
ain_sample_period
 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings.attribute*), 128
ArgumentError, 17
asytensyen (*ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_sync_params_s.attribute*), 130
attribute), 132
attribute), 133
attribute), 144
attribute), 91
attribute), 97
attribute), 100
attribute), 102
attribute), 107
attribute), 109
attribute), 124
attribute), 125
attribute), 127
attribute), 130
attribute), 132
attribute), 144
ArbIDOrHeader (*ics.ics.SpyMessage attribute*), 18
ArbIDOrHeader (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray.attribute*), 81
ArbIDOrHeader (*ics.structures.ics_spy_message_long.ics_spy_message_long.attribute*), 83
ArbIDOrHeader (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb.attribute*), 84
asytensyen (*ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_sync_params_s.attribute*), 130

attribute), 112
 AUTO (*in module ics.ics*), 161
 auto_baud (*ics.structures.can_settings.can_settings attribute*), 73
 auto_baud (*ics.structures.swcan_settings.swcan_settings attribute*), 158
 auto_neg (*ics.structures.ethernet_settings.ethernet_settings attribute*), 77
 AutoHandleClose (*ics.ics.NeoDevice attribute*), 18

B

backupPowerEnabled (*ics.structures.ics_fire2_device_status.ics_fire2_device_status attribute*), 80
 backupPowerGood (*ics.structures.ics_fire2_device_status.ics_fire2_device_status attribute*), 80
 bag (*ics.structures.s_pluto_vl_policing_entry_s.s_pluto_vl_policing_entry_s attribute*), 119
 base (*ics.structures.s_pluto_mac_config.s.s_pluto_mac_config attribute*), 117
 base36enc () (*in module ics.ics*), 28
 Baudrate (*ics.structures.can_settings.can_settings attribute*), 73
 Baudrate (*ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000 attribute*), 87
 Baudrate (*ics.structures.lin_settings.lin_settings attribute*), 88
 Baudrate (*ics.structures.swcan_settings.swcan_settings attribute*), 157
 Baudrate (*ics.structures.uart_settings.uart_settings attribute*), 159
 bc_domain (*ics.structures.s_pluto_l2_forwarding_entry_s.s_pluto_l2_forwarding_entry_s attribute*), 116
 bExtended (*ics.structures.s_text_api_settings.s_text_api_settings attribute*), 121
 bIPV4_Address (*ics.structures.j2534_adapter_information.j2534_adapter_information attribute*), 88
 bIPV6_Address (*ics.structures.j2534_adapter_information.j2534_adapter_information attribute*), 88
 bitPos (*ics.structures.serdescam_settings.serdescam_settings attribute*), 126
 blockSize (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute*), 86
 blockSize (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute*), 150
 blockSize (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute*), 151
 bMAC_Address (*ics.structures.j2534_adapter_information.j2534_adapter_information attribute*), 88
 bOptions (*ics.structures.uart_settings.uart_settings attribute*), 159
 BPS100 (*in module ics.ics*), 161
 BPS1000 (*in module ics.ics*), 161
 BPS100000 (*in module ics.ics*), 161
 BPS10400 (*in module ics.ics*), 161
 BPS117647 (*in module ics.ics*), 161
 BPS125 (*in module ics.ics*), 161
 BPS20 (*in module ics.ics*), 161
 BPS2000 (*in module ics.ics*), 161
 BPS250 (*in module ics.ics*), 161
 BPS33 (*in module ics.ics*), 161
 BPS33333 (*in module ics.ics*), 161
 BPS4000 (*in module ics.ics*), 161
 BPS50 (*in module ics.ics*), 161
 BPS500 (*in module ics.ics*), 161
 BPS5000 (*in module ics.ics*), 161
 BPS50000 (*in module ics.ics*), 161
 BPS62 (*in module ics.ics*), 161
 BPS666 (*in module ics.ics*), 161
 BPS6660 (*in module ics.ics*), 161
 BPS800 (*in module ics.ics*), 161
 BPS883 (*in module ics.ics*), 161
 BPS83333 (*in module ics.ics*), 162
 brgh (*ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000 attribute*), 87
 brgh (*ics.structures.lin_settings.lin_settings attribute*), 88
 brgh (*ics.structures.uart_settings.uart_settings attribute*), 159
 BRP (*ics.structures.can_settings.can_settings attribute*), 73
 BRP (*ics.structures.swcan_settings.swcan_settings attribute*), 157
 bStufff2 (*ics.structures.spy_filter_long.spy_filter_long attribute*), 132
 bc_domain (*ics.structures.s_pluto_l2_forwarding_entry_s.s_pluto_l2_forwarding_entry_s attribute*), 116
 build_datetime (*in module ics.ics*), 162
 bUCArBIdRangeFilter (*ics.structures.spy_filter_long.spy_filter_long attribute*), 132
 busMessagesToAndroid (*ics.structures.s_fire3_settings.s_fire3_settings attribute*), 91
 busMessagesToAndroid (*ics.structures.s_fire3_settings.s_fire3_settings attribute*), 97
 busMessagesToAndroid (*ics.structures.s_fire3_settings.s_fire3_settings attribute*), 105
 busMessagesToAndroid (*ics.structures.svcn4_ind_settings.svcn4_ind_settings attribute*), 153
 ByteDataLength (*ics.structures.spy_filter_long.spy_filter_long attribute*), 131
 ByteDataLSB (*ics.structures.spy_filter_long.spy_filter_long attribute*), 131
 ByteDataMaskLSB (*ics.structures.spy_filter_long.spy_filter_long attribute*), 131

ByteDataMaskMSB (*ics.structures.spy_filter_long.spy_filter_long*.*ics.structures.svcn3_settings.svcn3_settings* attribute), 131
 ByteDataMSB (*ics.structures.spy_filter_long.spy_filter_long*.*ics.structures.svcn412_settings.svcn412_settings* attribute), 131
 bytesPerSector (*ics.structures.s_disk_status.s_disk_status*.*ics.structures.svcn4_ind_settings.svcn4_ind_settings* attribute), 96

C

caentmout (*ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params*.*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 112
 can1 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 91
 can1 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 97
 can1 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 100
 can1 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 102
 can1 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 105
 can1 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings* attribute), 107
 can1 (*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 109
 can1 (*ics.structures.s_red_settings.s_red_settings* attribute), 121
 can1 (*ics.structures.s_vivid_can_settings.s_vivid_can_settings* attribute), 122
 can1 (*ics.structures.scan_hub_settings.scan_hub_settings* attribute), 122
 can1 (*ics.structures.secu_avb_settings.secu_avb_settings* attribute), 123
 can1 (*ics.structures.secu_settings.secu_settings* attribute), 124
 can1 (*ics.structures.seevb_settings.seevb_settings* attribute), 125
 can1 (*ics.structures.sievb_settings.sievb_settings* attribute), 127
 can1 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 128
 can1 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings* attribute), 130
 can1 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 132
 can1 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings* attribute), 135
 can1 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 137
 can1 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings* attribute), 140
 can1 (*ics.structures.srad_pluto_settings.srad_pluto_settings* attribute), 142
 can1 (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 144

can1 (*ics.structures.svcn3_settings.svcn3_settings* attribute), 152
 can1 (*ics.structures.svcn412_settings.svcn412_settings* attribute), 152
 can1 (*ics.structures.svcn4_ind_settings.svcn4_ind_settings* attribute), 153
 can1 (*ics.structures.svcn4_settings.svcn4_settings* attribute), 154
 can1 (*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 156
 can1_options (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
 can1_rx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
 can1_tx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
 can2 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 91
 can2 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 97
 can2 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 100
 can2 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 103
 can2 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 105
 can2 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings* attribute), 107
 can2 (*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 109
 can2 (*ics.structures.s_red_settings.s_red_settings* attribute), 121
 can2 (*ics.structures.svcn3_settings.svcn3_settings* attribute), 123
 can2 (*ics.structures.svcn412_settings.svcn412_settings* attribute), 124
 can2 (*ics.structures.svcn4_settings.svcn4_settings* attribute), 127
 can2 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 128
 can2 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings* attribute), 130
 can2 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 132
 can2 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings* attribute), 135
 can2 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 137
 can2 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings* attribute), 140
 can2 (*ics.structures.srad_pluto_settings.srad_pluto_settings* attribute), 142
 can2 (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 144

can2 (*ics.structures.svcn3_settings.svcn3_settings* attribute), 152
can2 (*ics.structures.svcn412_settings.svcn412_settings* attribute), 152
can2 (*ics.structures.svcn4_ind_settings.svcn4_ind_settings* attribute), 153
can2 (*ics.structures.svcn4_settings.svcn4_settings* attribute), 154
can2 (*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 156
can2_options (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can2_rx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can2_tx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can3 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 91
can3 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 97
can3 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 100
can3 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 103
can3 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 105
can3 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 128
can3 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 132
can3 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings* attribute), 135
can3 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 135
can3 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 138
can3 (*ics.structures.svcn4_settings.svcn4_settings* attribute), 155
can3 (*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 156
can3_options (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can3_rx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can3_tx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 91
can4 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 97
can4 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 100
can4 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 103
can4 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 105
can4 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 128
can4 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 132
can4 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings* attribute), 135
can4 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 138
can4 (*ics.structures.svcn4_settings.svcn4_settings* attribute), 155
can4 (*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 156
can4_options (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4_rx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4_tx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4 (*ics.structures.srd_galaxy_settings.srd_galaxy_settings* attribute), 132
can4 (*ics.structures.srd_gigalog_settings.srd_gigalog_settings* attribute), 135
can4 (*ics.structures.srd_gigastar_settings.srd_gigastar_settings* attribute), 138
can4 (*ics.structures.svcn4_settings.svcn4_settings* attribute), 155
can4 (*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 156
can4_options (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4_rx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4_tx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4 (*ics.structures.srd_galaxy_settings.srd_galaxy_settings* attribute), 132
can4 (*ics.structures.srd_gigalog_settings.srd_gigalog_settings* attribute), 135
can4 (*ics.structures.srd_gigastar_settings.srd_gigastar_settings* attribute), 138
can4 (*ics.structures.svcn4_settings.svcn4_settings* attribute), 155
can4 (*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 156
can4_options (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4_rx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4_tx_id (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 121
can4 (*ics.structures.srd_galaxy_settings.srd_galaxy_settings* attribute), 132

can7 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute*), 142
 can8 (*ics.structures.s_cyan_settings.s_cyan_settings attribute*), 91
 can8 (*ics.structures.s_fire3_settings.s_fire3_settings attribute*), 98
 can8 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute*), 132
 can8 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute*), 135
 CAN_BPS10000 (*in module ics.ics*), 162
 CAN_BPS5000 (*in module ics.ics*), 162
 CAN_BPS6667 (*in module ics.ics*), 162
 CAN_BPS8000 (*in module ics.ics*), 162
 can_settings (*class in ics.structures.can_settings*), 73
 CAN_SETTINGS_SIZE (*in module ics.ics*), 162
 can_switch_mode (*ics.structures.s_cyan_settings.s_cyan_settings attribute*), 91
 can_switch_mode (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute*), 107
 can_switch_mode (*ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute*), 122
 can_switch_mode (*ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute*), 128
 can_switch_mode (*ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute*), 130
 can_switch_mode (*ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute*), 132
 can_switch_mode (*ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute*), 132
 can_switch_mode (*ics.structures.srad_star2_settings.srad_star2_settings attribute*), 144
 canfd1 (*ics.structures.s_cyan_settings.s_cyan_settings attribute*), 91
 canfd1 (*ics.structures.s_fire3_settings.s_fire3_settings attribute*), 98
 canfd1 (*ics.structures.s flex_vnetz_settings.s flex_vnetz_settings attribute*), 105
 canfd1 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute*), 107
 canfd1 (*ics.structures.scan_hub_settings.scan_hub_settings attribute*), 123
 canfd1 (*ics.structures.secu_avb_settings.secu_avb_settings attribute*), 123
 canfd1 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute*), 128
 canfd1 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute*), 130
 canfd1 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute*), 132
 canfd1 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute*), 135
 canfd1 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute*), 138
 canfd1 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute*), 140
 canfd1 (*ics.structures.srd_pluto_settings.srd_pluto_settings attribute*), 142
 canfd2 (*ics.structures.srd_star2_settings.srd_star2_settings attribute*), 144
 canfd1 (*ics.structures.svcn412_settings.svcn412_settings attribute*), 152
 canfd1 (*ics.structures.svcn4_ind_settings.svcn4_ind_settings attribute*), 153
 canfd1 (*ics.structures.svcn4_settings.svcn4_settings attribute*), 155
 canfd2 (*ics.structures.s_cyan_settings.s_cyan_settings attribute*), 91
 canfd2 (*ics.structures.s_fire3_settings.s_fire3_settings attribute*), 98
 canfd2 (*ics.structures.s flex_vnetz_settings.s flex_vnetz_settings attribute*), 105
 canfd2 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute*), 107
 canfd2 (*ics.structures.secu_avb_settings.secu_avb_settings attribute*), 123
 canfd2 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute*), 128
 canfd2 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute*), 130
 canfd2 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings attribute*), 132
 canfd2 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute*), 135
 canfd2 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute*), 138
 canfd2 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute*), 140
 canfd2 (*ics.structures.srad_pluto_settings.srad_pluto_settings attribute*), 142
 canfd2 (*ics.structures.svcn412_settings.svcn412_settings attribute*), 152
 canfd2 (*ics.structures.svcn4_ind_settings.svcn4_ind_settings attribute*), 153
 canfd2 (*ics.structures.svcn4_settings.svcn4_settings attribute*), 155
 canfd3 (*ics.structures.s_cyan_settings.s_cyan_settings attribute*), 91
 canfd3 (*ics.structures.s_fire3_settings.s_fire3_settings attribute*), 98
 canfd3 (*ics.structures.s flex_vnetz_settings.s flex_vnetz_settings attribute*), 105
 canfd3 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute*), 129
 canfd3 (*ics.structures.srd_gigastar_settings.srd_gigastar_settings attribute*), 132
 canfd3 (*ics.structures.srd_jupiter_settings.srd_jupiter_settings attribute*), 140
 canfd3 (*ics.structures.srd_pluto_settings.srd_pluto_settings attribute*), 143
 canfd3 (*ics.structures.srd_gigalog_settings.srd_gigalog_settings attribute*), 135

```

        attribute), 138
canfd3 (ics.structures.svcn4_settings.svcn4_settings    canfd8 (ics.structures.s_fire3_settings.s_fire3_settings
        attribute), 155                                attribute), 98
canfd4 (ics.structures.s_cyan_settings.s_cyan_settings    canfd8 (ics.structures.srad_galaxy_settings.srad_galaxy_settings
        attribute), 91                                attribute), 133
canfd4 (ics.structures.s_fire3_settings.s_fire3_settings    canfd8 (ics.structures.srad_gigalog_settings.srad_gigalog_settings
        attribute), 98                                attribute), 136
canfd4 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings    CANFD_BRS_ENABLED (in module ics.ics), 162
        attribute), 106                                CANFD_BRS_ENABLED_ISO (in module ics.ics), 162
canfd4 (ics.structures.sobd2_pro_settings.sobd2_pro_settings    CANFD_ENABLED (in module ics.ics), 162
        attribute), 129                                CANFD_ENABLED_ISO (in module ics.ics), 162
canfd4 (ics.structures.srad_galaxy_settings.srad_galaxy_settings    (class      in
        attribute), 132                                ics.structures.canfd_settings), 73
canfd4 (ics.structures.srad_gigalog_settings.srad_gigalog_settings    CANFD_SETTINGS_SIZE (in module ics.ics), 162
        attribute), 135                                canhub (ics.structures.global_settings.global_settings
                                                        attribute), 77
canfd4 (ics.structures.srad_gigastar_settings.srad_gigastar_settings    canhub (ics.structures.s_device_settings.s_device_settings
        attribute), 138                                attribute), 94
canfd4 (ics.structures.svcn4_settings.svcn4_settings    CANNODE_STATUS_COREMINI_IS_RUNNING (in
        attribute), 155                                module ics.ics), 162
canfd5 (ics.structures.s_cyan_settings.s_cyan_settings    CANNODE_STATUS_IN_BOOTLOADER (in module
        attribute), 91                                ics.ics), 162
canfd5 (ics.structures.s_fire3_settings.s_fire3_settings    CANOptions (ics.structures.tag_options_find_neo_ex.tag_options_find_neo_ex),
        attribute), 98                                attribute), 158
canfd5 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings    CANOptions (ics.structures.tag_options_open_neo_ex.tag_options_open_neo_ex),
        attribute), 106                                attribute), 158
canfd5 (ics.structures.srad_galaxy_settings.srad_galaxy_settings    canterm_settings (class      in
        attribute), 132                                ics.structures.canterm_settings), 74
canfd5 (ics.structures.srad_gigalog_settings.srad_gigalog_settings    CANTERM_SETTINGS_SIZE (in module ics.ics), 162
        attribute), 135
canfd5 (ics.structures.srad_gigastar_settings.srad_gigastar_settings    canterm_attributes (ics.structures.s_pluto_general_params.s.s_pluto_general_params),
        attribute), 138                                attribute), 114
canfd6 (ics.structures.s_cyan_settings.s_cyan_settings    cf_timeout (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message),
        attribute), 91                                attribute), 150
canfd6 (ics.structures.s_fire3_settings.s_fire3_settings    cgi_baud (ics.structures.s_fire_settings.s_fire_settings),
        attribute), 98                                attribute), 100
canfd6 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings    cgi_baud (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings),
        attribute), 106                                attribute), 103
canfd6 (ics.structures.srad_galaxy_settings.srad_galaxy_settings    cgi_cksum_enable
        attribute), 132                                (ics.structures.s_fire_settings.s_fire_settings
                                                        attribute), 132
canfd6 (ics.structures.srad_gigalog_settings.srad_gigalog_settings    cgi_cksum_enable
        attribute), 100                                attribute), 135
canfd6 (ics.structures.srad_gigastar_settings.srad_gigastar_settings    cgi_cksum_enable
        attribute), 138                                (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
                                                        attribute), 103
canfd7 (ics.structures.s_cyan_settings.s_cyan_settings    cgi_enable_reserved
        attribute), 91                                (ics.structures.s_fire_settings.s_fire_settings
                                                        attribute), 100
canfd7 (ics.structures.s_fire3_settings.s_fire3_settings    cgi_enable_reserved
        attribute), 98                                attribute), 100
canfd7 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings    (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
        attribute), 106                                attribute), 103
canfd7 (ics.structures.srad_galaxy_settings.srad_galaxy_settings    (ics.structures.s_fire_settings.s_fire_settings
        attribute), 133                                attribute), 103
canfd7 (ics.structures.srad_gigalog_settings.srad_gigalog_settings    cgi_rx_ifs_bit_times
        attribute), 100                                (ics.structures.s_fire_settings.s_fire_settings
                                                        attribute), 135
canfd8 (ics.structures.s_cyan_settings.s_cyan_settings    cgi_rx_ifs_bit_times
        attribute), 98                                (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
                                                        attribute), 100

```

attribute), 103
`cgi_tx_ifs_bit_times` (*ics.structures.s_fire_settings.s_fire_settings attribute*), 100
`cgi_tx_ifs_bit_times` (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute*), 103
`chA` (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray.attribute*), 82
`chB` (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray.attribute*), 82
`chksum` (*ics.structures.global_settings.global_settings attribute*), 77
`chksum` (*ics.structures.s_extended_data_flash_header.s_extended_data_flash_header.attribute*), 97
`chksum` (*ics.structures.serdespoc_settings.serdespoc_setting attribute*), 126
`chksum_enabled` (*ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings attribute*), 87
`clause22` (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute*), 111
`clause45` (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute*), 111
`Clause45Enable` (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute*), 110
`close_device()` (*in module ics.ics*), 28
`ClosePort()` (*in module ics.ics*), 20
`cmd` (*ics.structures.s_ext_sub_cmd_hdr.s_ext_sub_cmd_hdrcyan attribute*), 97
`cmprobe` (*ics.structures.global_settings.global_settings attribute*), 77
`cmprobe` (*ics.structures.s_device_settings.s_device_settings attribute*), 94
`cmprobe_versions` (*ics.structures.st_chip_versions.st_chip_versions.SpyMessage attribute*), 147
`CommandByteLength` (*ics.structures.tagicsneo_vi_command.tagicsneo_vi_command attribute*), 158
`CommandType` (*ics.structures.tagicsneo_vi_command.tagicsneo_vi_command attribute*), 158
`Config` (*ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway_settings attribute*), 109
`converter` (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings attribute*), 120
`converter1Mode` (*ics.structures.rad_moon_duo_converter_settings.rad_moon_duo_converter_settings attribute*), 90
`core_maj` (*ics.structures.st_chip_versions.st_chip_versions attribute*), 147
`core_major` (*ics.structures.st_chip_versions.st_chip_versions attribute*), 147
`core_min` (*ics.structures.st_chip_versions.st_chip_versions attribute*), 147
`core_minor` (*ics.structures.st_chip_versions.st_chip_versions attribute*), 147
`coremini_clear()` (*in module ics.ics*), 28
`coremini_get_fblock_status()` (*in module ics.ics*), 29
`coremini_get_status()` (*in module ics.ics*), 29
`coremini_load()` (*in module ics.ics*), 29
`coremini_read_app_signal()` (*in module ics.ics*), 29
`coremini_start()` (*in module ics.ics*), 30
`coremini_start_fblock()` (*in module ics.ics*), 30
`coremini_stop_fblock()` (*in module ics.ics*), 31
`coremini_write_tx_message()` (*in module ics.ics*), 31
`create_neovi_radio_message()` (*in module ics.ics*), 31
`cyan` (*ics.structures.global_settings.global_settings attribute*), 78
`cyan` (*ics.structures.s_device_settings.s_device_settings attribute*), 94
`cycle` (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 82
D
`Data` (*ics.ics.SpyMessageJ1850 attribute*), 19
`Data` (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 81
`Data` (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 81
`data` (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute*), 66
`data` (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute*), 51
`DataLsb` (*ics.structures.ics_spy_message_long.ics_spy_message_long attribute*), 83
`DataMsb` (*ics.structures.ics_spy_message_long.ics_spy_message_long attribute*), 83
`debugen` (*ics.structures.s_pluto_vl_forwarding_params.s_pluto_vl_forwarding_params attribute*), 119
`DescriptionID` (*ics.ics.SpyMessage attribute*), 18
`DescriptionID` (*ics.ics.SpyMessageJ1850 attribute*), 19

DescriptionID (*ics.structures.ics_spy_message_flex_ray_attributes.e_device_settings_type.e_device_settings_type*)
attribute), 81
DescriptionID (*ics.structures.ics_spy_message_long.ics_spy_message_structures.e_device_settings_type.e_device_settings_type*)
attribute), 83
DeviceOBD2SimSettingsType
DescriptionID (*ics.structures.ics_spy_message_vsb.ics_spy_message_structures.e_device_settings_type.e_device_settings_type*)
attribute), 84
destmeta (*ics.structures.s_pluto_avb_params.s_pluto_attributes.e_device_settings_type.e_device_settings_type*)
attribute), 112
DeviceRADGalaxySettingsType
destports (*ics.structures.s_pluto_l2_address_lookup_entry.s.s_pluto_attributes.e_device_settings_type.e_device_settings_type*)
attribute), 115
DeviceRADGigalogSettingsType
destports (*ics.structures.s_pluto_retagging_entry.s.s_pluto_retagging_structures.e_device_settings_type.e_device_settings_type*)
attribute), 118
DeviceRADForwardingSettingsType
destports (*ics.structures.s_pluto_vl_forwarding_entry.s.s_pluto_attributes.e_device_settings_type.e_device_settings_type*)
attribute), 119
DeviceRADJupiterSettingsType
details (*ics.structures.s_ext_sub_cmd.comm.s_ext_sub_cmd.com_attributes.e_device_settings_type*)
attribute), 75
DeviceRADMoon2SettingsType
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 74
DeviceRADPlutoSettingsType
DeviceCANHUBSettingsType
DeviceRadMoonDuoSettingsType
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 74
DeviceRADPlutoSettingsType
DeviceECU_AVBSettingsType
DeviceRADPlutoSwitchSettingsType
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 74
DeviceEEVBSettingsType
DeviceRADStar2SettingsType
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 74
DeviceEtherBadgeSettingsType
DeviceRADSUPERMOONSettingsType
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 75
DeviceFire2SettingsType
DeviceRedSettingsType
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 75
DeviceFire3SettingsType
DeviceSettingsNone
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 75
DeviceFireSettingsType
DeviceSettingsTypeMax
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 75
DeviceFlexVnetzSettingsType
DeviceSettingType
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 75
DeviceIEVBSettingsType
DeviceType (*ics.ics.NeoDevice attribute*), 18
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 75
DeviceNeoECU12SettingsType
DeviceType CAN3SettingsType
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 75
DeviceNeoECU12SettingsType
DeviceType CAN412SettingsType
(*ics.structures.e_device_settings_type.e_device_settings_type.e_device_settings_type.e_device_settings_type*)
attribute), 75

attribute), 75
DeviceVCAN4IndSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type.attribute), 75
DeviceVCAN4SettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type.attribute), 75
DeviceVCANRFSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type.attribute), 75
DeviceVividCANSettingsType
 (ics.structures.e_device_settings_type.e_device_settings_type.attribute), 75
digitalIoThresholdEnable
 (ics.structures.s_cyan_settings.s_cyan_settings.attribute), 92
digitalIoThresholdEnable
 (ics.structures.s_fire3_settings.s_fire3_settings.attribute), 98
digitalIoThresholdTicks
 (ics.structures.s_cyan_settings.s_cyan_settings.attribute), 92
digitalIoThresholdTicks
 (ics.structures.s_fire3_settings.s_fire3_settings.attribute), 98
DISABLE *(in module ics.ics), 162*
disableFwLEDs *(ics.structures.svcanrf_settings.svcanrf_settings.attribute), 156*
disableUsbCheckOnBoot
 (ics.structures.s_cyan_settings.s_cyan_settings.attribute), 92
disableUsbCheckOnBoot
 (ics.structures.s_fire3_settings.s_fire3_settings.attribute), 98
disableUsbCheckOnBoot
 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_SETTINGS_SIZE.attribute), 106
disableUsbCheckOnBoot
 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_SETTINGS_STATUS_FLAG_INITIALIZED.attribute), 107
disableUsbCheckOnBoot
 (ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_usetting_attributes), 120
disableUsbCheckOnBoot
 (ics.structures.s_vivid_can_settings.s_vivid_can_settig_attributes), 122
disableUsbCheckOnBoot
 (ics.structures.secu_avb_settings.secu_avb_settings.attribute), 123
disableUsbCheckOnBoot
 (ics.structures.sobd2_pro_settings.sobd2_pro_settings.attribute), 129
disableUsbCheckOnBoot
 (ics.structures.srad_gigalog_settings.srad_gigalog_settings.attribute), 76
attribute), 136
disableUsbCheckOnBoot
 (ics.structures.srad_jupiter_settings.srad_jupiter_settings.attribute), 140
disableUsbCheckOnBoot
 (ics.structures.srad_pluto_settings.srad_pluto_settings.attribute), 143
disableUsbCheckOnBoot
 (ics.structures.svcan412_settings.svcan412_settings.attribute), 153
disableUsbCheckOnBoot
 (ics.structures.svcan4_ind_settings.svcan4_ind_settings.attribute), 153
disk *(ics.structures.s_cyan_settings.s_cyan_settings.attribute), 92*
disk *(ics.structures.s_fire3_settings.s_fire3_settings.attribute), 98*
disk *(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings.attribute), 106*
disk *(ics.structures.srad_galaxy_settings.srad_galaxy_settings.attribute), 133*
disk *(ics.structures.srad_gigalog_settings.srad_gigalog_settings.attribute), 136*
disk *(ics.structures.srad_gigastar_settings.srad_gigastar_settings.attribute), 138*
disk_enables *(ics.structures.disk_settings.disk_settings.attribute), 74*
disk_format *(ics.structures.disk_settings.disk_settings.attribute), 74*
disk_format *(in module ics.ics), 32*
disk_format_cancel *(in module ics.ics), 32*
disk_layout *(ics.structures.disk_settings.disk_settings.attribute), 74*
disk_settings *(class in ics.structures.disk_settings), 74*
DISK_SETTINGS_SIZE *(in module ics.ics), 162*
DISK_STATUS_FLAG_INITIALIZED *(in module ics.ics), 162*
DISK_STATUS_FLAG_PRESENT *(in module ics.ics), 162*
DISK_STRUCTURE_FLAG_FULL_FORMAT *(in mod-*
DiskFormatexFAT *(ics.structures.e_disk_format.e_disk_format.attribute), 75*
DiskFormatFAT32 *(ics.structures.e_disk_format.e_disk_format.attribute), 75*
DiskFormatUnknown
 (ics.structures.e_disk_format.e_disk_format.attribute), 75
DiskLayoutIndividual
 (ics.structures.e_disk_layout.e_disk_layout.attribute), 76
DiskLayoutRAID0 *(ics.structures.e_disk_layout.e_disk_layout.attribute), 76*

DiskLayoutRAID1 (*ics.structures.e_disk_layout.e_disk_layout_id* (*ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute*), 76
 DiskLayoutRAID5 (*ics.structures.e_disk_layout.e_disk_layout_id* (*ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute*), 76
 DiskLayoutSpanned
 (*ics.structures.e_disk_layout.e_disk_layout attribute*), 76
 do_not_learn (*ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s attribute*), 118
 drpdtag (*ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_attribute*), 76
 (*attribute*), 117
 drpnona664 (*ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_attribute*), 117
 (*attribute*), 117
 drpuntag (*ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_attribute*), 118
 (*attribute*), 117
 duplex (*ics.structures.ethernet_settings.ethernet_settings attribute*), 77
 DWord (*ics.structures.s_text_api_settings.s_text_api_settings attribute*), 121
 dyn_learn (*ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_attribute*), 117
 (*attribute*), 117
 dyn_tbsz (*ics.structures.s_pluto_l2_address_lookup_params.s_pluto_l2_address_lookup_params attribute*), 33
 (*attribute*), 116
 dynamic (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 82

E

e_device_settings_type	(class <i>ics.structures.e_device_settings_type</i>), 74	in	enableBusVoltageMonitor () (in module <i>ics.ics</i>), 32
e_disk_format	(class <i>ics.structures.e_disk_format</i>), 75	in	enableConvertMode
e_disk_layout	(class <i>ics.structures.e_disk_layout</i>), 75	in	egress (<i>ics.structures.s_pluto_mac_config_s.s_pluto_mac_config_s attribute</i>), 117
e_plasma_ion_vnet_channel_t	(class <i>ics.structures.e_plasma_ion_vnet_channel_t</i>), 76	in	enableBusVoltageMonitor () (in module <i>ics.ics</i>), 32
ecu	(<i>ics.structures.global_settings.global_settings attribute</i>), 78	in	enableDefaultLogger
ecu	(<i>ics.structures.s_device_settings.s_device_settings attribute</i>), 95	in	enableDefaultLogger
ecu_id	(<i>ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute</i>), 107	in	enableDefaultUpload
ecu_id	(<i>ics.structures.s_pendant_settings.s_pendant_settings attribute</i>), 109	in	(<i>ics.structures.s_cyan_settings.s_cyan_settings attribute</i>), 92
ecu_id	(<i>ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute</i>), 122	in	enableDefaultLogger
ecu_id	(<i>ics.structures.scan_hub_settings.scan_hub_settings attribute</i>), 123	in	(<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 98
ecu_id	(<i>ics.structures.secu_settings.secu_settings attribute</i>), 124	in	enableDefaultUpload
ecu_id	(<i>ics.structures.seevb_settings.seevb_settings attribute</i>), 125	in	(<i>ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute</i>), 106
ecu_id	(<i>ics.structures.sievb_settings.sievb_settings attribute</i>), 127	in	enableFlowControlTransmission
		enableDefaultUpload	(<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 98
		enableLatencyTest	(<i>ics.structures.s_cyan_settings.s_cyan_settings attribute</i>), 92
		enableLatencyTest	(<i>ics.structures.s_fire3_settings.s_fire3_settings attribute</i>), 92

attribute), 98
enableLatencyTest
(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings.attribute), 106
enableLatencyTest
(ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings.attribute), 107
enableLatencyTest
(ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings.attribute), 120
enableLatencyTest
(ics.structures.s_vivid_can_settings.s_vivid_can_settings.attribute), 122
enableLatencyTest
(ics.structures.secu_avb_settings.secu_avb_settings.attribute), 123
enableLatencyTest
(ics.structures.sobd2_pro_settings.sobd2_pro_settings.attribute), 129
enableLatencyTest
(ics.structures.sobd2_sim_settings.sobd2_sim_settings.attribute), 130
enableLatencyTest
(ics.structures.srad_jupiter_settings.srad_jupiter_settings.attribute), 140
enableLatencyTest
(ics.structures.srad_pluto_settings.srad_pluto_settings.attribute), 143
enableLatencyTest
(ics.structures.svcanc412_settings.svcanc412_settings.attribute), 153
enableLatencyTest
(ics.structures.svcanc4_settings.svcanc4_settings.attribute), 155
EnableNetworkCom() (*in module ics.ics*), 20
enablePcEthernetComm
(ics.structures.s_cyan_settings.s_cyan_settings.attribute), 92
enablePcEthernetComm
(ics.structures.s_fire3_settings.s_fire3_settings.attribute), 98
enablePcEthernetComm
(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings.attribute), 106
enablePcEthernetComm
(ics.structures.srad_jupiter_settings.srad_jupiter_settings.attribute), 140
enablePcEthernetComm
(ics.structures.srad_pluto_settings.srad_pluto_settings.attribute), 143
enablePcEthernetComm

(ics.structures.svcanc4_ind_settings.svcanc4_ind_settings.attribute), 153
(ics.structures.svcanc4_settings.svcanc4_settings.attribute), 153
(ics.structures.svcanc412_settings.svcanc412_settings.attribute), 153
(ics.structures.svcanc4_settings.svcanc4_settings.attribute), 155
(ics.structures.ethernet10_g_settings) (*class in ics.structures.ethernet10_g_settings*), 76
(ics.structures.srd_gigalog_settings.srd_gigalog_settings.attribute), 136
ETHERNET10G_SETTINGS_SIZE (*in module ics.ics*), 162

(ics.structures.svcanc4_settings.svcanc4_settings.attribute), 153
(ics.structures.svcanc4_settings.svcanc4_settings.attribute), 155
(ics.structures.svcanc412_settings.svcanc412_settings.attribute), 155
(ics.structures.svcanc4_settings.svcanc4_settings.attribute), 155
(ics.structures.svcanc412_settings.svcanc412_settings.attribute), 155
(ics.structures.svcanc4_settings.svcanc4_settings.attribute), 155
(ics.structures.srd_gigalog_settings.srd_gigalog_settings.attribute), 136
(ics.structures.srd_gigalog_settings.srd_gigalog_settings.attribute), 140
(ics.structures.srd_gigalog_settings.srd_gigalog_settings.attribute), 143
(ics.structures.srd_star2_settings.srd_star2_settings.attribute), 144
(ics.structures.svcanc4_ind_settings.svcanc4_ind_settings.attribute), 154
(ics.structures.svcanc4_settings.svcanc4_settings.attribute), 155
(ics.structures.srd_galaxy_settings.srd_galaxy_settings.attribute), 133
(ics.structures.srd_gigastar_settings.srd_gigastar_settings.attribute), 138
(ics.structures.ethernet10_g_settings) (*class in ics.structures.ethernet10_g_settings*), 76
(ics.structures.srd_gigalog_settings.srd_gigalog_settings.attribute), 136

```

ethernet2 (ics.structures.s_cyan_settings.s_cyan_settings) 162
    attribute), 92                                     ETHERNET_SETTINGS_SIZE (in module ics.ics), 162
ethernet2 (ics.structures.s_fire3_settings.s_fire3_setting) ethernetActivationLineEnabled
    attribute), 99                                     (ics.structures.ics_fire2_device_status.ics_fire2_device_status
ethernet2 (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_setting) attribute), 80
    attribute), 106                                     ethernetActivationLineEnabled
ethernet2 (ics.structures.sobd2_pro_settings.sobd2_pro_settings) (ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_device
    attribute), 129                                     attribute), 80
ethernet2 (ics.structures.srad_galaxy_settings.srad_galaxy_setting) ethernetActivationLineEnabled
    attribute), 133                                     (ics.structures.ics_fire3_device_status.ics_fire3_device_status
ethernet2 (ics.structures.srad_gigalog_settings.srad_gigalog_setting) attribute), 80
    attribute), 136                                     ethernetActivationLineEnabled
ethernet2 (ics.structures.srad_gigastar_settings.srad_gigastar_setting) (ics.structures.ics_flex_vnetz_device_status.ics_flex_vnetz_device
    attribute), 138                                     attribute), 80
ethernet2 (ics.structures.srad_jupiter_settings.srad_jupiter_setting) ethernetActivationLineEnabled
    attribute), 140                                     (ics.structures.ics_vcan4_device_status.ics_vcan4_device_status
ethernet2 (ics.structures.srad_pluto_settings.srad_pluto_setting) attribute), 86
    attribute), 143                                     ethernetStatus (ics.structures.ics_fire2_device_status.ics_fire2_device_
ethernet2 (ics.structures.svcan4_ind_settings.svcan4_ind_setting) attribute), 80
    attribute), 154                                     ethernetStatus (ics.structures.ics_fire2_vnet_device_status.ics_fire2_vnet_
ethernet2 (ics.structures.svcan4_settings.svcan4_setting) attribute), 80
    attribute), 155                                     ethernetStatus (ics.structures.ics_fire3_device_status.ics_fire3_device_
ethernet_network_status_t (class) in 76
    ics.structures.ethernet_network_status_t), 76
    attribute), 80                                     ethernetStatus (ics.structures.ics_flex_vnetz_device_status.ics_flex_vnet_
ethernet_settings (class) in 76
    ics.structures.ethernet_settings), 77
    attribute), 80                                     ethernetStatus (ics.structures.ics_oobd2_pro_device_status.ics_oobd2_
ETHERNET_SETTINGS10G_FLAG_AUTO_NEG (in module ics.ics), 162
    attribute), 80                                     ethernetStatus (ics.structures.ics_rad_jupiter_device_status.ics_rad_jupiter_
ETHERNET_SETTINGS10G_FLAG_COMM_IN_USE (in module ics.ics), 162
    attribute), 81                                     ethernetStatus (ics.structures.ics_rad_moon_duo_device_status.ics_rad_moon_duo_
ETHERNET_SETTINGS10G_FLAG_DEVICE_HOSTING_ENABLE (in module ics.ics), 162
    attribute), 81                                     ethernetStatus (ics.structures.ics_rad_pluto_device_status.ics_rad_pluto_
ETHERNET_SETTINGS10G_FLAG_FULL_DUPLEX (in module ics.ics), 162
    attribute), 86                                     ethernetStatus (ics.structures.ics_vcan4_device_status.ics_vcan4_device_
ETHERNET_SETTINGS10G_FLAG_RTSP_ENABLE (in module ics.ics), 162
    attribute), 86                                     ethernetStatus (ics.structures.ics_vcan4_industrial_device_status.ics_vcan4_
ETHERNET_SETTINGS10G_FLAG_TCPIP_ENABLE (in module ics.ics), 162
    attribute), 112                                     etssrcpcf (ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_
ethernet_settings2 (class) in 77
    ics.structures.ethernet_settings2), 77
    attribute), 131                                     ExpectedLength (ics.structures.spy_filter_long.spy_filter_long_
ETHERNET_SETTINGS2_FLAG_AUTO_NEG (in module ics.ics), 162
    attribute), 86                                     ext_address_enable
ETHERNET_SETTINGS2_FLAG_COMM_IN_USE (in module ics.ics), 162
    attribute), 86                                     (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_
ETHERNET_SETTINGS2_FLAG_DEVICE_HOSTING_ENABLE (in module ics.ics), 162
    attribute), 150                                     ext_address_enable
ETHERNET_SETTINGS2_FLAG_FULL_DUPLEX (in module ics.ics), 162
    attribute), 150                                     (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_
ETHERNET_SETTINGS2_FLAG_RTSP_ENABLE (in module ics.ics), 162
    attribute), 151                                     ext_address_enable
ETHERNET_SETTINGS2_FLAG_TCPIP_ENABLE (in module ics.ics), 162
    attribute), 147                                     ext_flash_maj (ics.structures.st_chip_versions.st_chip_versions_
ETHERNET_SETTINGS2_SIZE (in module ics.ics),
    attribute), 148                                     ext_flash_min (ics.structures.st_chip_versions.st_chip_versions_

```

extendedAddress (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute*), 86
 extendedAddress (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute*), 150
 extendedAddress (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute*), 151
 extraction_timeout (*ics.structures.logger_settings.logger_settings attribute*), 88
 ExtraDataPtr (*ics.ics.SpyMessage attribute*), 18
 ExtraDataPtr (*ics.ics.SpyMessageJ1850 attribute*), fc_id_29_bit_enable
 ExtraDataPtr (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 81
 ExtraDataPtr (*ics.structures.ics_spy_message_long.ics_spy_message_long attribute*), 83
 ExtraDataPtr (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 84
 ExtraDataPtrEnabled (*ics.ics.SpyMessage attribute*), 18
 ExtraDataPtrEnabled (*ics.ics.SpyMessageJ1850 attribute*), 19
 ExtraDataPtrEnabled (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 81
 ExtraDataPtrEnabled (*ics.structures.ics_spy_message_long.ics_spy_message_long attribute*), 83
 ExtraDataPtrEnabled (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 85

F

fast_init_network_enables_1 (*ics.structures.s_fire_settings.s_fire_settings attribute*), 100
 fast_init_network_enables_1 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute*), 103
 fast_init_network_enables_2 (*ics.structures.s_fire_settings.s_fire_settings attribute*), 101
 fast_init_network_enables_2 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute*), 103
 FAST_MODE (*in module ics.ics*), 162
 fc_ext_address_enable (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute*), 86
 fc_ext_address_enable (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute*), 150
 fc_ext_address_enable (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute*), 151
 fc_id (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute*), 86
 fc_id (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute*), 150
 fc_id (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute*), 151
 fc_id_29_bit_enable
 (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 86
 ExtraDataPtr (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 82
 fcrc0 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 82
 fcrc1 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 82
 fcrc2 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 82
 fEdge_valgate (*ics.structures.canfd_settings.canfd_settings attribute*), 74
 FDBRP (*ics.structures.canfd_settings.canfd_settings attribute*), 74
 FDMode (*ics.structures.canfd_settings.canfd_settings attribute*), 74
 FDTDC (*ics.structures.canfd_settings.canfd_settings attribute*), 74
 FDTqProp (*ics.structures.canfd_settings.canfd_settings attribute*), 74
 FDTqSeg1 (*ics.structures.canfd_settings.canfd_settings attribute*), 74
 FDTqSeg2 (*ics.structures.canfd_settings.canfd_settings attribute*), 74
 FDTqSync (*ics.structures.canfd_settings.canfd_settings attribute*), 74
 find_devices () (*in module ics.ics*), 33
 findNeoDevices () (*in module ics.ics*), 21
 fire (*ics.structures.global_settings.global_settings attribute*), 78
 fire (*ics.structures.s_device_settings.s_device_settings attribute*), 95
 fire2Status (*ics.structures.ics_device_status.ics_device_status attribute*), 79
 fire3 (*ics.structures.s_device_settings.s_device_settings attribute*), 95

fire3_versions (ics.structures.st_chip_versions.st_chip_version attribute), 148
fire3Status (ics.structures.ics_device_status.ics_device_status attribute), 79
fire_versions (ics.structures.st_chip_versions.st_chip_version attribute), 148
firevnet (ics.structures.global_settings.global_settings attribute), 78
firevnet (ics.structures.s_device_settings.s_device_setting attribute), 95
firmware_update_required() (in module ics.ics), 33
FirmwareUpdateRequired() (in module ics.ics), 21
fl_domain (ics.structures.s_pluto_l2_forwarding_entry_sf1_pluto_l2_forwarding_entry.flex_vnetz_settings.s_flex_vnetz_settings attribute), 116
flags (ics.structures.ethernet10_g_settings.ethernet10_g_settings attribute), 76
flags (ics.structures.ethernet_settings2.ethernet_settings2.flex_vnet_mode attribute), 77
flags (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message.oldStart attribute), 86
flags (ics.structures.op_eth_general_settings.op_eth_general_setting attribute), 89
flags (ics.structures.rad_reporting_settings.rad_reporting_settings attribute), 90
flags (ics.structures.s_cyan_settings.s_cyan_settings attribute), 92
flags (ics.structures.s_fire3_settings.s_fire3_settings attribute), 99
flags (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings attribute), 106
flags (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 108
flags (ics.structures.s_phy_reg_pkt.s_phy_reg_pkt attribute), 111
flags (ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings attribute), 120
flags (ics.structures.s_vivid_can_settings.s_vivid_can_settings attribute), 122
flags (ics.structures.secu_avb_settings.secu_avb_settings attribute), 123
flags (ics.structures.serdescam_settings.serdescam_settings attribute), 126
flags (ics.structures.sobd2_pro_settings.sobd2_pro_settings attribute), 129
flags (ics.structures.sobd2_sim_settings.sobd2_sim_settings attribute), 130
flags (ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 136
flags (ics.structures.srad_gigastar_settings.srad_gigastar_settings attribute), 138
flags (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 140
firevnet (ics.structures.srad_pluto_settings.srad_pluto_settings attribute), 143
firevnet (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 150
firevnet (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 151
firevnet (ics.structures.svcan412_settings.svcan412_settings attribute), 153
firevnet (ics.structures.svcan4_ind_settings.svcan4_ind_settings attribute), 154
firmware_update_required() (in module ics.ics), 155
flashHeader (ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings attribute), 118
flexVnetModeOneDual (ics.structures.flex_vnet_mode.flex_vnet_mode attribute), 77
flexVnetModeOneSingle (ics.structures.flex_vnet_mode.flex_vnet_mode attribute), 77
flexVnetModeTwoSingle (ics.structures.flex_vnet_mode.flex_vnet_mode attribute), 77
flexvnet (ics.structures.global_settings.global_settings attribute), 77
flexvnet (ics.structures.s_device_settings.s_device_settings attribute), 78
flexVnetStatus (ics.structures.ics_device_status.ics_device_status attribute), 95
flow_control (ics.structures.uart_settings.uart_settings attribute), 79
flowControlExtendedAddress (ics.structures.uart_settings.uart_settings attribute), 159
flowControlExtendedAddress (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 86
flowControlExtendedAddress (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 150
flowControlExtendedAddress (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 151
force_firmware_update() (in module ics.ics), 34
ForceFirmwareUpdate() (in module ics.ics), 21

frame_len_12_5ns (*ics.structures.ics_spy_message_flex.spy_message.flex.rdy* (in module *ics.ics*), 37
 attribute), 82
 get_library_path() (in module *ics.ics*), 37

frame_reserved (*ics.structures.ics_spy_message_flex.rqe* (in module *ics.ics*), 37
 attribute), 82
 get_performance_parameters() (in module *ics.ics*), 38

FrameMaster (*ics.structures.spy_filter_long.spy_filter_long* (in module *ics.ics*), 38
 attribute), 131
 get_RTC() (in module *ics.ics*), 38

frameSkip (*ics.structures.serdescam_settings.serdescam_getting* (in module *ics.ics*), 38
 attribute), 126
 get_script_status() (in module *ics.ics*), 38
 get_serial_number() (in module *ics.ics*), 38

from_param (*ics.structures.e_device_settings_type.e_device_settings_stamp_for_msg* (in module *ics.ics*), 38
 attribute), 75
 GetActiveVNETChannel() (in module *ics.ics*), 21

from_param (*ics.structures.e_disk_format.e_disk_format* (in module *ics.ics*), 21
 attribute), 75
 GetBackupPowerEnabled() (in module *ics.ics*), 21
 GetBackupPowerReady() (in module *ics.ics*), 21

from_param (*ics.structures.e_disk_layout.e_disk_layout* (in module *ics.ics*), 21
 attribute), 76
 GetBusVoltage() (in module *ics.ics*), 21
 GetDeviceSettings() (in module *ics.ics*), 22

from_param (*ics.structures.e_plasma_ion_vnet_channel_get_plasma_ion_vnet_channel* (in module *ics.ics*), 22
 attribute), 76
 GetDLLFirmwareInfo() (in module *ics.ics*), 21

from_param (*ics.structures.flex_vnet_mode.flex_vnet_mode* (in module *ics.ics*), 22
 attribute), 77
 GetErrorMessages() (in module *ics.ics*), 22

from_param (*ics.structures.op_eth_link_mode.op_eth_link_mode* (in module *ics.ics*), 22
 attribute), 89
 GetFirmwareInfo() (in module *ics.ics*), 22
 GetLastError() (in module *ics.ics*), 22

fs_timeout (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message* (in module *ics.ics*), 22
 attribute), 86
 GetPerformanceParameters() (in module *ics.ics*), 22

fs_timeout (*ics.structures.st_cm_iso157652_tx_message.st_cm_isods7652tx_message* (in module *ics.ics*), 23
 attribute), 151
 GetRTC() (in module *ics.ics*), 23

fs_wait (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message* (in module *ics.ics*), 23
 attribute), 86
 GetTimeStampForMsg() (in module *ics.ics*), 23

fs_wait (*ics.structures.st_cm_iso157652_tx_message.st_cm_isods7652tx_message* (class in *ics.structures.global_settings*), 77
 attribute), 151

fullcbg (*ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params_size* (in module *ics.ics*), 163
 attribute), 112
 gps_interval_ms (*ics.structures.rad_reporting_settings.rad_reporting* (in module *ics.ics*), 90
 attribute), 90

GS_VERSION (in module *ics.ics*), 163

G

gateway (*ics.structures.ethernet10_g_settings.ethernet10_g_settings* (in module *ics.ics*), 76
 attribute), 76

gateway (*ics.structures.ethernet_settings2.ethernet_settings2alf_duplex* (in module *ics.ics*), 159
 attribute), 77

generalParams (*ics.structures.s_pluto_switch_settings.Hardware_NetDiagSize* attribute), 18
 attribute), 118

get_active_vnet_channel() (in module *ics.ics*), 34

get_backup_power_enabled() (in module *ics.ics*), 34
 attribute), 34

get_backup_power_ready() (in module *ics.ics*), 34

get_bus_voltage() (in module *ics.ics*), 34

get_device_settings() (in module *ics.ics*), 34

get_device_status() (in module *ics.ics*), 35

get_disk_details() (in module *ics.ics*), 35

get_disk_format_progress() (in module *ics.ics*), 36

get_dll_firmware_info() (in module *ics.ics*), 36

get_dll_version() (in module *ics.ics*), 36

get_error_messages() (in module *ics.ics*), 36

get_hw_firmware_info() (in module *ics.ics*), 36

H

HARDWARE_TIMESTAMP_ID_AVT_716 (in module *ics.ics*), 163

HARDWARE_TIMESTAMP_ID_AVT_717 (in module *ics.ics*), 163

HARDWARE_TIMESTAMP_ID_DOUBLE_SEC (in module *ics.ics*), 163

HARDWARE_TIMESTAMP_ID_NEORED_10NS (in module *ics.ics*), 163

HARDWARE_TIMESTAMP_ID_NEORED_10US (in module *ics.ics*), 163

HARDWARE_TIMESTAMP_ID_NEORED_25NS (in module *ics.ics*), 163

HARDWARE_TIMESTAMP_ID_NEOVI (in module *ics.ics*), 163

HARDWARE_TIMESTAMP_ID_NI_CAN (in module *ics.ics*), 163

HARDWARE_TIMESTAMP_ID_NONE (in module `iBoardRevMinor (ics.structures.st_api_firmware_info.st_api_firmware_ics.ics)`, 163) `attribute), 146`

HARDWARE_TIMESTAMP_ID_VSI (in module `ics.ics`), `iBootLoaderVersionMajor (ics.structures.st_api_firmware_info.st_api_firmware_info_hcrc_lsbs (ics.structures.ics_spy_message_flex_ray.ics_spy_message_attributes.ics_device_status), 163)` `attribute), 146`

`attribute), 82` `iBootLoaderVersionMinor`

`attribute), 83` `attribute), 146`

`attribute), 17`

`attribute), 97` `ics_device_status (class in`

`Header (ics.ics.SpyMessageJ1850 attribute), 19` `ics.structures.ics_device_status), 79`

`Header (ics.structures.spy_filter_long.spy_filter_long ics_fire2_device_status (class in` `attribute), 131` `ics.structures.ics_fire2_device_status), 80`

`HeaderLength (ics.structures.spy_filter_long.spy_filter_long_fire2_vnet_device_status (class in` `attribute), 131` `ics.structures.ics_fire2_vnet_device_status), 80`

`HeaderMask (ics.structures.spy_filter_long.spy_filter_long cs_fire3_device_status (class in` `attribute), 131` `ics.structures.ics_fire3_device_status), 80`

`hid_maj (ics.structures.st_chip_versions.st_chip_versions ics_flex_vnetz_device_status (class in` `attribute), 148` `ics.structures.ics_flex_vnetz_device_status), 80`

`hid_min (ics.structures.st_chip_versions.st_chip_versions ics_obd2_pro_device_status (class in` `attribute), 148` `ics.structures.ics_obd2_pro_device_status), 80`

`high_speed_auto_switch ics_rad_jupiter_device_status (class in`

`(ics.structures.swcan_settings.swcan_settings attribute), 158` `ics.structures.ics_rad_jupiter_device_status), 81`

`host_port (ics.structures.s_pluto_general_params.s_s_pluto_general_params_duo_device_status (class in` `attribute), 114` `ics.structures.ics_rad_moon_duo_device_status),`

`hostprior (ics.structures.s_pluto_general_params.s_s_pluto_general_params_s_attribute), 114` `ics_rad_pluto_device_status (class in`

`hwComLatencyTestEn (ics.structures.srad_galaxy_settings.srad_galaxy_settings_spy_message_flex_ray (class in` `attribute), 133` `ics.structures.ics_spy_message_flex_ray), 81`

`hwComLatencyTestEn (ics.structures.srad_gigalog_settings.srad_gigalog_settings_spy_message_long (class in` `attribute), 136` `ics.structures.ics_spy_message_long), 83`

`hwComLatencyTestEn (ics.structures.srad_gigastar_settings.srad_gigastar_settings_ics_spy_message_vsb (class in` `attribute), 138` `ics.structures.ics_spy_message_vsb), 84`

`hwComLatencyTestEn (ics.structures.srad_moon2_settings.srad_moon2_settings_ics_vcan4_device_status (class in` `attribute), 142` `ics.structures.ics_vcan4_device_status), 85`

`hwComLatencyTestEn (ics.structures.srad_star2_settings.srad_star2_settings_neoClosePort () (in module ics.ics), 38` `attribute), 144` `icsneoEnableBusVoltageMonitor () (in module ics.ics), 39`

`hwComLatencyTestEn (ics.structures.srad_super_moon_settings.srad_super_settings_neoEnableNetworkCom () (in module ics.ics), 39` `attribute), 146`

`icsneoFindNeoDevices () (in module ics.ics), 39`

`icsneoFirmwareUpdateRequired () (in module iAppMajor (ics.structures.st_api_firmware_info.st_api_firmware_info_ics), 39` `attribute), 146` `icsneoForceFirmwareUpdate () (in module`

`iAppMinor (ics.structures.st_api_firmware_info.st_api_firmware_info_ics), 39` `attribute), 146` `icsneoGetActiveVNETChannel () (in module`

`iBoardRevMajor (ics.structures.st_api_firmware_info.st_api_firmware_info_ics), 39` `attribute), 146` `icsneoGetBackupPowerEnabled () (in module`

```

    ics.ics), 39
icsneoGetBackupPowerReady() (in module
    ics.ics), 39
icsneoGetBusVoltage() (in module ics.ics), 40
icsneoGetDeviceSettings() (in module ics.ics),
    40
icsneoGetDeviceStatus() (in module ics.ics), 40
icsneoGetDLLFirmwareInfo() (in module
    ics.ics), 40
icsneoGetDLLVersion() (in module ics.ics), 40
icsneoGetErrorMessages() (in module ics.ics),
    40
icsneoGetHWFirmwareInfo() (in module ics.ics),
    40
icsneoGetLastError() (in module ics.ics), 40
icsneoGetMessages() (in module ics.ics), 41
icsneoGetPerformanceParameters() (in mod-
    ule ics.ics), 41
icsneoGetRTC() (in module ics.ics), 41
icsneoGetSerialNumber() (in module ics.ics), 41
icsneoGetTimeStampForMsg() (in module
    ics.ics), 41
icsneoISO15765_DisableNetworks() (in mod-
    ule ics.ics), 41
icsneoISO15765_EnableNetworks() (in mod-
    ule ics.ics), 41
icsneoISO15765_ReceiveMessage() (in mod-
    ule ics.ics), 41
icsneoISO15765_TransmitMessage() (in mod-
    ule ics.ics), 42
icsneoLoadDefaultSettings() (in module
    ics.ics), 42
icsneoOpenNeoDevice() (in module ics.ics), 42
icsneoReadJupiterFirmware() (in module
    ics.ics), 42
icsneoReadSDCard() (in module ics.ics), 42
icsneoRequestDiskDetails() (in module
    ics.ics), 42
icsneoRequestDiskFormat() (in module ics.ics),
    42
icsneoRequestDiskFormatCancel() (in mod-
    ule ics.ics), 42
icsneoRequestDiskFormatProgress() (in
    module ics.ics), 43
icsneoRequestEnterSleepMode() (in module
    ics.ics), 43
icsneoScriptClear() (in module ics.ics), 43
icsneoScriptGetFBlockStatus() (in module
    ics.ics), 43
icsneoScriptGetScriptStatus() (in module
    ics.ics), 43
icsneoScriptGetScriptStatusEx() (in mod-
    ule ics.ics), 43
icsneoScriptLoad() (in module ics.ics), 43
icsneoScriptReadAppSignal() (in module
    ics.ics), 43
icsneoScriptReadRxMessage() (in module
    ics.ics), 44
icsneoScriptReadTxMessage() (in module
    ics.ics), 44
icsneoScriptStart() (in module ics.ics), 44
icsneoScriptStartFBlock() (in module ics.ics),
    44
icsneoScriptStop() (in module ics.ics), 44
icsneoScriptStopFBlock() (in module ics.ics),
    44
icsneoScriptWriteAppSignal() (in module
    ics.ics), 44
icsneoScriptWriteRxMessage() (in module
    ics.ics), 44
icsneoScriptWriteTxMessage() (in module
    ics.ics), 45
icsneoSetActiveVNETChannel() (in module
    ics.ics), 45
icsneoSetBackupPowerEnabled() (in module
    ics.ics), 45
icsneoSetBitRate() (in module ics.ics), 45
icsneoSetBitRateEx() (in module ics.ics), 45
icsneoSetContext() (in module ics.ics), 45
icsneoSetDeviceSettings() (in module ics.ics),
    45
icsneoSetFDBitRate() (in module ics.ics), 45
icsneoSetReflashDisplayCallbacks() (in
    module ics.ics), 46
icsneoSetRTC() (in module ics.ics), 46
icsneoTxMessages() (in module ics.ics), 46
icsneoValidateHObject() (in module ics.ics), 46
icsneoWriteJupiterFirmware() (in module
    ics.ics), 46
icsneoWriteSDCard() (in module ics.ics), 46
id(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray
    attribute), 83
id(ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message
    attribute), 86
id(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_mes-
    sage_attribute), 150
id(ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_mes-
    sage_attribute), 151
id(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_mes-
    sage_attribute), 150
id_29_bit_enable(ics.structures.iso15765_2015_tx_message.iso15765_
    attribute), 86
id_29_bit_enable(ics.structures.st_cm_iso157652_tx_message.st_cm_
    attribute), 150
id_29_bit_enable(ics.structures.st_cm_iso157652_rx_message.st_cm_
    attribute), 150
id_29_bit_enable(ics.structures.st_cm_iso157652_tx_message.st_cm_
    attribute), 151
id_mask(ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_
    attribute), 150
idle_wakeup_network_enables_1
    (ics.structures.s_cyan_settings.s_cyan_settings

```

attribute), 92
idle_wakeup_network_enables_1
(*ics.structures.sievb_settings.sievb_settings*
attribute), 127
idle_wakeup_network_enables_1
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings*
attribute), 133
idle_wakeup_network_enables_1
(*ics.structures.srad_gigalog_settings.srad_gigalog_settings*
attribute), 136
idle_wakeup_network_enables_1
(*ics.structures.srad_gigastar_settings.srad_gigastar_settings*
attribute), 138
idle_wakeup_network_enables_1
(*ics.structures.srad_star2_settings.srad_star2_settings*
attribute), 144
idle_wakeup_network_enables_1
(*ics.structures.svcancrf_settings.svcancrf_settings*
attribute), 156
idle_wakeup_network_enables_2
(*ics.structures.s_cyan_settings.s_cyan_settings*
attribute), 92
idle_wakeup_network_enables_2
(*ics.structures.sievb_settings.sievb_settings*
attribute), 127
idle_wakeup_network_enables_2
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings*
attribute), 133
idle_wakeup_network_enables_2
(*ics.structures.srad_gigalog_settings.srad_gigalog_settings*
attribute), 136
idle_wakeup_network_enables_2
(*ics.structures.srad_gigastar_settings.srad_gigastar_settings*
attribute), 138
idle_wakeup_network_enables_2
(*ics.structures.srad_star2_settings.srad_star2_settings*
attribute), 144
idle_wakeup_network_enables_2
(*ics.structures.svcancrf_settings.svcancrf_settings*
attribute), 156
idle_wakeup_network_enables_3
(*ics.structures.s_cyan_settings.s_cyan_settings*
attribute), 92
idle_wakeup_network_enables_3
(*ics.structures.srad_galaxy_settings.srad_galaxy_settings*
attribute), 133
idle_wakeup_network_enables_3
(*ics.structures.srad_gigalog_settings.srad_gigalog_settings*
attribute), 136
idle_wakeup_network_enables_3
(*ics.structures.srad_gigastar_settings.srad_gigastar_settings*
attribute), 138
idle_wakeup_network_enables_3
(*ics.structures.srad_star2_settings.srad_star2_settings*
attribute), 144
idle_wakeup_network_enables_1
(*ics.structures.global_settings.global_settings*
attribute), 78
ievb (*ics.structures.s_device_settings.s_device_settings*
attribute), 95
ievb (*ics.structures.s_pluto_mac_config.s.s_pluto_mac_config_s*
attribute), 117
ignore2stf (*ics.structures.s_pluto_general_params.s.s_pluto_general_params*
attribute), 114
iMainFirmChkSum (*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 146
iMainFirmDateDay (*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 146
iMainFirmDateHour
(*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iMainFirmDateMin (*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iMainFirmDateMonth
(*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iMainFirmDateSecond
(*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iMainFirmDateYear
(*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iMainVnetHWrevMajor
(*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iMainVnetHWrevMinor
(*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iMainVnetSRAMSize
(*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iManufactureDay (*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iManufactureMonth
(*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
iManufactureYear (*ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 147
incl_srcpt0 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params*
attribute), 114
incl_srcpt1 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params*
attribute), 115
iNetworkID (*ics.structures.tag_options_find_neo_ex.tag_options_find_neo_ex*
attribute), 158
iNetworkID (*ics.structures.tag_options_open_neo_ex.tag_options_open_neo_ex*
attribute), 158
mirr (*ics.structures.s_pluto_mac_config.s.s_pluto_mac_config_s*
attribute), 158

<i>attribute)</i> , 117	
ing_port (<i>ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry</i>), 118	163
ingress (<i>ics.structures.s_pluto_mac_config_s.s_pluto_mac_config</i>), 117	163
init_step_count (<i>ics.structures.iso9141_keyword2000_setting</i>), 87	163
init_steps (<i>ics.structures.iso9141_keyword2000_setting</i>), 87	163
innerFrameDelay25us (<i>ics.structures.can_settings.can_settings</i>)	ISO15765_2_NETWORK_HSCAN6 (in module <i>ics.ics</i>), 163
<i>attribute)</i> , 73	ISO15765_2_NETWORK_HSCAN7 (in module <i>ics.ics</i>),
intcydur (<i>ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params</i>)	ISO15765_2_NETWORK_MSCAN (in module <i>ics.ics</i>), 112
<i>attribute)</i> , 112	ISO15765_2_NETWORK_SWCAN (in module <i>ics.ics</i>),
inttosynch (<i>ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params</i>)	ISO15765_2_NETWORK_SWCAN2 (in module <i>ics.ics</i>), 112
<i>attribute)</i> , 112	ISO15765_2_NETWORK_SWCAN (in module <i>ics.ics</i>), 112
invert_rx (<i>ics.structures uart_settings.uart_settings</i>)	163
<i>attribute)</i> , 159	iso15765_disable_networks () (in module <i>ics.ics</i>), 46
invert_tx (<i>ics.structures uart_settings.uart_settings</i>)	ISO15765_DisableNetworks () (in module
<i>attribute)</i> , 159	iso15765_enable_networks () (in module
io_interval_ms (<i>ics.structures rad_reporting_settings.rad_reporting_settings</i>)	iso15765_EnableNetworks () (in module <i>ics.ics</i>), 90
<i>attribute)</i> , 90	iso15765_receive_message () (in module
ip_addr (<i>ics.structures ethernet10_g_settings.ethernet10_g_settings</i>), 46	ipAddress (<i>ics.structures rad_moon_duo_converter_settings.rad_moon_duo_converter_settings</i>)
<i>attribute)</i> , 76	ISO15765_ReceiveMessage () (in module <i>ics.ics</i>), 90
ip_addr (<i>ics.structures ethernet_settings2.ethernet_settings2</i>)	ipcframesy (<i>ics.structures s_pluto_clock_sync_params.s.s_pluto_clock_sync_params</i>)
<i>attribute)</i> , 77	ISO15765_separation_time_offset
ipGateway (<i>ics.structures rad_moon_duo_converter_settings.rad_moon_duo_converter_settings.s_cyan_settings</i>)	ipGateway (<i>ics.structures rad_moon_duo_converter_settings.rad_moon_duo_converter_settings.s_cyan_settings</i>)
<i>attribute)</i> , 90	ISO15765_separation_time_offset
iPhySiliconRev (<i>ics.structures st_api_firmware_info.st_api_firmware_info</i>)	ipMask (<i>ics.structures rad_moon_duo_converter_settings.rad_moon_duo_converter_settings</i>)
<i>attribute)</i> , 147	ISO15765_separation_time_offset
ipMask (<i>ics.structures rad_moon_duo_converter_settings.rad_moon_duo_converter_settings</i>)	isBRSEnabled (<i>ics.structures iso15765_2015_tx_message.iso15765_2015_tx_message.message_settings.s_fire_settings</i>)
<i>attribute)</i> , 90	ISO15765_separation_time_offset
isBRSEnabled (<i>ics.structures iso15765_2015_tx_message.iso15765_2015_tx_message.message_settings.s_fire_settings</i>)	iscanFD (<i>ics.structures iso15765_2015_tx_message.iso15765_2015_tx_message.message_settings.s_fire_vnet_settings</i>)
<i>attribute)</i> , 86	ISO15765_separation_time_offset
isBRSEnabled (<i>ics.structures st_cm_iso157652_rx_message.st_cm_iso157652_rx_message</i>)	iscanFD (<i>ics.structures st_cm_iso157652_rx_message.st_cm_iso157652_rx_message</i>)
<i>attribute)</i> , 150	ISO15765_separation_time_offset
isBRSEnabled (<i>ics.structures st_cm_iso157652_tx_message.st_cm_iso157652_tx_message</i>)	iso15765_2015_tx_message (<i>class</i> in <i>ics.structures iso15765_2015_tx_message</i>),
<i>attribute)</i> , 151	ISO15765_separation_time_offset
iscanFD (<i>ics.structures iso15765_2015_tx_message.iso15765_2015_tx_message.message_settings.s_fire_vnet_settings</i>)	iso15765_separation_time_offset
<i>attribute)</i> , 87	ISO15765_separation_time_offset
iscanFD (<i>ics.structures st_cm_iso157652_rx_message.st_cm_iso157652_rx_message</i>)	iso15765_separation_time_offset
<i>attribute)</i> , 150	(<i>ics.structures s_neo_ecu12_settings.s_neo_ecu12_settings</i>)
iscanFD (<i>ics.structures st_cm_iso157652_tx_message.st_cm_iso157652_tx_message</i>)	iso15765_separation_time_offset
<i>attribute)</i> , 151	ISO15765_separation_time_offset
iso15765_2015_tx_message (<i>class</i> in <i>ics.structures iso15765_2015_tx_message</i>),	iso15765_separation_time_offset
<i>attribute)</i> , 86	ISO15765_separation_time_offset
ISO15765_2_NETWORK_HSCAN (in module <i>ics.ics</i>),	(<i>ics.structures s_vivid_can_settings.s_vivid_can_settings</i>)

```

    attribute), 122
iso15765_separation_time_offset      attribute), 156
(ics.structures.scan_hub_settings.scan_hub_settings iso15765_transmit_message() (in module
attribute), 123                      ics.ics), 47
                                         ISO15765_TransmitMessage() (in module
                                         ics.ics), 23
iso15765_separation_time_offset      ISO9141_KEYWORD2000_INIT_STEP_SIZE (in
(ics.structures.secu_avb_settings.secu_avb_settings module ics.ics), 163
attribute), 123
                                         iso9141_keyword2000_init_step (class in
                                         ics.structures.iso9141_keyword2000_init_step),
                                         87
iso15765_separation_time_offset      iso9141_keyword2000_settings (class in
(ics.structures.secu_settings.secu_settings  ics.structures.iso9141_keyword2000_settings),
attribute), 124                         87
                                         ISO9141_KEYWORD2000_SETTINGS_SIZE (in
                                         module ics.ics), 163
iso15765_separation_time_offset      iso9141_kwp_enable_reserved
(ics.structures.sievb_settings.sievb_settings (ics.structures.s_fire_settings.s_fire_settings
attribute), 126                      attribute), 101
                                         iso9141_kwp_enable_reserved
                                         (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
                                         attribute), 103
                                         iso9141_kwp_enable_reserved
                                         (ics.structures.srad_jupiter_settings.srad_jupiter_settings
                                         attribute), 140
                                         iso9141_kwp_enable_reserved
                                         (ics.structures.srad_pluto_settings.srad_pluto_settings
                                         attribute), 143
                                         iso9141_kwp_enable_reserved
                                         (ics.structures.svcancrf_settings.svcancrf_settings
                                         attribute), 156
                                         iso9141_kwp_settings
iso15765_separation_time_offset      (ics.structures.s_fire_settings.s_fire_settings
(ics.structures.srad_gigalog_settings.srad_gigalog_settings attribute), 101
attribute), 130
                                         iso9141_kwp_settings
                                         (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
                                         attribute), 103
                                         iso9141_kwp_settings
                                         (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
                                         attribute), 108
                                         iso9141_kwp_settings
                                         (ics.structures.s_pendant_settings.s_pendant_settings
                                         attribute), 109
                                         iso9141_kwp_settings
                                         (ics.structures.svcanc3_settings.svcanc3_settings
                                         attribute), 152
                                         iso9141_kwp_settings
                                         (ics.structures.secu_settings.secu_settings
                                         attribute), 124
                                         iso9141_kwp_settings
                                         (ics.structures.sievb_settings.sievb_settings
                                         attribute), 127
                                         iso9141_kwp_settings
                                         (ics.structures.srad_jupiter_settings.srad_jupiter_settings
                                         attribute), 140
                                         iso9141_kwp_settings
                                         (ics.structures.srad_pluto_settings.srad_pluto_settings
                                         attribute), 143
                                         iso9141_kwp_settings
                                         (ics.structures.svcancrf_settings.svcancrf_settings
                                         attribute), 143

```

iso9141_kwp_settings (<i>ics.structures.svcn4_ind_settings.svcn4_ind_settings</i> <i>attribute</i>), 154	iso9141_kwp_settings_2 (<i>ics.structures.svcnrf_settings.svcnrf_settings</i> <i>attribute</i>), 156
iso9141_kwp_settings (<i>ics.structures.svcnrf_settings.svcnrf_settings</i> <i>attribute</i>), 156	iso9141_kwp_settings_3 (<i>ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute</i>), 92
iso9141_kwp_settings_1 (<i>ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute</i>), 92	iso9141_kwp_settings_3 (<i>ics.structures.s_fire_settings.s_fire_settings</i> <i>attribute</i>), 101
iso9141_kwp_settings_1 (<i>ics.structures.s_fire3_settings.s_fire3_settings</i> <i>attribute</i>), 99	iso9141_kwp_settings_3 (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> <i>attribute</i>), 103
iso9141_kwp_settings_1 (<i>ics.structures.sobd2_pro_settings.sobd2_pro_settings</i> <i>attribute</i>), 129	iso9141_kwp_settings_4 (<i>ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute</i>), 92
iso9141_kwp_settings_1 (<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings</i> <i>attribute</i>), 133	iso9141_kwp_settings_4 (<i>ics.structures.s_fire_settings.s_fire_settings</i> <i>attribute</i>), 101
iso9141_kwp_settings_1 (<i>ics.structures.srad_gigalog_settings.srad_gigalog_settings</i> (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> <i>attribute</i>), 136	iso9141_kwp_settings_4 (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> <i>attribute</i>), 103
iso9141_kwp_settings_1 (<i>ics.structures.srad_gigastar_settings.srad_gigastar_setting</i> <i>attribute</i>), 138	iso_9141_kwp_enable_reserved (<i>ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute</i>), 92
iso9141_kwp_settings_1 (<i>ics.structures.srad_star2_settings.srad_star2_settings</i> <i>attribute</i>), 144	iso_9141_kwp_enable_reserved (<i>ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings</i> <i>attribute</i>), 108
iso9141_kwp_settings_1 (<i>ics.structures.svcn4_settings.svcn4_settings</i> <i>attribute</i>), 155	iso_9141_kwp_enable_reserved (<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings</i> <i>attribute</i>), 133
iso9141_kwp_settings_2 (<i>ics.structures.s_cyan_settings.s_cyan_settings</i> <i>attribute</i>), 92	iso_9141_kwp_enable_reserved (<i>ics.structures.srad_gigalog_settings.srad_gigalog_settings</i> <i>attribute</i>), 136
iso9141_kwp_settings_2 (<i>ics.structures.s_fire3_settings.s_fire3_settings</i> <i>attribute</i>), 99	iso_9141_kwp_enable_reserved (<i>ics.structures.srad_gigastar_settings.srad_gigastar_settings</i> <i>attribute</i>), 139
iso9141_kwp_settings_2 (<i>ics.structures.s_fire_settings.s_fire_settings</i> <i>attribute</i>), 101	iso_9141_kwp_enable_reserved (<i>ics.structures.srad_star2_settings.srad_star2_settings</i> <i>attribute</i>), 144
iso9141_kwp_settings_2 (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> <i>attribute</i>), 103	iso_9141_kwp_enable_reserved (<i>ics.structures.svcn4_settings.svcn4_settings</i> <i>attribute</i>), 155
iso9141_kwp_settings_2 (<i>ics.structures.s_pendant_settings.s_pendant_settings</i> <i>attribute</i>), 109	iso_msg_termination (<i>ics.structures.s_fire_settings.s_fire_settings</i> <i>attribute</i>), 101
iso9141_kwp_settings_2 (<i>ics.structures.secu_settings.secu_settings</i> <i>attribute</i>), 124	iso_msg_termination (<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> <i>attribute</i>), 103
iso9141_kwp_settings_2 (<i>ics.structures.sievb_settings.sievb_settings</i> <i>attribute</i>), 127	iso_msg_termination (<i>ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings</i> <i>attribute</i>), 108
iso9141_kwp_settings_2 (<i>ics.structures.sobd2_pro_settings.sobd2_pro_settings</i> <i>attribute</i>), 129	iso_msg_termination (<i>ics.structures.s_pendant_settings.s_pendant_settings</i> <i>attribute</i>), 109

iso_msg_termination
 (*ics.structures.secu_settings.secu_settings*
 attribute), 124

iso_msg_termination
 (*ics.structures.sievb_settings.sievb_settings*
 attribute), 127

iso_msg_termination
 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings*
 attribute), 140

iso_msg_termination
 (*ics.structures.srad_pluto_settings.srad_pluto_settings*
 attribute), 143

iso_msg_termination
 (*ics.structures.svcn4_ind_settings.svcn4_ind_settings*
 attribute), 154

iso_msg_termination
 (*ics.structures.svcnrf_settings.svcnrf_settings*
 attribute), 156

iso_msg_termination_1
 (*ics.structures.s_cyan_settings.s_cyan_settings*
 attribute), 93

iso_msg_termination_1
 (*ics.structures.s_fire3_settings.s_fire3_settings*
 attribute), 99

iso_msg_termination_1
 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings*
 attribute), 129

iso_msg_termination_1
 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*
 attribute), 133

iso_msg_termination_1
 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*
 attribute), 136

iso_msg_termination_1
 (*ics.structures.srad_gigastar_settings.srad_gigastar_setting*
 attribute), 139

iso_msg_termination_1
 (*ics.structures.srad_star2_settings.srad_star2_settings*
 attribute), 144

iso_msg_termination_1
 (*ics.structures.svcn4_settings.svcn4_settings*
 attribute), 155

iso_msg_termination_2
 (*ics.structures.s_cyan_settings.s_cyan_settings*
 attribute), 93

iso_msg_termination_2
 (*ics.structures.s_fire3_settings.s_fire3_settings*
 attribute), 99

iso_msg_termination_2
 (*ics.structures.s_fire_settings.s_fire_settings*
 attribute), 101

iso_msg_termination_2
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
 attribute), 103

iso_msg_termination_2
 (*ics.structures.s_pendant_settings.s_pendant_settings*
 attribute), 109

iso_msg_termination_2
 (*ics.structures.secu_settings.secu_settings*
 attribute), 124

iso_msg_termination_2
 (*ics.structures.sievb_settings.sievb_settings*
 attribute), 127

iso_msg_termination_2
 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings*
 attribute), 129

iso_msg_termination_2
 (*ics.structures.svcnrf_settings.svcnrf_settings*
 attribute), 156

iso_msg_termination_3
 (*ics.structures.s_cyan_settings.s_cyan_settings*
 attribute), 93

iso_msg_termination_3
 (*ics.structures.s_fire_settings.s_fire_settings*
 attribute), 101

iso_msg_termination_3
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
 attribute), 103

iso_msg_termination_4
 (*ics.structures.s_cyan_settings.s_cyan_settings*
 attribute), 93

iso_msg_termination_4
 (*ics.structures.s_fire_settings.s_fire_settings*
 attribute), 101

iso_msg_termination_4
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
 attribute), 104

iso_parity(*ics.structures.s_fire_settings.s_fire_settings*
 attribute), 101

iso_parity(*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
 attribute), 104

iso_parity(*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*
 attribute), 108

iso_parity(*ics.structures.s_pendant_settings.s_pendant_settings*
 attribute), 109

iso_parity(*ics.structures.secu_settings.secu_settings*
 attribute), 124

iso_parity(*ics.structures.sievb_settings.sievb_settings*
 attribute), 127

iso_parity(*ics.structures.srad_jupiter_settings.srad_jupiter_settings*
 attribute), 140

iso_parity(*ics.structures.srad_pluto_settings.srad_pluto_settings*
 attribute), 143

iso_parity(*ics.structures.svcn4_ind_settings.svcn4_ind_settings*
 attribute), 154

iso_parity(*ics.structures.svcnrf_settings.svcnrf_settings*
 attribute), 156

iso_parity_1(*ics.structures.s_cyan_settings.s_cyan_settings*

attribute), 93
iso_parity_1 (ics.structures.s_fire3_settings.s_fire3_settings *iso_tester_pullup_enable*
attribute), 99 *(ics.structures.srad_jupiter_settings.srad_jupiter_settings*
attribute), 141
iso_parity_1 (ics.structures.sobd2_pro_settings.sobd2_pro_settings *iso_tester_pullup_enable*
attribute), 129 *(ics.structures.srad_pluto_settings.srad_pluto_settings*
attribute), 143 *iso_tester_pullup_enable*
iso_parity_1 (ics.structures.srad_gigalog_settings.srad_gigalog_settings *iso_parity_1 (ics.structures.svcancrf_settings.svcancrf_settings*
attribute), 136 *attribute), 157*
iso_parity_1 (ics.structures.srad_gigastar_settings.srad_gigastar_settings *iType (ics.structures.st_api_firmware_info.st_api_firmware_info*
attribute), 139 *attribute), 18*
iso_parity_1 (ics.structures.srad_star2_settings.srad_star2_settings *iso_parity_1 (ics.structures.srad_star2_settings.srad_star2_settings*
attribute), 144 *attribute), 147*
iso_parity_1 (ics.structures.svcanc4_settings.svcanc4_settings *j1708_settings (class* *in*
attribute), 155 *ics.structures.j1708_settings), 88*
iso_parity_2 (ics.structures.s_cyan_settings.s_cyan_settings *J1708_SETTINGS_SIZE (in module ics.ics), 163*
attribute), 93
iso_parity_2 (ics.structures.s_fire3_settings.s_fire3_settings *j2534_adapter_information (class* *in*
attribute), 99 *ics.structures.j2534_adapter_information), 88*
iso_parity_2 (ics.structures.s_fire_settings.s_fire_settings *jitter (ics.structures.s_pluto_vl_policing_entry_s.s_pluto_vl_policing_e*
attribute), 101
iso_parity_2 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings *jpnic_ma_j (ics.structures.st_chip_versions.st_chip_versions*
attribute), 104
iso_parity_2 (ics.structures.s_pendant_settings.s_pendant_settings *jpnic_min (ics.structures.st_chip_versions.st_chip_versions*
attribute), 109
iso_parity_2 (ics.structures.secu_settings.secu_settings *attribute), 148*
attribute), 124
iso_parity_2 (ics.structures.sievb_settings.sievb_settings *jupiter (ics.structures.global_settings.global_settings*
attribute), 127
iso_parity_2 (ics.structures.sobd2_pro_settings.sobd2_pro_settings *jupiter (ics.structures.s_device_settings.s_device_settings*
attribute), 129
iso_parity_2 (ics.structures.svcancrf_settings.svcancrf_settings *jupiter_versions (ics.structures.st_chip_versions.st_chip_versions*
attribute), 148
iso_parity_2 (ics.structures.s_fire_settings.s_fire_settings *jupiterStatus (ics.structures.ics_device_status.ics_device_status*
attribute), 157
iso_parity_3 (ics.structures.s_cyan_settings.s_cyan_settings *k (ics.structures.iso9141_keyword2000_init_step.iso9141_keyword2000_in*
attribute), 93
iso_parity_3 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings *attribute), 87*
attribute), 104
iso_parity_4 (ics.structures.s_cyan_settings.s_cyan_settings *l (ics.structures.iso9141_keyword2000_init_step.iso9141_keyword2000_in*
attribute), 93
iso_parity_4 (ics.structures.s_fire_settings.s_fire_settings *attribute), 87*
attribute), 101
iso_parity_4 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings *12_addressLookupEntries*
attribute), 104
iso_tester_pullup_enable
(ics.structures.s_fire_settings.s_fire_settings *(ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings*
attribute), 101 *attribute), 118*
iso_tester_pullup_enable
(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings *12_addressLookupParams*
attribute), 104 *(ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings*
attribute), 119
iso_tester_pullup_enable
(ics.structures.sievb_settings.sievb_settings *12_ForwardingEntries*
attribute), 127 *(ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings*
attribute), 118
iso_tester_pullup_enable
(ics.structures.sievb_settings.sievb_settings *12_forwardingParams*
attribute), 127 *(ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings*
attribute), 119

```
12_policing (ics.structures.s_pluto_switch_settings.s.s_pluto_switchics_structures.s_fire_settings.s_fire_settings
attribute), 119                                         attribute), 101
learnedEntry (ics.structures.s_pluto_l2_address_lookup_entryics_structures.s_pluto_l2_address_and_to_leapingentryfire_vnet_settings
attribute), 115                                         attribute), 104
led_mode (ics.structures.ethernet_settings.ethernet_settingics_structures.s_pendant_settings.s_pendant_settings
attribute), 77                                         attribute), 110
len (ics.structures.global_settings.global_settings at- lin2 (ics.structures.s_red_settings.s_red_settings
tribute), 78                                         attribute), 121
len (ics.structures.s_extended_data_flash_header.s_extended_data_flash_headerics_structures.s_ecu_settings.s_ecu_settings
attribute), 97                                         attribute), 124
length (ics.structures.s_ext_sub_cmd_hdr.s_ext_sub_cmdics_structures.sievb_settings.sievb_settings
attribute), 97                                         attribute), 127
lin1 (ics.structures.s_cyan_settings.s_cyan_settings at- lin2 (ics.structures.sobd2_pro_settings.sobd2_pro_settings
tribute), 93                                         attribute), 129
lin1 (ics.structures.s_fire3_settings.s_fire3_settings at- lin2 (ics.structures.svcancrf_settings.svcancrf_settings
tribute), 99                                         attribute), 157
lin1 (ics.structures.s_fire_settings.s_fire_settings lin3 (ics.structures.s_cyan_settings.s_cyan_settings at-
attribute), 101                                         attribute), 93
lin1 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settingics_structures.s_fire_settings.s_fire_settings
attribute), 104                                         attribute), 101
lin1 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settingsics_structures.s_fire_vnet_settings.s_fire_vnet_settings
attribute), 108                                         attribute), 104
lin1 (ics.structures.s_pendant_settings.s_pendant_settingslin4 (ics.structures.s_cyan_settings.s_cyan_settings at-
attribute), 109                                         attribute), 93
lin1 (ics.structures.s_red_settings.s_red_settings lin4 (ics.structures.s_fire_settings.s_fire_settings
attribute), 121                                         attribute), 101
lin1 (ics.structures.secu_settings.secu_settings at- lin4 (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
tribute), 124                                         attribute), 104
lin1 (ics.structures.sievb_settings.sievb_settings at- lin5 (ics.structures.s_cyan_settings.s_cyan_settings at-
tribute), 127                                         attribute), 93
lin1 (ics.structures.sobd2_pro_settings.sobd2_pro_settingics_structures.s_fire_vnet_settings.s_fire_vnet_settings
attribute), 129                                         attribute), 104
lin1 (ics.structures.srad_galaxy_settings.srad_galaxy_settingics_structures.s_cyan_settings.s_cyan_settings
attribute), 133                                         attribute), 93
lin1 (ics.structures.srad_gigalog_settings.srad_gigalog_settingsclass in ics.structures.lin_settings, 88
attribute), 136                                         LIN_SETTINGS_SIZE (in module ics.ics), 163
lin1 (ics.structures.srad_gigastar_settings.srad_gigastar_settingics_structures.op_eth_settings.op_eth_settings
attribute), 139                                         attribute), 89
lin1 (ics.structures.srad_jupiter_settings.srad_jupiter_settingics_structures.ethernet10g_settings.ethernet10g_settings
attribute), 141                                         attribute), 76
lin1 (ics.structures.srad_pluto_settings.srad_pluto_settingics_structures.ethernet_settings.ethernet_settings
attribute), 143                                         attribute), 77
lin1 (ics.structures.srad_star2_settings.srad_star2_settingics_structures.ethernet_settings2.ethernet_settings2
attribute), 145                                         attribute), 77
lin1 (ics.structures.svcanc4_ind_settings.svcanc4_ind_settingics_structures.ethernet_network_status_t.ethernet_ne
attribute), 154                                         linkFullDuplex (ics.structures.ethernet_network_status_t.ethernet_ne
attribute), 76
lin1 (ics.structures.svcanc4_settings.svcanc4_settings at- linkMode (ics.structures.ethernet_network_status_t.ethernet_network_st
tribute), 155                                         attribute), 76
lin1 (ics.structures.svcancrf_settings.svcancrf_settings linkMode0 (ics.structures.rad_moon_duo_converter_settings.rad_moon_
attribute), 157                                         attribute), 90
lin2 (ics.structures.s_cyan_settings.s_cyan_settings at- linkMode1 (ics.structures.rad_moon_duo_converter_settings.rad_moon_
tribute), 93                                         attribute), 90
lin2 (ics.structures.s_fire3_settings.s_fire3_settings at- linkSpeed (ics.structures.ethernet_network_status_t.ethernet_network_s
tribute), 99                                         attribute), 76
```

linkStatus (*ics.structures.ethernet_network_status_t.ethernet_network_status_structures.s_pluto_general_params.s.s_pluto_general_attribute*), 76

LISTEN_ALL (*in module ics.ics*), 163

LISTEN_ONLY (*in module ics.ics*), 163

listentmout (*ics.structures.s_pluto_clock_sync_params.mac_pluto_clock_sync_params.s_pluto_clock_sync_params.op_eth_settings.op_eth_settings_attribute*), 112

load_default_settings () (*in module ics.ics*), 47

LoadDefaultSettings () (*in module ics.ics*), 23

logger (*ics.structures.srad_galaxy_settings.srad_galaxy_settings_attribute*), 89

logger (*ics.structures.srad_gigalog_settings.srad_gigalog_settings_attribute*), 115

logger (*ics.structures.srad_gigastar_settings.srad_gigastar_setting_attribute*), 119

logger_settings (class *in ics.structures.logger_settings*), 88

LOGGER_SETTINGS_SIZE (*in module ics.ics*), 163

LOOPBACK (*in module ics.ics*), 163

lpic_maj (*ics.structures.st_chip_versions.st_chip_version_attributes*), 148

lpic_min (*ics.structures.st_chip_versions.st_chip_version_attributes*), 148

lsftcan (*ics.structures.s_fire_settings.s_fire_settings_attributes*), 101

lsftcan (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings_attributes*), 104

lsftcan (*ics.structures.s_pendant_settings.s_pendant_settings_attributes*), 110

lsftcan (*ics.structures.secu_settings.secu_settings_attributes*), 124

lsftcan1 (*ics.structures.s_cyan_settings.s_cyan_settings_attributes*), 93

lsftcan1 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_attributes*), 108

lsftcan1 (*ics.structures.s_vivid_can_settings.s_vivid_can_settings_attributes*), 122

lsftcan2 (*ics.structures.s_cyan_settings.s_cyan_settings_attributes*), 93

lsftcan2 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_attributes*), 108

lsftcan2 (*ics.structures.s_pendant_settings.s_pendant_settings_attributes*), 110

lsftcan2 (*ics.structures.secu_settings.secu_settings_attributes*), 124

M

mac_addr1 (*ics.structures.op_eth_settings.op_eth_setting_attributes*), 89

mac_addr2 (*ics.structures.op_eth_settings.op_eth_setting_attributes*), 89

mac_flt0 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params_attributes*), 115

mac_flt1 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params_attributes*), 115

mac_fltres1 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params_attributes*), 115

mac_spoofing_isDstOrSrc (*ics.structures.op_eth_settings.op_eth_settings_attributes*), 89

macConfig (*ics.structures.s_pluto_switch_settings.s.s_pluto_switch_settings_attributes*), 159

MAIN_VNET (*in module ics.ics*), 163

MasterEnable (*ics.structures.timesync_icshardware_settings.timesync_icshardware_settings_attributes*), 159

MasterNetwork (*ics.structures.timesync_icshardware_settings.timesync_icshardware_settings_attributes*), 159

MasterResistor (*ics.structures.lin_settings.lin_settings_attributes*), 88

max_dynp (*ics.structures.s_pluto_l2_forwarding_params.s.s_pluto_l2_forwarding_params_attributes*), 116

MAX_NUMBYTES_PHYSETTINGS (*in module ics.ics*), 163

MAX_PHY_REG_PKT_ENTRIES (*in module ics.ics*), 163

MAX_PHY_SETTINGS_STRUCT (*in module ics.ics*), 163

MAX_VL_FORWARDING_ENTRIES (*in module ics.ics*), 163

MAX_VL_POLICING_ENTRIES (*in module ics.ics*), 163

MaxAllowedClients (*ics.ics.NeoDevice_attributes*), 18

maxlen (*ics.structures.s_pluto_vl_policing_entry.s.s_pluto_vl_policing_entry_attributes*), 120

maxtranspclk (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_attributes*), 112

mchip_major (*ics.structures.st_chip_versions.st_chip_versions_attributes*), 148

mchip_minor (*ics.structures.st_chip_versions.st_chip_versions_attributes*), 148

MessageID (*ics.ics.SpyMessage_attributes*), 18

MessagePieceID (*ics.ics.SpyMessageJ1850_attributes*), 19

MessagePieceID (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_attributes*), 19

```
        attribute), 81
MessagePieceID (ics.structures.ics_spy_message_long.ics_spy_message_long.ics_spy_message_long.message_attributes.sievb_settings.sievb_settings
               attribute), 83
MessagePieceID (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb.message_attributes.s_cyan_settings.s_cyan_settings
               attribute), 85
mirr_port (ics.structures.s_pluto_general_params.s.s_pluto_general_params.s_attributes.s_attributes
           attribute), 115
mirr_ptacu (ics.structures.s_pluto_general_params.s.s_pluto_general_params.s_attributes.s_attributes
           attribute), 115
misc_io_analog_enable
    (ics.structures.s_cyan_settings.s_cyan_settings
     attribute), 93
misc_io_analog_enable
    (ics.structures.s_fire3_settings.s_fire3_settings
     attribute), 99
misc_io_analog_enable
    (ics.structures.s_fire_settings.s_fire_settings
     attribute), 102
misc_io_analog_enable
    (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
     attribute), 104
misc_io_analog_enable
    (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
     attribute), 108
misc_io_analog_enable
    (ics.structures.s_pendant_settings.s_pendant_settings
     attribute), 110
misc_io_analog_enable
    (ics.structures.secu_settings.secu_settings
     attribute), 125
misc_io_analog_enable
    (ics.structures.sievb_settings.sievb_settings
     attribute), 127
misc_io_analog_enable
    (ics.structures.sobd2_pro_settings.sobd2_pro_settings
     attribute), 129
misc_io_analog_enable
    (ics.structures.sobd2_sim_settings.sobd2_sim_settings
     attribute), 130
misc_io_analog_enable
    (ics.structures.srad_galaxy_settings.srad_galaxy_settings
     attribute), 133
misc_io_analog_enable
    (ics.structures.srad_jupiter_settings.srad_jupiter_settings
     attribute), 141
misc_io_analog_enable
    (ics.structures.srad_pluto_settings.srad_pluto_settings
     attribute), 143
misc_io_analog_enable
    (ics.structures.srad_star2_settings.srad_star2_settings
     attribute), 145
misc_io_analog_enable
    (ics.structures.svcancrf_settings.svcancrf_settings
     attribute), 157
                    misc_io_analog_enable_2
                        (ics.structures.s_fire_settings.s_fire_settings
                         attribute), 127
                    misc_io_initial_ddr
                        (ics.structures.s_cyan_settings.s_cyan_settings
                         attribute), 93
                    misc_io_initial_ddr
                        (ics.structures.s_fire3_settings.s_fire3_settings
                         attribute), 99
                    misc_io_initial_ddr
                        (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
                         attribute), 104
                    misc_io_initial_ddr
                        (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
                         attribute), 108
                    misc_io_initial_ddr
                        (ics.structures.s_pendant_settings.s_pendant_settings
                         attribute), 110
                    misc_io_initial_ddr
                        (ics.structures.secu_settings.secu_settings
                         attribute), 125
                    misc_io_initial_ddr
                        (ics.structures.sievb_settings.sievb_settings
                         attribute), 127
                    misc_io_initial_ddr
                        (ics.structures.sobd2_sim_settings.sobd2_sim_settings
                         attribute), 130
                    misc_io_initial_ddr
                        (ics.structures.srad_galaxy_settings.srad_galaxy_settings
                         attribute), 133
                    misc_io_initial_ddr
                        (ics.structures.srad_star2_settings.srad_star2_settings
                         attribute), 145
                    misc_io_initial_ddr
                        (ics.structures.svcanc3_settings.svcanc3_settings
                         attribute), 152
                    misc_io_initial_ddr
                        (ics.structures.svcancrf_settings.svcancrf_settings
                         attribute), 157
                    misc_io_initial_latch
                        (ics.structures.s_cyan_settings.s_cyan_settings
                         attribute), 93
                    misc_io_initial_latch
                        (ics.structures.s_fire3_settings.s_fire3_settings
                         attribute), 99
                    misc_io_initial_latch
                        (ics.structures.s_fire_settings.s_fire_settings
                         attribute), 102
                    misc_io_initial_latch
                        (ics.structures.s_fire_vnet_settings.s_fire_vnet_settings
                         attribute), 104
```

misc_io_initial_latch	misc_io_on_report_events
(<i>ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings</i> .attribute), 108	(<i>ics.structures.sobd2_sim_settings.sobd2_sim_settings</i> .attribute), 130
misc_io_initial_latch	misc_io_on_report_events
(<i>ics.structures.s_pendant_settings.s_pendant_settings</i> .attribute), 110	(<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings</i> .attribute), 133
misc_io_initial_latch	misc_io_on_report_events
(<i>ics.structures.secu_settings.secu_settings</i> .attribute), 125	(<i>ics.structures.srad_star2_settings.srad_star2_settings</i> .attribute), 145
misc_io_initial_latch	misc_io_on_report_events
(<i>ics.structures.sievb_settings.sievb_settings</i> .attribute), 127	(<i>ics.structures.svcanc3_settings.svcanc3_settings</i> .attribute), 152
misc_io_initial_latch	misc_io_on_report_events
(<i>ics.structures.sobd2_sim_settings.sobd2_sim_settings</i> .attribute), 130	(<i>ics.structures.svcancrf_settings.svcancrf_settings</i> .attribute), 157
misc_io_initial_latch	misc_io_report_period
(<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings</i> .attribute), 133	(<i>ics.structures.s_cyan_settings.s_cyan_settings</i> .attribute), 93
misc_io_initial_latch	misc_io_report_period
(<i>ics.structures.srad_star2_settings.srad_star2_settings</i> .attribute), 145	(<i>ics.structures.s_fire3_settings.s_fire3_settings</i> .attribute), 99
misc_io_initial_latch	misc_io_report_period
(<i>ics.structures.svcanc3_settings.svcanc3_settings</i> .attribute), 152	(<i>ics.structures.s_fire_settings.s_fire_settings</i> .attribute), 102
misc_io_initial_latch	misc_io_report_period
(<i>ics.structures.svcancrf_settings.svcancrf_settings</i> .attribute), 157	(<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> .attribute), 104
misc_io_on_report_events	misc_io_report_period
(<i>ics.structures.s_cyan_settings.s_cyan_settings</i> .attribute), 93	(<i>ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings</i> .attribute), 108
misc_io_on_report_events	misc_io_report_period
(<i>ics.structures.s_fire3_settings.s_fire3_settings</i> .attribute), 99	(<i>ics.structures.s_pendant_settings.s_pendant_settings</i> .attribute), 110
misc_io_on_report_events	misc_io_report_period
(<i>ics.structures.s_fire_settings.s_fire_settings</i> .attribute), 102	(<i>ics.structures.secu_settings.secu_settings</i> .attribute), 125
misc_io_on_report_events	misc_io_report_period
(<i>ics.structures.s_fire_vnet_settings.s_fire_vnet_settings</i> .attribute), 104	(<i>ics.structures.sievb_settings.sievb_settings</i> .attribute), 128
misc_io_on_report_events	misc_io_report_period
(<i>ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings</i> .attribute), 106	(<i>ics.structures.sobd2_sim_settings.sobd2_sim_settings</i> .attribute), 130
misc_io_on_report_events	misc_io_report_period
(<i>ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings</i> .attribute), 108	(<i>ics.structures.srad_galaxy_settings.srad_galaxy_settings</i> .attribute), 133
misc_io_on_report_events	misc_io_report_period
(<i>ics.structures.s_pendant_settings.s_pendant_settings</i> .attribute), 110	(<i>ics.structures.srad_star2_settings.srad_star2_settings</i> .attribute), 145
misc_io_on_report_events	misc_io_report_period
(<i>ics.structures.secu_settings.secu_settings</i> .attribute), 125	(<i>ics.structures.svcanc3_settings.svcanc3_settings</i> .attribute), 152
misc_io_on_report_events	misc_io_report_period
(<i>ics.structures.sievb_settings.sievb_settings</i> .attribute), 128	(<i>ics.structures.svcancrf_settings.svcancrf_settings</i> .attribute), 157

MiscData (*ics.ics.SpyMessage attribute*), 18
MiscData (*ics.ics.SpyMessageJ1850 attribute*), 19
MiscData (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray attribute*), 81
MiscData (*ics.structures.ics_spy_message_long.ics_spy_message_long attribute*), 83
MiscData (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb attribute*), 85
MiscData (*ics.structures.spy_filter_long.spy_filter_long attribute*), 131
MiscDataMask (*ics.structures.spy_filter_long.spy_filter_long attribute*), 131
Mode (*ics.structures.can_settings.can_settings attribute*), 73
Mode (*ics.structures.lin_settings.lin_settings attribute*), 88
mode (*ics.structures.s_pluto_custom_params.s.s_pluto_custom_params attribute*), 114
mode (*ics.structures.serdescam_settings.serdescam_setting attribute*), 126
mode (*ics.structures.serdespoc_settings.serdespoc_settings attribute*), 126
Mode (*ics.structures.swcan_settings.swcan_settings attribute*), 157
mpic_maj (*ics.structures.st_chip_versions.st_chip_version attribute*), 148
mpic_min (*ics.structures.st_chip_versions.st_chip_version attribute*), 148

N
Name (*ics.ics.NeoDevice attribute*), 18
NEO_CFG_MPIC_HS_CAN_CNF1 (*in module ics.ics*), 165
NEO_CFG_MPIC_HS_CAN_CNF2 (*in module ics.ics*), 165
NEO_CFG_MPIC_HS_CAN_CNF3 (*in module ics.ics*), 165
NEO_CFG_MPIC_HS_CAN_MODE (*in module ics.ics*), 165
NEO_CFG_MPIC_LSFT_CAN_CNF1 (*in module ics.ics*), 165
NEO_CFG_MPIC_LSFT_CAN_CNF2 (*in module ics.ics*), 165
NEO_CFG_MPIC_LSFT_CAN_CNF3 (*in module ics.ics*), 166
NEO_CFG_MPIC_MS_CAN_CNF1 (*in module ics.ics*), 166
NEO_CFG_MPIC_MS_CAN_CNF2 (*in module ics.ics*), 166
NEO_CFG_MPIC_MS_CAN_CNF3 (*in module ics.ics*), 166
NEO_CFG_MPIC_SW_CAN_CNF1 (*in module ics.ics*), 166
NEO_CFG_MPIC_SW_CAN_CNF2 (*in module ics.ics*), 166
NEO_MESSAGE_MESSAGE_SW_CAN_CNF3 (*in module ics.ics*), 166
NEODEVICE_ANY_ION (*in module ics.ics*), 164
NEODEVICE_EVEV1 (*in module ics.ics*), 164
NEODEVICE_BLUE (*in module ics.ics*), 164
NEODEVICE_CMPROBE (*in module ics.ics*), 164
NEODEVICE_CT_OBD (*in module ics.ics*), 164
NEODEVICE_DONT_REUSE0 (*in module ics.ics*), 164
NEODEVICE_DONT_REUSE1 (*in module ics.ics*), 164
NEODEVICE_DONT_REUSE2 (*in module ics.ics*), 164
NEODEVICE_DONT_REUSE3 (*in module ics.ics*), 164
NEODEVICE_DW_VCAN (*in module ics.ics*), 164
NEODEVICE_ECU (*in module ics.ics*), 164
NEODEVICE_ECU22 (*in module ics.ics*), 164
NEODEVICE_ECU_AVB (*in module ics.ics*), 164
NEODEVICE_ECUCHIP_UART (*in module ics.ics*), 164
NEODEVICE_EEVB (*in module ics.ics*), 164
NEODEVICE_FIRE (*in module ics.ics*), 164
NEODEVICE_FIRE2 (*in module ics.ics*), 164
NEODEVICE_FIRE3 (*in module ics.ics*), 164
NEODEVICE_FLEX (*in module ics.ics*), 164
NEODEVICE_GIGASTAR (*in module ics.ics*), 164
NEODEVICE_IEVB (*in module ics.ics*), 164
NEODEVICE_ION (*in module ics.ics*), 164
NEODEVICE_NEONALOG (*in module ics.ics*), 164
NEODEVICE_NEOECU12 (*in module ics.ics*), 164
NEODEVICE_NEOECUCHIP (*in module ics.ics*), 164
NEODEVICE_OBD2_LCBADGE (*in module ics.ics*), 164
NEODEVICE_OBD2_PRO (*in module ics.ics*), 164
NEODEVICE_OBD2_SIM (*in module ics.ics*), 164
NEODEVICE_PENDANT (*in module ics.ics*), 164
NEODEVICE_PLASMA (*in module ics.ics*), 164
NEODEVICE_RAD_MOON_DUO (*in module ics.ics*), 165
NEODEVICE_RADGALAXY (*in module ics.ics*), 164
NEODEVICE_RADGIGALOG (*in module ics.ics*), 164
NEODEVICE_RADIO_CANHUB (*in module ics.ics*), 164
NEODEVICE_RADJUPITER (*in module ics.ics*), 164
NEODEVICE_RADMOON2 (*in module ics.ics*), 164
NEODEVICE_RADPLUTO (*in module ics.ics*), 164
NEODEVICE_RADSTAR (*in module ics.ics*), 165
NEODEVICE_RADSTAR2 (*in module ics.ics*), 165
NEODEVICE_RADSUPERMOON (*in module ics.ics*), 165
NEODEVICE_RED (*in module ics.ics*), 165
NEODEVICE_RED2 (*in module ics.ics*), 165
NEODEVICE_UNKNOWN (*in module ics.ics*), 165
NEODEVICE_VCAN3 (*in module ics.ics*), 165
NEODEVICE_VCAN41 (*in module ics.ics*), 165
NEODEVICE_VCAN42 (*in module ics.ics*), 165
NEODEVICE_VCAN42_EL (*in module ics.ics*), 165
NEODEVICE_VCAN44 (*in module ics.ics*), 165
NEODEVICE_VCAN4_IND (*in module ics.ics*), 165

NEODEVICE_VCANRF (*in module* `ics.ics`), 165
 NEODEVICE_VIVIDCAN (*in module* `ics.ics`), 165
`neoecu12` (*ics.structures.global_settings.global_settings* attribute), 78
`neoecu12` (*ics.structures.s_device_settings.s_device_setting* attribute), 95
`neoecu_avb` (*ics.structures.global_settings.global_setting* attribute), 78
`neoecu_avb` (*ics.structures.s_device_settings.s_device_setting* attribute), 95
`neoecu_avb_versions` (*ics.structures.st_chip_versions.st_chip_versions* attribute), 148
`neoMostGateway` (*ics.structures.s_fire_settings.s_fire_setting* attribute), 102
`neoMostGateway` (*ics.structures.s_fire_vnet_settings.s_fire_vnet_setting* attribute), 104
`neoobd2_sim` (*ics.structures.global_settings.global_setting* attribute), 78
`neoobd2_sim` (*ics.structures.s_device_settings.s_device_setting* attribute), 95
`NEOVI6_VCAN_TIMESTAMP_1` (*in module* `ics.ics`), 165
`NEOVI6_VCAN_TIMESTAMP_2` (*in module* `ics.ics`), 165
`NEOVI_3G_MAX_SETTINGS_SIZE` (*in module* `ics.ics`), 165
`NEOVI_COMMTYPE_FIRE_USB` (*in module* `ics.ics`), 165
`NEOVI_COMMTYPE_RS232` (*in module* `ics.ics`), 165
`NEOVI_COMMTYPE_TCPIP` (*in module* `ics.ics`), 165
`NEOVI_COMMTYPE_USB_BULK` (*in module* `ics.ics`), 165
`NEOVI_RED_TIMESTAMP_1_10NS` (*in module* `ics.ics`), 165
`NEOVI_RED_TIMESTAMP_1_25NS` (*in module* `ics.ics`), 165
`NEOVI_RED_TIMESTAMP_2_10NS` (*in module* `ics.ics`), 165
`NEOVI_RED_TIMESTAMP_2_25NS` (*in module* `ics.ics`), 165
`NEOVI_TIMESTAMP_1` (*in module* `ics.ics`), 165
`NEOVI_TIMESTAMP_2` (*in module* `ics.ics`), 165
`NEOVIPRO_VCAN_TIMESTAMP_1` (*in module* `ics.ics`), 165
`NEOVIPRO_VCAN_TIMESTAMP_2` (*in module* `ics.ics`), 165
`netId` (*ics.structures.s_neo_most_gateway_settings.s_neo* attribute), 109
`NETID_3G_APP_SIGNAL_STATUS` (*in module* `ics.ics`), 166
`NETID_3G_FB_STATUS` (*in module* `ics.ics`), 166
`NETID_3G_LOGGING_OVERFLOW` (*in module* `ics.ics`), 166
`NETID_3G_READ_DATALINK_CM_RX_MSG` (*in module* `ics.ics`), 166
`NETID_3G_READ_DATALINK_CM_TX_MSG` (*in module* `ics.ics`), 166
`NETID_3G_RESET_STATUS` (*in module* `ics.ics`), 166
`NETID_AUTOSAR` (*in module* `ics.ics`), 166
`NETID_AUX` (*in module* `ics.ics`), 166
`NETID_CGI` (*in module* `ics.ics`), 166
`NETID_DATA_TO_HOST` (*in module* `ics.ics`), 166
`NETID_DEVICE` (*in module* `ics.ics`), 166
`NETID_DEVICE_STATUS` (*in module* `ics.ics`), 166
`NETID_ETHERNET` (*in module* `ics.ics`), 166
`NETID_ETHERNET2` (*in module* `ics.ics`), 166
`NETID_FLEXRAY_DAQ` (*in module* `ics.ics`), 166
`NETID_FLEXRAY` (*in module* `ics.ics`), 166
`NETID_FLEXRAY1A` (*in module* `ics.ics`), 166
`NETID_FLEXRAY1B` (*in module* `ics.ics`), 166
`NETID_FLEXRAY2` (*in module* `ics.ics`), 166
`NETID_FLEXRAY2A` (*in module* `ics.ics`), 166
`NETID_FLEXRAY2B` (*in module* `ics.ics`), 166
`NETID_FORDSCP` (*in module* `ics.ics`), 166
`NETID_FORWARDED_MESSAGE` (*in module* `ics.ics`), 166
`NETID_GMFSA` (*in module* `ics.ics`), 166
`NETID_HSCAN` (*in module* `ics.ics`), 166
`NETID_HSCAN2` (*in module* `ics.ics`), 166
`NETID_HSCAN3` (*in module* `ics.ics`), 166
`NETID_HSCAN4` (*in module* `ics.ics`), 166
`NETID_HSCAN5` (*in module* `ics.ics`), 167
`NETID_HSCAN6` (*in module* `ics.ics`), 167
`NETID_HSCAN7` (*in module* `ics.ics`), 167
`NETID_HW_COM_LATENCY_TEST` (*in module* `ics.ics`), 167
`NETID_I2C1` (*in module* `ics.ics`), 167
`NETID_I2C2` (*in module* `ics.ics`), 167
`NETID_I2C3` (*in module* `ics.ics`), 167
`NETID_I2C4` (*in module* `ics.ics`), 167
`NETID_INVALID` (*in module* `ics.ics`), 167
`NETID_ISO` (*in module* `ics.ics`), 167
`NETID_ISO14230` (*in module* `ics.ics`), 167
`NETID_ISO2` (*in module* `ics.ics`), 167
`NETID_ISO3` (*in module* `ics.ics`), 167
`NETID_ISO4` (*in module* `ics.ics`), 167
`NETID_ISOPIC` (*in module* `ics.ics`), 167
`NETID_J1708` (*in module* `ics.ics`), 167
`NETID_GATEWAY_SETTING` (*in module* `ics.ics`), 167
`NETID_LIN` (*in module* `ics.ics`), 167
`NETID_LIN2` (*in module* `ics.ics`), 167
`NETID_LIN3` (*in module* `ics.ics`), 167
`NETID_LIN4` (*in module* `ics.ics`), 167
`NETID_LIN5` (*in module* `ics.ics`), 167
`NETID_LIN6` (*in module* `ics.ics`), 167

NETID_LSFTCAN (*in module ics.ics*), 167
NETID_LSFTCAN2 (*in module ics.ics*), 167
NETID_MAIN51 (*in module ics.ics*), 167
NETID_MAX (*in module ics.ics*), 167
NETID_MOST (*in module ics.ics*), 167
NETID_MOST150 (*in module ics.ics*), 167
NETID_MOST25 (*in module ics.ics*), 167
NETID_MOST50 (*in module ics.ics*), 167
NETID_MSCAN (*in module ics.ics*), 167
NETID_OP_ETHERNET1 (*in module ics.ics*), 167
NETID_OP_ETHERNET10 (*in module ics.ics*), 167
NETID_OP_ETHERNET11 (*in module ics.ics*), 167
NETID_OP_ETHERNET12 (*in module ics.ics*), 167
NETID_OP_ETHERNET2 (*in module ics.ics*), 168
NETID_OP_ETHERNET3 (*in module ics.ics*), 168
NETID_OP_ETHERNET4 (*in module ics.ics*), 168
NETID_OP_ETHERNET5 (*in module ics.ics*), 168
NETID_OP_ETHERNET6 (*in module ics.ics*), 168
NETID_OP_ETHERNET7 (*in module ics.ics*), 168
NETID_OP_ETHERNET8 (*in module ics.ics*), 168
NETID_OP_ETHERNET9 (*in module ics.ics*), 168
NETID_RED (*in module ics.ics*), 168
NETID_RED_APP_ERROR (*in module ics.ics*), 168
NETID_RED_VBAT (*in module ics.ics*), 168
NETID_RS232 (*in module ics.ics*), 168
NETID_SCI (*in module ics.ics*), 168
NETID_SPI1 (*in module ics.ics*), 168
NETID_SWCAN (*in module ics.ics*), 168
NETID_SWCAN2 (*in module ics.ics*), 168
NETID_TCP (*in module ics.ics*), 168
NETID_TEXTAPI_TO_HOST (*in module ics.ics*), 168
NETID_UART (*in module ics.ics*), 168
NETID_UART2 (*in module ics.ics*), 168
NETID_UART3 (*in module ics.ics*), 168
NETID_UART4 (*in module ics.ics*), 168
NETID_UDP (*in module ics.ics*), 168
netmask (*ics.structures.ethernet10_g_settings.ethernet10_g_settings* attribute), 76
netmask (*ics.structures.ethernet_settings2.ethernet_settings2* attribute), 77
network_enabled_on_boot
 (*ics.structures.s_cm_probe_settings.s_cm_probe_settings* attribute), 90
network_enabled_on_boot
 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 94
network_enabled_on_boot
 (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 99
network_enabled_on_boot
 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 102
network_enabled_on_boot
 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 104
network_enabled_on_boot
 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 106
network_enabled_on_boot
 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings* attribute), 108
network_enabled_on_boot
 (*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 110
network_enabled_on_boot
 (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings* attribute), 120
network_enabled_on_boot
 (*ics.structures.s_vivid_can_settings.s_vivid_can_settings* attribute), 122
network_enabled_on_boot
 (*ics.structures.scan_hub_settings.scan_hub_settings* attribute), 123
network_enabled_on_boot
 (*ics.structures.secu_avb_settings.secu_avb_settings* attribute), 123
network_enabled_on_boot
 (*ics.structures.secu_settings.secu_settings* attribute), 125
network_enabled_on_boot
 (*ics.structures.seevb_settings.seevb_settings* attribute), 126
network_enabled_on_boot
 (*ics.structures.sievb_settings.sievb_settings* attribute), 128
network_enabled_on_boot
 (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 129
network_enabled_on_boot
 (*ics.structures.sobd2_sim_settings.sobd2_sim_settings* attribute), 130
network_enabled_on_boot
 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134
network_enabled_on_boot
 (*ics.structures.srad_gigalog_settings.srad_gigalog_settings* attribute), 136
network_enabled_on_boot
 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 139
network_enabled_on_boot
 (*ics.structures.srad_jupiter_settings.srad_jupiter_settings* attribute), 141
network_enabled_on_boot
 (*ics.structures.srad_moon2_settings.srad_moon2_settings* attribute), 142
network_enabled_on_boot
 (*ics.structures.srad_pluto_settings.srad_pluto_settings* attribute), 144

attribute), 143

`network_enabled_on_boot` (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 145

`network_enabled_on_boot` (*ics.structures.srad_super_moon_settings.srad_super_moon_attributes*, 146)

`network_enabled_on_boot` (*ics.structures.svcn3_settings.svcn3_settings* attribute), 152

`network_enabled_on_boot` (*ics.structures.svcn412_settings.svcn412_settings* attribute), 153

`network_enabled_on_boot` (*ics.structures.svcn4_ind_settings.svcn4_ind_settings* attribute), 154

`network_enabled_on_boot` (*ics.structures.svcn4_settings.svcn4_settings* attribute), 155

`network_enabled_on_boot` (*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 157

`network_enables` (*ics.structures.s_cm_probe_settings.s_cm_probe_settings* attribute), 91

`network_enables` (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 94

`network_enables` (*ics.structures.s_fire3_settings.s_fire3_settings* attribute), 99

`network_enables` (*ics.structures.s_fire_settings.s_fire_settings* attribute), 102

`network_enables` (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings* attribute), 104

`network_enables` (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_attributes* attribute), 106

`network_enables` (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings* attribute), 108

`network_enables` (*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 110

`network_enables` (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings* attribute), 120

`network_enables` (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 122

`network_enables` (*ics.structures.s_vivid_can_settings.s_vivid_can_settings* attribute), 122

`network_enables` (*ics.structures.scan_hub_settings.scan_hub_settings* attribute), 123

`network_enables` (*ics.structures.secu_avb_settings.secu_avb_settings* attribute), 123

`network_enables` (*ics.structures.secu_settings.secu_settings* attribute), 125

`network_enables` (*ics.structures.seevb_settings.seevb_settings* attribute), 126

`network_enables` (*ics.structures.sievb_settings.sievb_settings* attribute), 128

network_enables (*ics.structures.sobd2_pro_settings.sobd2_pro_settings* attribute), 129

network_enables (*ics.structures.sobd2_sim_settings.sobd2_sim_settings* attribute), 130

network_enables (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134

network_enables (*ics.structures.srad_gigalog_settings.srad_gigalog_settings* attribute), 136

network_enables (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 139

network_enables (*ics.structures.srad_jupiter_settings.srad_jupiter_settings* attribute), 141

network_enables (*ics.structures.srad_moon2_settings.srad_moon2_settings* attribute), 142

network_enables (*ics.structures.srad_pluto_settings.srad_pluto_settings* attribute), 143

network_enables (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 145

network_enables (*ics.structures.srad_super_moon_settings.srad_super_moon_attributes*, 146)

network_enables (*ics.structures.svcn3_settings.svcn3_settings* attribute), 152

network_enables (*ics.structures.svcn412_settings.svcn412_settings* attribute), 153

network_enables (*ics.structures.svcn4_ind_settings.svcn4_ind_settings* attribute), 154

network_enables (*ics.structures.svcn4_settings.svcn4_settings* attribute), 155

network_enables (*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 157

network_enables (*ics.structures.s_cm_probe_settings.s_cm_probe_settings* attribute), 153

network_enables (*ics.structures.svcn412_settings.svcn412_settings* attribute), 153

network_enables (*ics.structures.svcn4_ind_settings.svcn4_ind_settings* attribute), 154

network_enables (*ics.structures.svcn4_settings.svcn4_settings* attribute), 155

network_enables (*ics.structures.svcnrf_settings.svcnrf_settings* attribute), 157

network_enables_2 (*ics.structures.s_cyan_settings.s_cyan_settings* attribute), 94

network_enables_2 (*ics.structures.s_fire_settings.s_fire_settings* attribute), 104

network_enables_2 (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings* attribute), 104

network_enables_2 (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings* attribute), 99

network_enables_2 (*ics.structures.s_pendant_settings.s_pendant_settings* attribute), 110

network_enables_2 (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings* attribute), 120

network_enables_2 (*ics.structures.s_text_api_settings.s_text_api_settings* attribute), 122

network_enables_2 (*ics.structures.s_vivid_can_settings.s_vivid_can_settings* attribute), 122

network_enables_2 (*ics.structures.scan_hub_settings.scan_hub_settings* attribute), 123

network_enables_2 (*ics.structures.secu_avb_settings.secu_avb_settings* attribute), 123

network_enables_2 (*ics.structures.secu_settings.secu_settings* attribute), 125

network_enables_2 (*ics.structures.seevb_settings.seevb_settings* attribute), 126

network_enables_2 (*ics.structures.sievb_settings.sievb_settings* attribute), 128

```
network_enables_2                                     network_enables_3
    (ics.structures.srad_galaxy_settings.srad_galaxy_settings
     attribute), 134                                     (ics.structures.srad_moon2_settings.srad_moon2_settings
                                                       attribute), 142
network_enables_2                                     network_enables_3
    (ics.structures.srad_gigalog_settings.srad_gigalog_settings
     attribute), 137                                     (ics.structures.srad_pluto_settings.srad_pluto_settings
                                                       attribute), 143
network_enables_2                                     network_enables_3
    (ics.structures.srad_gigastar_settings.srad_gigastar_setting
     attribute), 139                                     (ics.structures.srad_star2_settings.srad_star2_settings
                                                       attribute), 145
network_enables_2                                     network_enables_3
    (ics.structures.srad_jupiter_settings.srad_jupiter_settings
     attribute), 141                                     (ics.structures.srad_super_moon_settings.srad_super_moon_settings
                                                       attribute), 146
network_enables_2                                     network_enables_3
    (ics.structures.srad_moon2_settings.srad_moon2_settings
     attribute), 142                                     (ics.structures.svcn4_ind_settings.svcn4_ind_settings
                                                       attribute), 154
network_enables_2                                     network_enables_3
    (ics.structures.srad_pluto_settings.srad_pluto_settings
     attribute), 143                                     (ics.structures.svcn4_settings.svcn4_settings
                                                       attribute), 155
network_enables_2                                     network_enables_4
    (ics.structures.srad_star2_settings.srad_star2_settings
     attribute), 145                                     (ics.structures.srad_galaxy_settings.srad_galaxy_settings
                                                       attribute), 134
network_enables_2                                     network_enables_4
    (ics.structures.srad_super_moon_settings.srad_super_moon
     attribute), 146                                     (ics.structures.srad_gigalog_settings.srad_gigalog_settings
                                                       attribute), 137
network_enables_2                                     network_enables_4
    (ics.structures.svcn4_ind_settings.svcn4_ind_settings
     attribute), 154                                     (ics.structures.srad_gigastar_settings.srad_gigastar_settings
                                                       attribute), 139
network_enables_2                                     NetworkID (ics.ics.SpyMessage attribute), 18
    (ics.structures.svcn4_settings.svcn4_settings
     attribute), 155                                     NetworkID (ics.ics.SpyMessageJ1850 attribute), 19
network_enables_2                                     networkID (ics.structures.ethernet_network_status_t.ethernet_network_s
    (ics.structures.svcnrf_settings.svcnrf_settings
     attribute), 157                                     attribute), 76
network_enables_3                                     NetworkID (ics.structures.ics_spy_message_flex_ray.ics_spy_message_fle
    (ics.structures.s_cyan_settings.s_cyan_settings
     attribute), 94                                     attribute), 81
network_enables_3                                     NetworkID (ics.structures.ics_spy_message_long.ics_spy_message_long
    (ics.structures.s_fire3_settings.s_fire3_settings
     attribute), 99                                     attribute), 83
network_enables_3                                     NetworkID (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
    (ics.structures.s_fire3_settings.s_fire3_settings
     attribute), 99                                     attribute), 85
network_enables_3                                     NetworkID (ics.structures.spy_filter_long.spy_filter_long
    (ics.structures.s_flex_vnetz_settings.s_flex_vnetz
     attribute), 106                                     attribute), 131
network_enables_3                                     NetworkID2 (ics.ics.SpyMessage attribute), 18
    (ics.structures.s_flex_vnetz_settings.s_flex_vnetz
     attribute), 106                                     NetworkID2 (ics.ics.SpyMessageJ1850 attribute), 19
network_enables_3                                     NetworkID2 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_fle
    (ics.structures.srad_galaxy_settings.srad_galaxy
     attribute), 134                                     attribute), 81
network_enables_3                                     NetworkID2 (ics.structures.ics_spy_message_long.ics_spy_message_long
    (ics.structures.srad_gigalog_settings.srad_gigalog_settings
     attribute), 134                                     attribute), 83
network_enables_3                                     NetworkID2 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
    (ics.structures.srad_gigalog_settings.srad_gigalog_settings
     attribute), 137                                     attribute), 85
network_enables_3                                     NO_CANFD (in module ics.ics), 168
    (ics.structures.srad_gigastar_settings.srad_gigastar_setting
     attribute), 139                                     no_enf_hostprt (ics.structures.s_pluto_l2_address_lookup_params_s.s
                                                       attribute), 116
network_enables_3                                     NetworkID (ics.ics.SpyMessage attribute), 18
    (ics.structures.srad_jupiter_settings.srad_jupiter
     attribute), 141                                     NodeID (ics.ics.SpyMessageJ1850 attribute), 19
```

NodeID (*ics.structures.ics_spy_message_flex_ray.ics_spy_message.flattribute*), 112
 attribute), 81

NodeID (*ics.structures.ics_spy_message_long.ics_spy_message_long*
 attribute), 84

NodeID (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb*
 attribute), 85

NodeID (*ics.structures.spy_filter_long.spy_filter_long*
 attribute), 131

noExtraDataPtrCleanup (*ics.ics.SpyMessage* attribute), 19

noExtraDataPtrCleanup
 (*ics.ics.SpyMessageJ1850* attribute), 20

NORMAL (in module *ics.ics*), 168

NORMAL_MODE (in module *ics.ics*), 168

nrf52_maj (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 148

nrf52_min (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 148

null_frame (*ics.structures.ics_spy_message_flex_ray.ics_spy_message.flattribute*), 83

num_bytes (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx.message* attribute), 87

num_bytes (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx.message* attribute), 151

NumberBytesData (*ics.ics.SpyMessage* attribute), 18

NumberBytesData (*ics.ics.SpyMessageJ1850* attribute), 20

NumberBytesData (*ics.structures.ics_spy_message_flex_ray.ics_spy_message.flattribute*), 81

NumberBytesData (*ics.structures.ics_spy_message_long.ics_spy_message.flattribute*), 84

NumberBytesData (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb* attribute), 85

NumberBytesHeader (*ics.ics.SpyMessage* attribute), 18

NumberBytesHeader (*ics.ics.SpyMessageJ1850* attribute), 20

NumberBytesHeader
 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message.flattribute*), 81

NumberBytesHeader
 (*ics.structures.ics_spy_message_long.ics_spy_message.flattribute*), 84

NumberBytesHeader
 (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb* attribute), 85

NumberOfClients (*ics.ics.NeoDevice* attribute), 18

numBitsDelay (*ics.structures.lin_settings.lin_settings* attribute), 88

numEntries (*ics.structures.s_phy_reg_pkt_hdr.s_phy_reg_pkt_hdr* attribute), 111

numstbcy (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params* attribute), 112

numunstbcy (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params* attribute), 112

O

obd2pro (*ics.structures.global_settings.global_settings* attribute), 78

obd2pro (*ics.structures.s_device_settings.s_device_settings* attribute), 95

obd2pro_versions (*ics.structures.st_chip_versions.st_chip_versions* attribute), 148

obd2proStatus (*ics.structures.ics_device_status.ics_device_status* attribute), 79

obvwinsz (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params* attribute), 112

op_eth_general_settings (class in *ics.structures.op_eth_general_settings*), 89

OP_ETH_GENERAL_SETTINGS_SIZE (in module *ics.ics*), 168

op_eth_link_mode (class in *ics.structures.op_eth_link_mode*), 89

op_eth_settings (class in *ics.structures.op_eth_settings*), 89

OP_ETH_SETTINGS_SIZE (in module *ics.ics*), 169

OpenNeoDevice () (in module *ics.ics*), 24

opEth1 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134

opEth1 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 134

opEth1 (*ics.structures.srad_moon2_settings.srad_moon2_settings* attribute), 134

opEth1 (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 134

opEth1 (*ics.structures.srad_super_moon_settings.srad_super_moon_settings* attribute), 146

opEth10 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134

opEth11 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134

opEth2 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134

opEth2 (*ics.structures.srad_gigastar_settings.srad_gigastar_settings* attribute), 134

opEth2 (*ics.structures.srad_star2_settings.srad_star2_settings* attribute), 139

opEth3 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134

opEth4 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134

opEth5 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134

opEth6 (*ics.structures.srad_galaxy_settings.srad_galaxy_settings* attribute), 134

```

opEth7 (ics.structures.srad_galaxy_settings.srad_galaxy_setting00us (ics.structures.iso9141_keyword2000_settings.iso9141_keyword00us attribute), 134
opEth8 (ics.structures.srad_galaxy_settings.srad_galaxy_setting00us (ics.structures.iso9141_keyword2000_settings.iso9141_keyword00us attribute), 134
opEth9 (ics.structures.srad_galaxy_settings.srad_galaxy_setting00us (ics.structures.s.s_pluto_custom_params_s.s_pluto_custom_params_s attribute), 134
OPETH_FUNC_MEDIA CONVERTER (in module ics.ics), pad (ics.structures.s.s_pluto_l2_address_lookup_params_s.s.s_pluto_l2_address_lookup_params_s attribute), 116
OPETH_FUNC_RAW MEDIA CONVERTER (in module ics.ics), pad (ics.structures.s.s_pluto_l2_forwarding_entry_s.s.s_pluto_l2_forwarding_entry_s attribute), 116
OPETH_FUNC_TAP (in module ics.ics), pad (ics.structures.s.s_pluto_l2_forwarding_params_s.s.s_pluto_l2_forwarding_params_s attribute), 116
OPETH_FUNC_TAP_LOW_LATENCY (in module ics.ics), pad (ics.structures.s.s_pluto_mac_config_s.s.s_pluto_mac_config_s attribute), 116
OPETH_LINK_AUTO (ics.structures.op_eth_link_mode.op_eth_link_mode attribute), pad (ics.structures.s.s_pluto_retagging_entry_s.s.s_pluto_retagging_entry_s attribute), 117
OPETH_LINK_AUTO (in module ics.ics), pad (ics.structures.s.s_pluto_vl_forwarding_params_s.s.s_pluto_vl_forwarding_params_s attribute), 118
OPETH_LINK_MASTER
    (ics.structures.op_eth_link_mode.op_eth_link_mode attribute), pad (ics.structures.s.s_pluto_vlan_lookup_s.s.s_pluto_vlan_lookup_s attribute), 119
OPETH_LINK_MASTER (in module ics.ics), pad (ics.structures.s.s_pluto_vlan_lookup_s.s.s_pluto_vlan_lookup_s attribute), 120
OPETH_LINK_SLAVE (ics.structures.op_eth_link_mode.op_eth_link_mode attribute), pad1 (ics.structures.s.s_pluto_clock_sync_params_s.s.s_pluto_clock_sync_params_s attribute), 141
OPETH_LINK_SLAVE (in module ics.ics), pad1 (ics.structures.s.s_pluto_l2_address_lookup_entry_s.s.s_pluto_l2_address_lookup_entry_s attribute), 112
OPETH_MAC_SPOOF_DST_ADDR (in module ics.ics), pad1 (ics.structures.s.s_pluto_l2_address_lookup_entry_s.s.s_pluto_l2_address_lookup_entry_s attribute), 116
OPETH_MAC_SPOOF_SRC_ADDR (in module ics.ics), pad2 (ics.structures.s.s_pluto_clock_sync_params_s.s.s_pluto_clock_sync_params_s attribute), 116
opEthGen (ics.structures.srad_galaxy_settings.srad_galaxy_setting attribute), pad2 (ics.structures.s.s_pluto_l2_address_lookup_entry_s.s.s_pluto_l2_address_lookup_entry_s attribute), 112
opEthGen (ics.structures.srad_gigastar_settings.srad_gigastar_setting attribute), pad2 (ics.structures.s.s_pluto_l2_address_lookup_entry_s.s.s_pluto_l2_address_lookup_entry_s attribute), 116
opEthGen (ics.structures.srad_moon2_settings.srad_moon2_setting attribute), pad3 (ics.structures.s.s_pluto_clock_sync_params_s.s.s_pluto_clock_sync_params_s attribute), 113
opEthGen (ics.structures.srad_star2_settings.srad_star2_setting attribute), pad3 (ics.structures.s.s_pluto_l2_address_lookup_entry_s.s.s_pluto_l2_address_lookup_entry_s attribute), 142
opEthGen (ics.structures.srad_star2_settings.srad_star2_setting attribute), padding (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 116
opEthGen (ics.structures.srad_super_moon_settings.srad_super_moon_setting attribute), padding (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 146
options (ics.structures.s.s_disk_structure.s.s_disk_structure attribute), padding (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 150
override_library_name () (in module ics.ics), padding (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 48
overrideBlockSize
    (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), paddingEnable (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), 87
overrideBlockSize
    (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), paddingEnable (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message attribute), 150
overrideSTmin (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message attribute), padding (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), 151
overrideSTmin (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message attribute), part_spc (ics.structures.s.s_pluto_l2_forwarding_params_s.s.s_pluto_l2_forwarding_params_s attribute), 117
p2_500us (ics.structures.iso9141_keyword2000_settings.iso9141_keyword2000_settings pluto_l2_policing_s.s.s_pluto_l2_policing_s attribute), 87

```

P

partition (*ics.structures.s_pluto_vl_forwarding_entry.sp*₁*e_pluto_vl_ifs_structuring_star2_pluto_settings.srad_pluto_settings*.
attribute), 119
 partspc (*ics.structures.s_pluto_vl_forwarding_params.s.p*₂*luto_vl_forwaring_params_star2_settings.srad_star2_settings*.
attribute), 119
 payload_preamble (*ics.structures.ics_spy_message_flexiflexiflexiflexiflexiflexi*₃*super_moon_settings.srad_super_moon_sett*
attribute), 83
 pc_com_mode (*ics.structures.srad_moon2_settings.srad_moon2_settings.svcan3_settings.svcan3_settings*.
attribute), 142
 pc_com_mode (*ics.structures.srad_star2_settings.srad_star2_settings.svcan412_settings.svcan412_settings*.
attribute), 145
 pc_com_mode (*ics.structures.srad_super_moon_settings.srad_super_i*₄*nsructure*₅*svcan4_ind_settings.svcan4_ind_settings*.
attribute), 146
 pcfpriority (*ics.structures.s_pluto_clock_sync_params.s.p*₆*luto_clock_sync_params_star4s_settings.svcan4_settings*.
attribute), 113
 pcfsze (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.svcanrf_settings.svcanrf_settings*.
attribute), 113
 pendant (*ics.structures.global_settings.global_settings*.
attribute), 78
 pendant (*ics.structures.s_device_settings.s_device_settings*.
attribute), 95
 perf_en (*ics.structures.s_cyan_settings.s_cyan_settings*.
attribute), 94
 perf_en (*ics.structures.s_fire3_settings.s_fire3_settings*.
attribute), 99
 perf_en (*ics.structures.s_fire_settings.s_fire_settings*.
attribute), 102
 perf_en (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*.
attribute), 105
 perf_en (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*.
attribute), 107
 perf_en (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*.
attribute), 108
 perf_en (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings*.
attribute), 120
 perf_en (*ics.structures.s_vivid_can_settings.s_vivid_can_settings*.
attribute), 122
 perf_en (*ics.structures.secvb_settings.secvb_settings*.
attribute), 126
 perf_en (*ics.structures.sobd2_pro_settings.sobd2_pro_settings*.
attribute), 129
 perf_en (*ics.structures.sobd2_sim_settings.sobd2_sim_settings*.
attribute), 131
 perf_en (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*.
attribute), 134
 perf_en (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*.
attribute), 137
 perf_en (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*.
attribute), 139
 perf_en (*ics.structures.srad_jupiter_settings.srad_jupiter_settings*.
attribute), 141
 perf_en (*ics.structures.srad_moon2_settings.srad_moon2_settings*.
attribute), 142

PHY_REG_PKT_VERSION (in module *ics.ics*), 169
 phyAddr (*ics.structures.s_phy_reg_pkt_clause22_mess.s_phy_reg_pkt_clause22_mess*.
attribute), 111
 phyMode (*ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch*.
attribute), 141
 plasma_fire_vnet (*ics.structures.st_chip_versions.st_chip_versions*.
attribute), 148
 PLASMA_SLAVE1_OFFSET (in module *ics.ics*), 169
 PLASMA_SLAVE1_OFFSET_RANGE2 (in module *ics.ics*), 169
 PLASMA_SLAVE2_OFFSET (in module *ics.ics*), 169
 PLASMA_SLAVE2_OFFSET_RANGE2 (in module *ics.ics*), 169
 PLASMA_SLAVE3_OFFSET (in module *ics.ics*), 169
 PLASMA_SLAVE3_OFFSET_RANGE2 (in module *ics.ics*), 169
 PLASMA_SLAVE_NUM (in module *ics.ics*), 169
 PlasmaIonVnetChannelA (*ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet*.
attribute), 76
 PlasmaIonVnetChannelB (*ics.structures.e_plasma_ion_vnet_channel_t.e_plasma_ion_vnet*.
attribute), 76
 pluto (i₇*c.structures.global_settings.global_settings*.
attribute), 78
 pluto (*ics.structures.s_device_settings.s_device_settings*.
attribute), 95
 PLUTO_MAX_FORWARDING_ENTRIES (in module *ics.ics*), 169
 PLUTO_MAX_L2_ADDRESS_LOOKUP (in module *ics.ics*), 169
 PLUTO_MAX_L2_POLICING (in module *ics.ics*), 169
 PLUTO_MAX_MAC_CONFIG_ENTRIES (in module *ics.ics*), 169
 PLUTO_MAX_RETAGGING_ENTRIES (in module *ics.ics*), 169

PLUTO_MAX_VLAN_LOOKUP (*in module ics.ics*), 169
PLUTO_NUM_PRIORITY (*in module ics.ics*), 169
pluto_versions (*ics.structures.st_chip_versions.st_chip_versions*).enable (*ics.structures.s_vivid_can_settings.s_vivid_can_settings*.attribute), 148
plutoStatus (*ics.structures.ics_device_status.ics_devicestatus*).man_enable (*ics.structures.scan_hub_settings.scan_hub_settings*.attribute), 79
plutoswitch (*ics.structures.s_device_settings.s_device_settings*).man_enable (*ics.structures.secu_avb_settings.secu_avb_settings*.attribute), 95
poly (*ics.structures.s_pluto_l2_address_lookup_params.s_pluto_l2_address_lookup_params*).secu_settings.secu_settings.attribute), 116
port (*ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt_clause45_mess*).sobd2_pro_settings.sobd2_pro_settings.attribute), 111
port7Select (*ics.structures.srad_jupiter_switch_setting.srad_jupiter_switch_setting*).sobd2_pro_settings.sobd2_pro_settings.attribute), 141
port8Legacy (*ics.structures.srad_jupiter_switch_setting.srad_jupiter_switch_setting*).sobd2_pro_settings.sobd2_pro_settings.attribute), 141
port8Select (*ics.structures.srad_jupiter_switch_setting.srad_jupiter_switch_setting*).sobd2_pro_settings.sobd2_pro_settings.attribute), 141
port8Speed (*ics.structures.srad_jupiter_switch_settings.srad_jupiter_switch_settings*).sobd2_pro_settings.sobd2_pro_settings.attribute), 142
preemption_en (*ics.structures.op_eth_settings.op_eth_settings*).man_enable (*ics.structures.srad_jupiter_settings.srad_jupiter_settings*.attribute), 90
priority (*ics.structures.s_pluto_vl_forwarding_entry_s.s_pluto_vl_forwarding_entry*).sobd2_pro_settings.sobd2_pro_settings.attribute), 119
progress (*ics.structures.s_ext_sub_cmd_comm.s_ext_subcmd*).enable (*ics.structures.srad_star2_settings.srad_star2_settings*.attribute), 97
Protocol (*ics.ics.SpyMessage* attribute), 19
Protocol (*ics.ics.SpyMessageJ1850* attribute), 20
Protocol (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray*).enable (*ics.structures.svcn4_ind_settings.svcn4_ind_settings*.attribute), 81
Protocol (*ics.structures.ics_spy_message_long.ics_spy_message_long*).enable (*ics.structures.svcn4_settings.svcn4_settings*.attribute), 84
Protocol (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb*).enable (*ics.structures.svcnrf_settings.svcnrf_settings*.attribute), 85
ptpParams (*ics.structures.s_pluto_custom_params.s_pluto_custom_params*).cyan_settings.cyan_settings.attribute), 114
pwm_man_timeout (*ics.structures.s_fire_settings.s_fire_settings*).fire3_settings.fire3_settings.attribute), 102
pwm_man_timeout (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*).flex_vnet_settings.flex_vnet_settings.attribute), 105
pwr_man_enable (*ics.structures.s_cyan_settings.s_cyan_settings*).neo_ecu12_settings.neo_ecu12_settings.attribute), 94
pwr_man_enable (*ics.structures.s_fire3_settings.s_fire3_settings*).pendant_settings.pendant_settings.attribute), 100
pwr_man_enable (*ics.structures.s_fire_settings.s_fire_settings*).rad_moon_duo_settings.rad_moon_duo_settings.attribute), 102
pwr_man_enable (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*).vivid_can_settings.vivid_can_settings.attribute), 105
pwr_man_enable (*ics.structures.s_flex_vnet_settings.s_flex_vnet_settings*).scan_hub_settings.scan_hub_settings.attribute), 107
pwr_man_enable (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*).secu_avb_settings.secavb_settings.attribute), 108
pwr_man_enable (*ics.structures.s_pendant_settings.s_pendant_settings*).secu_settings.secu_settings.attribute), 110
pwr_man_enable (pwr_man_enable (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings*).attribute), 120
pwr_man_enable (pwr_man_enable (*ics.structures.s_vivid_can_settings.s_vivid_can_settings*).attribute), 122
pwr_man_enable (pwr_man_enable (*ics.structures.s_flex_vnet_settings.s_flex_vnet_settings*).attribute), 123
pwr_man_enable (pwr_man_enable (*ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings*).secu_avb_settings.secavb_settings.attribute), 124
pwr_man_enable (pwr_man_enable (*ics.structures.s_pendant_settings.s_pendant_settings*).secu_settings.secu_settings.attribute), 110
pwr_man_enable (pwr_man_enable (*ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_settings*).attribute), 125

pwr_man_timeout (*ics.structures.sievb_settings.sievb_settings*.REPORTING_SETTINGS_FLAG_MISC2_PWMIN
 attribute), 128
 pwr_man_timeout (*ics.structures.sobd2_pro_settings.sobd2_pro_settings*.REPORTING_SETTINGS_FLAG_TEMP_ENABLE
 attribute), 130
 pwr_man_timeout (*ics.structures.srad_galaxy_settings.srad_galaxy_settings*.SETTINGS_SIZE (in module
 attribute), 134
 pwr_man_timeout (*ics.structures.srad_gigalog_settings.srad_gigalog_settings*.~~rest~~global_settings.global_settings
 attribute), 137
 pwr_man_timeout (*ics.structures.srad_gigastar_settings.srad_gigastar_settings*.~~rest~~s_device_settings.s_device_settings
 attribute), 139
 pwr_man_timeout (*ics.structures.srad_jupiter_settings.srad_jupiter_settings*
 attribute), 141
 pwr_man_timeout (*ics.structures.srad_pluto_settings.srad_pluto_attributes*, 149
 attribute), 143
 pwr_man_timeout (*ics.structures.srad_star2_settings.srad_star2_attributes*, 78
 attribute), 145
 pwr_man_timeout (*ics.structures.svcanc412_settings.svcanc412_attributes*, 95
 attribute), 153
 pwr_man_timeout (*ics.structures.svcanc4_in_settings.svcanc4_in_attributes*, 149
 attribute), 154
 pwr_man_timeout (*ics.structures.svcanc4_settings.svcanc4_attributes*, 156
 attribute), 156
 pwr_man_timeout (*ics.structures.svcancrf_settings.svcancrf_attributes*, 149
 attribute), 157

Q

q2112_phy_mode (*ics.structures.op_eth_settings.op_eth_settings*.attribute), 95

R

rad_moon_duo_converter_settings (class in *ics.structures.rad_moon_duo_converter_settings*,
 90
 rad_moon_duo_versions
 ics.structures.st_chip_versions.st_chip_versions.attribute), 148
 rad_reporting_settings (class in *ics.structures.rad_reporting_settings*, 90
 RAD_REPORTING_SETTINGS_FLAG_AIN1 (in module *ics.ics*), 169
 RAD_REPORTING_SETTINGS_FLAG_AIN2 (in module *ics.ics*), 169
 RAD_REPORTING_SETTINGS_FLAG_INT_GPS_ENABLE (in module *ics.ics*), 169
 RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE (in module *ics.ics*), 169
 RAD_REPORTING_SETTINGS_FLAG_MIC2_GPS_ENABLE2 (in module *ics.ics*), 169
 RAD_REPORTING_SETTINGS_FLAG_MISC1_DIN (in module *ics.ics*), 169
 RAD_REPORTING_SETTINGS_FLAG_MISC1_PWMIN (in module *ics.ics*), 169
 RAD_REPORTING_SETTINGS_FLAG_MISC2_DIN (in module *ics.ics*), 169

rad_gigalog (ics.structures.global_settings.global_settings.attribute), 78
 rad_gigalog3_versions
 rad_gigastar (ics.structures.global_settings.global_settings.attribute), 78
 rad_gigastar (ics.structures.s_device_settings.s_device_settings.attribute), 149
 rad_gigastar_usbz_versions
 (ics.structures.st_chip_versions.st_chip_versions.attribute), 149
 radgigastar_versions
 (ics.structures.st_chip_versions.st_chip_versions.attribute), 149
 RADJUPITER_NUM_PORTS (in module *ics.ics*), 169
 radmoon2 (ics.structures.global_settings.global_settings.attribute), 78
 radmoon2 (ics.structures.s_device_settings.s_device_settings.attribute), 95
 radmoon2_versions
 (ics.structures.st_chip_versions.st_chip_versions.attribute), 149
 radmoon_duo (ics.structures.s_device_settings.s_device_settings.attribute), 95
 radmoonduo (ics.structures.global_settings.global_settings.attribute), 79
 RADMOONDUO_CONVERTER_SETTINGS_SIZE (in module *ics.ics*), 169
 radMoonDuoStatus (ics.structures.ics_device_status.ics_device_status.attribute), 79
 radstar2 (ics.structures.global_settings.global_settings.attribute), 79
 radstar2 (ics.structures.s_device_settings.s_device_settings.attribute), 96
 radstar2_versions

```

(ics.structures.st_chip_versions.st_chip_versions RequestDiskDetails () (in module ics.ics), 24
attribute), 149 RequestDiskFormat () (in module ics.ics), 24
radsupermoon (ics.structures.global_settings.global_setting RequestDiskFormatCancel () (in module ics.ics),
attribute), 79 24
radsupermoon (ics.structures.s_device_settings.s_device RequestDiskFormatProgress () (in module
attribute), 96 ics.ics), 24
radsupermoon_versions RequestEnterSleepMode () (in module ics.ics), 24
(ics.structures.st_chip_versions.st_chip_versions res1 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray
attribute), 149 attribute), 83
rate (ics.structures.s_pluto_l2_policing_s.s_pluto_l2_policing RequestDiskFormatProgress () (in module
attribute), 117 ics.ics), 24
reach_port (ics.structures.s_pluto_l2_forwarding_entry RequestEnterSleepMode () (in module ics.ics), 24
attribute), 116
read_jupiter_firmware () (in module ics.ics), 48 reserved (ics.structures.canterm_settings.canterm_settings
read_sdcard () (in module ics.ics), 48 attribute), 74
ReadJupiterFirmware () (in module ics.ics), 24 Reserved (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex
ReadSDCard () (in module ics.ics), 24 attribute), 82
red (ics.structures.global_settings.global_settings Reserved (ics.structures.ics_spy_message_long.ics_spy_message_long
attribute), 79 attribute), 84
red (ics.structures.s_device_settings.s_device_settings Reserved (ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
attribute), 96 attribute), 85
regAddr (ics.structures.s_phy_reg_pkt_clause22_mess.s_phy_reg_pkt (class) (in module ics.ics), 90
attribute), 111 (class) (in module ics.ics), 90
regAddr (ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt (class) (in module ics.ics), 94
attribute), 111 (class) (in module ics.ics), 94
regVal (ics.structures.s_phy_reg_pkt_clause22_mess.s_phy_reg_pkt (class) (in module ics.ics), 100
attribute), 111 (class) (in module ics.ics), 100
regVal (ics.structures.s_phy_reg_pkt_clause45_mess.s_phy_reg_pkt (class) (in module ics.ics), 107
attribute), 111 (class) (in module ics.ics), 107
REPORT_ON_GPS (in module ics.ics), 169 reserved (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings
REPORT_ON_KLINE (in module ics.ics), 169 attribute), 108
REPORT_ON_LED1 (in module ics.ics), 169 reserved (ics.structures.s_phy_reg_pkt.s_phy_reg_pkt
REPORT_ON_LED2 (in module ics.ics), 169 attribute), 111
REPORT_ON_MISC1 (in module ics.ics), 169 reserved (ics.structures.s_rad_moon_duo_settings.s_rad_moon_duo_set
REPORT_ON_MISC2 (in module ics.ics), 169 tting attribute), 121
REPORT_ON_MISC3 (in module ics.ics), 169 reserved (ics.structures.s_text_api_settings.s_text_api_settings
REPORT_ON_MISC3_AIN (in module ics.ics), 169 attribute), 122
REPORT_ON_MISC4 (in module ics.ics), 170 reserved (ics.structures.s_vivid_can_settings.s_vivid_can_settings
REPORT_ON_MISC4_AIN (in module ics.ics), 170 attribute), 122
REPORT_ON_MISC5 (in module ics.ics), 170 reserved (ics.structures.secu_avb_settings.secu_avb_settings
REPORT_ON_MISC5_AIN (in module ics.ics), 170 attribute), 124
REPORT_ON_MISC6 (in module ics.ics), 170 reserved (ics.structures.sobd2_pro_settings.sobd2_pro_settings
REPORT_ON_MISC6_AIN (in module ics.ics), 170 attribute), 130
REPORT_ON_PERIODIC (in module ics.ics), 170 reserved (ics.structures.sobd2_sim_settings.sobd2_sim_settings
reporting (ics.structures.srad_galaxy_settings.srad_galaxy_setting attribute), 131
attribute), 135 reserved (ics.structures.srad_gigalog_settings.srad_gigalog_settings
reporting (ics.structures.srad_gigalog_settings.srad_gigalog_setting attribute), 137
attribute), 137 reserved (ics.structures.srad_gigastar_settings.srad_gigastar_settings
reporting (ics.structures.srad_gigastar_settings.srad_gigastar_setting attribute), 139
attribute), 139 reserved (ics.structures.srad_jupiter_settings.srad_jupiter_settings
reporting (ics.structures.srad_star2_settings.srad_star2_setting attribute), 141
attribute), 145 reserved (ics.structures.srad_pluto_settings.srad_pluto_settings
request_enter_sleep_mode () (in module ics.ics), 48 attribute), 144
reserved (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652

```

attribute), 150
 reserved(ics.structures.svcancan412_settings.svcancan412_settings) (attribute), 153
 reserved(ics.structures.svcancan4_ind_settings.svcancan4_ind_settings) (attribute), 154
 reserved(ics.structures.svcancan4_settings.svcancan4_settings) (attribute), 156
 RESERVED(ics.structures.swcan_settings.swcan_settings) (attribute), 157
 Reserved(ics.structures.tag_options_find_neo_ex.tag_options_find_neo_ex) (attribute), 158
 Reserved(ics.structures.tag_options_open_neo_ex.tag_options_open_neo_ex) (attribute), 158
 reserved0(ics.structures.op_eth_general_settings.op_eth_general_settings) (attribute), 89
 reserved0(ics.structures.op_eth_settings.op_eth_settings) (attribute), 90
 reserved_1(ics.structures.sievb_settings.sievb_settings) (attribute), 128
 reserved_1(ics.structures.uart_settings.uart_settings) (attribute), 159
 reserved_2(ics.structures.sievb_settings.sievb_settings) (attribute), 128
 reserved_bits(ics.structures.uart_settings.uart_settings) (attribute), 159
 reserved_bits2(ics.structures.uart_settings.uart_settings) (attribute), 159
 reservedZero(ics.structures.svcancanrf_settings.svcancanrf_settings) (attribute), 157
 resHeight(ics.structures.serdescam_settings.serdescam_settings) (attribute), 126
 RESISTOR_OFF (in module ics.ics), 170
 RESISTOR_ON (in module ics.ics), 170
 resWidth(ics.structures.serdescam_settings.serdescam_settings) (attribute), 126
 retag(ics.structures.s_pluto_mac_config.s_pluto_mac_config) (attribute), 118
 retagging(ics.structures.s_pluto_switch_settings.s_pluto_switch_settings) (attribute), 119
 rsvd (ics.structures.disk_settings.disk_settings) (attribute), 74
 rsvd (ics.structures.ethernet_settings.ethernet_settings) (attribute), 77
 rsvd(ics.structures.ethernet_settings2.ethernet_settings2) (attribute), 77
 rsvd(ics.structures.logger_settings.logger_settings) (attribute), 89
 rsvd(ics.structures.rad_reporting_settings.rad_reporting_settings) (attribute), 90
 rsvd(ics.structures.seevb_settings.seevb_settings) (attribute), 126
 rsvd(ics.structures.serdespoc_settings.serdespoc_settings) (attribute), 126
 rsvd1(ics.structures.serdescam_settings.serdescam_settings) (attribute), 126
 attribute), 126
 s_cm_probe_settings (class), in
 s_cyan_settings (class), in
 ics.structures.s_cyan_settings), 91
 s_device_settings (class), in
 ics.structures.s_device_settings), 94
 s_disk_details (class), in
 ics.structures.s_disk_details), 96
 s_disk_format_progress (class), in
 ics.structures.s_disk_format_progress), 96
 s_disk_status (class in ics.structures.s_disk_status), 96
 s_disk_structure (class), in
 ics.structures.s_disk_structure), 96
 s_ext_sub_cmd_comm (class), in
 ics.structures.s_ext_sub_cmd_comm), 97
 s_ext_sub_cmd_hdr (class), in
 ics.structures.s_ext_sub_cmd_hdr), 97
 s_extended_data_flash_header (class in ics.structures.s_extended_data_flash_header), 97
 ics.structures.s_extended_data_flash_header), 97
 s_fire3_settings (class), in
 ics.structures.s_fire3_settings), 97
 s_fire_settings (class), in
 ics.structures.s_fire_settings), 100
 s_fire_vnet_settings (class), in
 ics.structures.s_fire_vnet_settings), 102
 s_flex_vnetz_settings (class), in
 ics.structures.s_flex_vnetz_settings), 105
 s_neo_ecu12_settings (class), in
 ics.structures.s_neo_ecu12_settings), 107
 s_neo_most_gateway_settings (class in ics.structures.s_neo_most_gateway_settings), 109
 ics.structures.s_neo_most_gateway_settings), 109
 s_pendant_settings (class), in
 ics.structures.s_pendant_settings), 109
 s_phy_reg_pkt (class), in
 ics.structures.s_phy_reg_pkt), 110
 s_phy_reg_pkt_clause22_mess (class in ics.structures.s_phy_reg_pkt_clause22_mess), 111
 ics.structures.s_phy_reg_pkt_clause22_mess), 111
 s_phy_reg_pkt_clause45_mess (class), in

```
    ics.structures.s_phy_reg_pkt_clause45_mess),      s_red_settings          (class           in
    111                                         in  s_text_api_settings   (class           in
                                                ics.structures.s_text_api_settings), 121
    s_phy_reg_pkt_hdr       (class           in  s_vivid_can_settings (class           in
                                                ics.structures.s_phy_reg_pkt_hdr), 111
    s_pluto_avb_params_s   (class           in  scan_hub_settings   (class           in
                                                ics.structures.s_pluto_avb_params_s), 112
    s_pluto_clock_sync_params_s (class   in  schip_major (ics.structures.st_chip_versions.st_chip_versions
                                                ics.structures.s_pluto_clock_sync_params_s),
    112                                         in  attribute), 149
    s_pluto_custom_params_s (class           in  schip_minor (ics.structures.st_chip_versions.st_chip_versions
                                                ics.structures.s_pluto_custom_params_s),
    114                                         in  attribute), 149
    s_pluto_general_params_s (class           in  SCRIPT_LOCATION_FLASH_MEM (in module ics.ics),
                                                ics.structures.s_pluto_general_params_s),
    114                                         in  170
    s_pluto_l2_address_lookup_entry_s (class   in  SCRIPT_LOCATION_INTERNAL_FLASH (in module
                                                ics.structures.s_pluto_l2_address_lookup_entry_s)
    115                                         in  170
    s_pluto_l2_address_lookup_params_s (class   in  SCRIPT_LOCATION_SDCARD (in module ics.ics), 170
                                                ics.structures.s_pluto_l2_address_lookup_params_s)
    116                                         in  SCRIPT_LOCATION_VCAN3_MEM (in module ics.ics),
    170
    s_pluto_l2_forwarding_params_s (class   in  170
                                                ics.structures.s_pluto_l2_forwarding_params_s),
    116                                         in  SCRIPT_STATUS_RUNNING (in module ics.ics), 170
    s_pluto_l2_policing_s     (class           in  SCRIPT_STATUS_STOPPED (in module ics.ics), 170
                                                ics.structures.s_pluto_l2_policing_s), 117
    s_pluto_mac_config_s     (class           in  ScriptClear () (in module ics.ics), 25
                                                ics.structures.s_pluto_mac_config_s), 117
    s_pluto_retagging_entry_s (class           in  ScriptGetFBlockStatus () (in module ics.ics), 25
                                                ics.structures.s_pluto_retagging_entry_s),
    116                                         in  ScriptGetScriptStatus () (in module ics.ics), 25
    s_pluto_l2_forwarding_entry_s (class   in  ScriptGetScriptStatusEx () (in module ics.ics),
                                                ics.structures.s_pluto_l2_forwarding_entry_s),
    116                                         in  25
    s_pluto_l2_policing_s     (class           in  ScriptLoad () (in module ics.ics), 25
                                                ics.structures.s_pluto_l2_policing_s), 117
    s_pluto_mac_config_s     (class           in  ScriptReadAppSignal () (in module ics.ics), 25
                                                ics.structures.s_pluto_mac_config_s), 117
    s_pluto_retagging_entry_s (class           in  ScriptReadRxMessage () (in module ics.ics), 25
                                                ics.structures.s_pluto_retagging_entry_s),
    118                                         in  ScriptReadTxMessage () (in module ics.ics), 25
    s_pluto_switch_settings_s (class           in  ScriptStart () (in module ics.ics), 26
                                                ics.structures.s_pluto_switch_settings_s),
    118                                         in  ScriptStartFBlock () (in module ics.ics), 26
    s_pluto_vl_forwarding_entry_s (class   in  ScriptStop () (in module ics.ics), 26
                                                ics.structures.s_pluto_vl_forwarding_entry_s),
    119                                         in  ScriptStopFBlock () (in module ics.ics), 26
    s_pluto_vl_forwarding_params_s (class   in  ScriptWriteAppSignal () (in module ics.ics), 26
                                                ics.structures.s_pluto_vl_forwarding_params_s),
    119                                         in  ScriptWriteRxMessage () (in module ics.ics), 26
    s_pluto_vl_forwarding_entry_s (class   in  ScriptWriteTxMessage () (in module ics.ics), 26
                                                ics.structures.s_pluto_vl_forwarding_entry_s),
    119                                         in  sectors (ics.structures.s_disk_status.s_disk_status at-
    119                                         in  tribute), 96
    s_pluto_vl_forwarding_params_s (class   in  sectorsRemaining (ics.structures.s_disk_format_progress.s_disk_form-
                                                ics.structures.s_pluto_vl_forwarding_params_s),
    119                                         in  attribute), 96
    s_pluto_vl_lookup_entry_s  (class           in  secu_avb_settings          (class           in
                                                ics.structures.s_pluto_vl_lookup_entry_s),
    119                                         in  123
    s_pluto_vl_policing_entry_s (class           in  secu_settings (class in ics.structures.secu_settings),
                                                ics.structures.s_pluto_vl_policing_entry_s),
    119                                         in  124
    s_pluto_vlan_lookup_s     (class           in  seevb_settings          (class           in
                                                ics.structures.s_pluto_vlan_lookup_s), 120
    s_rad_moon_duo_settings   (class           in  selected_network (ics.structures.s_pendant_settings.s_pendant_setting
                                                ics.structures.s_rad_moon_duo_settings),
    120                                         in  attribute), 110
    send_meta0 (ics.structures.s_pluto_general_params_s.s_pluto_general_

```

attribute), 115
send_meta1(*ics.structures.s_pluto_general_params_s.s_PLUTO_GENERAL_PARAMS_S_FORMAT_BAYER_BGGR_16BE attribute*), 115
serdes_interval_ms SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_16LE
(ics.structures.rad_reporting_settings.rad_reporting_settingattribute), 90 SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_8 (in
serdescam1(*ics.structures.srad_gigalog_settings.srad_gigalog_settingattribute* *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_COUNT (in module
attribute), 137
serdescam1(*ics.structures.srad_gigastar_settings.srad_gigastar_settingattribute*), 170 SERDESCAM_VIDEO_FORMAT_CSII_BAYER_BGGR_10LE_PACKED
attribute), 139
serdescam2(*ics.structures.srad_gigalog_settings.srad_gigalog_settingmodule ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_BAYER_BGGR_12LE_PACKED
attribute), 137
serdescam2(*ics.structures.srad_gigastar_settings.srad_gigastar_settingmodule ics.ics*), 171 SERDESCAM_VIDEO_FORMAT_CSII_BAYER_BGGR_8
attribute), 139
serdescam3(*ics.structures.srad_gigalog_settings.srad_gigalog_settingmodule ics.ics*), 171 SERDESCAM_VIDEO_FORMAT_CSII_RAW_10 (in
attribute), 137
serdescam3(*ics.structures.srad_gigastar_settings.srad_gigastar_settingattribute ics.ics*), 171 SERDESCAM_VIDEO_FORMAT_CSII_RAW_12 (in
attribute), 139
serdescam4(*ics.structures.srad_gigalog_settings.srad_gigalog_settingattribute* *ics.ics*), 171 SERDESCAM_VIDEO_FORMAT_CSII_RAW_14 (in
attribute), 137
serdescam4(*ics.structures.srad_gigastar_settings.srad_gigastar_settingattribute ics.ics*), 171 SERDESCAM_VIDEO_FORMAT_CSII_RAW_16 (in
attribute), 140
SERDESCAM_CONFIG_MODE_EXTERNAL_OVER_TAP (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_RAW_20 (in
SERDESCAM_CONFIG_MODE_LOCAL_SCRIPT (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_RAW_24 (in
SERDESCAM_MODE_PASSTHROUGH (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_RAW_30 (in
SERDESCAM_MODE_PLAYBACK (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_RAW_32 (in
SERDESCAM_MODE_TAP (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_RAW_8 (in
SERDESCAM_PIXEL_BIT_POS_0 (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_RGB565 (in
SERDESCAM_PIXEL_BIT_POS_1 (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_RGB666 (in
SERDESCAM_PIXEL_BIT_POS_2 (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_RGB888 (in
SERDESCAM_PIXEL_BIT_POS_3 (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_UYVY_422_10LE_PACKED
serdescam_settings (class in *ics.structures.serdescam_settings*), 126 (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_UYVY_422_12LE_PACKED
SERDESCAM_SETTINGS_AUTO_DETECT_ENABLE (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_VYUY_422_8 (in module *ics.ics*), 171
SERDESCAM_SETTINGS_CONFIG_ENABLE (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_VYUY_422_10LE_PACKED
SERDESCAM_SETTINGS_FLAG_ENABLE (in module *ics.ics*), 170 (in module *ics.ics*), 171 SERDESCAM_VIDEO_FORMAT_CSII_VYUY_422_12LE_PACKED
SERDESCAM_SETTINGS_RTSP_ENABLE (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_YUYV_422_10LE_PACKED
SERDESCAM_SETTINGS_SIZE (in module *ics.ics*), 170 (in module *ics.ics*), 171 SERDESCAM_VIDEO_FORMAT_CSII_YUYV_422_12LE_PACKED
SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_10LE_PACKED (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_YUYV_422_8 (in module *ics.ics*), 171
SERDESCAM_VIDEO_FORMAT_BAYER_BGGR_12LE_PACKED (in module *ics.ics*), 170 SERDESCAM_VIDEO_FORMAT_CSII_YUYV_422_10LE_PACKED

(*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_12LE_PÈKEDVIDEO_FORMAT_YUV422_16LE_PLANAR
(in module `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_CSI2_YUYV_422_8 SERDESCAM_VIDEO_FORMAT_YUYV_422_10LE_PACKED
(in module `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_10LE_PÈKEDVIDEO_FORMAT_YUYV_422_12LE_PACKED
(in module `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_12LE_PÈKEDVIDEO_FORMAT_YUYV_422_8 (*in*
module `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_CSI2_YVYU_422_8 SERDESCAM_VIDEO_FORMAT_YVYU_422_10LE_PACKED
(in module `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_JPEG (*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_NONE (*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_RAW_10 (*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_RAW_12 (*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_RAW_14 (*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_RAW_16 (*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_RAW_20 (*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_RAW_24 (*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_RAW_30 (*in module* `ics.ics`), 171

SERDESCAM_VIDEO_FORMAT_RAW_32 (*in module* `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_RAW_36 (*in module* `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_RAW_8 (*in module* `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_RGB565 (*in module* `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_RGB666 (*in module* `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_RGB888 (*in module* `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_UYVY_422_10LE_PACKEDActiveVNETChannel () (*in module* `ics.ics`), 26
(in module `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_UYVY_422_12LE_PACKEDBaudrate (`ics.structures.can_settings.can_settings`
attribute), 73

SERDESCAM_VIDEO_FORMAT_UYVY_422_8 (*in module* `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_VYUY_422_10LE_PACKEDBitRate () (*in module* `ics.ics`), 27
(in module `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_VYUY_422_12LE_PACKEDContext () (*in module* `ics.ics`), 27
(in module `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_VYUY_422_8 (*in module* `ics.ics`), 172

SERDESCAM_VIDEO_FORMAT_YUV422_10LE_PLANAR (*in module* `ics.ics`), 27

(

SetRTC () (in module <code>ics.ics</code>), 27	<code>SPY_PROTOCOL_BEAN</code> (in module <code>ics.ics</code>), 172
<code>Settings</code> (<code>ics.structures.s_device_settings.s_device_setting</code> attribute), 94	<code>SPY_PROTOCOL_CAN</code> (in module <code>ics.ics</code>), 172 <code>SPY_PROTOCOL_CANFD</code> (in module <code>ics.ics</code>), 172
<code>settings</code> (<code>ics.structures.s_disk_structure.s_disk_structure</code> attribute), 97	<code>SPY_PROTOCOL_CGI</code> (in module <code>ics.ics</code>), 172 <code>SPY_PROTOCOL_CHRYSLER_CCD</code> (in module <code>ics.ics</code>), 172
<code>shared_learn</code> (<code>ics.structures.s_pluto_l2_address_lookup_params</code> attribute), 116	<code>SPY_PROTOCOL_CHRYSLER_JVPW</code> (in module <code>ics.ics</code>), 172
<code>sharindx</code> (<code>ics.structures.s_pluto_l2_policing_s.s_pluto_l2_policing</code> attribute), 117	<code>SPY_PROTOCOL_CHRYSLER_SCI</code> (in module <code>ics.ics</code>), 172
<code>sharindx</code> (<code>ics.structures.s_pluto_vl_policing_entry_s.s_pluto_vl_policing_entry</code> attribute), 120	<code>SPY_PROTOCOL_CUSTOM</code> (in module <code>ics.ics</code>), 173
<code>sievb_settings</code> (class <code>ics.structures.sievb_settings</code>), 126	<code>SPY_PROTOCOL_DALLAS_1WIRE</code> (in module <code>ics.ics</code>), 173
<code>SLAVE_VNET_A</code> (in module <code>ics.ics</code>), 172	<code>SPY_PROTOCOL_ETHERNET</code> (in module <code>ics.ics</code>), 173
<code>SLAVE_VNET_B</code> (in module <code>ics.ics</code>), 172	<code>SPY_PROTOCOL_FLEXRAY</code> (in module <code>ics.ics</code>), 173
<code>SlaveEnable</code> (<code>ics.structures.timesync_icshardware_settings</code> attribute), 159	<code>SPY_PROTOCOL_HARDWARE_SETTINGS</code> (in module <code>ics.ics</code>), 173 <code>SPY_PROTOCOL_GENERIC_MANCHSESTER</code> (in module <code>ics.ics</code>), 173
<code>SlaveNetwork</code> (<code>ics.structures.timesync_icshardware_settings</code> attribute), 159	<code>SPY_PROTOCOL_GENERIC_UART</code> (in module <code>ics.ics</code>), 173
<code>slaveVnetA</code> (<code>ics.structures.s_cyan_settings.s_cyan_settings</code> attribute), 94	<code>SPY_PROTOCOL_GM_ALDL_UART</code> (in module <code>ics.ics</code>), 173
<code>slaveVnetA</code> (<code>ics.structures.s_fire3_settings.s_fire3_settings</code> attribute), 100	<code>SPY_PROTOCOL_GME_CIM_SCL_KLINE</code> (in module <code>ics.ics</code>), 173
<code>slaveVnetA</code> (<code>ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings</code> attribute), 107	<code>SPY_PROTOCOL_GMFSA</code> (in module <code>ics.ics</code>), 173
<code>slaveVnetB</code> (<code>ics.structures.s_cyan_settings.s_cyan_settings</code> attribute), 94	<code>SPY_PROTOCOL_GMLAN</code> (in module <code>ics.ics</code>), 173 <code>SPY_PROTOCOL_I2C</code> (in module <code>ics.ics</code>), 173
<code>slaveVnetB</code> (<code>ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings</code> attribute), 107	<code>SPY_PROTOCOL_ISO9141</code> (in module <code>ics.ics</code>), 173 <code>SPY_PROTOCOL_J1708</code> (in module <code>ics.ics</code>), 173
<code>SLEEP_MODE</code> (in module <code>ics.ics</code>), 172	<code>SPY_PROTOCOL_J1850PWM</code> (in module <code>ics.ics</code>), 173
<code>SLOW_MODE</code> (in module <code>ics.ics</code>), 172	<code>SPY_PROTOCOL_J1850VPW</code> (in module <code>ics.ics</code>), 173
<code>smax</code> (<code>ics.structures.s_pluto_l2_policing_s.s_pluto_l2_policing</code> attribute), 117	<code>SPY_PROTOCOL_J1939</code> (in module <code>ics.ics</code>), 173 <code>SPY_PROTOCOL_JTAG</code> (in module <code>ics.ics</code>), 173
<code>sobd2_pro_settings</code> (class <code>ics.structures.sobd2_pro_settings</code>), 128	<code>SPY_PROTOCOL_LIN</code> (in module <code>ics.ics</code>), 173
<code>sobd2_sim_settings</code> (class <code>ics.structures.sobd2_sim_settings</code>), 130	<code>SPY_PROTOCOL_MOST</code> (in module <code>ics.ics</code>), 173 <code>SPY_PROTOCOL_SENT_PROTOCOL</code> (in module <code>ics.ics</code>), 173
<code>spbrg</code> (<code>ics.structures.iso9141_keyword2000_settings</code> . <code>iso9141_keyword2000_setting</code> attribute), 88	<code>SPY_PROTOCOL_TCP</code> (in module <code>ics.ics</code>), 173
<code>spbrg</code> (<code>ics.structures.lin_settings.lin_settings</code> attribute), 88	<code>SPY_PROTOCOL_UART</code> (in module <code>ics.ics</code>), 173 <code>SPY_PROTOCOL_UDP</code> (in module <code>ics.ics</code>), 173
<code>spbrg</code> (<code>ics.structures.uart_settings.uart_settings</code> attribute), 159	<code>SPY_PROTOCOL_UNIO</code> (in module <code>ics.ics</code>), 173 <code>SPY_STATUS2_CAN_HAVE_LINK_DATA</code> (in module <code>ics.ics</code>), 173
<code>speed</code> (<code>ics.structures.s_pluto_custom_params.s_pluto_custom_params</code> attribute), 114	<code>SPY_STATUS2_CAN_ISO15765_LOGICAL_FRAME</code> (in module <code>ics.ics</code>), 173
<code>speed</code> (<code>ics.structures.s_pluto_mac_config.s_pluto_mac_config</code> attribute), 118	<code>SPY_STATUS2_END_OF_LONG_MESSAGE</code> (in module <code>ics.ics</code>), 173
<code>spoofedMac</code> (<code>ics.structures.srad_jupiter_switch_settings</code> . <code>srad_jupiter_switch_settings</code> attribute), 142	<code>SPY_STATUS2_ERROR_FRAME</code> (in module <code>ics.ics</code>), 173
<code>spoofMacFlag</code> (<code>ics.structures.srad_jupiter_switch_settings</code> . <code>srad_jupiter_switch_settings</code> attribute), 142	<code>SPY_STATUS2_ETHERNET_CRC_ERROR</code> (in module <code>ics.ics</code>), 173
<code>spy_filter_long</code> (class <code>ics.structures.spy_filter_long</code>), 131	<code>SPY_STATUS2_ETHERNET_FCS_AVAILABLE</code> (in module <code>ics.ics</code>), 173
<code>SPY_PROTOCOL_AUTOSAR</code> (in module <code>ics.ics</code>), 172	

SPY_STATUS2_ETHERNET_FRAME_TOO_SHORT (*in module ics.ics*), 173
SPY_STATUS2_ETHERNET_NO_PADDING (*in module ics.ics*), 173
SPY_STATUS2_ETHERNET_PREEMPTION_ENABLED (*in module ics.ics*), 173
SPY_STATUS2_FLEXRAY_NO_CRC (*in module ics.ics*), 173
SPY_STATUS2_FLEXRAY_NO_HEADERCRC (*in module ics.ics*), 174
SPY_STATUS2_FLEXRAY_TX_AB (*in module ics.ics*), 174
SPY_STATUS2_FLEXRAY_TX_AB_NO_A (*in module ics.ics*), 174
SPY_STATUS2_FLEXRAY_TX_AB_NO_B (*in module ics.ics*), 174
SPY_STATUS2_FLEXRAY_TX_AB_NO_MATCH (*in module ics.ics*), 174
SPY_STATUS2_GLOBAL_CHANGE (*in module ics.ics*), 174
SPY_STATUS2_HAS_VALUE (*in module ics.ics*), 174
SPY_STATUS2_HIGH_VOLTAGE (*in module ics.ics*), 174
SPY_STATUS2_I2C_DIR_READ (*in module ics.ics*), 174
SPY_STATUS2_I2C_ERR_NACK (*in module ics.ics*), 174
SPY_STATUS2_I2C_ERR_TIMEOUT (*in module ics.ics*), 174
SPY_STATUS2_ISO_FRAME_ERROR (*in module ics.ics*), 174
SPY_STATUS2_ISO_OVERFLOW_ERROR (*in module ics.ics*), 174
SPY_STATUS2_ISO_PARITY_ERROR (*in module ics.ics*), 174
SPY_STATUS2_LIN_ERR_MSG_ID_PARITY (*in module ics.ics*), 174
SPY_STATUS2_LIN_ERR_RX_BREAK_NOT_0 (*in module ics.ics*), 174
SPY_STATUS2_LIN_ERR_RX_BREAK_TOO_SHORT (*in module ics.ics*), 174
SPY_STATUS2_LIN_ERR_RX_DATA_GREATER_8 (*in module ics.ics*), 174
SPY_STATUS2_LIN_ERR_RX_SYNC_NOT_55 (*in module ics.ics*), 174
SPY_STATUS2_LIN_ERR_TX_RX_MISMATCH (*in module ics.ics*), 174
SPY_STATUS2_LIN_ID_FRAME_ERROR (*in module ics.ics*), 174
SPY_STATUS2_LIN_NO_SLAVE_DATA (*in module ics.ics*), 174
SPY_STATUS2_LIN_SLAVE_BYTE_ERROR (*in module ics.ics*), 174
SPY_STATUS2_LIN_SYNC_FRAME_ERROR (*in module ics.ics*), 174
SPY_STATUS2_LONG_MESSAGE (*in module ics.ics*), 174
SPY_STATUS2_MOST_CHANGED_PAR (*in module ics.ics*), 174
SPY_STATUS2_MOST_CONTROL_DATA (*in module ics.ics*), 174
SPY_STATUS2_MOST_I2S_DUMP (*in module ics.ics*), 174
SPY_STATUS2_MOST_LOW_LEVEL (*in module ics.ics*), 174
SPY_STATUS2_MOST_MHP_CONTROL_DATA (*in module ics.ics*), 174
SPY_STATUS2_MOST_MHP_USER_DATA (*in module ics.ics*), 174
SPY_STATUS2_MOST_MOST150 (*in module ics.ics*), 174
SPY_STATUS2_MOST_MOST50 (*in module ics.ics*), 174
SPY_STATUS2_MOST_PACKET_DATA (*in module ics.ics*), 174
SPY_STATUS2_MOST_STATUS (*in module ics.ics*), 174
SPY_STATUS2_MOST_TOO_SHORT (*in module ics.ics*), 174
SPY_STATUS2_RX_TIMEOUT_ERROR (*in module ics.ics*), 175
SPY_STATUS2_VALUE_IS_BOOLEAN (*in module ics.ics*), 175
SPY_STATUS3_CANFD_BRS (*in module ics.ics*), 175
SPY_STATUS3_CANFD_ESI (*in module ics.ics*), 175
SPY_STATUS3_CANFD_FDF (*in module ics.ics*), 175
SPY_STATUS3_CANFD_IDE (*in module ics.ics*), 175
SPY_STATUS3_CANFD_RTR (*in module ics.ics*), 175
SPY_STATUS3_LIN_JUST_BREAK_SYNC (*in module ics.ics*), 175
SPY_STATUS3_LIN_ONLY_UPDATE_SLAVE_TABLE_ONCE (*in module ics.ics*), 175
SPY_STATUS3_LIN_SLAVE_DATA_TOO_SHORT (*in module ics.ics*), 175
SPY_STATUS_ANALOG_DIGITAL_INPUT (*in module ics.ics*), 175
SPY_STATUS_AUDIO_COMMENT (*in module ics.ics*), 175
SPY_STATUS_AVSI_REC_OVERFLOW (*in module ics.ics*), 175
SPY_STATUS_BAD_MESSAGE_BIT_TIME_ERROR (*in module ics.ics*), 175
SPY_STATUS_BREAK (*in module ics.ics*), 175
SPY_STATUS_BUS_RECOVERED (*in module ics.ics*), 175
SPY_STATUS_BUS_SHORTED_GND (*in module ics.ics*), 175
SPY_STATUS_BUS_SHORTED_PLUS (*in module ics.ics*), 175

`ics.ics), 175`

`SPY_STATUS_CAN_BUS_OFF (in module ics.ics), 175`

`SPY_STATUS_CAN_ERROR_PASSIVE (in module ics.ics), 175`

`SPY_STATUS_CANFD (in module ics.ics), 175`

`SPY_STATUS_CHECKSUM_ERROR (in module ics.ics), 175`

`SPY_STATUS_COMM_IN_OVERFLOW (in module ics.ics), 175`

`SPY_STATUS_CRC_ERROR (in module ics.ics), 175`

`SPY_STATUS_EXPECTED_LEN_MISMATCH (in module ics.ics), 175`

`SPY_STATUS_EXTENDED (in module ics.ics), 175`

`SPY_STATUS_FLEXRAY_PDU (in module ics.ics), 175`

`SPY_STATUS_FLEXRAY_PDU_NO_UPDATE_BIT (in module ics.ics), 175`

`SPY_STATUS_FLEXRAY_PDU_UPDATE_BIT_SET (in module ics.ics), 175`

`SPY_STATUS_GLOBAL_ERR (in module ics.ics), 175`

`SPY_STATUS_GPS_DATA (in module ics.ics), 175`

`SPY_STATUS_HEADERCRC_ERROR (in module ics.ics), 175`

`SPY_STATUS_HIGH_SPEED (in module ics.ics), 175`

`SPY_STATUS_INCOMPLETE_FRAME (in module ics.ics), 175`

`SPY_STATUS_INIT_MESSAGE (in module ics.ics), 175`

`SPY_STATUS_LIN_MASTER (in module ics.ics), 175`

`SPY_STATUS_LOST_ARBITRATION (in module ics.ics), 176`

`SPY_STATUS_MSG_NO_MATCH (in module ics.ics), 176`

`SPY_STATUS_NETWORK_MESSAGE_TYPE (in module ics.ics), 176`

`SPY_STATUS_PDU (in module ics.ics), 176`

`SPY_STATUS_REMOTE_FRAME (in module ics.ics), 176`

`SPY_STATUS_TEST_TRIGGER (in module ics.ics), 176`

`SPY_STATUS_TEXT_COMMENT (in module ics.ics), 176`

`SPY_STATUS_TX_MSG (in module ics.ics), 176`

`SPY_STATUS_TX_NOMATCH (in module ics.ics), 176`

`SPY_STATUS_UNDEFINED_ERROR (in module ics.ics), 176`

`SPY_STATUS_VSI_IFR_CRC_BIT (in module ics.ics), 176`

`SPY_STATUS_VSI_TX_UNDERRUN (in module ics.ics), 176`

`SPY_STATUS_XTD_FRAME (in module ics.ics), 176`

`SpyMessage (class in ics.ics), 18`

`SpyMessageJ1850 (class in ics.ics), 19`

`srad_galaxy_settings (class in ics.structures.srad_galaxy_settings), 132`

`srad_gigalog_settings (class in ics.structures.srad_gigalog_settings), 135`

`srad_gigastar_settings (class in ics.structures.srad_gigastar_settings), 137`

`srad_jupiter_settings (class in ics.structures.srad_jupiter_settings), 140`

`srad_jupiter_switch_settings (class in ics.structures.srad_jupiter_switch_settings), 141`

`srad_moon2_settings (class in ics.structures.srad_moon2_settings), 142`

`srad_pluto_settings (class in ics.structures.srad_pluto_settings), 142`

`srad_star2_settings (class in ics.structures.srad_star2_settings), 144`

`srad_super_moon_settings (class in ics.structures.srad_super_moon_settings), 145`

`srcmeta (ics.structures.s_pluto_avb_params_s.s_pluto_avb_params_s attribute), 112`

`srcport (ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_sync attribute), 113`

`st_api_firmware_info (class in ics.structures.st_api_firmware_info), 146`

`st_chip_versions (class in ics.structures.st_chip_versions), 147`

`st_cm_iso157652_rx_message (class in ics.structures.st_cm_iso157652_rx_message), 150`

`st_cm_iso157652_tx_message (class in ics.structures.st_cm_iso157652_tx_message), 151`

`stabasyen (ics.structures.s_pluto_clock_sync_params_s.s_pluto_clock_s attribute), 113`

`startup (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex attribute), 83`

`state (ics.structures.s_disk_format_progress.s_disk_format_progress attribute), 96`

`Status (ics.structures.j2534_adapter_information.j2534_adapter_information attribute), 88`

`status (ics.structures.s_disk_details.s_disk_details attribute), 96`

`status (ics.structures.s_disk_status.s_disk_status attribute), 96`

`Status2Mask (ics.structures.spy_filter_long.spy_filter_long attribute), 131`

`Status2Value (ics.structures.spy_filter_long.spy_filter_long attribute), 131`

`StatusBitField (ics.ics.SpyMessage attribute), 19`

`StatusBitField (ics.ics.SpyMessageJ1850 attribute), 20`

`StatusBitField (ics.structures.ics_spy_message_flex_ray.ics_spy_message attribute), 82`

`StatusBitField (ics.structures.ics_spy_message_long.ics_spy_message attribute), 82`

```

        attribute), 84
StatusBitField(ics.structures.ics_spy_message_vsb.ics_spy_message_vsbs.svcn4_ind_settings), 153
        attribute), 85
StatusBitField2 (ics.ics.SpyMessage attribute), 19
StatusBitField2 (ics.ics.SpyMessageJ1850 attribute), 20
StatusBitField2 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_vsbs.svcn4_settings.s_fire_settings attribute), 102
StatusBitField2 (ics.structures.ics_spy_message_long.ics_spy_message_vsbs.svcn4_settings.s_fire_vnet_settings attribute), 105
StatusBitField2 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsbs.svcn4_settings.s_pendant_settings attribute), 110
StatusBitField3 (ics.ics.SpyMessage attribute), 19
StatusBitField3 (ics.ics.SpyMessageJ1850 attribute), 20
StatusBitField3 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_vsbs.svcn4_settings.s_cyan_settings attribute), 108
StatusBitField3 (ics.structures.ics_spy_message_long.ics_spy_message_vsbs.svcn4_settings.s_neo_ecu12_settings attribute), 109
StatusBitField3 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsbs.svcn4_settings.s_neo_ecu12_settings attribute), 110
StatusBitField4 (ics.ics.SpyMessage attribute), 19
StatusBitField4 (ics.ics.SpyMessageJ1850 attribute), 20
StatusBitField4 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_vsbs.svcn4_settings.s_cyan_settings attribute), 94
StatusBitField4 (ics.structures.ics_spy_message_long.ics_spy_message_vsbs.svcn4_settings.s_fire_vnet_settings attribute), 105
StatusBitField4 (ics.structures.ics_spy_message_vsb.ics_spy_message_vsbs.svcn4_settings.s_neo_ecu12_settings attribute), 109
StatusMask (ics.structures.spy_filter_long.spy_filter_long attribute), 131
StatusValue (ics.structures.spy_filter_long.spy_filter_long attribute), 132
stMin (ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message.srad_galaxy_settings.srad_galaxy_settings attribute), 135
stMin (ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message.DISABLED (in module ics.ics), attribute), 150
stMin (ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message.DISABLED_RESISTOR_ENABLED (in module ics.ics), 152
stop_bits (ics.structures.uart_settings.uart_settings attribute), 159
structure (ics.structures.s_disk_details.s_disk_details attribute), 96
structure (ics.structures.s_ext_sub_cmd_comm.s_ext_subcmd_settings attribute), 97
stth (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.SWCAN_SETTINGS_SIZE (in module ics.ics), 176
        attribute), 113
sttointth (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.PLUTO_CLOCK_SYNC_PARAMS_SIZE (in module ics.ics), 113
        attribute), 113
svcan3_settings (class ics.structures.svcan3_settings), 152
svcan412_settings (class ics.structures.svcan412_settings), 152
svcan4_ind_settings (class ics.structures.svcan4_settings), 153
        svcan4_settings (class ics.structures.svcan4_settings), 154
        svcanrf_settings (class ics.structures.svcanrf_settings), 156
svcanrf_settings (class ics.structures.svcanrf_settings), 156
swcan (ics.structures.secu_settings.secu_settings attribute), 125
swcan1 (ics.structures.s_cyan_settings.s_cyan_settings attribute), 125
swcan1 (ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings attribute), 130
swcan1 (ics.structures.srd_galaxy_settings.srd_galaxy_settings attribute), 135
swcan2 (ics.structures.s_pendant_settings.s_pendant_settings attribute), 110
swcan2 (ics.structures.srd_galaxy_settings.srd_galaxy_settings attribute), 135
swcan2 (ics.structures.srd_jupiter_settings.srd_jupiter_settings attribute), 176
SWCAN_AUTOSWITCH_NO_RESISTOR (in module ics.ics), 176
SWCAN_AUTOSWITCH_WITH_RESISTOR (in module ics.ics), 176
switchSettings (ics.structures.srad_jupiter_settings.srad_jupiter_settings attribute), 141
swmaster (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 113
syasyen (ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params attribute), 113

```

attribute), 113
 sydomain (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_attributes_params_s_attribute*), 113
termination_enables
 sync (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_attributes.s_fire3_settings.s_fire3_settings_attribute*), 100
 sypriority (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_attributes_params_s_attribute*), 113
(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings_attributes)
 syrelen (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_attributes_params_s_attribute*), 113
termination_enables
 sysyen (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_attributes_params.s_neo_ecu12_settings.s_neo_ecu12_settings_attribute*), 113
attribute), 109
 syth (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_attributes_params_attributes*), 113
(ics.structures.s_vivid_can_settings.s_vivid_can_settings_attributes)
 sytostben (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_attributes_params_attributes*), 113
termination_enables
 sytousyth (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_attributes_params_attributes_attributes*), 113
(ics.structures.s_radar_scan_hub_settings.scan_hub_settings_attributes)
attribute), 123
 szDeviceName (*ics.structures.j2534_adapter_information.j2534_adapter_information_attributes*), 88
(ics.structures.secu_avb_settings.secu_avb_settings_attributes)
 szName (*ics.structures.j2534_adapter_information.j2534_adapter_information_attributes*), 124
termination_enables
(ics.structures.srad_gigalog_settings.srad_gigalog_settings_attributes)
attribute), 137
T
 tag_options_find_neo_ex (*class* in *termination_enables*)
(ics.structures.tag_options_find_neo_ex), 158
(ics.structures.srad_gigastar_settings.srad_gigastar_settings_attributes)
attribute), 140
 tag_options_open_neo_ex (*class* in *termination_enables*)
(ics.structures.tag_options_open_neo_ex), 158
(ics.structures.srad_jupiter_settings.srad_jupiter_settings_attributes)
attribute), 141
 tag_port (*ics.structures.s_pluto_vlan_lookup.s.s_pluto_vlan_lookup_attributes*), 120
termination_enables
(ics.structures.srad_pluto_settings.srad_pluto_settings_attributes)
attribute), 144
 tagicsneo_vi_command (*class* in *termination_enables*)
(ics.structures.tagicsneo_vi_command), 158
(ics.structures.svcn412_settings.svcn412_settings_attributes)
attribute), 153
 tapPair0 (*ics.structures.op_eth_general_settings.op_eth_general_settings_attributes*), 89
(ics.structures.svcn4_ind_settings.svcn4_ind_settings_attributes)
attribute), 153
 tapPair1 (*ics.structures.op_eth_general_settings.op_eth_general_settings_attributes*), 89
(ics.structures.svcn4_ind_settings.svcn4_ind_settings_attributes)
attribute), 154
 tapPair2 (*ics.structures.op_eth_general_settings.op_eth_general_settings_attributes*), 89
termination_enables
 tapPair3 (*ics.structures.op_eth_general_settings.op_eth_general_settings_attributes*), 89
(ics.structures.svcn4_settings.svcn4_settings_attributes)
attribute), 156
 tapPair4 (*ics.structures.op_eth_general_settings.op_eth_general_settings_attributes*), 89
(ics.structures.s_cyan_settings.s_cyan_settings_attributes)
attribute), 94
 tapPair5 (*ics.structures.op_eth_general_settings.op_eth_general_settings_attributes*), 89
(ics.structures.s_fire3_settings.s_fire3_settings_attributes)
attribute), 100
 temp_interval_ms (*ics.structures.rad_reporting_settings.rad_reporting_settings_attributes*), 90
(ics.structures.s_fire_settings.s_fire_settings_attributes)
attribute), 102
 tentsyrelen (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_attributes_params_attributes_attributes*), 113
(ics.structures.s_fire_vnet_settings.s_fire_vnet_settings_attributes)
attribute), 105
 term_enabled (*ics.structures.canterm_settings.canterm_settings_attributes*), 74
(ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings_attributes)
attribute), 107
 term_network (*ics.structures.canterm_settings.canterm_settings_attributes*), 74
(ics.structures.s_neo_ecu12_settings.s_neo_ecu12_settings_attributes)
attribute), 109
 termination_enables
text_api (ics.structures.s_pendant_settings.s_pendant_settings_attributes)

```

        attribute), 110
text_api (ics.structures.secu_avb_settings.secu_avb_settingTime StampHardwareID
        attribute), 124
text_api (ics.structures.secu_settings.secu_settings
        attribute), 125
text_api (ics.structures.sievb_settings.sievb_settings
        attribute), 128
text_api (ics.structures.sobd2_pro_settings.sobd2_pro_settingTime StampHardwareID
        attribute), 130
text_api (ics.structures.sobd2_sim_settings.sobd2_sim_settings
        attribute), 131
text_api (ics.structures.srad_galaxy_settings.srad_galaxy_settings
        attribute), 135
text_api (ics.structures.srad_gigalog_settings.srad_gigalog_settingTime StampSystemID
        attribute), 137
text_api (ics.structures.srad_gigastar_settings.srad_gigastar_settingTime StampHardwareID
        attribute), 140
text_api (ics.structures.srad_jupiter_settings.srad_jupiterSettingTime StampSystemID
        attribute), 141
text_api (ics.structures.srad_moon2_settings.srad_moon2_settingTime StampSystemID
        attribute), 142
text_api (ics.structures.srad_pluto_settings.srad_pluto_settings
        attribute), 144
text_api (ics.structures.srad_star2_settings.srad_star2_settingSync (ics.structures.s_cyan_settings.s_cyan_settings
        attribute), 145
text_api (ics.structures.srad_super_moon_settings.srad_super_moon_settingSync (ics.structures.s_fire3_settings.s_fire3_settings
        attribute), 146
text_api (ics.structures.svcan412_settings.svcan412_settingSync (ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings
        attribute), 153
text_api (ics.structures.svcan4_settings.svcan4_settings timesync_icshardware_settings (class in
        attribute), 156
time_500us (ics.structures.iso9141_keyword2000_init_step.iso91415Keyword2000_init_step
        attribute), 87
TimeHardware (ics.ics.SpyMessage attribute), 19
TimeHardware (ics.ics.SpyMessageJ1850 attribute), timeSyncSettings (ics.structures.srad_galaxy_settings.srad_galaxy_s
        20
TimeHardware (ics.ics_spy_message_flex_ray.timeSyncMessage_flexRay (ics.structures.srad_gigalog_settings.srad_gigalog_
        attribute), 82
TimeHardware (ics.ics_spy_message_long.ics_timeMessageLongings (ics.structures.srad_gigastar_settings.srad_gigasta
        attribute), 84
TimeHardware (ics.ics_spy_message_vsb.ics_spy_messageSettings (ics.structures.srad_moon2_settings.srad_moon2_s
        attribute), 85
TimeHardware2 (ics.ics.SpyMessage attribute), 19
TimeHardware2 (ics.ics.SpyMessageJ1850 attribute),
        20
TimeHardware2 (ics.structures.ics_spy_message_flex_ray.ics_spy_message_flexRay
        attribute), 82
TimeHardware2 (ics.structures.ics_spy_message_long.ics_timeMessageLong (ics.SpyMessageJ1850 attribute), 20
        attribute), 84
TimeHardware2 (ics.structures.ics_spy_message_vsb.ics_spy_messageVsb), 82
        attribute), 85
TimeStampHardwareID (ics.ics.SpyMessage at-
        tribute), 19
TimeStampHardwareID (ics.ics.SpyMessageJ1850
        attribute), 85
        attribute), 20
(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_r
        attribute), 82
TimeStampHardwareID
        attribute), 84
(ics.structures.ics_spy_message_long.ics_spy_message_long
        attribute), 84
TimeStampHardwareID
        attribute), 85
TimeStampSystemID (ics.ics.SpyMessage attribute),
        19
TimeStampSystemID (ics.ics.SpyMessageJ1850 at-
        tribute), 85
TimeStampSystemID
        attribute), 84
(ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
        attribute), 85
TimeStampSystemID (ics.ics.SpyMessage attribute),
        19
TimeStampSystemID (ics.ics.SpyMessageJ1850 at-
        tribute), 85
TimeStampSystemID
        attribute), 84
(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_r
        attribute), 82
TimeStampSystemID
        attribute), 84
(ics.structures.ics_spy_message_long.ics_spy_message_long
        attribute), 84
TimeStampSystemID
        attribute), 85
TimeStampSystemID (ics.ics.SpyMessage attribute),
        19
TimeStampSystemID (ics.ics.SpyMessageJ1850 at-
        tribute), 85
TimeStampSystemID
        attribute), 84
(ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
        attribute), 85
TimeStampSystemID (ics.ics.SpyMessage attribute),
        19
TimeStampSystemID (ics.ics.SpyMessageJ1850 at-
        tribute), 85
TimeStampSystemID
        attribute), 84
(ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_r
        attribute), 82
TimeStampSystemID
        attribute), 84
(ics.structures.ics_spy_message_long.ics_spy_message_long
        attribute), 84
TimeStampSystemID
        attribute), 85
TimeStampSystemID (ics.ics.SpyMessage attribute),
        19
TimeStampSystemID (ics.ics.SpyMessageJ1850 at-
        tribute), 85
TimeStampSystemID
        attribute), 84
(ics.structures.ics_spy_message_vsb.ics_spy_message_vsb
        attribute), 85

```

TimeSystem2 (*ics.ics.SpyMessage attribute*), 19
 TimeSystem2 (*ics.ics.SpyMessageJ1850 attribute*), 20
 TimeSystem2 (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray_to_vl_forwarding_entry_s.s_pluto_vl_forwarding_attribute*), 82
 TimeSystem2 (*ics.structures.ics_spy_message_long.ics_spy_message_long_to_vl_policing_entry_s.s_pluto_vl_policing_entry_attribute*), 84
 TimeSystem2 (*ics.structures.ics_spy_message_vsb.ics_spy_message_vsb_attribute*), 85
 top (*ics.structures.s_pluto_mac_config.s.s_pluto_mac_config attribute*), 118
 tp_delin (*ics.structures.s_pluto_mac_config.s.s_pluto_mac_config.attribute*), 118
 tp_delout (*ics.structures.s_pluto_mac_config.s.s_pluto_mac_config.attribute*), 118
 tpid (*ics.structures.s_pluto_general_params.s.s_pluto_general_params.attribute*), 115
 tpid2 (*ics.structures.s_pluto_general_params.s.s_pluto_general_params.attribute*), 115
 TqProp (*ics.structures.can_settings.can_settings attribute*), 73
 TqProp (*ics.structures.swcan_settings.swcan_settings attribute*), 158
 TqSeg1 (*ics.structures.can_settings.can_settings attribute*), 73
 TqSeg1 (*ics.structures.swcan_settings.swcan_settings attribute*), 158
 TqSeg2 (*ics.structures.can_settings.can_settings attribute*), 73
 TqSeg2 (*ics.structures.swcan_settings.swcan_settings attribute*), 158
 TqSync (*ics.structures.can_settings.can_settings attribute*), 73
 TqSync (*ics.structures.swcan_settings.swcan_settings attribute*), 158
 transceiver_mode (*ics.structures.can_settings.can_settings attribute*), 73
 transceiver_mode (*ics.structures.swcan_settings.swcan_settings attribute*), 158
 transmit_messages () (*in module ics.ics*), 51
 tss_len_12_5ns (*ics.structures.ics_spy_message_flex_ray.ics_spy_message_flex_ray_to_vl_policing_entry_s.s_pluto_clock_sync_params_s.s_pluto_clock_sync_params_attribute*), 83
 tsyth (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.attribute*), 113
 tsytoesyth (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.attribute*), 113
 tsytoesyth (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.attribute*), 113
 tx_dl (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message_attributes.ics_vcan4_device_status.ics_vcan4_device_status attribute*), 87
 tx_dl (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message_attributes.st_chip_versions.st_chip_versions attribute*), 152
 tx_index (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message_attributes.st_chip_versions.st_chip_versions attribute*), 87
 tx_index (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message_attributes.st_chip_versions.st_chip_versions attribute*), 149
 attribute), 152
 TxMessages () (*in module ics.ics*), 28
 type (*ics.message_types.s_splulo_vl_forwarding_entry_s.s_pluto_vl_forwarding_attribute*), 119
 U
 ics.structures.s_fire_settings.s_fire_settings attribute), 102
 ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute), 105
 ics.structures.s_pendant_settings.s_pendant_settings attribute), 110
 ics.structures.secu_settings.secu_settings attribute), 125
 ics.structures.sievb_settings.sievb_settings attribute), 128
 uart2 (*ics.structures.s_fire_settings.s_fire_settings attribute*), 102
 uart2 (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings attribute*), 105
 uart2 (*ics.structures.s_pendant_settings.s_pendant_settings attribute*), 110
 uart2 (*ics.structures.secu_settings.secu_settings attribute*), 125
 uart2 (*ics.structures.sievb_settings.sievb_settings attribute*), 128
 uart_settings (*class in ics.structures.uart_settings*), 159
 UART_SETTINGS_SIZE (*in module ics.ics*), 176
 ucConfigMode (*ics.structures.op_eth_settings.op_eth_settings attribute*), 90
 ucInterfaceType (*ics.structures.op_eth_general_settings.op_eth_general_settings attribute*), 89
 uFlags (*ics.structures.op_eth_general_settings.op_eth_general_settings attribute*), 89
 unsytoesyth (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params.attribute*), 113
 attribute), 114
 attribute), 80
 attribute), 80
 attribute), 80
 attribute), 80
 attribute), 86
 attribute), 86
 attribute), 149
 attribute), 149
 attribute), 149

usbHostPowerEnabled
 version (ics.structures.s_phy_reg_pkt.s_phy_reg_pkt
 attribute), 111
 version (ics.structures.s_phy_reg_pkt_hdr.s_phy_reg_pkt_hdr
 attribute), 111
usbSelect (ics.structures.s_pluto_custom_params.s.s_pluto_custom_params)
 attribute), 114
use_dest_ports (ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s
 attribute), 118
USE_TQ (in module ics.ics), 176

V

validate_hobject () (in module ics.ics), 51
ValidateHObject () (in module ics.ics), 28
vcan3 (ics.structures.global_settings.global_settings attribute), 79
vcan3 (ics.structures.s_device_settings.s_device_settings attribute), 96
vcan3_versions (ics.structures.st_chip_versions.st_chip_version attribute), 149
vcan4 (ics.structures.global_settings.global_settings attribute), 79
vcan4 (ics.structures.s_device_settings.s_device_settings attribute), 96
vcan412 (ics.structures.global_settings.global_settings attribute), 79
vcan412 (ics.structures.s_device_settings.s_device_settings attribute), 96
vcan41_versions (ics.structures.st_chip_versions.st_chip_version attribute), 149
vcan42_versions (ics.structures.st_chip_versions.st_chip_version attribute), 149
vcan4_12 (ics.structures.global_settings.global_settings attribute), 79
vcan4_12 (ics.structures.s_device_settings.s_device_settings attribute), 96
vcan4_ind (ics.structures.global_settings.global_settings attribute), 79
vcan4_ind (ics.structures.s_device_settings.s_device_settings attribute), 96
vcan4indStatus (ics.structures.ics_device_status.ics_device_status attribute), 80
vcan4Status (ics.structures.ics_device_status.ics_device_status attribute), 79
vcanrf (ics.structures.global_settings.global_settings attribute), 79
vcanrf (ics.structures.s_device_settings.s_device_settings attribute), 96
vcanrf_versions (ics.structures.st_chip_versions.st_chip_version attribute), 149
vegr_mirr (ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_s attribute), 120
version (ics.structures.global_settings.global_settings attribute), 79
version (ics.structures.s_extended_data_flash_headers.s_extended_data_flash_header attribute), 97
 version (ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_s attribute), 120
 videoFormat (ics.structures.serdescam_settings.serdescam_settings attribute), 126
 ving_mirr (ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_s attribute), 120
vividcan (ics.structures.global_settings.global_settings attribute), 79
vividcan (ics.structures.s_device_settings.s_device_settings attribute), 96
vividcan_versions
 (ics.structures.st_chip_versions.st_chip_versions attribute), 149
 vlan_bc (ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_s attribute), 120
 vlan_egress (ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s attribute), 118
 vlan_ingress (ics.structures.s_pluto_retagging_entry_s.s_pluto_retagging_entry_s attribute), 118
 vlan_LookupEntries
 (ics.structures.s_pluto_switch_settings.s_pluto_switch_settings attribute), 119
 vlan_pmap (ics.structures.s_pluto_l2_forwarding_entry_s.s_pluto_l2_forwarding_entry_s attribute), 116
 vlan_vlaidmin (ics.structures.s_pluto_l2_address_lookup_entry_s.s_pluto_l2_address_lookup_entry_s attribute), 116
 vlan_vlanid (ics.structures.s_pluto_vlan_lookup_s.s_pluto_vlan_lookup_s attribute), 120
 vlan_vlan prio (ics.structures.s_pluto_mac_config.s_pluto_mac_config attribute), 118
 vlidimnmin (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params attribute), 114
 vlidmax (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params attribute), 114
 vlidmin (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params attribute), 114
 vlidmax (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params attribute), 114
 vlidselect (ics.structures.s_pluto_clock_sync_params.s_pluto_clock_sync_params attribute), 114
 vllupformat (ics.structures.s_pluto_general_params.s_pluto_general_params attribute), 115
 vllupformat0 (ics.structures.s_pluto_vl_lookup_entry_s.s_pluto_vl_lookup_entry_s attribute), 119
 vllupformat1 (ics.structures.s_pluto_vl_lookup_entry_s.s_pluto_vl_lookup_entry_s attribute), 119
 vllupformat2 (ics.structures.s_pluto_vl_lookup_entry_s.s_pluto_vl_lookup_entry_s attribute), 115
 vlmask (ics.structures.s_pluto_general_params.s_pluto_general_params attribute), 115
 vnlmask (ics.structures.s_pluto_general_params.s_pluto_general_params attribute), 120

vnetBits (*ics.structures.s_fire_settings.s_fire_settings*
 attribute), 102
vnetBits (*ics.structures.s_fire_vnet_settings.s_fire_vnet_settings*
 attribute), 105
VNETBITS_FEATURE_ANDROID_MSGS (in module
 ics.ics), 176
VNETBITS_FEATURE_DISABLE_USB_CHECK (in
 module ics.ics), 176
voltage (*ics.structures.serdespoc_settings.serdespoc_settings*
 attribute), 126
vs_netid (*ics.structures.iso15765_2015_tx_message.iso15765_2015_tx_message*
 attribute), 87
vs_netid (*ics.structures.st_cm_iso157652_rx_message.st_cm_iso157652_rx_message*
 attribute), 150
vs_netid (*ics.structures.st_cm_iso157652_tx_message.st_cm_iso157652_tx_message*
 attribute), 152

W

waitthsync (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s*
 attribute), 114
wfintmout (*ics.structures.s_pluto_clock_sync_params.s.s_pluto_clock_sync_params_s*
 attribute), 114
WIFI_CONNECTION (in module *ics.ics*), 176
word (*ics.structures.s_fire3_settings.s_fire3_settings* at-
 tribute), 100
word (*ics.structures.s_flex_vnetz_settings.s_flex_vnetz_settings*
 attribute), 107
word (*ics.structures.svcn4_ind_settings.svcn4_ind_settings*
 attribute), 154
write_jupiter_firmware () (in module *ics.ics*),
 51
write_sdcard () (in module *ics.ics*), 51
WriteEnable (*ics.structures.s_phy_reg_pkt.s_phy_reg_pkt*
 attribute), 111
WriteJupiterFirmware () (in module *ics.ics*), 28
WriteSDCard () (in module *ics.ics*), 28

Z

zchip_major (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 149
zchip_minor (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 149
zero0 (*ics.structures.s_neo_most_gateway_settings.s_neo_most_gateway_settings*
 attribute), 109
zyng_core_major (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 149
zyng_core_minor (*ics.structures.st_chip_versions.st_chip_versions*
 attribute), 149